


INTEGRATED MIXER

EMX150/200/300

SERVICE MANUAL



EMX300

CONTENTS <目次>

SPECIFICATIONS <仕様>	1	BLOCK DIAGRAM <ブロックダイアグラム>	5
INPUT/OUTPUT CHARACTERISTICS <入・出力特性>	2	CIRCUIT BOARDS (Parts side)	6 ~ 22
PANEL LAYOUT <パネルレイアウト>	3	PARTS LIST	23 ~ 39
DISASSEMBLY PROCEDURES <分解手順>	4	SCHEMATIC DIAGRAM <総回路図>	40/41
ADJUSTMENTS <調整仕様>	4		

006572

SINCE 1887



YAMAHA

NIPPON GAKKI CO., LTD. HAMAMATSU, JAPAN
2.6K-705 ㊞ ㊟ Printed in Japan 84.1

SPECIFICATIONS <仕様>

MODEL	EMX150	EMX200	EMX300
MAXIMUM OUTPUT POWER	150W + 150W @ 4 ohms 110W + 110W @ 8 ohms 0.5% 20 Hz — 20 kHz	250W + 250W @ 4 ohms 170W + 170W @ 8 ohms 0.5% 20 Hz — 20 kHz	
MAXIMUM OUTPUT LEVEL (LINE OUT)	+20 dB @ 10k-ohms 0.5% 20 Hz — 10 kHz		
T.H. Distortion (SPEAKER OUT) (LINE OUT)	Less than 0.05% 20 Hz — 20 kHz @ 75W 4 ohms	Less than 0.05% 20 Hz — 20 kHz @ 125W 4 ohms	
Frequency Response (SPEAKER OUT) (LINE OUT)	+1, —3 dB 20 Hz — 20 kHz @ 1W 8 ohms +1, +3 dB 20 Hz — 20 kHz @ +4 dB 10 k-ohms		
Hum & Noise* (20 Hz — 20 kHz) Rg = 150 ohms Input GAIN = —50 dB	—64 dB residual output noise (SPEAKER OUT)	—62 dB residual output noise (SPEAKER OUT)	
	—126 dB Equivalent Input Noise (66 dB S/N) —90 dB residual output noise (LINE OUT) —77 dB (81 dB S/N) LINE OUT Master fader at maximum and all CH fader at minimum. —62 dB (66 dB S/N) LINE OUT Master fader at maximum and one Input fader at maximum. —77 dB (81 dB S/N) FB OUT Master fader at maximum and all Input FB volume at minimum. —62 dB (66 dB S/N) FB OUT Master fader at maximum and one Input FB volume at maximum. —85 dB (75 dB S/N) ECHO SEND Master level control at maximum and all Input ECHO volume at minimum level. —76 dB (66 dB S/N) ECHO SEND Master level control and one Input fader at maximum and one ECHO volume at nominal level.		
Crosstalk	—60 dB at 1 kHz : adjacent Input —60 dB at 1 kHz : Input to Output		
Maximum Voltage Gain	SP OUT (L, R) 90 dB CH IN to SP OUT	SP OUT (L, R) 92 dB CH IN to SP OUT	
	LINE OUT (L, R) FB OUT (1, 2) ECHO SEND ECHO RETURN AUX IN (1, 2) AUX IN (1, 2) CH INSERT OUT CH INSERT IN	64 dB CH IN to LINE OUT 64 dB CH IN to FB OUT 56 dB CH IN to ECHO SEND 24 dB ECHO RETURN to LINE OUT 24 dB AUX IN to LINE OUT 24 dB AUX IN to FB OUT 50 dB CH IN to CH INSERT OUT 14 dB CH INSERT IN to LINE OUT	
Ch Controls EMX150 (1-6) EMX200 (1-8) EMX300 (1-12)	Fader PAD (0 dB/—20 dB) GAIN (—20 dB ~ —60 dB) HI-EQ MID-EQ (Level/Freq.)	LO-EQ FB (1, 2) ECHO Pan pot	
Master Controls	PGM Fader (L, R) FB Fader (1, 2) ECHO SEND ECHO RETURN	ECHO (Feedback/Delay time) AUX IN (1, 2) (Volume/Pan pot/FB1/FB2) 9-band Graphic EQ (in-out sw.)	
Channel Equalization	+15, —15 dB maximum HIGH : 8 kHz shelving MID : 0.35 kHz — 5 kHz peaking LOW : 100 Hz shelving		
Master Equalization (GEQ)	+12, —12 dB maximum 63, 125, 250, 500, 1k, 2k, 4k, 8k, 16 kHz peaking		
VU meters (+3 VU full power) (0 VU = +4 dB)	2 illuminated meters, SPEAKER OUT (L, R)		
	—	2 illuminated meters, FB OUT (1, 2)	
Peak Indicators	LED (red) built into each Channel Input turns ON when pre-fader level reaches 3 dB below clipping.		
Finish	Black		
Power Requirements (Japanese model) (U.S. & Canadian models) (General model)	100V, 50/60 Hz 120V, 60 Hz 110 — 120/220 — 240V, 50/60 Hz		
Power Consumption (Japanese model) (U.S. & Canadian models) (General model)	260W 500W 800W	450W 800W 1500W	450W 800W 1500W
Dimension (Width) (Depth) (Height)	538 mm (21-3/16") 672 mm (26-7/16") 240 mm (9-7/16")	618 mm (24-3/4") 672 mm (26-7/16") 240 mm (9-7/16")	778 mm (30-11/16") 672 mm (26-7/16") 240 mm (9-7/16")
Weight	26 kg (57 lbs. 3 oz.)	31 kg (68 lbs. 6 oz.)	35 kg (77 lbs.)

* Hum and Noise are measured with 6 dB/octave filter at 12.47 kHz: equivalent to a 20 kHz filter with infinite dB/octave attenuation.
 ** 0 dB = 775mVrms. * @ 12.47kHz, 6dB/oct. のLPFで補正。 ** 0dB = 0.775Vrms.

INPUT/OUTPUT CHARACTERISTICS<入・出力特性>

● INPUT

Connection		CH Controls		Actual Load Impedance	For Use with Nominal	Sensitivity** (at maximum gain)	Input Level		Connector in Console
		PAD	GAIN				Nominal	Max. before Clip	
CH INPUT	Lo-Z EMX150 1~6 EMX200 1~8 EMX300 1~12	0 dB (off)	-60 dB	1 kΩ	50Ω ~ 250Ω Microphones or 600Ω Lines	-60 dB (0.8mV)	-60 dB (0.8mV)	-30 dB (24.5mV)	XLR Type (balanced)
		20 dB (on)	}			-20 dB (78mV)	-20 dB (78mV)	+10 dB (2.45V)	
			-20 dB			0 dB (775mV)	0 dB (775mV)	+24 dB (12.3V)	
	Hi-Z EMX150 1~4 EMX200 1~4 EMX300 1~8	0 dB (off)	-60 dB	10 kΩ	50Ω ~ 10kΩ Microphones or 600Ω Lines	-60 dB (0.8mV)	-60 dB (0.8mV)	-30 dB (24.5mV)	TRS Jack (unbalanced)
		20 dB (on)	}			-20 dB (78mV)	-20 dB (78mV)	+10 dB (2.45V)	
			-20 dB			0 dB (775mV)	0 dB (775mV)	+24 dB (12.3V)	
CH INSERT IN		EMX150 5~6 EMX200 5~8 EMX300 9~12		10 kΩ	600Ω Lines	-10 dB (245mV)	-10 dB (245mV)	+20 dB (7.75V)	TRS Jack (balanced)
AUX IN (1, 2)				15 kΩ	600Ω Lines	-20 dB (78mV)	-20 dB (78mV)	+24 dB (12.3V)	Phone Jack (unbalanced)
ECHO RETURN				15 kΩ	600Ω Lines	-20 dB (78mV)	-20 dB (78mV)	+24 dB (12.3V)	Phone Jack (unbalanced)
GEQ IN (L, R)				47 kΩ	600Ω Lines	+ 4 dB (1.23V)	+ 4 dB (1.23V)	+20 dB (7.75V)	Phone Jack (unbalanced)
POWER AMP IN (L, R)				25 kΩ	600Ω Lines	+4 dB (1.23V)	+ 4 dB (1.23V)	N/A	Phone Jack (unbalanced)

● OUTPUT

Connection		Actual Source Impedance	For Use with Nominal	OUTPUT LEVEL		Connector in Console (unbalanced)
				Nominal	Max. before Clip	
SPEAKER OUT (L, R)	EMX150	0.05Ω	4Ω	150W	N/A	Phone Jack and Barrier Strip type
	EMX200 EMX300			250W		
LINE OUT (L, R)		370Ω	10kΩ	+4 dB (1.23V)	+20 dB (7.75V)	Phone Jack
GEQ OUT (L, R)		370Ω	10kΩ	+4 dB (1.23V)	+20 dB (7.75V)	Phone Jack
FB OUT (1, 2)		150Ω	10kΩ	+4 dB (1.23V)	+20 dB (7.75V)	Phone Jack
ECHO SEND		560Ω	10kΩ	−10 dB (245mV)	+20 dB (7.75V)	Phone Jack
PHONES		25Ω	8Ω	0 dB (75mV)	N/A	Stereo Phone Jack
CH INSERT OUT	EMX150 5~6 EMX200 5~8 EMX300 9~12	560Ω	10kΩ	−10 dB (245mV)	+20 dB (7.75V)	Phone Jack (TRS)

* 0dB = 775mVrms.

** Sensitivity is the lowest level that will produce an output of full power or the output level when the unit is set to maximum gain.

● Specifications subject to change without notice.



* 0dB = 0.775Vrms.

** 感度 (Sensitivity) はユニットを最大ゲインにしたときの最大出力レベルを得るために必要な最少限の値です。


● 仕様および外観は改良のため、予告なく変更することがあります。

PANEL LAYOUT <パネルレイアウト>

CONTROL PANEL




REAR PANEL



EMX300 (U.S. & Canadian models)

■ DISASSEMBLY PROCEDURES<分解手順>



9 Screws

■ ADJUSTMENTS

- For the measurements, use an oscillator with an output impedance of below 10Ω , an oscilloscope and an AC voltmeter/dB meter with an input impedance of over $100k\Omega$.
- Before turning ON the power switch, make sure that the pots VR501 and VR601 on the MA1 or MA2 circuit board is turned counterclockwise fully.

1. Adjusting bias current of power amplifier

Adjust the voltage across TP501, TP502 and TP601 TP602 on the MA1 or MA2 circuit board as specified below with VR501 and VR601 respectively.

EMX150	$11mV \pm 1mV$
EMX200, 300	$15mV \pm 1mV$

2. Adjusting delay circuit (DL circuit board)

a. Clock frequency

Connect the frequency counter across the test terminals CP and E and adjust the pot (B22K/CLOCK) so that the clock frequency becomes $10.5kHz \pm 0.3kHz$.

(Never connect the frequency counter to the CP terminal except when measuring the clock frequency.)

b. Bias adjustment of BBD IC

Adjust the pot (B4.7K/BIAS) so that the waveform of the output terminal DO doesn't clip when +20dBm (1kHz) signal is applied to the input terminal DI (or so that the clipping occurs only symmetrically at the top and the bottom).

(DI terminal is 9pin of CN401 and DO terminal is 5pin of CN402.)

■ 調整仕様

- 測定には、出力インピーダンス 10Ω 以下の発振器、入力インピーダンス $100k\Omega$ 以上のレベル計およびオシロスコープを使用してください。

- 電源スイッチをONにする前にMA1またはMA2シート内の半固定ボリュームVR501、VR601が反時計方向いっぱいの状態であることを確認してください。

1. パワーアンプのバイアス電流の調整

MA1シートまたはMA2シート内のTP501～TP502間の電圧をVR501で、TP601～TP602間の電圧をVR601で下表の様に調整します。

EMX150	$11mV \pm 1mV$
EMX200, 300	$15mV \pm 1mV$

2. ディレイ回路の調整(DLシート)

a. クロック周波数



テストポイントCP～E間に周波数カウンターを接続した時、クロック周波数が $10.5kHz \pm 0.3kHz$ になるように半固定ボリューム(B22K・CLOCK)を調整します。


(CP端子への周波数カウンターの接続はクロック周波数を測定するときのみとし、他の測定時には絶対に接続しないでください。)

b. BBD ICのバイアス調整

入力端子DIに+20dBm(1kHz)の信号を加えた時、出力端子DOの波形がクリップしないように(クリップする場合は上下対称にクリップするように)半固定ボリューム(B4.7k, BIAS)を調整します。(CN401の9ピンがDI端子、CN402の5ピンがDO端子です。)

BLOCK DIAGRAM<ブロックダイアグラム>






IN2 CIRCUIT BOARD

IC101 ~ 108	NJM4558DV
Tr101 ~ 104,	2SA999L
109 ~ 112	
Tr105, 108,	2SC2320 (E, F)
113, 116	
Tr106, 107,	2SA999 (E, F)
114, 115	
LED101 ~ 104	TLR124 (Red)

MT1 CIRCUIT BOARD(NA812350)



MT1 CIRCUIT BOARD


D961 ~ 964 1S1555

Modification of Meter Sensitivity

output level of full scale	resistors
250 W	12K Ω
150 W	9.1K Ω
100 W	7.5K Ω
50 W	5.1K Ω
25 W	3.6K Ω
10 W	2K Ω

EMX200/300
(when shipped)


MT2 CIRCUIT BOARD(NA812360)



MT2 CIRCUIT BOARD

D981 ~ 988 OA95

MT3 CIRCUIT BOARD(NA812370)



MT3 CIRCUIT BOARD



D961 ~ 964 1S1555

Modification of Meter Sensitivity


output level of full scale	resistors
150 W	9.1K Ω
100 W	7.5K Ω
50 W	5.1K Ω
25 W	3.6K Ω
10 W	2K Ω

EMX150
(when shipped)

J11 CIRCUIT BOARD(NA812380)

Modification Circuit Board of
phantom Power Supply



J12 CIRCUIT BOARD(NA812390)




IC201, 202, 204, 205, 207	NJM4558DV
IC203	NJM2041
IC206	NJM4556

-10dB —————> +4dB
47K —————> 240K
33P —————> 6P

MP CIRCUIT BOARD(NA812410)



DC1 CIRCUIT BOARD (JAPANESE:NA812420
U.S. & CANADIAN:NA812430
GENERAL:NA812440)




DC1 CIRCUIT BOARD

IC801	μPC7815H
IC802	μPC7915H
Tr801, 802	2SC1815 (Y)
Tr803	2SD667 (C, D)
D802, 805, 806	1G4B1
D803, 804, 807, 808	W03B

MODEL	F801, 802, 805	F803, 804
JAPANESE	▽ 1A 250V	▽ 1A 250V
U.S. & CANADIAN	Ⓢ ST-4 1A 250V	Ⓢ ST-4 1A 250V
GENERAL	Ⓢ T1A 250V	Ⓢ T500mA 250V

DC2 CIRCUIT BOARD (JAPANESE:NA812450
U.S. & CANADIAN:NA812460
GENERAL:NA812470)




DC2 CIRCUIT BOARD

IC801	μPC7815H
IC802	μPC7915H
Tr801, 802	2SC1815 (Y)
Tr803	2SD667 (C, D)
D802, 805, 806	1G4B1
D803, 804, 807, 808	W03B


MODEL	F801, 802, 805, 806	F803, 804
JAPANESE	▽ 1A 250V	▽ 1A 250V
U.S. & CANADIAN	Ⓢ ST-4 1A 250V	Ⓢ ST-4 1A 250V
GENERAL	Ⓢ T1A 250V	Ⓢ T500mA 250V

AC CIRCUIT BOARD


JAPANESE:NA812480



U.S. & CANADIAN:NA812490



GENERAL:NA812500




AC CIRCUIT BOARD

IC701	BS08A
Tr701	2SA1321
Tr702	2SC3334
D701	10D4
D702, 703	1SS82
D704 ~ 709	1S1555
D710	Refer to following table
ZD701, 702	RD16EB1
ZD703	RD8.2EB2

MODEL	D710
JAPANESE, U.S. & CANADIAN	SM25GZ41
GENERAL	SM16JZ41

MA1 CIRCUIT BOARD(NA812510)



MA1 CIRCUIT BOARD

Tr501, 601	2SC2259 (F, G)	D501 ~ 503, 505, 507,	1S 2473
Tr502, 503, 602, 603	2SA1144 (O, Y)	508, 601 ~ 603, 605,	
Tr504, 604	2SC2704 (O, Y)	607, 608	
Tr505, 605	2SC1953 (R)	D506, 509 ~ 512, 606,	1SS82
Tr506, 514, 515, 606	2SC2240 (GR, BL)	609 ~ 612	
Tr507, 516, 607	2SA970 (GR, BL)	D513, 514	10D1
Tr508, 608	2SC2238 (O, Y)	ZD501, 601	RD24EB2
Tr509, 609	2SA968 (O, Y)	LED501, 502, 601, 602	LTZ-R17
Tr510, 511, 610, 611	2SC2581 (O, Y)	RY501	MS4UDC12V
Tr512, 513, 612, 613	2SA1106 (O, Y)	TH501, 502	STR60R70
Tr517	2SC1815 (GR)		
Tr518	2SD667 (B, C)		

Tr501, 601	2SA979 (G)	Tr514 ~ 517, 614 ~ 617	2SC2581 (O, Y)
Tr502, 602	2SA995 (G)	Tr518 ~ 521, 618 ~ 621	2SA1106 (O, Y)
Tr503, 603	2SC2291 (G)	Tr526	2SD667 (B, C)
Tr504, 506, 522, 523, 525, 604, 606	2SC1815 (GR)	D501 ~ 504, 601 ~ 604	1S2473
Tr505, 510, 605, 610	2SC2704 (O, Y)	D505 ~ 508, 605 ~ 608	1SS82
Tr507, 511, 607, 611	2SA1144 (O, Y)	D509, 609	STV-3H
Tr508, 608	2SC2240 (GR, BL)	D510, 511	10D1
Tr509, 524, 609	2SA970 (GR, BL)	ZD501, 601	RD24EB2
Tr512, 612	2SC2238 (O, Y)	LED501 ~ 505, 601 ~ 605	LTZ-R17
Tr513, 613	2SA968 (O, Y)	RY501	MSJ12D2-0
		TH501, 601	STR60R70


The diagram illustrates a complex electronic circuit board, likely for a stereo amplifier or tuner. Key components include:

- Input Sections:** Two input stages at the top, labeled SW 301 and SW 302, each featuring a volume control potentiometer (marked 0, 10, 25) and associated resistors/capacitors.
- Resistors:** Numerous fixed resistors are distributed across the board, with values ranging from 10K to 100K, and some smaller values like 0.001, 0.002, 0.005, 0.01, 0.02, 0.03, 0.05, 0.1, 0.2, 0.5, 1, 2, 5, 10, 20, 50, 100, 200, 500, 1K, 2K, 5K, 10K, 20K, 50K, 100K, 200K, 500K, 1M, 2M, 5M, 10M, 20M, 50M, 100M, 200M, 500M, 1G, 2G, 5G, 10G, 20G, 50G, 100G, 200G, 500G, 1T, 2T, 5T, 10T, 20T, 50T, 100T, 200T, 500T, 1P, 2P, 5P, 10P, 20P, 50P, 100P, 200P, 500P, 1N, 2N, 5N, 10N, 20N, 50N, 100N, 200N, 500N, 1F, 2F, 5F, 10F, 20F, 50F, 100F, 200F, 500F, 1M, 2M, 5M, 10M, 20M, 50M, 100M, 200M, 500M, 1G, 2G, 5G, 10G, 20G, 50G, 100G, 200G, 500G, 1T, 2T, 5T, 10T, 20T, 50T, 100T, 200T, 500T, 1P, 2P, 5P, 10P, 20P, 50P, 100P, 200P, 500P, 1N, 2N, 5N, 10N, 20N, 50N, 100N, 200N, 500N, 1F, 2F, 5F, 10F, 20F, 50F, 100F, 200F, 500F, 1M, 2M, 5M, 10M, 20M, 50M, 100M, 200M, 500M, 1G, 2G, 5G, 10G, 20G, 50G, 100G, 200G, 500G, 1T, 2T, 5T, 10T, 20T, 50T, 100T, 200T, 500T, 1P, 2P, 5P, 10P, 20P, 50P, 100P, 200P, 500P, 1N, 2N, 5N, 10N, 20N, 50N, 100N, 200N, 500N, 1F, 2F, 5F, 10F, 20F, 50F, 100F, 200F, 500F, 1M, 2M, 5M, 10M, 20M, 50M, 100M, 200M, 500M, 1G, 2G, 5G, 10G, 20G, 50G, 100G, 200G, 500G, 1T, 2T, 5T, 10T, 20T, 50T, 100T, 200T, 500T, 1P, 2P, 5P, 10P, 20P, 50P, 100P, 200P, 500P, 1N, 2N, 5N, 10N, 20N, 50N, 100N, 200N, 500N, 1F, 2F, 5F, 10F, 20F, 50F, 100F, 200F, 500F, 1M, 2M, 5M, 10M, 20M, 50M, 100M, 200M, 500M, 1G, 2G, 5G, 10G, 20G, 50G, 100G, 200G, 500G, 1T, 2T, 5T, 10T, 20T, 50T, 100T, 200T, 500T, 1P, 2P, 5P, 10P, 20P, 50P, 100P, 200P, 500P, 1N, 2N, 5N, 10N, 20N, 50N, 100N, 200N, 500N, 1F, 2F, 5F, 10F, 20F, 50F, 100F, 200F, 500F, 1M, 2M, 5M, 10M, 20M, 50M, 100M, 200M, 500M, 1G, 2G, 5G, 10G, 20G, 50G, 100G, 200G, 500G, 1T, 2T, 5T, 10T, 20T, 50T, 100T, 200T, 500T, 1P, 2P, 5P, 10P, 20P, 50P, 100P, 200P, 500P, 1N, 2N, 5N, 10N, 20N, 50N, 100N, 200N, 500N, 1F, 2F, 5F, 10F, 20F, 50F, 100F, 200F, 500F, 1M, 2M, 5M, 10M, 20M, 50M, 100M, 200M, 500M, 1G, 2G, 5G, 10G, 20G, 50G, 100G, 200G, 500G, 1T, 2T, 5T, 10T, 20T, 50T, 100T, 200T, 500T, 1P, 2P, 5P, 10P, 20P, 50P, 100P, 200P, 500P, 1N, 2N, 5N, 10N, 20N, 50N, 100N, 200N, 500N, 1F, 2F, 5F, 10F, 20F, 50F, 100F, 200F, 500F, 1M, 2M, 5M, 10M, 20M, 50M, 100M, 200M, 500M, 1G, 2G, 5G, 10G, 20G, 50G, 100G, 200G, 500G, 1T, 2T, 5T, 10T, 20T, 50T, 100T, 200T, 500T, 1P, 2P, 5P, 10P, 20P, 50P, 100P, 200P, 500P, 1N, 2N, 5N, 10N, 20N, 50N, 100N, 200N, 500N, 1F, 2F, 5F, 10F, 20F, 50F, 100F, 200F, 500F, 1M, 2M, 5M, 10M, 20M, 50M, 100M, 200M, 500M, 1G, 2G, 5G, 10G, 20G, 50G, 100G, 200G, 500G, 1T, 2T, 5T, 10T, 20T, 50T, 100T, 200T, 500T, 1P, 2P, 5P, 10P, 20P, 50P, 100P, 200P, 500P, 1N, 2N, 5N, 10N, 20N, 50N, 100N, 200N, 500N, 1F, 2F, 5F, 10F, 20F, 50F, 100F, 200F, 500F, 1M, 2M, 5M, 10M, 20M, 50M, 100M, 200M, 500M, 1G, 2G, 5G, 10G, 20G, 50G, 100G, 200G, 500G, 1T, 2T, 5T, 10T, 20T, 50T, 100T, 200T, 500T, 1P, 2P, 5P, 10P, 20P, 50P, 100P, 200P, 500P, 1N, 2N, 5N, 10N, 20N, 50N, 100N, 200N, 500N, 1F, 2F, 5F, 10F, 20F, 50F, 100F, 200F, 500F, 1M, 2M, 5M, 10M, 20M, 50M, 100M, 200M, 500M, 1G, 2G, 5G, 10G, 20G, 50G, 100G, 200G, 500G, 1T, 2T, 5T, 10T, 20T, 50T, 100T, 200T, 500T, 1P, 2P, 5P, 10P, 20P, 50P, 100P, 200P, 500P, 1N, 2N, 5N, 10N, 20N, 50N, 100N, 200N, 500N, 1F, 2F, 5F, 10F, 20F, 50F, 100F, 200F, 500F, 1M, 2M, 5M, 10M, 20M, 50M, 100M, 200M, 500M, 1G, 2G, 5G, 10G, 20G, 50G, 100G, 200G, 500G, 1T, 2T, 5T, 10T, 20T, 50T, 100T, 200T, 500T, 1P, 2P, 5P, 10P, 20P, 50P, 100P, 200P, 500P, 1N, 2N, 5N, 10N, 20N, 50N, 100N, 200N, 500N, 1F, 2F, 5F, 10F, 20F, 50F, 100F, 200F, 500F, 1M, 2M, 5M, 10M, 20M, 50M, 100M, 200M, 500M, 1G, 2G, 5G, 10G, 20G, 50G, 100G, 200G, 500G, 1T, 2T, 5T, 10T, 20T, 50T, 100T, 200T, 500T, 1P, 2P, 5P, 10P, 20P, 50P, 100P, 200P, 500P, 1N, 2N, 5N, 10N, 20N, 50N, 100N, 200N, 500N, 1F, 2F, 5F, 10F, 20F, 50F, 100F, 200F, 500F, 1M, 2M, 5M, 10M, 20M, 50M, 100M, 200M, 500M, 1G, 2G, 5G, 10G, 20G, 50G, 100G, 200G, 500G, 1T, 2T, 5T, 10T, 20T, 50T, 100T, 200T, 500T, 1P, 2P, 5P, 10P, 20P, 50P, 100P, 200P, 500P, 1N, 2N, 5N, 10N, 20N, 50N, 100N, 200N

IC301 ~ 311	NJM4558DV
-------------	-----------


PARTS. LIST

■ MAIN CHASSIS



ランク : Japan only

CONTROL PANEL UNIT




Ref. No.	Part No.	Description	部 品 名	Remarks	Common Model	Markets	ランク
※ 1	AA 82 87 80	Control Panel		コントロールパネル	EMX150		16*
※ "	AA 82 87 90	"		"	EMX200		160
※ "	AA 82 88 00	"		"	EMX300		170
※ 2	CB 83 09 00	Dust Proof filter		防 塵 フ ィ ル タ ー			030
※ 3	AA 81 20 30	Radiator Grill		放 熱 グ リ ル			050
※ 4	NB 82 82 80	Handle Assembly		取 手 Ass'y			060
4-1	EF 35 03 52	Oval Head Screw	5×35 BI	丸 皿 小 ネ ジ			010
※ 5	CB 83 07 70	Escutcheon, LED		LED エスカッション			010
6	CB 82 66 90	Dust Proof Cover		防 塵 カ バ ー			010
※ 7		Meter Unit	PGM	メーターユニット	Refer to Page 27.		
※ 8		"	FB	"	"		
※ 9		G.EQ-Unit		G.EQ ユニット	Refer to Page 28.		
※ 10	NA 81 24 00	Circuit Board, MAS		M A S シ ー ト			21*
11	CB 81 78 10	PC Support		P C サ ポ ー ト			010
※ 12	NA 81 23 40	Circuit Board, DL		D L シ ー ト			25*
※ 13	NA 81 23 10	Circuit Board, IN1		I N 1 シ ー ト			30*
※ 14	NA 81 23 20	" , IN2		I N 2 シ ー ト	EMX200,300		30*
※ "	NA 81 23 30	" , IN3		I N 3 シ ー ト	EMX150		22*
※ 15	CB 83 07 80	Knob, Push Switch		ツ マ ミ			010
※ 16	NA 81 24 80	Circuit Board, AC	#90540	A C シ ー ト	EMX200,300	J	18*
※ "	NA 81 24 90	"	#90540	"	"	U,C	
※ "	NA 81 25 00	"	#90540	"	"	G	
17	ED 33 00 66	Bind Head Screw	3×6 BI	バ イ ン ド 小 ネ ジ			010
18	ED 34 00 86	"	4×8 BI	"			010
19	Ei 33 00 66	Bind Head Tapping Screw	3×6 BI	バ イ ン ド タ ッ プ イ ン グ ネ ジ			010
20	Ei 33 00 86	"	3×8 BI	"			010
21	CB 81 00 90	Insulation Nut		絶 縁 ナ ッ ト			010
※ 22	EX 80 01 36	Hexagonal Nut	8S BI	特 殊 六 角 ナ ッ ト	2t, 8S, 0.75P, 対辺10		01*
23	LX 20 00 60	"	9S BI	"			010
24	EK 00 23 70	Washer		フ ァ イ バ ー ワ ッ シ ャ ー			010
25	LX 20 00 10	Plain Washer	9S BI	特 殊 平 座 金			010
26	EV 41 30 36	Toothed Lock Washer	A3S BI	歯 付 座 金			010
27	EV 41 30 46	"	A4S BI	"			010
28	LB 00 90 90	Connector Housing	9P	コ ネ ク タ ハ ウ ジ ン グ	XH		010
29	LB 60 24 80	"	8P	"	NH		010
30	LB 10 11 30	Contact Pin		コ ン タ ク ト ピ ン	XH		010
31	BB 00 44 30	"		"	NH		010
※ 32	AA 82 88 10	Top Panel		ト ッ プ パ ネ ル	EMX150		13*
※ "	AA 82 88 20	"		"	EMX200		140
※ "	AA 82 88 30	"		"	EMX300		150
※ 33	CB 83 07 20	Side Panel	LEFT	サ イ ド パ ネ ル			160
※ 34	CB 83 07 30	"	RIGHT	"			160
35	ED 34 02 00	Bind Head Screw	4×20 BI	バ イ ン ド 小 ネ ジ			010
36	Ei 34 01 06	Bind Head Tapping Screw	4×10 BI	バ イ ン ド タ ッ プ イ ン グ ネ ジ			010
※ 37	CB 83 07 40	Pad		パ ッ ド	EMX150		14*
※ "	CB 83 07 50	"		"	EMX200		150
※ "	CB 83 07 60	"		"	EMX300		160
38	Ei 34 01 26	Bind Head Tapping Screw	4×12 BI	バ イ ン ド タ ッ プ イ ン グ ネ ジ			010

※New Parts (新規部品)

ランク: Japan only

METER UNIT (PGM),(FB)




Ref. No.	Part No.	Description	部 品 名	Remarks	Common Model	Markets	ランク
※ 1	Ji 00 13 70	VU Meter	V U メ ー タ ー				070
※ 2	NA 81 23 70	Circuit Board, MT3	M T 3 シ ー ト	EMX150 PGM			09*
※ "	NA 81 23 50	" , MT1	M T 1 シ ー ト	EMX200,300 PGM			09*
※ "	NA 81 23 60	" , MT2	M T 2 シ ー ト	EMX200,300 FB			09*
3	CB 06 88 80	Plastic Rivet	プラスチックリベット				010
4	CB 06 86 20	Lamp Holder	ランプホルダー				010
5	CB 81 68 40	Cable Clip	ケーブルクリップ	EMX150(P) EMX200,300(F)			010

※ New Parts (新規部品)

ランク : Japan only


GRAPHIC EQUALIZER UNIT



Ref. No.	Part No.	Description	部 品 名	Remarks	Common Model	Markets	ランク
※ 1	NA 81 25 60	Circuit Board, G.EQ	G.EQ シ ー ト				21*
※ 2	CB 83 09 20	Dust Proof Cover	防 塵 カ バ ー				020
3	CB 81 21 60	Knob, EQ	E Q ツ マ ミ				010
4	CB 80 52 30	Knob, Switch	ス イ ッ チ ツ マ ミ				010
5	CB 81 66 60	Wire Clip	ワ イ ヤ ー ク リ ッ プ				010
6	ED 32 00 46	Bind Head Screw	2×4 BI バ イ ン ド 小 ネ ジ				010
7	EV 42 30 26	Toothed Lock Washer	B2S BI 歯 付 座 金				010


ランク : Japan only

■ BOTTOM COVER ASSEMBLY



ランク : Japan only

ELECTROLYTIC CAPACITOR UNIT




Ref. No.	Part No.	Description	部 品 名	Remarks	Common Model	Markets	ランク
※ 1	NA 81 25 40	Circuit Board, CO1	C O 1 シ ー ト	EMX150			17 *
※ "	NA 81 25 50	" , CO2	C O 2 シ ー ト	EMX200,300			18 *
2	BB 06 85 40	Lug Terminal	ラ グ 端 子				020
※ 3	NA 81 26 10	Circuit Board, DI1	D I 1 シ ー ト	EMX150			10 *
※ "	NA 81 25 30	" , DI2	D I 2 シ ー ト	EMX200,300			12 *
4	CB 80 68 40	Insulator, Voltage Selection	V S インシュレーター	"		G	
5	KA 40 04 10	Slide Switch	スライドスイッチ	"		G	
6	ED 33 00 66	Bind Head Screw	3×6 BI	バインド小ネジ	"	G	
7	ED 34 00 86	"	4×8 BI	"			010
8	ED 34 01 66	"	4×16 BI	"			010
9	Ei 33 00 66	Bind Head Tapping Screw	3×6 BI	バインドタッピングネジ			010
10	EV 30 34 06	Spring Lock Washer	4S BI	バネ座金			010
11	EV 42 30 46	Toothed Lock Washer	B4S BI	歯付座金			010
12	LB 01 40 30	Housing	3P	スボックスハウジング			010
13	LB 10 10 00	Terminal		スボックスターミナル			010
14	LB 10 11 80	Housing		ハウジング	EMX200,300	G	
15	LB 10 11 60	Receptacle		リセプタクル	"	G	

※New Parts (新規部品)

ランク : Japan Only


MAIN AMP UNIT



Ref. No.	Part No.	Description	部 品 名	Remarks	Common Model	Markets	ランク
1	AA 07 75 90	Prop	支 柱				020
※ 2	NA 81 25 10	Circuit Board, MA1	M A 1 シ ー ト	EMX150			31*
※ "	NA 81 25 20	" , MA2	M A 2 シ ー ト	EMX200,300			36*
※ 3	iL 00 06 80	Mica Insulator	マイ カ ベ ー ス				010
※ 4	JC 00 10 10	Radiate Fan	放 熱 フ ァ ン				160
5	ED 33 00 66	Bind Head Screw	3×6 BI	バ イ ン ド 小 ネ ジ			010
6	ED 33 01 26	"	3×12 BI	"			010
7	Ei 33 00 86	Bind Head Tapping Screw	3×8 BI	バ イ ン ド タ ッ ピ ン グ ネ ジ			010
8	EV 20 30 36	Flat Washer	3S BI	平 座 金			010
9	EV 30 33 06	Spring Lock Washer	3S BI	バ ネ 座 金			010

※ New Parts (新規部品)

ランク : Japan Only

REAR PANEL ASSEMBLY

Ref. No.	Part No.	Description	部 品 名	Remarks	Common Model	Markets	ランク
※ 1	AA 82 88 40	Rear Panel	リ ア パ ネ ル	EMX150		J	10*
※ "	AA 82 88 50	"	"	"		U,C	
※ "	AA 82 88 60	"	"	"		G	
※ "	AA 82 88 70	"	"	EMX200		J	110
※ "	AA 82 88 80	"	"	"		U,C	
※ "	AA 82 88 90	"	"	"		G	
※ "	AA 82 89 00	"	"	EMX300		J	120
※ "	AA 82 89 10	"	"	"		U,C	
※ "	AA 82 89 20	"	"	"		G	
2	AA 80 11 20	Hinge	蝶 番				020
3	CB 02 25 70	Power Cord Holder	コ ー ド リ ー ル				030
※ 4	LB 30 20 20	Cannon Connector	キャノンソケット				070
※ 5	NA 81 23 80	Circuit Board, J11	J 1 1 シ ー ト	HI Z			09*
※ 6	NA 81 23 90	" ,J12	J 1 2 シ ー ト	INSERT			09*
※ 7	NA 81 24 10	" ,MP	M P シ ー ト				12*
8	LB 20 11 20	Phone Jack	ホ ー ン ジャ ッ ク				030
※ 9	LA 00 48 30	Speakers Terminal	スピーカターミナル				050
※ 10	KA 30 07 00	Power Switch	電 源 ス イ ッ チ			J,U,C	080
※ "	KA 10 12 50	"	"			G	
11	LA 00 07 60	Lug Terminal	ラ グ 端 子 板				020
12	MG 00 06 10	Power Cord	電 源 コ ー ド			J	060
"	MG 00 05 30	"	"			U,C	
"	MG 00 11 30	"	"			G	
13	CB 80 68 50	Cord Stopper	コードストッパー			J,U,C	020
"	CB 03 28 40	"	"			G	
14	LB 20 12 10	Fuse Holder	ヒューズホルダー			J,U,C	030
"	LB 20 14 70	"	"			G	
15	KB 00 14 90	Fuse	10A 250V	ヒ ュ ー ズ	EMX150	J	010
"	KB 00 13 90	"	10A 250V	"	"	U,C	
"	KB 00 07 80	"	T5A 250V	"	"	G	
"	KB 00 13 00	"	7A 250V	"	EMX200,300	J	020
"	KB 00 15 20	"	7A 125V	"	"	U,C	
"	KB 00 07 90	"	T4A 250V	"	"	G	
16	Fi 38 41 00	Spark Suppressor	0.01 μ F 250V	ス パ ー ク キ ラ ー		J,U,C	010
17	CB 09 52 60	Capacitor Cover		コンデンサーカバー		J,U,C	010
18	EB 34 03 06	Flat Head Screw	4 $\times$ 30 Bl	皿 小 ネ ジ			010
19	ED 33 00 66	Bind Head Screw	3 $\times$ 6 Bl	バ イ ン ド 小 ネ ジ			010
20	ED 34 00 86	"	4 $\times$ 8 Bl	"			010
21	Ei 33 01 46	Bind Head Tapping Screw	3 $\times$ 14 Bl	バ イ ン ド タ ッ ピ ン グ ネ ジ			010
22	Ei 34 00 86	"	4 $\times$ 8 Bl	"			010
23	EM 23 00 86	Oval Head Tapping Screw	3 $\times$ 8 Cr	丸 皿 タ ッ ピ ン グ ネ ジ			010
24	CB 81 00 90	Insulation Nut		絶 縁 ナ ッ ト			010
25	EK 00 23 70	Washer		ファイバーワッシャー			010
26	LX 20 00 10	Plain Washer	9S Cr	特 殊 平 座 金			010
27	EV 41 30 36	Toothed Lock Washer	A3S Bl	歯 付 座 金			010
28	EV 41 30 46	"	A4S Bl	"			010
29	LX 20 00 60	Hexagonal Nut	9S Ni	特 殊 六 角 ナ ッ ト			010
30	LB 10 11 80	Housing		ハ ウ ジ ン グ	EMX200,300		010
31	LB 10 11 60	Receptacle		リ セ プ タ ク ル	"		010
32	LB 00 90 30	Connector Housing	3P	コ ネ ク タ ハ ウ ジ ン グ	XH		010
33	LB 40 08 20	"	4P	"	SM		010
34	LB 00 70 50	Housing	5P	ス ボ ッ ク ス ハ ウ ジ ン グ			010
35	LB 10 11 30	Contact Pin		コ ン タ ク ト ピ ン	XH		010
36	BB 00 44 30	"		"	SM		010
37	LB 10 10 00	Terminal		ス ボ ッ ク ス タ ー ミ ナ ル			010

※New Parts (新規部品)

ランク: Japan only

ELECTRICAL PARTS

Ref. No.	Part No.	Description	部 品 名	Remarks	Common Model	Markets	ランク
※	NA 81 23 10	Circuit Board, IN1	#90560	I N 1 シ ー ト			30*
※	NA 81 23 30	" , IN3	#90570	I N 3 シ ー ト	EMX150		22*
※	NA 81 23 20	" , IN2	#90560	I N 2 シ ー ト	EMX200,300		30*
※	HQ 40 02 50	Slide pot	A25kΩ	スライドボリューム	FADER		040
※	HS 31 22 80	Rotary pot	A25kΩ	ロータリーボリューム	FB1・2,ECHO		030
※	HS 31 22 90	"	ZY10kΩ	"	GAIN		030
※	HS 31 23 00	"	B50kΩ	"	HIGH,LOW		030
※	HS 31 23 10	"	B25kΩ	"	MID		030
※	HS 31 23 20	"	C100kΩ × 2	"	MID FREQ		040
※	HS 31 23 30	"	T・ZT20kΩ × 2	"	PAN		040
	iA 09 99 10	Transistor	2SA999(E,F)	ト ラ ン ジ ス タ			031
	iA 09 99 30	"	2SA999L	"			031
	iC 23 20 10	"	2SC2320(E,F)	"			031
	iF 00 11 90	LED	TLR124(Red)	L E D			020
	iG 00 13 90	IC	NJM4558DV	I C			030
※	KA 80 42 60	Push Switch		プッシュスイッチ	PAD		030
※	CB 83 09 70	Spacer,LED		L E D ス ペ ー サ ー			010
	CB 09 76 10	PC Support		P C サ ポ ー ト			010
	LB 91 90 30	Connector Base Pin	3P	2.5ピッチベースピン	XH		010
	LB 91 90 40	"	4P	"	"		010
	LB 90 90 60	"	6P	"	"		010
	LB 60 30 10	"	8P	"	NH		030
	LB 60 24 80	Connector Housing	8P	コネクタハウジング	NH		010
	BB 00 44 30	Contact Pin		コ ン タ ク ト ピ ン	NH		010
※	NA 81 23 40	Circuit Board, DL	#90600	D L シ ー ト			
	HT 41 00 40	Semi Variable Resistor	B4.7kΩ	半 固 定 抵 抗	BIAS		020
	HT 41 00 80	"	B22kΩ	"	CLOCK		020
	iA 09 99 10	Transistor	2SA999(E,F)	ト ラ ン ジ ス タ			031
	iC 23 20 10	"	2SC2320(E,F)	"			031
	iF 00 00 40	Diode	1S1555	ダ イ オ ー ド			010
	iG 03 12 00	IC	MN3005	I C			200
	iG 03 13 00	"	NE570N	"			080
	iG 03 75 00	"	MN3101	"			050
	LB 10 01 10	Test Point Pin		テストポイントピン			010
	LB 91 90 50	Connector Base Pin	5P	2.5ピッチベースピン	XH		010
	LB 91 90 90	"	9P	"	XH		020
※	NA 81 23 50	Circuit Board, MT1	#90610	M T 1 シ ー ト			09*
※	NA 81 23 70	" , MT3	#90610	M T 3 シ ー ト	EMX150		09*
※	NA 81 23 60	" , MT2	#90610	M T 2 シ ー ト	EMX200,300		09*
	iF 00 00 40	Diode	1S1555	ダ イ オ ー ド	MT1・3		010
	iF 00 56 40	"	0A95	"	MT2		010
	JB 00 02 30	Pilot Lamp	12V 60mA	パイロットランプ			030
	LB 60 30 10	Connector Base Pin	8P	2.5ピッチベースピン	NH		030
※	NA 81 23 80	Circuit Board, JI1	#90621	J I 1 シ ー ト			09*
※	NA 81 23 90	" , JI2	#90631	J I 2 シ ー ト			09*
※	LB 20 27 00	Phone Jack		ホ ー ン ジャ ッ ク			030
	LB 91 80 30	Connector Base Pin	3P	2.5ピッチベースピン	XH		010
	LB 91 80 60	"	6P	"	XH		010
	LB 91 80 70	"	7P	"	XH		010

※New Parts (新規部品)

ランク : Japan only

Ref. No.	Part No.	Description	部 品 名	Remarks	Common Model	Markets	ランク
※	NA 81 24 00	Circuit Board, MAS	# 90580	M A S シ ー ト			21 *
※	HS 31 22 80	Rotary Pot.	A25kΩ	ロータリーボリューム			030
※	HS 31 23 00	"	B50kΩ	"	DELAY TIME		030
※	HS 31 23 30	"	T-ZT20kΩ	"	AUX PAN		040
※	HQ 40 02 50	Slide Pot	A25kΩ	スライドボリューム	PGM L-R, FB1-2		040
	iG 00 13 90	IC	NJM4558DV	I C			030
	iG 04 25 00	"	NJM4556	"			040
	iG 06 92 00	"	NJM2041	"			050
※	LB 30 20 70	Phone Jack	Stereo	ホ ー ン ジャ ッ ク			030
	LB 91 80 50	Connector Base Pin	5P	2.5ピッチベースピン	XH		010
	LB 60 30 10	"	8P	"	NH		030
	LB 60 31 50	"	12P	"	"		030
※	NA 81 24 10	Circuit Board, MP	# 90641	M P シ ー ト			12 *
	LB 20 26 00	Phone Jack		ホ ー ン ジャ ッ ク			020
	BB 80 69 80	Terminal		タ ッ プ タ ー ミ ナ ル			030
	LB 91 90 30	Connector Base Pin	3P	2.5ピッチベースピン	XH		010
	LB 91 90 60	"	6P	"	"		010
	LB 91 90 70	"	7P	"	"		010
	LB 91 90 80	"	8P	"	"		020
	LB 91 91 00	"	10P	"	"		020
※	NA 81 24 20	Circuit Board, DC1	# 90480	D C 1 シ ー ト	EMX150	J	18 *
※	NA 81 24 30	"	# 90480	"	"	U,C	
※	NA 81 24 40	"	# 90490	"	"	G	
※	NA 81 24 50	Circuit Board, DC2	# 90480	D C 2 シ ー ト	EMX200,300	J	18 *
※	NA 81 24 60	"	# 90480	"	"	U,C	
※	NA 81 24 70	"	# 90490	"	"	G	
※	FZ 00 52 40	Metallized Mylar Cap.	0.1μF AC125V	メタライズドマイラーコン			03 *
※	Ui 99 83 30	Electrolytic Cap.	330μF 100V	ケ ミ コ ン			030
※	HM 07 46 80	Wire Wound Resistor	10pF 68V	セ メ ン ト 抵 抗			020
	iC 18 15 20	Transistor	2SC1815(Y)	ト ラ ン ジ ス タ			031
	iD 06 67 00	"	2SC667(C,D)	"			031
	iH 00 07 20	Diode	W03B	ダ イ オ ー ド			010
	iH 00 14 00	"	1G4B1	"			030
	iG 06 39 00	IC	μPC7815H	I C			050
	iG 07 75 00	"	μPC7915H	"			050
	KB 00 03 30	Fuse	1A 250V	ヒ ュ ー ズ		J	010
	KB 00 10 60	"	1A 250V	"		U,C	
	KB 00 07 30	"	T1A 250V	"		G	
	KB 00 07 10	"	T500mA 250V	"		G	
	KC 00 06 10	Relay	HB1 DC12V	リ レ ー			050
	CB 07 28 80	Insulation Bush		絶 縁 ブ ッ シ ュ			010
	iL 00 06 90	Mica Base		マ イ カ ベ ー ス			010
	CB 81 66 60	Wire Clip	S	ワイアークリップ			010
	CB 82 56 80	"	L	"			010
	LB 20 15 30	Fuse Holder Pin		ヒューズホルダーピン			010
	ED 32 60 86	Bind Head Screw	2.6×8 Ye	バインド小ネジ			010
	EV 20 30 36	Flat Washer	3S Ye	平 座 金			010
	Ei 33 00 86	Bind Head Tapping Screw	3×8 BI	バインドタッピングネジ			010
	EV 42 30 36	Toothed Lock Washer	B3S BI	歯 付 座 金			010
	LB 91 80 30	Connector Base Pin	3P	2.5ピッチベースピン	XH		010
	LB 91 80 60	"	6P	"	XH		010

※New Parts (新規部品)

ランク: Japan only

Ref. No.	Part No.	Description	部 品 名	Remarks	Common Model	Markets	ランク
	LB 91 81 00	Connector Base Pin	10P	2.5ピッチベースピン	XH		020
	LB 30 14 50	Connecton-Wafer	3P	コネクトコンウェハー			010
	LB 40 08 90	"	4P	"			020
※	NA 81 24 80	Circuit Board, AC	#90540	A C シ ー ト	EMX200,300	J	18*
※	NA 81 24 90	"	#90540	"	"	U,C	
※	NA 81 25 00	"	#90540	"	"	G	
※	FZ 00 52 30	Mylar Film Cap.	1.2 μ F	マイ ラ ー コ ン			030
※	FZ 00 52 40	"	0.1 μ F AC125V	"			030
※	FZ 00 52 50	"	0.22 μ F AC125V	"			040
	FQ 09 46 80	Paper Film Cap.	0.068 μ F 450V	オ イ ル コ ン			040
	FR 15 54 70	Metallized Paper Cap.	0.47 μ F AC250V	M P コ ン			060
	FR 16 36 80	"	6800pF AC250V	"			030
※	HV 85 41 50	Flame Proof Carbon Resistor	15 Ω 1/2W	不 燃 化 カ ー ボ ン 抵 抗			010
※	HV 85 81 50	"	150k Ω 1/2W	"		U,C	
※	HV 85 82 20	"	220k Ω 1/2W	"		J	010
※	HV 85 84 70	"	470k Ω 1/2W	"		G	
※	HZ 00 44 30	Metal Oxide Film Resistor	150k Ω 2 W	酸 金 被 膜 抵 抗		G	
※	HM 07 63 30	Wire Wound Resistor	3.3k Ω 10W	セ メ ン ト 抵 抗		J,U,C	020
※	HM 07 71 50	"	15k Ω 10W	"		G	
※	GE 90 14 00	Coil	80 μ H	ト ロ イ ダ ル コ イ ル		J,U,C	070
※	GE 90 14 10	"	270 μ H	"		G	
※	iA 13 21 00	Transistor	2SA1321	ト ラ ン ジ ス タ			031
※	iC 33 34 00	"	2SC3334	"			031
	iF 00 00 40	Diode	1S1555	ダ イ オ ー ド			010
	iF 00 14 00	"	1SS82	"			020
	iH 00 00 60	"	10D4	"			010
※	iH 00 14 40	"	SM25GZ41	"		J,U,C	080
※	iH 00 14 50	"	SM16JZ41	"		G	
※	iF 00 33 40	Zener Diode	RD8.2EB2	ツ ェ ナ ー ダ イ オ ー ド			010
※	iF 10 56 90	"	RD16EB1	"			010
※	iG 12 01 00	IC	BS08A	I C			031
	LA 00 44 00	Terminal		フ ェ ス ト ン 端 子			010
	ED 33 01 26	Bind Head Screw	3 $\times$ 12 BI	バ イ ン ド 小 ネ ジ			010
	EV 30 33 06	Spring Washer	3S	バ ネ 座 金			010
	EV 10 30 36	Hexagonal Nut	M3	六 角 ナ ッ ト			01Q
※	NA 81 25 10	Circuit Board, MA1	#90460	M A 1 シ ー ト	EMX150		31*
※	NA 81 25 20	" MA2	#90470	M A 2 シ ー ト	EMX200,300		36*
	UW 63 74 70	Electrolytic Cap.	47 μ F 16V	ケ ミ コ ン			010
	UW 63 81 00	"	100 μ F 16V	"			010
	UW 55 74 70	"	47 μ F 35V	"	MA2		010
	UW 67 82 20	"	220 μ F 63V	"	MA1		030
	UJ 28 82 20	"	220 μ F 80V	"	"		030
※	Ui 99 83 30	"	330 μ F 100V	"	MA2		030
	UK 73 82 20	Bipolar Electrolytic Cap.	220 μ F 16V	B P コ ン			020
	UK 74 81 00	"	100 μ F 25V	"			020
	UK 16 63 30	"	3.3 μ F 50V	"			010
	FU 35 13 30	Mica Cap.	33pF 500V	F E マ イ カ コ ン	MA2		010
	FU 35 14 70	"	47pF 500V	"	MA1		010
※	FU 35 16 80	"	68pF	"	MA2		020
	FT 55 14 70	Polypropylene Film Cap.	47pF 50V	ポ リ プ ロ コ ン			030
	FT 55 16 80	"	68pF 50V	"	MA1		030

※New Parts (新規部品)

ランク : Japan only

Ref. No.	Part No.	Description	部 品 名	Remarks	Common Model	Markets	ランク
	FT 55 21 00	Polypropylene Film Cap.	100pF 50V	ポ リ プ ロ コ ン			030
	FT 55 22 20	"	220pF 50V	"	MA1		030
	FT 55 24 70	"	470pF 50V	"	MA2		030
	FT 55 25 60	"	560pF 50V	"			030
※	FZ 00 52 00	Metalized Mylar Cap.	0.1 μ F 100V	M M コ ン			010
※	FZ 00 52 10	"	0.22 μ F 100V	"			020
※	FZ 00 52 20	"	0.47 μ F 100V	"			020
	HV 35 51 00	Flame Proof Carbon Resistor	100 Ω	不 燃 化 カ ー ボ ン 抵 抗			010
	HV 35 52 20	"	220 Ω	"	MA2		010
	HV 35 52 70	"	270 Ω	"	"		010
	HV 35 55 60	"	560 Ω	"	"		010
※	HV 35 63 00	"	3k Ω	"			010
	HL 31 34 70	Metal Oxide Film Resistor	4.7 Ω 1W	酸 金 被 膜 抵 抗			010
	HL 31 41 00	"	10 Ω 1W	"			010
	HL 31 48 20	"	82 Ω 1W	"	MA2		010
	HL 31 51 00	"	100 Ω 1W	"	MA1		010
	HL 31 64 70	"	4.7k Ω 1W	"	"		010
	HL 31 66 80	"	6.8k Ω 1W	"	MA2		010
	HL 31 68 20	"	8.2k Ω 1W	"	MA1		010
	HL 32 34 70	"	4.7 Ω 2W	"			010
	HU 57 52 70	Metal Film Resistor	270 Ω	金 属 被 膜 抵 抗			020
	HU 57 71 20	"	12k Ω	"			020
※	HZ 00 35 50	Cement Resistor	10 Ω 5W	セ メ ン ト 抵 抗			020
※	HZ 00 35 60	"	270 Ω 5W	"	MA2		020
※	HZ 00 36 00	"	0.47 Ω 5W	"	"		021
	HZ 00 38 70	"	220 Ω 5W	"	MA1		020
	HZ 00 39 50	"	0.33 Ω 5W	"	"		021
	HT 41 01 20	Semi Variable Resistor	B470 Ω	半 固 定 抵 抗			020
	GD 90 03 40	Coil	1.5 μ H	コ イ ル	MA1		021
※	GD 90 05 80	"	1.6 μ H	"	MA2		010
	iA 09 68 00	Transistor	2SA968(O,Y)	ト ラ ン ジ ス タ			041
	iA 09 70 00	"	2SA970(GR,BL)	"			031
	iA 09 79 10	"	2SA979(G)	"	MA2		031
	iA 09 95 00	"	2SA995(G)	"	MA2		031
	iA 11 06 00	"	2SA1106(O,Y)	"			060
	iA 11 44 00	"	2SA1144(O,Y)	"			031
	iC 18 15 30	"	2SC1815(GR)	"			031
	iC 19 53 40	"	2SC1953(R)	"	MA1		041
	iC 22 38 00	"	2SC2238(O,Y)	"			041
	iC 22 40 00	"	2SC2240(GR,BL)	"			031
	iC 22 59 00	"	2SC2259(F,G)	"	MA1		031
	iC 25 81 00	"	2SC2581(O,Y)	"			061
	iC 27 04 00	"	2SC2704(O,Y)	"	MA1		030
※	iC 22 91 00	"	2SC2291(G)	"	MA2		031
※	iC 27 04 00	"	2SC2704(O,Y)	"	"		030
	iD 06 67 10	"	2SD667(B,C)	"			030
	iF 00 06 70	Diode	1S2473	ダ イ オ ー ド	MA1		010
	iF 00 06 70	"	1S2473	"	MA2		010
	iF 00 14 00	"	1SS82	"			020
	iH 00 00 30	"	10D1	"			010
※	iF 00 56 70	Zener Diode	RD24EB2	ツ ェ ナ ー ダ イ オ ー ド			010
※	iF 00 61 90	LED	LTZ-R17	L E D			010
	iF 00 04 50	Varistor Diode	STV-3H	バ リ ス タ	MA2		040

※ New Parts (新規部品)

ランク: Japan only

ランク : Japan only

EMX150 SCHEMATIC DIAGRAM 2/2

Lch Power Amp

Rch Power Amp
Same as Lch

Component Values:

T1501, 601	25C2259F(G)	T1506, 514, 515, 606	25C2240(GR, BL)	T1510, 514, 610, 611	25A259810, Y)	L501, 502, 601, 602		L12, R17
T1502, 503, 602, 603	25A1144(0, Y)	T1507, 516, 607	25A970(GR, BL)	T1512, 515, 612, 613	25A1106(0, Y)	D501-503, 505, 507, 508, 601-603, 605, 607, 608		IS2473
T1504, 604	25C2704	T1508, 608	25C2238(0, Y)	T1517	25C1815(0, R)	D505, 509-512, 606, 609-612		
T1505, 605	25C1953	T1509, 609	25A968(0, Y)	T1518	25C6678(0, C)			

Component Types:

T1501, 601	25C2259F(G)	T1506, 514, 515, 606	25C2240(GR, BL)	T1510, 514, 610, 611	25A259810, Y)	L501, 502, 601, 602		L12, R17
T1502, 503, 602, 603	25A1144(0, Y)	T1507, 516, 607	25A970(GR, BL)	T1512, 515, 612, 613	25A1106(0, Y)	D501-503, 505, 507, 508, 601-603, 605, 607, 608		IS2473
T1504, 604	25C2704	T1508, 608	25C2238(0, Y)	T1517	25C1815(0, R)	D505, 509-512, 606, 609-612		
T1505, 605	25C1953	T1509, 609	25A968(0, Y)	T1518	25C6678(0, C)			


The schematic diagram illustrates the internal circuitry of a vintage radio receiver, organized into several functional sections:

- MAS (Master Audio Section):** Features a 6X4 tube (VU961) and a 6X5 tube (VU962) for audio processing. It includes a 12V 60mA power supply and various capacitors and resistors.
- MT1 (Tuner/Mixer Section):** Contains a 6X4 tube (VU961) and a 6X5 tube (VU962) for tuning and mixing. It includes a 12V 60mA power supply and various capacitors and resistors.
- DC2 (Detector/AF Amplifier Section):** Features a 6X4 tube (VU961) and a 6X5 tube (VU962) for detection and audio frequency amplification. It includes a 12V 60mA power supply and various capacitors and resistors.
- AC (Audio Amplifier Section):** Contains a 6X4 tube (VU961) and a 6X5 tube (VU962) for audio amplification. It includes a 12V 60mA power supply and various capacitors and resistors.
- CO2 (Cathode Ray Section):** Features a 6X4 tube (VU961) and a 6X5 tube (VU962) for cathode ray operation. It includes a 12V 60mA power supply and various capacitors and resistors.
- DI2 (Detector/AF Amplifier Section):** Contains a 6X4 tube (VU961) and a 6X5 tube (VU962) for detection and audio frequency amplification. It includes a 12V 60mA power supply and various capacitors and resistors.

The diagram also shows the power supply section, including a 12V 60mA power supply and a 12V 60mA power supply. It includes various components like capacitors, resistors, and a speaker.

	R701	R702	R703	R704	R705	R706	R709	R712	R713	R714	R717	R718	R719	R720	J701	J702	C701	C702	C703	C704	C705	C710		L701	D710	F801	F803	F804	F8
JAPANESE	X	X	1/2P 220K	X	X	1K	2P56K	13K	2.2K	8.2K	10P3.3K	X	○	X	○	X	330P 1AC25	0.22 1AC25	0.1 1AC125	0.1 1AC125	80μH	SM25 J241	1A	250V	1A	250V	1A	250V	1A
US & CANADIAN	X	X	1/2P 150K	X	X	680	2P 68K	10K	1.5K	8.2K	10P3.3K	X	○	X	○	X	330P 1AC125	0.22 1AC125	0.1 1AC125	0.1 1AC125	80μH	SM25 J241	1A	250V	1A	250V	1A	250V	1A
GENERAL	1/2P 470K	1/2P 470K	1/2P 470K	2P22K	680	2P150K	12K	2.2K	10K	10P15K	10P15K	X	680P 1AC250	680P 1AC250	0.47 1AC25	X	0.068 1AC250	0.068 1AC250	250V	SM16 -J241	T1A	250V	T500mA	250V	T1	250V	T1	250V	T1

Q:




* Schematic diagram is subject to change without notice

※本回路図は、改良のため予告なく変更することがあります。

• **WIRE COLOR ABBREVIATIONS**
BE ▶ Blue BR ▶ Brown GY ▶ Gray PK ▶ Pink SB ▶ Sky Blue WH ▶ White
BL ▶ Black GR ▶ Green OR ▶ Orange RE ▶ Red VI ▶ Violet YE ▶ Yellow

■ SCHEMATIC DIAGRAM (総回路図) 1/2



* Schematic diagram is subject to change without notice.
* 本回路図は、改良のため予告なく変更することがあります。