AV RECEIVER/AV AMPLIFIER

RX-V3900/DSP-AX3900

SERVICE MANUAL

IMPORTANT NOTICE

This manual has been provided for the use of authorized YAMAHA Retailers and their service personnel.
It has been assumed that basic service procedures inherent to the industry, and more specifically YAMAHA Products, are already known and understood by the users, and have therefore not been restated.

WARNING: Failure to follow appropriate service and safety procedures when servicing this product may result in personal injury, destruction of expensive components, and failure of the product to perform as specified. For these reasons, we advise all YAMAHA product owners that any service required should be performed by an authorized YAMAHA Retailer or the appointed service representative.

IMPORTANT: The presentation or sale of this manual to any individual or firm does not constitute authorization, certification or recognition of any applicable technical capabilities, or establish a principle-agent relationship of any form.

The data provided is believed to be accurate and applicable to the unit(s) indicated on the cover. The research, engineering, and service departments of YAMAHA are continually striving to improve YAMAHA products. Modifications are, therefore, inevitable and specifications are subject to change without notice or obligation to retrofit. Should any discrepancy appear to exist, please contact the distributor's Service Division.

WARNING: Static discharges can destroy expensive components. Discharge any static electricity your body may have accumulated by grounding yourself to the ground buss in the unit (heavy gauge black wires connect to this buss).

IMPORTANT: Turn the unit OFF during disassembly and part replacement. Recheck all work before you apply power to the unit.

■ CONTENTS

TO SERVICE PERSONNEL 2–3
FRONT PANELS 3–4
REAR PANELS 5–8
REMOTE CONTROL PANELS 9
SPECIFICATIONS / 参考仕様 10–15
INTERNAL VIEW 16
DISASSEMBLY PROCEDURES / 分解手順 17–25
UPDATING FIRMWARE /
ファームウェアの書き込み 26–29
SELF-DIAGNOSTIC FUNCTION /
ダイアグ（自己診断機能）.....30–82
AMP ADJUSTMENT / アンプ部調整 83
DISPLAY DATA 84–85
IC DATA 86–103
BLOCK DIAGRAMS 104–108
PIN CONNECTION DIAGRAMS 109–111
PRINTED CIRCUIT BOARDS 112–143
SCHEMATIC DIAGRAMS 145–170
REPLACEMENT PARTS LIST 171–212
REMOTE CONTROL 213–216
ADVANCED SETUP / 本機の設定を変更する 217–224

このサービスマニュアルは、エコマーク認定の再生紙を使用しています。
This Service Manual uses recycled paper.

101115


Copyright © 2008 YAMAHA CORPORATION All rights reserved.
This manual is copyrighted by YAMAHA and may not be copied or redistributed either in print or electronically without permission.

YAMAHA
YAMAHA CORPORATION
P.O.Box 1, Hamamatsu, Japan
animate '08.10

■ TO SERVICE PERSONNEL

1. Critical Components Information
   Components having special characteristics are marked ⚠ and must be replaced with parts having specifications equal to those originally installed.
2. Leakage Current Measurement (For 120V Models Only)
   When service has been completed, it is imperative to verify that all exposed conductive surfaces are properly insulated from supply circuits.

- Meter impedance should be equivalent to 1500 ohms shunted by 0.15 µF.



- Leakage current must not exceed 0.5mA.
- Be sure to test for leakage with the AC plug in both polarities.



"CAUTION"

"F1: FOR CONTINUED PROTECTION AGAINST RISK OF FIRE, REPLACE ONLY WITH SAME TYPE 10A, 125V FUSE."

"F2: FOR CONTINUED PROTECTION AGAINST RISK OF FIRE, REPLACE ONLY WITH SAME TYPE 4A, 125V FUSE."

CAUTION

F1: REPLACE WITH SAME TYPE 10A, 125V FUSE.
F2: REPLACE WITH SAME TYPE 4A, 125V FUSE.

ATTENTION

F1: UTILISER UN FUSIBLE DE RECHANGE DE MÉME TYPE DE 10A, 125V.
F2: UTILISER UN FUSIBLE DE RECHANGE DE MÉME TYPE DE 4A, 125V.

WARNING: CHEMICAL CONTENT NOTICE!

This product contains chemicals known to the State of California to cause cancer, or birth defects or other reproductive harm.

DO NOT PLACE SOLDER, ELECTRICAL/ELECTRONIC OR PLASTIC COMPONENTS IN YOUR MOUTH FOR ANY REASON WHATSOEVER!

Avoid prolonged, unprotected contact between solder and your skin! When soldering, do not inhale solder fumes or expose eyes to solder/flux vapor!

If you come in contact with solder or components located inside the enclosure of this product, wash your hands before handling food.

About lead free solder / 無鉛ハンダについて

All of the P.C.B.s installed in this unit and solder joints are soldered using the lead free solder.

Among some types of lead free solder currently available, it is recommended to use one of the following types for the repair work.

- Sn + Ag + Cu (tin + silver + copper)
- Sn + Cu (tin + copper)
- Sn + Zn + Bi (tin + zinc + bismuth)

Caution:

As the melting point temperature of the lead free solder is about 30°C to 40°C (50°F to 70°F) higher than that of the lead solder, be sure to use a soldering iron suitable to each solder.

本機に搭載されているすべての基板およびハンダ付けによる接合部は無鉛ハンダでハンダ付けされています。

無鉛ハンダにはいくつかの種類がありますが、修理時には下記のような無鉛ハンダの使用を推奨します。

- Sn+Ag+Cu（錫＋銀＋銅）
- Sn+Cu（錫＋銅）
- Sn+Zn+Bi（錫＋亜鉛＋ビスマス）

注意：

無鉛ハンダの融点温度は通常の鉛入りハンダに比べ 30 ～ 40℃程度高くなっていますので、それぞれのハンダに合ったハンダごてをご使用ください。

WARNING: Lithium batteries

CAUTION

Danger of explosion if battery is incorrectly replaced. Replace only with the same or equivalent type.

WARNING: Lithium batteries are dangerous because they can be exploded by improper handling. Observe the following precautions when handling or replacing lithium batteries.

- Leave lithium battery replacement to qualified service personnel.
- Always replace with batteries of the same type.
- When installing on the PC board by soldering, solder using the connection terminals provided on the battery cells. Never solder directly to the cells. Perform the soldering as quickly as possible.
- Never reverse the battery polarities when installing.
- Do not short the batteries.
- Do not attempt to recharge these batteries.
- Do not disassemble the batteries.
- Never heat batteries or throw them into fire.

注意

正しい電池と交換しないと爆発が起きるおそれがあります。
同一型名または同等品以外の電池とは絶対に交換しないようにしてください。

ADVARSEL!

Lithiumbatteri –Eksplosionsfare ved fejlagtig håndtering. Udskiftning må kun ske med batteri af samme fabrikat og type. Levér det brugte batteri tilbage til leverandøren.

VARNING


Explosionsfara vid felaktigt batteribyte. Använd samma batterityp eller an ekvivalent typ som rekommenderas av apparattillverkaren. Kassera använt batteri enligt fabrikantens instruktion.

VAROITUS


Paristo voi räjähtää, jos se on virheellisesti asennettu. Vaihda paristo ainoastaan laitevalmistajan suosittelemaan tyyppiin. Hävitä käytetty peristo valmistajan ohjeiden mukaisesti.

■ FRONT PANELS


RX-V3900 (U, C models)



RX-V3900 (R, T, K, A, B, G, E, L models)




DSP-AX3900 (J model)




■ REAR PANELS


RX-V3900 (U model)




RX-V3900 (C model)




RX-V3900 (R model)




RX-V3900 (T model)




RX-V3900 (K model)




RX-V3900 (A model)




RX-V3900 (B model)




RX-V3900 (G, E models)



RX-V3900 (L model)




DSP-AX3900 (J model)




■ REMOTE CONTROL PANELS


RAV386
RX-V3900 (U, C models)




RAV388
RX-V3900 (R, T, K, A, B, G, E, L models)



RAV387
DSP-AX3900 (J model)



RAV36
RX-V3900 (U, C, R, T, K, A, B, G, E, L models)



■ SPECIFICATIONS / 参考仕様

■ Audio Section / オーディオ部

Minimum RMS Output Power (Power Amp. Section) / 定格出力 (パワーアンプ部) (20 Hz to 20 kHz)
FRONT L/R
U, C, R, T, K, A, B, G, E, L models (0.04 % THD, 8 ohms) ..... 140 W + 140 W
J model (0.06 % THD, 6 ohms) ..... 140 W + 140 W
CENTER
U, C, R, T, K, A, B, G, E, L models (0.04 % THD, 8 ohms) ..... 140 W
J model (0.06 % THD, 6 ohms) ..... 140 W
SURROUND L/R
U, C, R, T, K, A, B, G, E, L models (0.04 % THD, 8 ohms) ..... 140 W + 140 W
J model (0.06 % THD, 6 ohms) ..... 140 W + 140 W
SURROUND BACK L/R
U, C, R, T, K, A, B, G, E, L models (0.04 % THD, 8 ohms) ..... 140 W + 140 W
J model (0.06 % THD, 6 ohms) ..... 140 W + 140 W

Maximum Power / 実用最大出力 (JEITA, 1 kHz, 10 % THD)
FRONT L/R
R, T, K, L models (8 ohms) ..... 185 W + 185 W
J model (6 ohms) ..... 185 W + 185 W
CENTER
R, T, K, L models (8 ohms) ..... 185 W
J model (6 ohms) ..... 185 W
SURROUND L/R
R, T, K, L models (8 ohms) ..... 185 W + 185 W
J model (6 ohms) ..... 185 W + 185 W
SURROUND BACK L/R
R, T, K, L models (8 ohms) ..... 185 W + 185 W
J model (6 ohms) ..... 185 W + 185 W

Dynamic Power Per Channel (IHF)
FRONT L/R (8/6/4/2 ohms)
U, C, R, T, K, A, L models ..... 170/205/265/345 W

Max. Power Per Channel (1 kHz, 0.7 % THD, 4 ohms)
[B, G, E models]
FRONT L/R ..... 200 W + 200 W
CENTER ..... 200 W
SURROUND L/R ..... 200 W + 200 W
SURROUND BACK L/R ..... 200 W + 200 W

Dynamic Headroom [U, C, R, T, K, A, L models]
8 ohms ..... 0.84 dB

IEC Power (1 kHz, 0.04 % THD, 8 ohms) [B, G, E models]
FRONT L/R ..... 145 W + 145 W

Damping Factor / ダンピングファクタ (1 kHz, 8 ohms)
FRONT L/R ..... 150 or more

Input Sensitivity/Input Impedance / 入力感度／入力インピーダンス
(1 kHz, 100 W/8 ohms)
PHONO (MM) ..... 3.5 mV / 47 k-ohms
CD, etc. ..... 200 mV / 47 k-ohms
MULTI CH INPUT
FRONT L/R, CENTER, SURROUND L/R, SUBWOOFER ..... 200 mV / 47 k-ohms

Maximum Input Signal Level / 最大許容入力
PHONO (MM) (1 kHz, 0.1 % THD) ..... 60 mV or more
CD, etc. (1 kHz, 0.5 % THD) ..... 2.4 V or more

Output Level/Output Impedance / 出力電圧／出力インピーダンス
REC OUT ..... 200 mV / 900 ohms
PRE OUT (FRONT L/R, CENTER, SURROUND L/R, SURROUND BACK L/R) ..... 1.0 V / 500 ohms
SUBWOOFER (20 Hz) ..... 1.0 V / 1.2 k-ohms
[U, C, R, T, K, A, B, G, E, L models]
ZONE 2 OUT ..... 1.0 V / 1.4 k-ohms
ZONE 3 OUT ..... 1.0 V / 1.4 k-ohms

Headphone Jack Rated Output/Impedance / ヘッドフォン出力／出力インピーダンス (1 kHz, 40 mV, 8 ohms)
CD, etc. ..... 150 mV / 100 ohms

Frequency Response / 周波数特性 (10 Hz to 100 kHz)
CD, etc. to FRONT L/R (Pure direct) ..... +0/-3 dB

RIAA Equalization Deviation / RIAA 偏差 (20 Hz to 20 kHz)
PHONO (MM) ..... 0 ±0.5 dB

Total Harmonic Distortion / 全高調波歪率 (20 Hz to 20 kHz)
PHONO (MM) to REC OUT (1 V) ..... 0.02 % or less
CD, etc. to FRONT L/R SP OUT (70 W, 8 ohms) ..... 0.04 % or less

Signal to Noise Ratio / 信号対雑音比 (IHF-A network)
PHONO (MM) (Input shorted) to SP OUT
U, C, R, T, K, L models (5 mV) ..... 86 dB or more
A, B, G, E models (5 mV) ..... 81 dB or more
J model (2.5 mV) ..... 80 dB or more
CD, etc. (Input shorted) to SP OUT
250 mV ..... 100 dB or more

Residual Noise / 残留ノイズ (IHF-A network)
FRONT L/R SP OUT ..... 150 µV or less

Channel Separation / チャンネルセパレーション (1 kHz/10 kHz)
PHONO (Input shorted) ..... 60 dB or more/55 dB or more
CD, etc. (Input 5.1 k-ohms shorted) ... 60 dB or more/45 dB or more

Tone Control Characteristics / トーンコントロール特性
BASS
Boost/Cut ..... ±6 dB (50 Hz)
Turnover frequency ..... 350 Hz
TREBLE
Boost/Cut ..... ±6 dB (20 kHz)
Turnover frequency ..... 3.5 kHz

ZONE2, ZONE3 Tone Control Characteristics
[U, C, R, T, K, A, B, G, E, L models]
BASS
Boost/Cut ..... ±10 dB (100 Hz)
Turnover frequency ..... 450 Hz
TREBLE
Boost/Cut ..... ±10 dB (10 kHz)
Turnover frequency ..... 2.0 kHz

Filter Characteristics / フィルター特性
FRONT, CENTER, SURROUND, SURROUND BACK small (H.P.F.)
..... fc=40/60/80/90/100/110/120/160/200 Hz, 12 dB/oct.
SUBWOOFER (L.P.F.)
..... fc=40/60/80/90/100/110/120/160/200 Hz, 24 dB/oct.

■ Video Section / ビデオ部

Video Signal Type / ビデオ信号方式
Monitor out (Wall paper) / モニターアウト（壁紙）
U, C, R, K, J models ..... NTSC/PAL
T, A, B, G, E, L models ..... PAL/NTSC
Video conversion / ビデオコンバージョン
..... NTSC/PAL
Zone out (Gray back)
U, C, R, K models ..... NTSC
T, A, B, G, E, L models ..... PAL

Composite Video Signal Level / コンポジットビデオ信号
..... 1 Vp-p / 75 ohms

S-Video Signal Level / S ビデオ信号
Y ..... 1 Vp-p / 75 ohms
C (NTSC) ..... 0.286 Vp-p / 75 ohms
(PAL) ..... 0.3 Vp-p / 75 ohms

Component Video Signal Level / コンポーネントビデオ信号
Y ..... 1 Vp-p / 75 ohms
Pb/Pr ..... 0.7 Vp-p / 75 ohms

Maximum Input Level / 最大許容入力
VIDEO CONV. OFF ..... 1.5 Vp-p or more

Signal to Noise Ratio / 信号対雑音比
VIDEO CONV. OFF ..... 60 dB or more

Monitor Out Frequency Response / モニターアウト周波数帯域
(VIDEO CONV. OFF)
Component video signal ..... 5 Hz to 100 MHz, ±3 dB
[J model]
D5-video signal ..... 5 Hz to 100 MHz, ±3 dB

■ FM Section / FM 部

Tuning Range / 受信周波数範囲
U, C models ..... 87.5 to 107.9 MHz
R, L models ..... 87.5 to 108.0 / 87.50 to 108.00 MHz
T, K, A, B, G, E models ..... 87.50 to 108.00 MHz
J model ..... 76.0 to 90.0 MHz

50dB Quieting Sensitivity / 50 dB SN 感度 (IHF)
(1 kHz, 100 % MOD.)
Mono ..... 2.0 µV (17.3 dBf)
Stereo ..... 25 µV (39.2 dBf)

Usable Sensitivity / 実用感度 (IHF)
Mono ..... 1.0 µV (11.2 dBf)

Selectivity / 選択度
at 400 kHz ..... 70 dB

Signal to Noise Ratio / 信号対雑音比 (IHF)
Mono ..... 76 dB
Stereo ..... 70 dB

Harmonic Distortion / 歪率 (1 kHz)
Mono ..... 0.2 %
Stereo ..... 0.3 %

Stereo Separation / ステレオセパレーション
..... 42 dB

Frequency Response / 周波数特性 (20 Hz to 15 kHz)
..... +0.5 / -2 dB

Antenna Input / アンテナ入力
..... 75 ohms unbalanced

■ AM Section / AM 部

Tuning Range / 受信周波数範囲
U, C models ..... 530 to 1,710 kHz
R, L models ..... 530 to 1,710 / 531 to 1,611 kHz
T, K, A, B, G, E, J models ..... 531 to 1,611 kHz

Usable Sensitivity / 実用感度 ..... 300 µV/m

Antenna Input / アンテナ入力 ..... Loop Antenna

■ General / 総合

Power Supply / 電源電圧
U, C models ..... AC 120 V, 60 Hz
R, L models ..... AC 110/120/220/230-240 V, 50/60 Hz
T model ..... AC 220 V, 50 Hz
K model ..... AC 220 V, 60 Hz
A model ..... AC 240 V, 50 Hz
B, G, E models ..... AC 230 V, 50 Hz
J model ..... AC 100 V, 50/60 Hz

Power Consumption / 消費電力
U, C models ..... 500 W / 630 VA
R, T, K, A, B, G, E, L models ..... 500 W
J model ..... 400 W

Standby Power Consumption (reference data) / 待機時消費電力 (参考値)
Advanced setup – wake on RS232C access: OFF
Setup (J model) – HDMI control: OFF
U, C, T, K, A, B, G, E, L, J models ..... 0.1 W or less
R model (AC 240 V / 50 Hz) ..... 0.33 W or less

Maximum Power Consumption (6ch drive, 10 % THD) [R model]
..... 1100 W

AC Outlets / AC アウトレット
2 switched outlets
U, C models ..... 100 W max. total / 0.8 A max. total
R model ..... 50 W max. total / 0.2 A max. total
T, L models ..... 50 W max. total
G, E models ..... 100 W max. total / 0.4 A max. total
J model ..... 100 W max. total
1 switched outlet
A model ..... 100 W max.
B model ..... 100 W max. / 0.4 A max.

Dimensions (W x H x D) / 寸法（幅 × 高さ × 奥行き）
..... 435 x 181 x 438.5 mm (17-1/8" x 7-1/8" x 17-1/4")

Weight / 質量
[RX-V3900]
U, C, R, K, A, B, G, E, L models ..... 17.4 kg (38 lbs. 6 oz.)
T model ..... 19.0 kg (41 lbs. 14 oz.)
[DSP-AX3900]
J model ..... 18.8 kg (41 lbs. 7 oz.)

Finish / 仕上げ
[RX-V3900]
Gold color ..... R, T, K models
Black color ..... U, C, R, T, A, B, G, E, L models
Titanium color ..... R, G, E, L models
[DSP-AX3900]
Gold color ..... J model
Black color ..... J model

Accessories / 付属品
Remote control ..... x 1
Simplified remote control (U, C, R, T, K, A, B, G, E, L models) ..... x 1
Batteries (LR03, AAA, UM-4) ..... x 4
Lithium battery (CR2025) (U, C, R, T, K, A, B, G, E, L models) ..... x 1
Indoor FM antenna (1.4 m) ..... x 1
AM loop antenna (1.2 m) (U model) ..... x 1
(1.0 m) (C, R, T, K, A, B, G, E, L, J models) ..... x 1
Power cable (2 m) (U, C, R, T, K, A, B, G, E, J models) ..... x 1
(L model) ..... x 2
Optimizer microphone (6 m) ..... x 1
Ferrite core for AM loop antenna (U model) ..... x 1
Binding tie for AM loop antenna (U model) ..... x 1

*** Specifications are subject to change without notice due to product improvements.**

※ 参考仕様および外観は予告なく変更されることがあります。

U ..... ***U.S.A. model***
C ..... ***Canadian model***
R ..... ***General model***
T ..... ***Chinese model***
K ..... ***Korean model***
A ..... ***Australian model***
B ..... ***British model***
G ..... ***European model***
E ..... ***South European model***
L ..... ***Singapore model***
J ..... ***Japanese model***

DOLBY TRUEHD
Manufactured under license from Dolby Laboratories.
Dolby and the double-D symbol are registered trademarks of Dolby Laboratories.
ドルビーラボラトリーズからの実施権に基づき製造されています。「ドルビー」、「PRO LOGIC」、「Surround EX」 およびダブル D 記号 は、ドルビーラボラトリーズの商標です。

dts-HD Master Audio
DTS is a registered trademark and the DTS logos, Symbol, DTS-HD and DTS-HD Master Audio are trademark of DTS, Inc.
DTS は DTS 社の登録商標です。また、DTS ロゴ、記号、および DTS-HD、DTS-HD Master Audio は DTS 社の商標です。

iPod™
"iPod" is a trademark of Apple Inc., registered in the U.S. and other countries.
iPod は、米国およびその他の国々で登録された Apple Inc. の商標または登録商標です。

Fraunhofer Institut Integrierte Schaltungen
MPEG Layer-3 audio coding technology licensed from Fraunhofer IIS and Thomson.
MPEG Layer 3 音声圧縮技術は Fraunhofer IIS および Thomson によってライセンス供与されています。

This receiver supports network connections.
本機はネットワーク接続に対応しています。

"HDMI", the "HDMI" logo and "High-Definition Multimedia Interface" are trademarks, or registered trademarks of HDMI Licensing LLC.
HDMI、HDMI ロゴ、および High-Definition Multimedia Interface は、HDMI Licensing, LLC の商標または登録商標です。

x.v.Color™
"x.v.Color" is a trademark of Sony Corporation.
「x.v.Color」は、ソニー株式会社の商標です。

SILENT ™
CINEMA
"SILENT CINEMA" is a trademark of Yamaha Corporation.
「サイレントシネマ ™ SILENT CINEMA™」はヤマハ株式会社の登録商標です。

The XM name and related logos are registered trademarks of XM Satellite Radio Inc.

This product is manufactured under license from Neural Audio Corporation and THX Ltd. YAMAHA CORPORATION hereby grants the user a non-exclusive, non-transferable, limited right of use to this product under U.S.A. and foreign patent, patent pending and other technology or trademarks owned by Neural Audio Corporation and THX Ltd. "Neural Surround", "Neural Audio", "Neural" and "NRL" are trademarks and logos owned by Neural Audio Corporation. THX is a trademark of THX Ltd., which may be registered in some jurisdictions. All rights reserved.

©2006 SIRIUS Satellite Radio Inc. "SIRIUS", "SiriusConnect", the SIRIUS dog logo, channel names and logos are trademarks of SIRIUS Satellite Radio Inc.

HD Radio™ Technology Manufactured Under License From iBiquity Digital Corp. U.S. and Foreign Patents. HD Radio™ and the HD Radio logo are proprietary trademarks of iBiquity Digital Corp.


Rhapsody and the Rhapsody logo are registered trademarks of RealNetworks, Inc.

Circle Surround II, Dialog Clarity, TruBass, SRS and the (●) symbol are trademarks of SRS Labs, Inc.
Circle Surround II, Dialog Clarity and TruBass technologies are incorporated under license from SRS Labs, Inc.
Circle Surround II、FOCUS、TruBass、SRS と (●) 記号は SRS Labs, Inc. の商標です。Circle Surround II、FOCUS と TruBass 技術は SRS Labs, Inc. からのライセンスに基づき製品化されています。

Windows XP, Windows Vista, Windows Media Audio, Windows Media Connect and Windows Media Player are either registered trademarks or trademarks of Microsoft corporation in the United States and/or other countries.
Windows XP、Windows Vista、Windows Media Audio、Windows Media Connect、Windows Media player は、米国 Microsoft Corporation の米国およびその他の国における登録商標、または商標です。

AAC ロゴマーク はドルビーラボラトリーズの商標です。

- **DIMENSIONS / 寸法図**



Unit: mm (inch)
単位：mm（インチ）

• SELECT MENU

Category	Sound Field	Parameter	Decode Type	DSP Level: -6dB to +3dB	Init. Delay: 1 to 99ms	Room Size: 0.1 to 2.0	Liveness: 0 to 10	Sur. Init. Delay: 1 to 49ms	Sur. Room Size: 0.1 to 2.0	Sur. Liveness: 0 to 10	SB. Init. Delay: 1 to 49ms	SB. Room Size: 0.1 to 2.0	SB. Liveness: 0 to 10	Rev. Time: 1.0 to 5.0s	Rev. Delay: 0 to 250ms	Rev. Level: 0 to 100%	Dialogue Lift: 0 to 5	Center Level: 0 to 100%	Surround L Level: 0 to 100%	Surround R Level: 0 to 100%	Sur.Back Level: 0 to 100%	Presence L Level: 0 to 100%	Presence R Level: 0 to 100%	Direct: Auto/Off	Effect Level: High/Low	Panorama: On/Off	Center Width: 0 to 7	Dimension: -3 to +3	Center Image: 0.0 to 1.0	FOCUS: 0 to 8	TruBass: 0 to 8	Initialize
CLASSICAL	Hall in Munich			●	●	●	●										●															●
	Hall in Vienna			●	●	●	●										●															●
	Hall in Amsterdam			●	●	●	●										●															●
	Church in Freiburg			●	●		●							●	●	●	●															●
	Chamber			●	●		●							●	●	●	●															●
LIVE/CLUB	Village Vanguard			●	●	●	●										●															●
	Warehouse Loft			●	●	●	●							●	●	●	●															●
	Cellar Club			●	●	●	●										●															●
	The Roxy Theatre			●	●	●	●							●	●	●	●															●
	The Bottom Line			●	●	●	●										●															●
ENTERTAINMENT	Sports			●	●	●		●	●		●	●					●															●
	Action Game			●	●	●		●	●		●	●					●															●
	Roleplaying Game			●	●	●		●	●		●	●					●															●
	Music Video			●	●	●		●	●		●	●					●															●
	Recital/Opera			●	●	●		●	●		●	●					●															●
MOVIE	Standard		●*1	●				●	●	●	●	●	●				●															●
	Spectacle		●*1	●	●	●		●	●		●	●					●															●
	Sci-Fi		●*1	●	●	●		●	●		●	●					●															●
	Adventure		●*1	●	●	●		●	●		●	●					●															●
	Drama		●*1	●	●	●		●	●		●	●					●															●
	Mono Movie			●	●	●	●							●	●	●	●															●
STEREO	2ch Stereo																							●								●
	7ch Stereo																	●	●	●	○	●	●									●
MUSIC ENHANCER	Straight Enhancer																								●							●
	7ch Enhancer																								●							●
SUR. DECODE	Surround Decoder		●*2																							△	△	△	▲	■	■	●
STRAIGHT																																

△ : Setting is possible only when Pro Logic II x Music (Pro Logic II Music) is selected using decode type. / Decode Type で Pro Logic II x Music（Pro Logic II Music）を選択時のみ設定可

▲ : Setting is possible only when Neo:6 Music is selected using decode type. / Decode Type で Neo:6 Music を選択時のみ設定可

■ : Setting is possible only when CS II Cinema/Music is selected using decode type. / Decode Type で CS II Cinema/Music を選択時のみ選択可

*1 Decode Type

Decode Type	PL II x Movie	PL II when Surround Back is None. / Surround Back が None の場合は PL II
	Neo:6 Cinema	

*2 Decode Type


Decode Type	Pro Logic	
	PL II x Movie	PL II when Surround Back is None. / Surround Back が None の場合は PL II
	PL II x Music	PL II when Surround Back is None. / Surround Back が None の場合は PL II
	PL II x Game	PL II when Surround Back is None. / Surround Back が None の場合は PL II
	Neo:6 Cinema	
	Neo:6 Music	
	CS II Cinema	(U, J models)
	CS II Music	(U, J models)
	Neural-THX	(U, C modes)
	Neural-THX Digital Music	(U, C modes)


- **SET MENU TABLE / セットメニュー**
  MANUAL SETUP (GUI)


MAIN MENU	SUB MENU	PARAMETER		VALUE [INITIAL VALUE]
1 SPEAKER MENU	CONFIG.	FRONT SP		[SMALL] / LARGE
		CENTER SP		NONE / [SMALL] / LARGE
		SUR. L/R SP		
		SUR. B L/R SP		NONE / LRGx2 / [SMLx2] / SMLx1 / LRGx1
		PRESENCE SP		NONE / [YES]
		CROSS OVER		FREQ · · · · 40 / 60 / [80] / 90 / 100 / 110 / 120 / 160 / 200 Hz
		FRONT PR.		NONE / [YES]
		SUBWOOFER PHASE		REVERSE / [NORMAL]
		BASS OUT	LFE	FRONT / [SWFR] / FRONT + SWFR
			LOW-FREQ.	
	DISTANCE	UNIT		feet (ft) / meters (m)
		FRONT L		0.30 to 24.00 m, [3.00 m], 0.05 m step / 1.0 to 80.0 ft, [10.0 ft], 0.2 ft step
		FRONT R		
		CENTER		
		SUR. L		
		SUR. R		
		SB L		
		SB R		
		FRONT PR. L		
		FRONT PR. R		
		SWFR		
	LEVEL	FRONT L		-10.0 to +10.0 dB, [0.0 dB], 0.5 dB step
		FRONT R		
		CENTER		
		SUR. L		
		SUR. R		
		SB L		
		SB R		
		FRONT PR. L		
		FRONT PR. R		
		SWFR		
2 VOLUME MENU	ADAPTIVE DRC			[OFF] / AUTO
	ADAPTIVE DSP LEVEL			
	MAX. VOL.			[+16.5 dB] / +15.0 dB / +10.0 dB / +5.0 dB / 0.0 dB / -5.0 dB / -10.0 dB / -15.0 dB / -20.0 dB / -25.0 dB / -30.0 dB
	INIT. VOL.			[OFF] / MUTE / -80.0 to +16.5 dB, 0.5 dB step
	MUTING TYPE			-40 dB / -20 dB / [FULL]
3 SOUND MENU	A) LFE LEVEL	SPEAKER		-20 to 0.0 dB, [0.0 dB], 1.0 dB step
		HEADPHONE		-20 to 0.0 dB, [0.0 dB], 1.0 dB step
	B) DYNAMIC RANGE	SPEAKER		MIN/AUTO / STD / [MAX]
		HEADPHONE		MIN/AUTO / STD / [MAX]
	C) PARAMETRIC EQ	PEQ data copy		NATURAL –> MANUAL / FRONT –> MANUAL / [FLAT –> MANUAL]
		PEQ SELECT		THROUGH / [NATURAL] / FRONT / FLAT / MANUAL
		TEST TONE		[OFF] / ON
	D) TONE CONTROL	CONTROL		HEADPHONE / [SPEAKER]
		BASS		125 / [350] / 500 Hz (-6.0 to +6.0, [0.0 dB])
		TREBLE		2.5 / [3.5] / 8.0 kHz (-6.0 to +6.0, [0.0 dB])
		AUTO BYPASS		OFF / [AUTO]
	E) LIPSYNC	HDMI AUTO		MANUAL / [AUTO]
		AUTO AUDIO DELAY		0 to 240 ms, [0 ms], 1 ms step
		MANUAL AUDIO DELAY		0 to 240 ms, [0 ms], 1 ms step
	F) PURE DIRECT			AUDIO+VIDEO / [AUDIO]
		DUAL MONO (J model)		SUB / [MAIN] / ALL
	E) CHANNEL MUTE	MODE		ENABLE / [DISABLE]
		Each SP SET	FRONT L	[MUTE OFF] / MUTE ON
			FRONT R	
			CENTER	
			SUR. L	
			SUR. R	
			SB. L	
			SB. R	
			FRONT PR. L	
			FRONT PR. R	
			SWFR	

MAIN MENU	SUB MENU	PARAMETER	VALUE [INITIAL VALUE]
4 VIDEO MENU	A) ANALOG –> ANALOG		[CONVERSION] / THROUGH
	B) ANALOG –> HDMI		PROCESSING / [THROUGH]
	C) HDMI –> HDMI		
	D) PROCESSING	Resolution	NTSC: [*THROUGH] / 480p / 720p / 1080i / 1080p PAL: [*THROUGH] / *576p / *720p / *1080i / *1080p
		Aspect	[THROUGH] / 16:9 (normal) / SMART ZOOM (smart zoom)
		Prog. Re-Processing	ON / [OFF]
5 HDMI MENU	A) STANDBY THROUGH	MODE	FIX / LAST / [OFF]
		INPUT	IN1: BD/HD DVD / IN2: DVD / IN3: CBL/SAT / IN4: DVR
		OUTPUT	OUT2 / OUT1 / [OUT1+OUT2]
	B) AUDIO OUTPUT		AMP+TV / TV / [AMP]
	C) CONTROL MONITOR		HDMI OUT2 / [HDMI OUT1]
	D) MONITOR INFO.		
6 NETWORK MENU	A) CONFIG.	DHCP	OFF (auto) / [ON (manual)]
		I/P address	xxx.xxx.xx.x
		SUBNET MASK	
		DEFAULT GATEWAY	
		DNS server (P)	
		DNS server (S)	
	B) NETWORK STANDBY		ON / [OFF]
	C) INFO.	MAC address	
		STATUS	10BASE-T, 100BASE-TX, NO Link, Full Duplex, Half Duplex
		SYSTEM	
7 MULTI ZONE (U, C, R, T, K, A, B, G, E, L models)	A) ZONE SP ASSIGN		M: Main zone, 2: Zone2, 3: Zone3
	B) ZONE2, 3 SET	VOLUME	[VARIABLE] / FIXED
		MAX. VOLUME	-30.0 to +15.0 dB, [+16.5 dB], 5.0 dB step
		INITIAL VOLUME	[OFF] / MUTE / -80.0 to +16.5 dB, 0.5 dB step
		BALANCE	L10 to L1 / [0] / R1 to R10
		TONE CONTROL	BASS: -10.0 to -10.0 dB, [0.0 dB] / TREBLE: -10.0 to -10.0 dB, [0.0 dB]
		MUTE TYPE	-40 dB / -20 dB / [FULL]
		OSD	[ALL] / ZONE2 / OFF
		RENAME	
8 OPTION MENU	A) MEMORY GUARD		ON / [OFF]
	B) I/O ASSIGN		
	C) INPUT RENAME		
	D) DISPLAY SET	DIMMER	-4 to 0, [0], 1 step
		FL SCROLL	ONCE / [CONT]
		SHORT MESSAGE	OFF / [ON]
		PLAYBACK SCREEN	[30S] / 10S / ALWAYS
		GUI position	-5 to +5, [0], 1 step
		WALL paper	Gray / Electric Guitar / Horn / [Piano] / None
	E) iPod	STANDBY CHARGE	OFF / [AUTO]
	F) INITIAL SET	AUDIO SELECT	LAST / [AUTO]
		DECODER MODE	
		EXTD SUR.	
	G) TRIGGER OUTPUT		TRIGGER2 / [TRIGGER1]
		MODE	MANUAL / SOURCE / POWER
		TARGET ZONE	ALL / ZONE3 / ZONE2 / MAIN
		INPUT LEVEL	LOW / [HIGH]
		MANUAL TEST	LOW / [HIGH]

■ INTERNAL VIEW







1 Power Transformer
2 POWER (4) P.C.B.
3 POWER (2) P.C.B. (R, L models)
4 DCCNVT (2) P.C.B.
5 HD Radio Tuner (U model)
AM/FM Tuner (C, R, T, K, A, B, G, E, L, J models)
6 MAIN (2) P.C.B.
7 FL (3) P.C.B.
8 FL (5) P.C.B.
9 CONNECT (1) P.C.B. (U model)
10 FL (6) P.C.B.
11 FL (4) P.C.B.
12 A-VIDEO P.C.B.
13 CONNECT (2) P.C.B. (U, C models)
14 FL (2) P.C.B.
15 D-VIDEO P.C.B.
16 FUNCTION (1) P.C.B.
17 FUNCTION (2) P.C.B.
18 DSP P.C.B.
19 MAIN (1) P.C.B.
20 POWER (3) P.C.B.
21 POWER (5) P.C.B.
22 DCCNVT (1) P.C.B.
23 POWER (6) P.C.B.
24 POWER (1) P.C.B.
25 OPERATION (5) P.C.B.
26 OPERATION (1) P.C.B.
27 OPERATION (4) P.C.B.
28 OPERATION (3) P.C.B.
29 OPERATION (6) P.C.B.
30 OPERATION (7) P.C.B.
31 FL (1) P.C.B.
32 OPERATION (2) P.C.B.
33 MAIN (3) P.C.B.
34 MAIN (4) P.C.B.

■ DISASSEMBLY PROCEDURES / 分解手順

(Remove parts in the order as numbered.)
Disconnect the power cable from the AC outlet.

1. Removal of Top Cover

a. Remove 2 screws (①), 4 screws (②) and 5 screws (③). (Fig. 1)
b. Slide the top cover rearward to remove it. (Fig. 1)

2. Removal of Front Panel

Remove 6 screws (④) and then remove the front panel forward. (Fig. 1)

3. Removal of Sub Chassis Unit

a. Remove 2 screws (⑤). (Fig. 1)
b. Remove the DCCNVT (2) P.C.B.. (Fig. 1)
c. Remove 2 screws (⑥) and then remove the frame top. (Fig. 1)
d. Remove screw (⑦), 2 screws (⑧) and 5 screws (⑨). (Fig. 1)
e. Remove CB12, CB805-807, CB814, CB970 and CB971. (Fig. 2)
d. Remove the sub chassis unit forward. (Fig. 1)

（番号順に部品を取り外してください。）
AC 電源コンセントから、電源コードを抜いてください。

1. トップカバーの外し方

a. ① のネジ 2 本、② のネジ 4 本、③ のネジ 5 本を外します。（Fig. 1）
b. トップカバーを後方へスライドさせ、取り外します。（Fig. 1）

2. フロントパネルの外し方

④ のネジ 6 本を外し、フロントパネルを前方に外します。（Fig. 1）

3. サブシャーシユニットの外し方

a. ⑤ のネジ 2 本を外します。（Fig. 1）
b. DCCNVT（2）P.C.B. を取り外します。（Fig. 1）
c. ⑥ のネジ 2 本を外し、フレーム／トップを取り外します。（Fig. 1）
d. ⑦ のネジ 1 本、⑧ のネジ 2 本、⑨ のネジ 5 本を外します。（Fig. 1）
e. CB12、CB805 ～ CB807、CB814、CB970、CB971 を外します。（Fig. 2）
f. サブシャーシユニットを前方に取り外します。（Fig. 1）




Fig. 2




Fig. 1

When checking the P.C.B.s:

- Spread the rubber sheet and the cloth. Then place the sub chassis unit on the cloth and check it. (Fig. 3)
- Reconnect all cables (connectors) that have been disconnected. Be sure to use the extension cable for servicing for the following section.
  FL (1) P.C.B. CB901–FL (2) P.C.B. CB970:
  WQ662700 (27P, 320mm, P=1.0)
  FL (2) P.C.B. CB971–OPERATION (2) P.C.B. CB803:
  MF115300 (15P, 300mm, P=1.25)
  FL (1) P.C.B. W9001–POWER (1) P.C.B. CB12:
  MF405400 (5P, 400mm, P=1.25)
- When connecting the flexible flat cable, be careful with polarity.
- Connect the ground point of the sub chassis unit to the chassis with a ground lead or the like. (Fig. 3)

P.C.B. をチェックする場合には：

- ゴムシートと布を敷き、その上にサブシャーシユニットを置いてチェックします。(Fig. 3)
- 外したケーブル（コネクター）をすべて接続します。ただし次の区間は、サービス用延長ケーブルを使用してください。
  FL（1）P.C.B. CB901 ～ FL（2）P.C.B. CB970：
  WQ662700（27P、320mm、P ＝ 1.0）
  FL（2）P.C.B. CB971 ～ OPERATION（2）P.C.B. CB803：
  MF115300（15P、300mm、P ＝ 1.25）
  FL（1）P.C.B. W9001 ～ POWER（1）P.C.B. CB12：
  MF405400（5P、400mm、P ＝ 1.25）
- フラットケーブルを接続する際、極性に注意してください。
- サブシャーシのアースをアース線等でシャーシに接続してください。(Fig. 3)




Fig. 3

4. Removal of D-VIDEO P.C.B.

a. Remove 4 screws (⑩). (Fig. 4)
b. Remove 6 screws (⑪). (Fig. 6)
c. Remove CB102, CB106-110 and CB710. (Fig. 4)
d. Remove CB700, CB701 and then remove the D-VIDEO P.C.B. which is connected directly to the A-VIDEO P.C.B. with board-to-board connectors. (Fig. 4)

5. Removal of A-VIDEO P.C.B.

a. Remove 6 screws (⑫). (Fig. 6)
b. Remove CB23, CB203 and CB209. (Fig. 5)
c. Remove the A-VIDEO P.C.B.. (Fig. 4)

4. D-VIDEO P.C.B. の外し方

a. ⑩ のネジ 4 本を外します。(Fig. 4)
b. ⑪ のネジ 6 本を外します。(Fig. 6)
c. CB102、CB106 ～ 110、CB710 を外します。(Fig. 4)
d. CB700、CB701 を外し、D-VIDEO P.C.B. を取り外します。ただし、D-VIDEO P.C.B. は、A-VIDEO P.C.B. に基板対基板コネクターで直接接続されています。(Fig. 4)

5. A-VIDEO P.C.B. の外し方

a. ⑫ のネジ 10 本を外します。(Fig. 6)
b. CB23、CB203、CB209 を外します。(Fig. 5)
c. A-VIDEO P.C.B. を取り外します。(Fig. 4)




Fig. 4





Fig. 5

U, C, R, T, K, A, B, G, E, L models



J model




Fig. 6

When checking the P.C.B.s:

- Put the rubber sheet and the cloth over this unit. Then place the D-VIDEO and A-VIDEO P.C.B.s upside down on the cloth and check them. (Fig. 7)
- Reconnect all cables (connectors) that have been disconnected. Be sure to use the extension cable for servicing for the following section.
  FL (2) P.C.B. CB953–D-VIDEO P.C.B. CB710:
  WM785100 (20P, 300mm, P=1.0)
  FUNCTION (1) P.C.B. CB410–A-VIDEO P.C.B. CB203:
  MF111300 (11P, 300mm, P=1.25)
  FL (2) P.C.B. CB957–D-VIDEO P.C.B. CB102:
  WQ724300 (37P, 340mm, P=1.0)
- When connecting the flexible flat cable, be careful with polarity.
- Connect the ground point of each P.C.B. shown below to the chassis with a ground lead or the like. (Fig. 7)
  D-VIDEO P.C.B. GND
  D-VIDEO P.C.B. CB704 (HDMI IN1)
  A-VIDEO P.C.B. PJ204 (COMPONENT VIDEO)

P.C.B. をチェックする場合には：

- 本機の上にゴムシートと布を敷き、その上にD-VIDEO および A-VIDEO P.C.B. を裏返しに置いてチェックします。(Fig. 7)
- 外したケーブル（コネクター）をすべて接続します。ただし次の区間は、サービス用延長ケーブルを使用してください。
  FL（2）P.C.B. CB953 ～ D-VIDEO P.C.B. CB710：
  WM785100（20P、300mm、P ＝ 1.0）
  FUNCTION（1）P.C.B. CB410 ～ A-VIDEO P.C.B. CB203：
  MF111300（11P、300mm、P ＝ 1.25）
  FL（2）P.C.B. CB957 ～ D-VIDEO P.C.B. CB102：
  WQ724300（37P、340mm、P ＝ 1.0）
- フラットケーブルを接続する際、極性に注意してください。
- 下記に示す各 P.C.B. のアースをアース線などでシャーシに接続してください。(Fig. 7)
  D-VIDEO P.C.B. GND
  D-VIDEO P.C.B. CB704（HDMI IN1）
  A-VIDEO P.C.B. PJ204（COMPONENT VIDEO）




Fig. 7

6. Removal of Rear Unit

a. Remove 10 (U, C, T, K, A, B, G, E models) / 12 (R, L models) screws (⑯) and 4 (U, C, R, T, A, B, G, E, L models) / 2 (K model) screws (⑰). (Fig. 6)
b. Remove 4 screws (⑱) and screw (⑲). (Fig. 8)
c. Remove CB16, CB17, CB20, CB303, CB405-407 and CB409. (Fig. 8)
d. Remove the rear unit and MAIN (2) P.C.B.. (Fig. 8)

6. リアユニットの外し方

a. ⑯ のネジ 9 本、⑰ のネジ 4 本を外します。(Fig. 6)
b. ⑱ のネジ 4 本、⑲ のネジ 1 本を外します。(Fig. 8)
c. CB16、CB17、CB20、CB303、CB405 ～ 407、CB409 を外します。(Fig. 8)
d. リアユニットおよび MAIN（2）P.C.B. を取り外します。




Fig. 8

When checking the P.C.B.s:

- Put the rubber sheet and the cloth over this unit. Then place the rear unit upside down on the cloth and check it. (Fig. 9)
- Reconnect all cables (connectors) that have been disconnected. Be sure to use the extension cable for servicing for the following section.
  FL (1) P.C.B. CB901–FL (2) P.C.B. CB970:
  WQ662700 (27P, 320mm, P=1.0)
  FL (2) P.C.B. CB971–OPERATION (2) P.C.B. CB803:
  MF115300 (5P, 300mm, P=1.25)
- When connecting the flexible flat cable, be careful with polarity.
- Connect the ground point of the rear unit to the chassis with a ground lead or the like. (Fig. 9)

P.C.B. をチェックする場合には：

- 本機の上にゴムシートと布を敷き、その上にリアユニットを裏返しに置いてチェックします。(Fig. 9)
- 外したケーブル（コネクター）をすべて接続します。ただし次の区間は、サービス用延長ケーブルを使用してください。
  FL（1）P.C.B. CB901 ～ FL（2）P.C.B. CB970：
  WQ662700（27P、320mm、P ＝ 1.0）
  FL（2）P.C.B. CB971 ～ OPERATION（2）P.C.B. CB803：
  MF115300（15P、300mm、P ＝ 1.25）
- フラットケーブルを接続する際、極性に注意してください。
- リアユニットのアースをアース線等でシャーシに接続してください。(Fig. 9)




Fig. 9

7. Removal of Amp Unit

a. Remove 2 screws (㉑), 5 screws (㉒) and 2 screws (㉓). (Fig. 10)
b. Remove CB6, CB11, CB15 and CB253. (Fig. 10)
c. Remove the amp unit. (Fig. 10)

7. アンプユニットの外し方

a. ㉑ のネジ 2 本、㉒ のネジ 5 本、㉓ のネジ 2 本を外します。（Fig. 10）
b. CB6、CB11、CB15、CB253 を外します。（Fig. 10）
c. アンプユニットを取り外します。（Fig. 10）




Fig. 10

When checking the P.C.B.s:

- Put the rubber sheet and the cloth over this unit. Then put the amp unit upright on the cloth and check it. (Fig. 11)
- Put the amp unit together with the heat sink upright and check. (Fig. 11)
- Reconnect all cables (connectors) that have been disconnected. Be sure to use the extension cable for servicing for the following section.
  FL (1) P.C.B. CB901–FL (2) P.C.B. CB970:
  WQ662700 (27P, 320mm, P=1.0)
  FL (2) P.C.B. CB971–OPERATION (2) P.C.B. CB803:
  MF115300 (15P, 300mm, P=1.25)
  FL (1) P.C.B. W9001–POWER (1) P.C.B. CB12:
  MF405400 (5P, 400mm, P=1.25)
- When connecting the flexible flat cable, be careful with polarity.
- Connect the ground points of the sub chassis unit, POWER (1) P.C.B. and heat sink to the chassis with a ground lead or the like. (Fig. 11)

P.C.B. をチェックする場合には：

- 本機の上にゴムシートと布を敷き、その上に アンプユニットを立てて置いてチェックします。(Fig. 11)
- アンプユニットはヒートシンクといっしょに立ててチェックします。(Fig. 11)
- 外したケーブル（コネクター）をすべて接続します。ただし次の区間は、サービス用延長ケーブルを使用してください。
  FL（1）P.C.B. CB901 ～ FL（2）P.C.B. CB970：
  WQ662700（27P、320mm、P ＝ 1.0）
  FL（2）P.C.B. CB971 ～ OPERATION（2）P.C.B. CB803：
  MF115300（15P、300mm、P ＝ 1.25）
  FL（1）P.C.B. W9001 ～ POWER（1）P.C.B. CB12：
  MF405400（5P、400mm、P ＝ 1.25）
- フラットケーブルを接続する際、極性に注意してください。
- サブシャーシユニット、POWER（1）P.C.B.、ヒートシンクのアースをアース線等でシャーシに接続してください。(Fig. 11)




Fig. 11

■ UPDATING FIRMWARE / ファームウェアの書き込み

Note) The user memories (sound field parameters, system memory, tuner presetting, etc.) are kept stored even when you write the firmware.

When replacing the following parts, be sure to write the latest firmware.

P.C.B. Ass'y DSP, FUNCTION or D-VIDEO P.C.B.s
IC540 (DSP flash ROM) of DSP P.C.B.
IC402 (Main microprocessor) of FUNCTION P.C.B.
IC103 (VNP2 flash ROM) of D-VIDEO P.C.B.

● Required tools

- USB flash memory
- Firmware (RXV3900-xxxx.bin)

● Operation procedures

1. Download the latest firmware from the specified download source to PC.
2. Copy the latest firmware into the root folder of the USB flash memory.

   Note) When the firmware is copied into the sub-folder, it is not possible to write data in it.
3. Insert the USB flash memory to the USB terminal of this unit. (Fig. 1)
4. Press the "MASTER ON/OFF" switch of this unit inward to the ON position. (Fig. 1)
5. Connect the power cable to the AC outlet while pressing the "INFO" key of this unit.
   Writing of the firmware is started. (Fig. 2)

注意） ファームウェアの書き込みを行っても、ユーザーメモリー（音場プログラムのパラメーターやシステムメモリー、チューナープリセット等）は保持されます。

下記の部品をサービス部品に交換した場合、最新のファームウェアの書き込みを行ってください。

P.C.B. ASSY	：DSP、FUNCTION、D-VIDEO
DSP P.C.B.	：IC540（DSP フラッシュ ROM）
FUNCTION P.C.B.	：IC402（メインマイコン）
D-VIDEO P.C.B.	：IC103（VNP2 フラッシュ ROM）

● 必要なツール

- USB フラッシュメモリー
- ファームウェア（RXV3900-xxxx.bin）

● 操作方法

1. PC へ指定のダウンロード先から最新のファームウェアをダウンロードしてください。
2. 最新のファームウェアを USB フラッシュメモリーのルートフォルダにコピーします。

   注意） ファームウェアをサブフォルダにコピーした場合、書き込みできません。
3. 本機の USB 端子に USB フラッシュメモリーを差し込みます。（Fig. 1）
4. 本機の "MASTER ON/OFF" スイッチを押して ON にします。（Fig. 1）
5. 本機の "INFO" キーを押しながら、電源コードを AC コンセントに接続します。
   ファームウェアの書き込みが開始されます。
   （Fig. 2）




Fig. 1




Fig. 2

6. When writing of the firmware is completed, the power of this unit turns off automatically.
   * When the error message is displayed before writing is completed, perform the operation procedures from step 1 to 5 all over again.

6. ファームウェアの書き込みが完了すると、自動で本機の電源が切れます。
   ※ 途中でエラーが表示された場合は、操作方法の 1 から 5 までをもう一度やり直してください。

Error display / エラー表示	Contents / 内容	
INVALID FILE	File error ファイルエラー	The firmware is not applicable to RX-V3900/DSP-AX3900. ファームウェアが RX-V3900 ／ DSP-AX3900 用ではない
DEVICE ERROR	USB flash memory error USB フラッシュメモリーエラー	The USB flash memory is damaged. USB フラッシュメモリーが壊れている
SYSTEM ERROR	System error システムエラー	• An un-applicable USB flash memory is used. • When the USB flash memory is disconnected while the firmware is being written. • The hardware is damaged. ・未対応の USB フラッシュメモリーが使われている ・ファームウェアの書き込みの途中で USB フラッシュメモリーが抜かれた ・ハードウェアが壊れている
NOT FOUND	No file error ファイルが無いエラー	The firmware is not written in the USB flash memory or does not exist in the root folder. ファームウェアが USB フラッシュメモリーに書き込まれていない、またはルートフォルダに無い
SOFTWARE ERROR	Software error ソフトエラー	The system software is damaged. システムソフトが壊れている
UNKNOWN ERROR	Other error その他のエラー	
ERASE ERROR	Device data clear error デバイスデータ消去エラー	
SUM ERROR	Checksum error チェックサムエラー	
FORMAT ERROR	Data format error データフォーマットエラー	
WRITE ERROR	Data writing error データ書込エラー	
VERIFY ERROR	Verification error after writing 書込後のベリファイエラー	

7. Press the “MASTER ON/OFF” switch of this unit to release it outward to the OFF position.
8. Disconnect the power cable of this unit from the AC outlet.

7. 本機の “MASTER ON/OFF” スイッチを押して OFF にします。
8. 本機の電源コードを AC コンセントから抜きます。

● Confirmation of firmware version and checksum

Using the self-diagnostic function menu, check that the firmware is updated successfully.
Start up the self-diagnostic function of this unit and select the “S4. ROM VER/SUM” menu. (See “SELF-DIAGNOSTIC FUNCTION”)
Check that the displayed firmware version and checksum are same as written ones.


* When the displayed firmware version and checksum are different from written ones, perform the “Writing the Firmware” procedure all over again.

● ファームウェアのバージョンおよびチェックサムの確認

ファームウェアが正しく更新されたことをダイアグメニューで確認します。
本機のダイアグを起動し、“S4. ROM VER/SUM” メニューを選択します。(「ダイアグ（自己診断機能）」参照)
表示されたファームウェアのバージョンおよびチェックサムが、書き込まれたファームウェアのものと同じであることを確認します。

※ 表示されたファームウェアのバージョンおよびチェックサムが、書き込まれたファームウェア のものと異なる場合、「ファームウェアの書き込み」をもう一度やり直してください。

S4. ROM VER/SUM



VNP2 (Video Microprocessor) VERSION
The version of VNP2 (IC105 D-VIDEO P.C.B.) firmware is displayed.
VNP2（IC105 D-VIDEO P.C.B.）のファームウェアのバージョンを表示します。

VNP2 (Video Microprocessor) SUM
The checksum of VNP2 (IC105 D-VIDEO P.C.B.) is displayed.
VNP2（IC105 D-VIDEO P.C.B.）のチェックサムを表示します。

M32C (Main Microprocessor) VERSION
The version of Main microprocessor (IC402 FUNCTION P.C.B.) firmware is displayed.
メインマイコン（IC402 FUNCTION P.C.B.）のファームウェアのバージョンを表示します。

M32C (Main Microprocessor) SUM
The checksum of Main microprocessor (IC402 FUNCTION P.C.B.) is displayed.
メインマイコン（IC402 FUNCTION P.C.B.）のチェックサムを表示します。

DSP1 VERSION
The version of DSP1 (IC534 DSP P.C.B.) firmware is displayed.
DSP1（IC534 DSP P.C.B.）のファームウェアのバージョンを表示します。

DSP2 VERSION
The version of DSP2 (IC567 DSP P.C.B.) firmware is displayed.
DSP2（IC567 DSP P.C.B.）のファームウェアのバージョンを表示します。

DSP FLASH SUM (4Byte)
The checksum of DSP (IC540 DSP P.C.B.) is displayed.
DSP（IC540 DSP P.C.B.）のチェックサムを表示します。

GUI VERSION
The version of GUI (IC714 D-VIDEO P.C.B.) firmware is displayed.
GUI（IC714 D-VIDEO P.C.B.）のファームウェアのバージョンを表示します。

FPGA VERSION
The version of FPGA (IC737 D-VIDEO P.C.B.) firmware is displayed.
FPGA（IC737 D-VIDEO P.C.B.）のファームウェアのバージョンを表示します。

XM VERSION (U, C models)
The version of XM firmware is displayed.

SIRIUS VERSION (U, C models)
The version of SIRIUS firmware is displayed.

CEC VERSION (J model)
The version of CEC (IC100 D-VIDEO P.C.B.) firmware is displayed.
CEC（IC100 D-VIDEO P.C.B.）のファームウェアのバージョンを表示します。


BT VERSION (DOCK (YBA-10) is connected)
The version of DOCK (YBA-10) version is displayed.
DOCK（YBA-10）のファームウェアのバージョンを表示します。

Note: With this unit, it is possible to check the firmware version and checksum by using the ADVANCED SETUP menu.

1. Press the “MASTER ON/OFF” switch inward to the ON position while pressing the “STRAIGHT” key of this unit. Then the ADVANCED SETUP mode is activated. (Fig. 3)
2. Keep pressing the “INFO” key of this unit for about 3 seconds. (Fig. 3)
   “Version/Sum” is displayed.
   Press the “STRAIGHT” key to change display.

備考：本機には、アドバンスドセットアップのメニューからファームウェアのバージョンおよびチェックサムを確認する方法があります。

1. 本機の “STRAIGHT” キーを押しながら “MASTER ON/OFF” スイッチを押して ON にし、アドバンスドセットアップモードを起動します。(Fig. 3)
2. 本機の“INFO”キーを約 3 秒間押し続けます。(Fig. 3)
   “Version/Sum” が表示されます。
   “STRAIGHT” キーを押し、表示を切り替えます。






Fig. 3

3. Press the “MASTER ON/OFF” switch of this unit to release it outward to the OFF position.

3. 本機の “MASTER ON/OFF” スイッチを押して OFF にします。

■ SELF-DIAGNOSTIC FUNCTION / ダイアグ（自己診断機能）

There are 30 main menu items, each of which has sub-menu items. Listed in the table below are menu items and sub-menu items.

メインメニューは 30 個あり、そのそれぞれにサブメニューがあります。下表はメニュー一覧です。

No.	MAIN MENU	SUB-MENU
A: Audio (Audio system / オーディオ系)		
A1	DSP THROUGH	1. MARGIN
		2. FULL BIT
		3. PLL=OFF
A2	BYPASS	1. ANALOG BYPASS
		2. DSP BYPASS
A3	HDMI AUDIO	1. AUTO
		2. DSD Direct
A4	SPEAKERS SET	1. LFE/B:FRONT
		2. Pres Mix
		3. FATT1 GAIN
		4. FATT2 GAIN
		5. Zone/Tone=MAX (U, C, R, T, K, A, B, G, E, L models)
		6. Zone/Tone=MIN (U, C, R, T, K, A, B, G, E, L models)
		7. Zone mono on (U, C, R, T, K, A, B, G, E, L models)
		8. Zone mono off (U, C, R, T, K, A, B, G, E, L models)
		9. Full mute
		10. D-Party mode
A5	MULTI CH INPUT	1. 6ch INPUT_6-ohm
		2. 8ch INPUT_6-ohm
		3. 6ch INPUT_8-ohm
		4. 8ch INPUT_8-ohm
		5. 8ch INPUT_6-ohm SP
		6. 8ch INPUT_8-ohm SP
A6	MIC CHECK	1. ENTER TO START
		2. MIC ROUTE
A7	MANUAL TEST	1. TEST ALL
		2. TEST FRNT L
		3. TEST CENTER
		4. TEST FRNT R
		5. TEST SURR R
		6. TEST SB R
		7. TEST SB L
		8. TEST SURR L
		9. TEST FP L
		10. TEST FP R
		11. TEST RP L
		12. TEST RP R
		13. TEST LFE
G: Graphic (Display system / 表示系)		
G1	FL CHECK	1. FL CHECK
		2. VFD DISP OFF
		3. VFD DISP ALL
		4. VFD DIMMER
		5. CHECK PATTERN
Z: Zone (Zone function confirmation item / Zone 機能確認項目)		
Z1	ZONE TEST (U, C, R, T, K, A, B, G, E, L models)	1. ZONE2, 3, 4 INPUT : BD/HD DVD
		2. ZONE2, 3, 4 INPUT : DVD
		3. ZONE2, 3, 4 INPUT : CBL/SAT
		4. ZONE2, 3, 4 INPUT : DVR
		5. ZONE2, 3, 4 INPUT : VCR
		6. ZONE2, 3, 4 INPUT : VIDEO-AUX
		7. ZONE2, 3, 4 INPUT : DOCK
		8. ZONE2, 3, 4 INPUT : MD/CD-R
		9. ZONE2, 3, 4 INPUT : TV
		10. ZONE2, 3, 4 INPUT : CD
		11. ZONE2, 3, 4 INPUT : TUNER
		12. ZONE2, 3, 4 INPUT : PHONO
		13. ZONE2, 3, 4 INPUT : XM (U, C models)
		14. ZONE2, 3, 4 INPUT : NET/USB
		15. ZONE2, 3, 4 INPUT : SIRIUS (U, C models)

No.	MAIN MENU	SUB-MENU
R: Radio (Tuner and Satellite broadcasting system / TUNER、衛星放送系)		
R1	XM TEST (U, C models)	1. 1k -1dB/44.1k
		2. 1k -61dB/44.1k
		3. Mute /44.1k
		4. XM Tone/44.1k
		5. ISO Tone/44.1k
		6. 1k -1dB/32k
		7. 1k -61dB/32k
		8. Mute /32k
		9. XM Tone/32k
		10. ISO Tone/32k
		11. XM/DT Bus Power:OFF
R2	SIRIUS TEST (U, C models)	1. SIRIUS : --
		2. SR : xx xx xx
		3. SSP : xx xx xx
		4. MAC : xx xx xx
		5. ADP : xx xx xx
		6. PRDID : xx xx xx
		7. SEGID : xx xx xx
R3	HD RADIO TEST (U model)	1. CPU version
		2. DIR version
		3. DOCK version
U: Universal (Special terminal system / 特殊端子系 (USB, Dock))		
U1	iPod	1. DOCK
U2	USB	1. VNP2 TEST 1k
		2. VNP2 TEST 20Hz
		3. VNP2 TEST 20k
		4. VNP2 TEST2
		5. USB_F 1 TRACK
		6. USB_F 2 TRACK
		7. USB_R 1 TRACK (Not applied to these models. / このモデルには適用されません。)
N: Network (Network function system / ネットワーク機能系)		
N1	Net	1. IP Address check
		2. MAC Address check
		3. MAC LABEL No. SET
		4. LINK check
		5. EXT TEST
		6. PHY TEST
		7. Line noise measurement 10Mbps
		8. Line noise measurement 100Mbps
C: Communication (Communication and BUS line check item, etc.. / 通信・バスラインチェック項目等)		
C1	FUNCTION P.C.B. CHECK	1. 232C DATA : xx
		2. ALL : xx xx xx
C2	DSP P.C.B. CHECK	1. TI1 BUS : xx
		2. TI2 BUS : xx
C3	D-VIDEO P.C.B. CHECK	1. ALL check
		2. SDRAM Bus check
		3. NPGA Bus check
		4. YGV Bus check
		5. I2C check
		6. FPGA SPI check
		7. EEPROM I2C check
C4	HDMI INFO.	1. HDMI Model Name
		2. HDMI Product ID
		3. HDMI Vendor Name
C5	EPROM CHECK	1. SPI-EPROM check


No.	MAIN MENU	SUB-MENU
V: Video (Video system / ビデオ系)		
V1	A-VIDEO P.C.B. CHECK	1. ANALOG BYPASS
		2. DIGITAL BYPASS
		3. REC ZONE
		4. MUTE CHECK 1
		5. MUTE CHECK 2
		6. OSD character pattern 1 (0-127)
		7. OSD character pattern 2 (128-255)
		8. TEST PATTERN
		9. VIDEO INFO.
V2	D-VIDEO P.C.B. ROUTE CHECK	1. HDMI loopback test 1
		2. HDMI loopback test 2
		3. HDMI loopback test 3
		4. HDMI loopback test 4
		5. HDMI to HDMI_out1
		6. CVBS to DA & HDMI_out1
		7. CVBS to DA & HDMI_out1 with DDR (Not applied to these models. / このモデルには適用されません。)
		8. Y/C to DA & HDMI_out1
		9. Component_480p to DA & HDMI_out1
		10 Component_720p to HDMI_out1
		11. YGV to DA & HDMI_out1
P: Power (Power system / パワー系)		
P1	SYSTEM MONITOR	1. DC 1 : xxx
		2. PS1 / PS2 / PS3
		3. THM 1 / THM2
		4. OUTLVL 1
		5. LMTCNT : xxx
		6. AMP-POW
		7. AMP-RY
		8. MODEL : xxx
		9. DESTINATION
		10. PANEL KEY (K0/K1)
P2	PROTECTION HIST.	1. LAST : I PROT
		2. HIST1 : DCxxx
		3. HIST2 : PCxxx
S: System (System setting confirmation item / システム設定確認項目)		
S1	FIRM UPDATE (Not applied to these models. / このモデルには適用されません。)	1. Microprocessor UPDATE ALL
		2. Microprocessor UPDATE VNP2
		3. Microprocessor UPDATE M32C
		4. Microprocessor UPDATE TI1
S2	TOOL UPDATE (Not applied to these models. / このモデルには適用されません。)	1. CEC MCU
		2. HD RADIO MOD. (U model)
S3	FACTORY PRESET	1. PRESET INH
		2. PRESET RSRV
S4	ROM VER/SUM	1. VNP2 microprocessor version
		2. VNP2 microprocessor SUM
		3. M32C microprocessor version
		4. M32C microprocessor SUM
		5. DSP1 version
		6. DSP2 version
		7. DSP1 SUM
		8. GUI version
		9. FPGA version
		10. XM version (U, C models)
		11. SIRIUS version (U, C models)
		12. CEC version (J model)
		13. BT version
		14. HD-RADIO version (U model)
S5	SET INFO.	1. MODEL
		2. DEST
		3. HARD (Not applied to these models. / このモデルには適用されません。)
S6	SOFT SW	(Not applied to these models. / このモデルには適用されません。)

● Starting Self-Diagnostic Function


Press the “MASTER ON/OFF” switch inward to the ON position while simultaneously pressing those two keys of this unit as indicated in the figure below, and keep pressing those two keys. Release those two keys when the “DIAGNOSTIC RX-V3900” is displayed. The self-diagnostic function mode is activated.

● ダイアグの起動

本機の下図に示す 2 つのキーを同時に押しながら“MASTER ON/OFF” スイッチを押してオンにし、この 2 つのキーを押し続けます。“DIAGNOSTIC DSP-AX3900” が表示されたら 2 つのキーを放します。ダイアグが起動します。



Display / ディスプレイ表示



● Starting Self-Diagnostic Function in the protection cancel mode

If the protection function works and causes hindrance to trouble shoot, cancel the protection function as described below, and it will be possible to enter the self-diagnostic function mode. (The protection functions other than the excess current detect function will be disabled.)

Press the “MASTER ON/OFF” switch inward to the ON position while simultaneously pressing those two keys of this unit as indicated in the figure above, and keep pressing those two keys. Release those two keys when the “SLEEP” flashes after the “DIAGNOSTIC RX-V3900” is displayed. The self-diagnostic function mode is activated with protection functions disabled.

In this mode, the “SLEEP” segment of the FL display of this unit flashes to indicate that the mode is self-diagnostic function mode with the protection functions disabled.

CAUTION!
Using this product with the protection function disabled may cause damage to itself. Use special care when using this mode.

● プロテクション解除モードでの起動

プロテクションが動作することにより、故障箇所の診断に支障をきたすような場合は、次の方法によりプロテクションを解除した状態でダイアグモードに入ることができます。（過電流検出以外のプロテクション動作を解除する）

上図に示す 2 つのキーを同時に押しながら “MASTER ON/OFF” スイッチを押してオンにし、この 2 つのキーを押し続けます。“DIAGNOSTIC DSP-AX3900” が表示された後、“SLEEP”が点滅したら 2 つのキーを放します。プロテクション解除モードでダイアグが起動します。

このモードでは本機 FL の “SLEEP” セグメントが点滅し、プロテクションを解除した状態でのダイアグモードであることを知らせます。

注意！
プロテクションを解除した状態でのダイアグモードは、危険な状態でもプロテクションが作動しないため、動作させると、機器を破壊することがあります。このモードを使用する場合は十分注意してください。


● Canceling Self-Diagnostic Function

① Before canceling self-diagnostic function, execute setting for PRESET of main menu No. S3 (Memory initialization inhibited or Memory initialized).
   * In order to keep the user memory stored, be sure to select PRESET INHIBIT (Memory initialization inhibited).
② Press the "MASTER ON/OFF" switch of this unit to release it outward to the OFF position.

● Display provided when Self-Diagnostic Function started


The FL display of this unit displays the model name, followed by the protection function history data, the firmware version (1 alphabet) and the main menu (sub-menu MARGIN of main menu No. A1 DSP THROUGH) at a few seconds intervals.

When there is no history of protection function:



When there is a history of protection function:

When there is a history of protection function due to excess current



Cause: An excessive current flowed through the power amplifier.
Supplementary information: As current of the power transistor is detected, the abnormal channel can be identified by checking the current detect transistor.

The power will not turn on even when the "MASTAER ON/OFF" switch is pressed. To turn on the power again, disconnect the power cable to this unit from the AC outlet and then reconnect it again.

● ダイアグの解除

① ダイアグを解除する前に、メインメニュー No. S3 の FACTORY PRESET（メモリーの初期化禁止 / またはメモリーの初期化）の設定をします。
   ※ ユーザーメモリーを保持したい場合は、必ず PRESET INHIBIT（メモリー初期化禁止）を選択してください。
② 本機の "MASTER ON/OFF" キーを押してオフにします。

● ダイアグ起動時の表示

本機の FL ディスプレイにモデル名が表示されます。その後、数秒間隔でプロテクション履歴情報とファームウェアバージョン（英 1 文字）、メインメニュー（No. A1 DSP THROUGH のサブメニュー MARGIN）が表示されます。

プロテクション履歴がない場合 :

プロテクション履歴がある場合 :


過電流によるプロテクション履歴がある場合

原因： パワーアンプに過電流が流れた。
補足： パワートランジスタの電流を検出していますので、電流検出トランジスタをチェックすれば異常チャンネルが特定できます。

"MASTER ON/OFF" スイッチを押しても電源が入らなくなります。再度電源を入れる場合、一度本機の電源コードを AC 電源コンセントから抜いて接続し直してください。

When there is a history of protection function due to a short between speaker terminals

スピーカー端子間のショートによるプロテクション履歴がある場合




Cause: The line between speaker terminals is shorted.
Supplementary information: As the excess current is detected after operation of the speaker relay, the shorted speaker terminal and the connected speaker can be identified.

Turning on the power without correcting the abnormality will cause the protection function to work immediately and the power supply will instantly be shut off.

原因： スピーカー端子間がショートしている。
補足： スピーカーリレー動作後に過電流を検出しているので、スピーカー端子および接続しているスピーカーのショートが特定できます。

異常状態のまま電源を入れると、瞬時にプロテクションが働き、すぐに電源が切れます。



Cause: The voltage in the power supply section is abnormal.
(Normal value: PS1 43 to 66, PS2 107 to 133, PS3 140 to 179)
Supplementary information: The abnormal voltage is displayed in based on 5V as 255.

Turning on the power without correcting the abnormality will cause the protection function to work 1 second later and the power supply will be shut off.

原因： 電源部の電圧が異常。
（正常値：PS1 40 ～ 69、PS2 103 ～ 133、PS3 140 ～ 179）
補足： 異常時の電圧の状態を、5V を 255 とした値で表示します。

異常状態のまま電源を入れると、1 秒後にプロテクションが働き、電源が切れます。


Note)

- **Applying the power to this unit without correcting the abnormality can be dangerous and cause additional circuit damage. To avoid this, if protection function has been activated 3 times continuously, the power will not turn on even when the "MASTER ON/OFF" switch is pressed. In order to turn on the power again, disconnect the power cable of this unit from the AC outlet once and then reconnect it again.**
- **The output transistors in each amplifier channel should be checked for damage before applying power of this unit.**
- **Amplifier current should be monitored by measuring DC voltage across the emitter resistors for each channel.**

注意！

- **異常状態のまま本機の電源を入れると、危険な状態になり、さらに回路が損傷を受ける原因になります。そのため連続してプロテクションが働いた場合、3回目以降 "MASTER ON/OFF" スイッチを押しても電源が入らなくなります。再度電源を入れる場合、一度本機の電源コードを AC 電源コンセントから抜いて接続し直してください。**
- **本機の電源をいれる前に、各アンプのチャンネル内の出力トランジスタに損傷がないかチェックしてください。**
- **アンプの電流は、各チャンネルのエミッターの抵抗器間電圧を測定することによりモニターしてください。**

When there is a history of protection function due to abnormal DC output
DC 出力異常によるプロテクション履歴がある場合



A/D conversion value of voltage
電圧の A/D 変換値
Firmware version
ファームウェアバージョン

Cause: DC output of the power amplifier is abnormal.
(Normal value: 5 to 34)
Supplementary information: The abnormal voltage is displayed in based on 5V as 255.

Turning on the power without correcting the abnormality will cause the protection function to work 4 seconds later and the power supply will be shut off.

原因： パワーアンプの DC 出力が異常。
（正常値：5 ～ 34）
補足： 異常時の電圧の状態を、5V を 255 とした値で表示します。

異常状態のまま電源を入れると、4 秒後にプロテクションが働き、電源が切れます。

When there is a history of protection function due to excessive heat sink temperature
放熱器の異常温度によるプロテクション履歴がある場合



A/D conversion value of voltage
電圧の A/D 変換値
Firmware version
ファームウェアバージョン

Cause: The temperature of the heat sink is excessive.
(Normal value: TMP1/TMP2 10 to 83)
Supplementary information: The abnormal voltage is displayed in based on 5V as 255.

Turning on the power without correcting the abnormality will cause the protection function to work 1 second later and the power supply will be shut off.

* Additional causes of protection can be due to loose connections, associated components, Microprocessor, etc.
* For the protection voltage value, refer to main menu No. P1 described later.

原因： 放熱器の温度が異常。
（正常値：TMP1/TMP2 10 ～ 83）
補足： 異常時の電圧の状態を、5V を 255 とした値で表示します。

異常状態のまま電源を入れると、1 秒後にプロテクションが働き、電源が切れます。

※ 前記の異常原因の他に、コネクターのはずれやマイコン周辺などに原因がある場合があります。
※ プロテクションの電圧値に関しては、後述のメインメニュー No. P1 を参照してください。

● **History of protection function**
When the protection function has worked, its history is stored in memory with a backup. Even if no abnormality is noted while servicing the unit, an abnormality which has occurred previously can be defined as long as the backup data has been stored.
The history of the protection function is cleared when self-diagnostic function is cancelled by selecting PRESET RESERVED (Memory initialized) of main menu No. S3 or when the backup data is erased.

● **プロテクションの履歴**
プロテクションが働いた場合、履歴をバックアップして記憶しています。サービスのときに異常が認められなくても、バックアップが残っていれば、お客様のところで起きた異常を区別できます。
プロテクションの履歴は、メインメニュー No. S3 で PRESET RESERVED（メモリーの初期化）を選んでダイアグを解除した場合や、バックアップが消えたときにはクリアされます。

● Display during menu operation

During the self-diagnostic function mode, the monitor screen shows the wall paper and the selected function among following functions as a short message.

- Input selection, multi channel input
- Muting
- Master volume

The FL display of this unit shows the selected function. The displayed contents are described in the later section on details of self-diagnostic function menu.

● Operation procedure of Main menu and Sub-menu

There are 30 menu items, each of having sub-menu items.

Main menu selection

Select the main menu using “PROGRAM” knob.

Sub-menu selection

Select the sub-menu using key of “ENTER” (Forward).

● メニュー動作中の表示

ダイアグ中、モニター画面には壁紙表示と以下の動作中の機能がショートメッセージとして表示されます。

- インプット切替、マルチチャンネルインプット
- ミューティング
- マスターボリューム

本機のFLディスプレイには動作中の機能が表示されます。機能動作中の表示内容については、後述の機能詳細で記述します。

● メインメニューとサブメニューの操作


ダイアグには30のメニューがあり、そのそれぞれにサブメニューがあります。

メインメニューの選択

“PROGRAM”ツマミで選択します。

サブメニューの選択

“ENTER”（順送り）キーで選択します。



● Functions in Self-Diagnostic Function mode

In addition to the self-diagnostic function menu items, functions listed below are available.

- Input selection, Multi channel input
- Center/Rear/Rear center/Sub-woofer level adjustment
- Muting
- Power on/off
- Master volume

* Functions related to the tuner and the set menu are not available.

● Initial settings used to start Self-Diagnostic Function

The following initial settings are used when starting self-diagnostic function. When self-diagnostic function is canceled, these settings are restored to those before starting self-diagnostic function.

- Master volume: -20dB
- Input: DVD (MULTI CHANNEL INPUT OFF)
- Effect level: 0dB
- Audio mute: OFF
- Speaker setting: LARGE / BASS OUT = BOTH
- Self-diagnostic function menu:
  A1. DSP-THROUGH / MARGIN

● Input change when Main menu is selected

There are points where the input changes automatically when main menu is selected.

A1. DVD
A4. DVD
A5. MULTI CH IN
A7. CD
R1. XM (U, C models)
R2. SIRIUS (U, C models)
R3. TUNER
U1. DOCK
U2. USB
C2. DVD

● ダイアグ中の機能

ダイアグメニューの他に、以下の機能が動作します。

- インプット切り換え、マルチチャンネルインプット
- センター、リア、リアセンター、サブウーファーレベル調整
- ミューティング
- パワーオン / オフ
- マスターボリューム

※ チューナー関連、セットメニュー関連は機能しません。

● ダイアグ開始時の初期設定

ダイアグ開始時に以下のような設定になります。ダイアグ解除時にはダイアグ開始前の状態に戻ります。

- マスターボリューム：-20dB
- インプット：DVD（マルチチャンネル INPUT オフ）
- エフェクトレベル：0dB
- オーディオミュート：オフ
- スピーカー設定：LARGE / BASS OUT=BOTH
- ダイアグメニュー：A1. DSP-THROUGH / MARGIN

● メインメニュー選択時のインプット切り換え

メインメニュー選択時に、自動でインプットが切り換わる箇所があります。

A1. DVD
A4. DVD
A5. MULTI CH IN
A7. CD
R1. XM（U、C models）
R2. SIRIUS（U、C models）
R3. TUNER
U1. DOCK
U2. USB
C2. DVD

● Details of Self-Diagnostic Function menu

With full-bit output specified in some modes, it is possible to execute 0dBFS output without head margin in each channel.

– A: Audio (Audio system) –

A1. DSP THROUGH

This function is for DSP2 only. Main DSP of DSP2 is selected for FRONT output.
Using the sub-menu, it is possible to select 0dB output level or full-bit output.

MARGIN

- The signal is output including the head margin.



INPUT: DVD ANALOG
SPEAKER OUT: 1kHz, SUBWOOFER OUTPUT: 50Hz

Input level	Volume	SPEAKER OUT						SUBWOOFER OUTPUT
		FRONT	CENTER	SURROUND	SURROUND BACK	PRESENCE (SP1)	ZONE2 (SP2)	
Both ch, -20 dBm	+6.5 dB	+13.0 dBm	+13.0 dBm	+13.0 dBm	+13.0 dBm	-∞	-∞	-16.0 dBm

FULL BIT

- The signal is output in digital full bit without including the head margin.
- The SWFR signal is output but not in digital full bit.



INPUT: DVD ANALOG
SPEAKER OUT: 1kHz, SUBWOOFER OUTPUT: 50Hz

Input level	Volume	SPEAKER OUT						SUBWOOFER OUTPUT
		FRONT	CENTER	SURROUND	SURROUND BACK	PRESENCE (SP1)	ZONE2 (SP2)	
Both ch, -20 dBm	+6.5 dB	+13.0 dBm	+13.0 dBm	+13.0 dBm	+13.0 dBm	-∞	-∞	-16.0 dBm

PLL=OFF

- Output with PLL (DSP P.C.B. IC513) turned off.



INPUT: DVD ANALOG
SPEAKER OUT: 1kHz, SUBWOOFER OUTPUT: 50Hz

Input level	Volume	SPEAKER OUT						SUBWOOFER OUTPUT
		FRONT	CENTER	SURROUND	SURROUND BACK	PRESENCE (SP1)	ZONE2 (SP2)	
Both ch, -20 dBm	+6.5 dB	+13.0 dBm	+13.0 dBm	+13.0 dBm	+13.0 dBm	-∞	-∞	-16.0 dBm

● ダイアグメニュー詳細

一部のモードでフルビット指定することで、各チャンネルのヘッドマージンを廃して 0dBFS 出力することが可能です。

– A：Audio（オーディオ系）–

A1. DSP THROUGH

DSP2 のみの動作です。FRONT 出力には DSP2 の Main DSP が選択されます。
サブメニューにより、出力レベル 0dB、フルビット出力が選択可能です。

MARGIN

・ ヘッドマージンを含んで出力されます。


FULL BIT

・ ヘッドマージンを含まず、デジタルフルビットで出力されます。
・ SWFR は出力されますが、デジタルフルビットではありません。

PLL=OFF

・ PLL（DSP P.C.B. IC513）をオフにして出力します。

DSP THROUGH
(ANALOG)



(Shaded items not used in this mode)

A2. BYPASS

ANALOG BYPASS

A2. BYPASS

ANALOG BYPASS



INPUT: DVD ANALOG
SPEAKER OUT: 1kHz, SUBWOOFER OUTPUT: 50Hz

Input level	Volume	SPEAKER OUT						SUBWOOFER OUTPUT
		FRONT	CENTER	SURROUND	SURROUND BACK	PRESENCE (SP1)	ZONE2 (SP2)	
Both ch, -20 dBm	+6.5 dB	+13.0 dBm	-∞	-∞	-∞	-∞	-∞	-∞

DSP BYPASS


DSP BYPASS



INPUT: DVD ANALOG
SPEAKER OUT: 1kHz, SUBWOOFER OUTPUT: 50Hz


Input level	Volume	SPEAKER OUT						SUBWOOFER OUTPUT
		FRONT	CENTER	SURROUND	SURROUND BACK	PRESENCE (SP1)	ZONE2 (SP2)	
Both ch, -20 dBm	+6.5 dB	-∞	-∞	-∞	-∞	-∞	-∞	-∞

ANALOG BYPASS
(ANALOG)



(Shaded items not used in this mode)

DSP BYPASS
(DIGITAL)




(Shaded items not used in this mode)

A3. HDMI AUDIO

The audio signals input to HDMI IN are selected by the sub-menu and output.

* When you select DSD Direct, be sure to connect an HDMI unit with DSD output function.

AUTO



DSD Direct

DSD (Direct Stream Digital) is output by the direct mode.



A3. HDMI AUDIO

HDMI IN に入力された音声信号をサブメニューで選択し、出力します。

※ DSD Direct を選択する場合、必ず DSD 出力が可能な HDMI 機器を接続してください。

AUTO

DSD Direct


DSD（Direct Stream Digital）をダイレクトモードで出力します。

A4. SPEAKERS SET

The input signal is automatically identified in the order of dts → DOLBY DIGITAL → AAC → PCM → Analog.
There are 10 sub-menu items as follows.

A4. SPEAKERS SET

入力は、dts → DOLBY DIGITAL → AAC → PCM →アナログの優先順で自動判別されます。
サブメニューは以下の 10 あります。



The analog switch settings for each sub-menu are as shown in the table below.

各サブメニューにおけるアナログスイッチの設定は以下の通りです。

SUB MENU	FRONT	CENTER	SURROUND	SURROUND BACK	PRESENCE (SP1)	ZONE2 (SP2)	SUB WOOFER
1. LFE/B: FRONT	LARGE	LARGE	LARGE	LARGE	–	–	FRONT
2. PRESENCE MIX	–	–	–	–	–	–	–
3. FATT1 GAIN	–	–	–	–	–	–	–
4. FATT2 GAIN	–	–	–	–	–	–	–
5. ZONE/TONE=MAX.	LARGE	LARGE	LARGE	LARGE	–	–	SWFR
6. ZONE/TONE=MIN.	LARGE	LARGE	LARGE	LARGE	–	–	SWFR
7. ZONE MONO ON (*1)	LARGE	LARGE	NONE	NONE	–	–	SWFR
8. ZONE MONO OFF (*1)	LARGE	LARGE	NONE	NONE	–	–	SWFR
9. FULL MUTE	LARGE	SMALL	SMALL	SMALL	–	–	SWFR
10. D-Party mode (*2)	LARGE	LARGE	LARGE	LARGE	–	–	SWFR

*1 ZONE MONO mode: The analog Zone2/3 input is output as a monaural signal.
アナログの Zone2 ／ 3 入力がモノラル信号として出力されます。
*2 D-Party mode: The digital input signal is output to Zone2/3.
Digital 入力信号が Zone2 ／ 3 に出力されます。

LARGE: This mode is used for a speaker with high bass reproduction performance (a large unit). Full bandwidth signals are output.
SMALL: This mode is used for a speaker with low bass reproduction performance (a small unit). The signals of 90Hz or less are mixed into the channel specified by LFE/BASS.
NONE: This mode is used for no center speaker. The center content is reduced by 3dB and distributed to FRONT L/R.
SWFR: LFE of 5.1ch signal or LFE/BASS lower than 90Hz is output through SUBWOOFER OUT.
FRONT: LFE of 5.1ch signal or LFE/BASS lower than 90Hz is distributed to FRONT L/R.

LARGE： 低音再生能力の高い（ユニットの大きい）スピーカーを使用するモードです。全帯域が出力されます。
SMALL： 低音再生能力の低い（ユニットの小さい）スピーカーを使用するモードです。90Hz 以下が LFE/BASS で指定したチャンネルにミックスされます。
NONE： センタースピーカーを使用しないモードです。センター成分は -3dB されて、FRONT L/R に振り分けられます。
SWFR： 5.1ch 信号の LFE または 90Hz 以下の LFE/BASS が SUBWOOFER OUT に出力されます。
FRONT： 5.1ch 信号の LFE または 90Hz 以下の LFE/BASS を FRONT L/R に振り分けます。

INPUT: DVD ANALOG
SPEAKER OUT: 1kHz, SUBWOOFER OUTPUT: 50Hz
Input level: Both ch, -20 dBm
Volume: +6.5 dB

SUB MENU	SPEAKER OUT						SUBWOOFER OUTPUT
	FRONT	CENTER	SURROUND	SURROUND BACK	PRESENCE (SP1)	ZONE2 (SP2)	
1. LFE/B: FRONT	+3.0 dBm	+13.0 dBm	+13.0 dBm	+13.0 dBm	-∞	-∞	-∞
2. PRESENCE MIX	+13.0 dBm	+13.0 dBm	+13.0 dBm	+13.0 dBm	-∞	-∞	-16.0 dBm
3. FATT1 GAIN	+8.5 dBm	-∞	-∞	-∞	-∞	-∞	-∞
4. FATT2 GAIN	-∞	+13.0 dBm	+13.0 dBm	+13.0 dBm	-∞	-∞	-16.0 dBm
5. ZONE/TONE=MAX.	-∞	-∞	-∞	-∞	+5.5 dBm	+5.5 dBm	-∞
6. ZONE/TONE=MIN.	-∞	-∞	-∞	-∞	+0.5 dBm	+0.5 dBm	-∞
7. ZONE MONO ON	-∞	-∞	-∞	-∞	-∞	-∞	-∞
8. ZONE MONO OFF	-∞	-∞	-∞	-∞	-∞	-∞	-∞
9. FULL MUTE	-∞	-∞	-∞	-∞	-∞	-∞	-∞
10. D-Party mode	+13.0 dBm	+13.0 dBm	+13.0 dBm	+13.0 dBm	-∞	-∞	-16.0 dBm

A5. MULTI CH INPUT

It is possible to select the 6ch/8ch input and 6-ohm/8-ohm by using the sub-menu.

6CH INPUT_6-ohm



INPUT: MULTI CH INPUT
SPEAKER OUT: 1kHz, SUBWOOFER OUTPUT: 50Hz

Input level	Volume	SPEAKER OUT						SUBWOOFER OUTPUT
		FRONT	CENTER	SURROUND	SURROUND BACK	PRESENCE (SP1)	ZONE2 (SP2)	
Both ch, -20 dBm	+6.5 dB	+13.0 dBm	+13.0 dBm	+13.0 dBm	-∞	-∞	-∞	-16.0 dBm

8CH INPUT_6-ohm



INPUT: MULTI CH INPUT
SPEAKER OUT: 1kHz, SUBWOOFER OUTPUT: 50Hz

Input level	Volume	SPEAKER OUT						SUBWOOFER OUTPUT
		FRONT (DVD)	CENTER	SURROUND	SURROUND BACK	PRESENCE (SP1)	ZONE2 (SP2)	
Both ch, -20 dBm	+6.5 dB	-∞	+13.0 dBm	+13.0 dBm	+13.0 dBm	-∞	-∞	-16.0 dBm

6CH INPUT_8-ohm



INPUT: MULTI CH INPUT
SPEAKER OUT: 1kHz, SUBWOOFER OUTPUT: 50Hz

Input level	Volume	SPEAKER OUT						SUBWOOFER OUTPUT
		FRONT	CENTER	SURROUND	SURROUND BACK	PRESENCE (SP1)	ZONE2 (SP2)	
Both ch, -20 dBm	+6.5 dB	+13.0 dBm	+13.0 dBm	+13.0 dBm	-∞	-∞	-∞	-16.0 dBm

8CH INPUT_8-ohm



INPUT: MULTI CH INPUT
SPEAKER OUT: 1kHz, SUBWOOFER OUTPUT: 50Hz

Input level	Volume	SPEAKER OUT						SUBWOOFER OUTPUT
		FRONT (DVD)	CENTER	SURROUND	SURROUND BACK	PRESENCE (SP1)	ZONE2 (SP2)	
Both ch, -20 dBm	+6.5 dB	+13.0 dBm	+13.0 dBm	+13.0 dBm	+13.0 dBm	-∞	-∞	-16.0 dBm

A5. MULTI CH INPUT

サブメニューにより、6ch/8ch 入力および 6 オーム /8 オームが選択可能です。

6CH INPUT_6 オーム

INPUT: MULTI CH INPUT
SPEAKER OUT: 1kHz, SUBWOOFER OUTPUT: 50Hz

Input level	Volume	SPEAKER OUT						SUBWOOFER OUTPUT
		FRONT	CENTER	SURROUND	SURROUND BACK	PRESENCE (SP1)	ZONE2 (SP2)	
Both ch, -20 dBm	+6.5 dB	+13.0 dBm	+13.0 dBm	+13.0 dBm	-∞	-∞	-∞	-16.0 dBm

8CH INPUT_6 オーム

INPUT: MULTI CH INPUT
SPEAKER OUT: 1kHz, SUBWOOFER OUTPUT: 50Hz

Input level	Volume	SPEAKER OUT						SUBWOOFER OUTPUT
		FRONT (DVD)	CENTER	SURROUND	SURROUND BACK	PRESENCE (SP1)	ZONE2 (SP2)	
Both ch, -20 dBm	+6.5 dB	-∞	+13.0 dBm	+13.0 dBm	+13.0 dBm	-∞	-∞	-16.0 dBm

6CH INPUT_8 オーム

INPUT: MULTI CH INPUT
SPEAKER OUT: 1kHz, SUBWOOFER OUTPUT: 50Hz

Input level	Volume	SPEAKER OUT						SUBWOOFER OUTPUT
		FRONT	CENTER	SURROUND	SURROUND BACK	PRESENCE (SP1)	ZONE2 (SP2)	
Both ch, -20 dBm	+6.5 dB	+13.0 dBm	+13.0 dBm	+13.0 dBm	-∞	-∞	-∞	-16.0 dBm

8CH INPUT_8 オーム

INPUT: MULTI CH INPUT
SPEAKER OUT: 1kHz, SUBWOOFER OUTPUT: 50Hz

Input level	Volume	SPEAKER OUT						SUBWOOFER OUTPUT
		FRONT (DVD)	CENTER	SURROUND	SURROUND BACK	PRESENCE (SP1)	ZONE2 (SP2)	
Both ch, -20 dBm	+6.5 dB	+13.0 dBm	+13.0 dBm	+13.0 dBm	+13.0 dBm	-∞	-∞	-16.0 dBm

8CH INPUT_6-ohm SP **8CH INPUT_6 オーム SP**



INPUT: MULTI CH INPUT
SPEAKER OUT: 1kHz, SUBWOOFER OUTPUT: 50Hz

Input level	Volume	SPEAKER OUT						SUBWOOFER OUTPUT
		FRONT (DVD)	CENTER	SURROUND	SURROUND BACK	PRESENCE (SP1)	ZONE2 (SP2)	
Both ch, -20 dBm	+6.5 dB	+13.0 dBm	-∞	-∞	-∞	-∞	-∞	-∞

8CH INPUT_8-ohm SP **8CH INPUT_8 オーム SP**



INPUT: MULTI CH INPUT
SPEAKER OUT: 1kHz, SUBWOOFER OUTPUT: 50Hz


Input level	Volume	SPEAKER OUT						SUBWOOFER OUTPUT
		FRONT (DVD)	CENTER	SURROUND	SURROUND BACK	PRESENCE (SP1)	ZONE2 (SP2)	
Both ch, -20 dBm	+6.5 dB	+13.0 dBm	-∞	-∞	-∞	-∞	-∞	-∞

A6. FL/OSD CHECK

The signals input through the microphone are output via A/D - D/A.

A6. MIC CHECK

マイク入力された信号を A/D − D/A 経由で出力します。



A7. MANUAL TEST


The noise generator with a built-in DSP outputs the test noise through the channels specified by the sub-menu.

The noise frequency for LFE is 30 to 80 Hz. Other than that, the noise frequency is 500 to 2 kHz.

A7. MANUAL TEST

DSP 内蔵のノイズ発生回路によって、サブメニューで指定したチャンネルへテストノイズを出力します。

LFE 用のノイズ周波数は 30 ～ 80Hz、それ以外はノイズ周波数 500 ～ 2kHz となります。



– G: Graphic (Display system) –

G1. FL CHECK

Use this program to check the FL display section.
Using the sub-menu operation, the display status of the FL display section vary as shown below.
For audio signal processing, use EFFECT OFF (L/R output by using ANALOG MAIN BYPASS).


Checking FL display section

– G：Graphic（表示系）–

G1. FL CHECK

FL 表示部のチェックプログラムです。
サブメニュー操作により、FL 表示部の表示状態が以下のように連動して変わります。
オーディオ信号処理は EFFECT OFF（ANALOG MAIN BYPASS で L/R を出力）です。

FL 表示部のチェック



Segment conditions of the FL driver and the FL tube are checked by turning ON and OFF all segments. Next, the operation of the FL driver is checked by using the dimmer control. Then a short between segments next to each other is checked by turning ON and OFF all segments alternately (in lattice). (In the above example, the segments in the second row from the top are shorted.)

全セグメント消灯・全セグメント点灯により FL ドライバー、FL 管のセグメントの不良を確認します。
次に、ディマーコントロールによって FL ドライバーの動作チェックを行います。
さらに全セグメントを交互（格子状）に点灯／消灯することで、隣り合うセグメントのショートをチェックします。


– Z: Zone (Zone function confirmation item) –

Z1. ZONE TEST (U, C, R, T, K, A, B, G, E, L models)
The INPUT source selected from SUB-MENU is output to ZONE 2, 3, 4.

ZONE2, 3, 4 INPUT : BD/HD DVD




ZONE2, 3, 4 INPUT : DVD



ZONE2, 3, 4 INPUT : CBL/SAT



ZONE2, 3, 4 INPUT : DVR




ZONE2, 3, 4 INPUT : VCR



ZONE2, 3, 4 INPUT : VIDEO AUX




ZONE2, 3, 4 INPUT : DOCK




ZONE2, 3, 4 INPUT : MD/CD-R



ZONE2, 3, 4 INPUT : TV



ZONE2, 3, 4 INPUT : CD



– Z：Zone（Zone 機能確認項目）–

Z1. ZONE TEST（U, C, R, T, K, A, B, G, E, L models）

ZONE2、3、4 INPUT：BD/HD DVD

ZONE2、3、4 INPUT：DVD

ZONE2、3、4 INPUT：CBL/SAT

ZONE2、3、4 INPUT：DVR

ZONE2、3、4 INPUT：VCR

ZONE2、3、4 INPUT：VIDEO AUX

ZONE2、3、4 INPUT：DOCK


ZONE2、3、4 INPUT：MD/CD-R

ZONE2、3、4 INPUT：TV

ZONE2、3、4 INPUT：CD


ZONE2, 3, 4 INPUT : TUNER

ZONE2、3、4 INPUT：TUNER




ZONE2, 3, 4 INPUT : PHONO

ZONE2、3、4 INPUT：PHONO



ZONE2, 3, 4 INPUT : XM (U, C models)

ZONE2、3、4 INPUT：XM（U、C models）



ZONE2, 3, 4 INPUT : NET/USB

ZONE2、3、4 INPUT：NET/USB



ZONE2, 3, 4 INPUT : SIRIUS (U, C models)

ZONE2、3、4 INPUT：SIRIUS（U、C models）



– R: Radio (Tuner and Satellite broadcasting system) –

– R：Radio（TUNER、衛星放送系）–

R1. XM TEST (U, C models)

The output check of XM Radio Antenna is executed.

R1. XM TEST（U、C models）

1k -1dB/44.1k

The test tone (1kHz, -1dB/44.1kHz) is output.

1k -1dB/44.1k



1k -61dB/44.1k

The test tone (1kHz, -61dB/44.1kHz) is output.

1k -61dB/44.1k



Mute /44.1k

Nothing is output.


Mute /44.1k



XM Tone/44.1k

The XM tone (44.1kHz) is output.

XM Tone/44.1k



ISO Tone/44.1k

The ISO tone (44.1kHz) is output.

ISO Tone/44.1k



1k -1dB/32k

The test tone (1kHz, -1dB/32kHz) is output.


1k -1dB/32k



1k -61dB/32k

The test tone (1kHz, -61dB/32kHz) is output.


1k -61dB/32k



Mute /32k

Nothing is output.

Mute /32k



XM Tone/32k

The XM tone (32kHz) is output.

XM Tone/32k



ISO Tone/32k

The ISO tone (32kHz) is output.

ISO Tone/32k



XM/DT Bus Power: OFF

The power of XM module is turned off.


XM/DT Bus Power: OFF



R2. SIRIUS TEST (U, C models)


SIRIUS:

Connection of the SIRIUS antenna module connection is checked.



SR:

The connection information of the SIRIUS antenna module is displayed.



SSP:

The SIRIUS version #0 (SSP) is displayed.



MAC:

The SIRIUS version #1 (MAC) is displayed.



ADP:

The SIRIUS version #2 (ADP) is displayed.



PRDID:

The PRD ID (product id) is displayed.



SEGID:

The SEG ID (sequence id) is displayed.



R2. SIRIUS TEST（U、C models）

SIRIUS：

SR：

SSP：

MAC：

ADP：

PRDID：

SEGID：

R3. HD RADIO TEST (U model)

CPU version

The firmware version is displayed.




DIR version

The DIR version is displayed.



DOCK version

The DOCK version is displayed.



R3. HD RADIO TEST（U model）

CPU version

DIR version

DOCK version

– U: Universal (Special terminal system (USB, Dock)) –


U1. DOCK

This menu is used to test the DOCK connector without the iPod itself. After turning off the power, short between pins No. 14 (TX) and No. 18 (RX), between pins No. 1 (PWR) and No. 17 (ACCPOW) and between pins No. 4 (iPDET) and No. 8 (DGND). (Make sure that the power is turned off when shorting pins.)

Start the self-diagnostic function and select the menu.

The check result is displayed according to the following display specifications.

Note) Be sure to return the shorted pins to their original condition after executing this test.



DOCK CONNECTOR

– U：Universal （特殊端子系（USB、Dock））–

U1. DOCK

iPod 本体無しで、DOCK コネクタの検査を行うメニューです。

パワーオフ状態にしてから、DOCK コネクタの 14 ピン（TX）と 18 ピン（RX）、1 ピン（PWR）と 17 ピン（ACCPOW）、4 ピン（iPDET）と 8 ピン（DGND）をショートさせます。（ショートさせる時は、必ず電源を切ってください。）

ダイアグを起動してメニューを選択します。

下記表示仕様に従って、チェック結果が表示されます。

注）検査後、ショートしたピンを必ず元の状態に戻してください。



All Y / 全て Y= OK
Others / その他 = NG

Check item / チェック項目	Judgment / 判定		Display / 表示
Is UART loop pack check result OK? / UART ループバックチェック結果は OK?	YES		Y
	NO		N
Is detect function of iPod Accessory Power OK? / iPod Accessory Power の検出機能は OK ？	IC105 (D-VIDEO P.C.B.) pin No. R25 state IC105（D-VIDEO P.C.B.）R25 pin の状態	High = YES	Y
		Low = No	N
Is detect function of iPod installation to DOCK OK? / DOCK への iPod 装着の検出機能は OK ？	IC402 (FUNCTION P.C.B.) pin No. 28 state IC402（FUNCTION P.C.B.）28 pin の状態	Low = installed / 装着	Y
		High = not installed / 非装着	N
Is the identification of the DOCK type correct? / DOCK タイプの識別は正しいか？	IC402 (FUNCTION P.C.B.) pin No. 125 state IC402（FUNCTION P.C.B.）125 pin の状態	iPod DOCK	Y
		Excluding iPod DOCK / iPod DOCK 以外	N

U2. USB CHECK

VNP2 TEST 1k
1kHz test tone is output.

U2. USB CHECK

VNP2 TEST 1k
1kHz のテストトーンを出力します。

```
U2.USB
VNP2 TEST 1k
```

VNP2 TEST 20Hz
20Hz test tone is output.

VNP2 TEST 20Hz
20Hz のテストトーンを出力します。

```
U2.USB
VNP2 TEST 20Hz
```

VNP2 TEST 20k
20kHz test tone is output.

VNP2 TEST 20k
20kHz のテストトーンを出力します。


```
U2.USB
VNP2 TEST 20k
```

VNP2 TEST2
1kHz test tone is output.

VNP2 TEST2
1kHz のテストトーンを出力します。

```
U2.USB
VNP2 TEST2
```

Signal path of test tone output / テストトーン出力の信号経路



The music file recorded in the USB flash memory is reproduced.

a. Copy 2 or more music files from PC into the root folder of the USB flash memory.
b. Insert the USB flash memory to the USB terminal of this unit.

USB_FRONT 1track

Reproduced at this time is the first piece of the music file in the USB flash memory connected to the USB terminal on the front panel.

USB フラッシュメモリーに記録された音楽ファイルを再生します。

a. USB フラッシュメモリーのルートフォルダに（PC から）音楽ファイルを 2 曲以上コピーします。
b. USB フラッシュメモリーを本機の USB 端子に接続します。

USB_FRONT 1track

前面の USB 端子に接続された USB フラッシュメモリーの音楽ファイルの 1 曲目を再生します。



USB_FRONT 2track

Reproduced at this time is the second piece of the music file in the USB flash memory connected to the USB terminal on the front panel.

USB_FRONT 2track

前面の USB 端子に接続された USB フラッシュメモリーの音楽ファイルの 2 曲目を再生します。



USB_REAR 1track

Not applied to these models.

USB_REAR 1track

このモデルには適用されません。



– N: Network (Network function system) –

N1. NET CHECK

* When the network condition varies while SUB-MENU is displayed (e.g., the network is deactivated once), the correct result will not be displayed. Activate the diagnostic function mode again and check.

IP Address Check

IP address obtained is checked.

– N：Network（ネットワーク機能系）–

N1. NET CHECK

※ サブメニュー表示中にネットワークの状態が変わると（たとえばネットワークが一時切れるなど）正しい結果が表示されません。
再度ダイアグを起動し、確認してください。

IP Address Check

IP アドレスの取得状態を確認します。

```
N1.Net
IP CHECK:NG
```

OK: Connected (IP address obtained)
接続（IP アドレス取得完了）
NG: No traffic / Unconnected
通信不能 ／ 未接続

MAC Address Check

MAC address information is checked.

MAC Address Check

MAC アドレス情報を確認します。

```
N1.Net
MAC CHECK:OK
```

OK: Normal
正常
NG: Unwritten
書き込まれていない

MAC LABEL No SET


After replacing D-VIDEO P.C.B., restore the MAC address number to old MAC address number which you wrote down when replacing D-VIDEO P.C.B..

MAC LABEL No SET

D-VIDEO P.C.B. を交換後、MAC アドレスナンバーを古い MAC アドレスナンバー（D-VIDEO P.C.B 交換時にメモしたもの）に戻します。


```
N1.Net
MAC No:1B0835
```

D-VIDEO P.C.B. top view



MAC address label
MAC アドレスラベル


MAC address label /
MAC アドレスラベル




MAC address number
MAC アドレスナンバー

- **Operation procedures**


a. Press the “MENU” key.
The digit that can be changed is indicated with [∗].



b. Turn the “PROGRAM” knob to change the alpha-numerical letter in the first digit.



c. Press the “ENTER” key to shift to the next digit.




- **操作手順**


a. “MENU” キーを押します。
変更できる桁が［∗］で表示されます。



b. “PROGRAM” ノブを回転し、1 桁目の英数字を変更します。




c. “ENTER” キーを押し次の桁へ移動します。




d. Repeat steps b. and c. to change all settings to the MAC address number of the old D-VIDEO P.C.B..


d. 操作手順 b.、c. を繰り返し、すべての設定を古い D-VIDEO P.C.B. の MAC アドレスナンバーに変更します。



e. Press the “MENU” key.
The procedure is completed when “OK” is displayed.

e. “MENU” キーを押します。
“OK” が表示されれば、完了です。





LINK CHECK

LAN cable connection is checked.

LINK CHECK

LAN ケーブルの接続状態を確認します。



Ext loopback test


This menu is used to test the NETWORK connector.
With the power to this unit turned off, short between pins No. 1 (Tx+) and No. 3 (Rx+) and between pins No. 2 (Tx-) and No. 6 (Rx-) of the NETWORK connector.
(Be sure to turn off the power to this unit when shorting these pins.)
Start self-diagnostic function and select this menu.

Note) Be sure to return the shorted pins to their original condition after executing this test.

Ext loopback test

NETWORK コネクタの送受信テストを行います。
本機の電源をオフ状態にして、NETWORK コネクタの 1 ピン（Tx+）と 3 ピン（Rx+）、2 ピン（Tx-）と 6 ピン（Rx-）をショートさせます。
（ショートさせるときは必ず本機の電源を切ってください。）
ダイアグを起動して本メニューを選択します。

注）テスト後、ショートしたピンを必ず元の状態に戻してください。




```
N1.Net
EXT TEST:NG
```

OK: Normal
正常
NG: Abnormal
異常

PHY TEST

Check the connection condition between PHY (IC118 D-VIDEO P.C.B.) and VNP2 (IC105 D-VIDEO P.C.B.).

PHY TEST

PHY（IC118 D-VIDEO P.C.B.）と VNP2（IC105 D-VIDEO P.C.B.）間の接続状態を確認します。

```
N1.Net
PHY TEST:OK
```

OK: Normal
正常
NG: Abnormal
異常

Line noise measurement 10Mbps

Measure the line noise 10Mbps.

Line noise measurement 10Mbps

ラインノイズ 10Mbps を測定します。

```
N1.Net
LINE 10Mbps
```

Line noise measurement 100Mbps

Measure the line noise 100Mbps.

Line noise measurement 100Mbps

ラインノイズ 100Mbps を測定します。

```
N1.Net
LINE 100Mbps
```

– C: Communication (Communication and BUS line check item, etc..) –


C1. FUNCTION P.C.B. CHECK

This menu is used to check transmission of the data and the flow port of the hardware.
With the power turned off, short between pins No. 2 (RxD) and No. 3 (TxD), and between pins No. 7 (RTS) and No. 8 (CTS) of the RS232C terminal. (Be sure to turn off the power when shorting the pins.)
Start self-diagnostic function and select the menu.
There are two sub-menu items.

– C：Communication （通信・バスラインチェック項目等）–

C1. FUNCTION P.C.B. CHECK

データ送受信チェック、ハードウェアフローポートチェックを行うメニューです。
パワーオフ状態にしてから、RS232C 端子の 2 ピン（RxD）と 3 ピン（TxD）、7 ピン（RTS）と 8 ピン（CTS）をショートさせます。（ショートさせるときは必ず電源を切ってください。）
ダイアグを起動してメニューを選択します。
サブメニューは 2 つあります。



RS232C DATA

The sub-menu is used to check transmission of the test data. “OK” appears when the data is transmitted properly and “NG” when it is not.
In this mode, NULL command transmission is continued after the test command is transmitted.

RS232C DATA

テストの送受信チェックを行います。正常に送受信完了した場合、“OK” と表示します。正常に送受信しなかった場合は “NG” と表示します。
このモードでは、テストコマンド送信後、200ms ごとに NULL コマンド（無効なコマンド）を送信し続けます。




ALL:

Check transmission of the tuner and satellite broadcasting.
OK : Normal
NG : Abnormal/No checked

ALL：

チューナーの送受信チェックを行います。
OK ：正常
NG ：異常／未確認



C2. DSP P.C.B. CHECK

The connection check for communication and bus line of the DSP P.C.B. with each device is self-diagnosed.

TI1 (DSP1) BUS

The TI1 (DSP1, IC534) bus line connection check is executed.

OK : No error detected
NG : An error is detected



TI2 (DSP2) BUS

The TI2 (DSP2, IC567) bus line connection check is executed.

OK : No error detected
NG : An error is detected



C2. DSP P.S.B. CHECK

DSP P.C.B. の各デバイスとの通信・バスラインの接続チェックを自己診断します。

TI1（DSP1）BUS

TI1（DSP1、IC534）のバスラインの接続をチェックします。

OK ：不良検出なし
NG ：不良検出あり

TI2（DSP2）BUS

TI2（DSP2、IC567）のバスラインの接続をチェックします。

OK ：不良検出なし
NG ：不良検出あり

C3. D-VIDEO P.C.B. CHECK

The connection check for communication and bus line of the D-VIDEO P.C.B. with each device is self-diagnosed.

ALL Check

The synthetic judgment result is displayed.

OK : No error detected
NG : An error is detected
No Check : Detection is not executed

C3. D-VIDEO P.S.B. CHECK

D-VIDEO P.C.B. の各デバイスとの通信・バスラインの接続チェックを自己診断します。

ALL Check

総合判定結果を表示します。

OK ：不良検出なし
NG ：不良検出あり
No Check：未検出

```
C3.DVIDEO PCB
ALL:OK
```

SDRAM BUS Check

The Read/Write check of SDRAM (IC104 and IC125) are executed.

OK : No error detected
NG : An error is detected

SDRAM BUS Check

SDRAM（IC104、IC125）の読み出し・書き込みをチェックします。

OK ：不良検出なし
NG ：不良検出あり

```
C3.DVIDEO PCB
BUS RAM:OK
```

NPGA BUS Check

The NPGA (IC114) bus line connection check is executed.

OK : No error detected
NG : An error is detected

NPGA BUS Check

NPGA（IC114）のバスラインの接続をチェックします。

OK ：不良検出なし
NG ：不良検出あり

```
C3.DVIDEO PCB
BUS NPGA:OK
```

YGV BUS Check

The YGV619 (IC714) bus line connection check is executed.

OK : No error detected
NG : An error is detected

YGV BUS Check

YGV619（IC714）のバスラインの接続をチェックします。

OK ：不良検出なし
NG ：不良検出あり

```
C3.DVIDEO PCB
BUS_YGV:OK
```

I2C Check

The I2C bus line connection check is executed.

0 : No error detected
1 : An error is detected

I2C Check

I2C バスラインの接続をチェックします。

0 ：不良検出なし
1 ：不良検出あり

```
C3.DVIDEO PCB
I2C:00000000
```

- Error detection of Video Encoder (IC702) / ビデオエンコーダー（IC702）の不良検出
- Error detection of Video Decoder (IC701) / ビデオデコーダー（IC701）の不良検出
- Error detection of Video Processor (IC751) / ビデオプロセッサ（IC751）の不良検出
- Error detection of HDMI Switch 1 (IC726) / HDMI SWITCH 1（IC726）の不良検出
- Error detection of HDMI Switch 2 (IC728) / HDMI SWITCH 2（IC728）の不良検出
- Error detection of HDMI Dual Receiver (IC727) / HDMI デュアルレシーバー（IC727）の不良検出
- Error detection of HDMI Transmitter 1 (IC729) / HDMI トランスミッター 1（IC729）の不良検出
- Error detection of HDMI Transmitter 2 (IC732) / HDMI トランスミッター 2（IC732）の不良検出

FPGA BUS Check

The SPI line of FPGA (IC737) is checked for connection.

OK : No error detected
NG : An error is detected

FPGA BUS Check

FPGA（IC737）の SPI ラインの接続をチェックします。

OK ：不良検出なし
NG ：不良検出あり



EEPROM Check

The I2C line of EEPROM (IC113 and IC124) is checked for connection

OK : No error detected
NG : An error is detected

EEPROM Check

EEPROM（IC113、IC124）の I2C ラインの接続をチェックします。

OK ：不良検出なし
NG ：不良検出あり



C4. HDMI INFORMATION

HDMI Model Name

The model name of this unit written in HDMI module is displayed.

RX-V3900

C4. HDMI INFORMATION

HDMI Model Name

HDMI モジュールに書き込まれている本機のモデル名を表示します。

DSP-AX3900



HDMI Product ID


The product ID of this unit written in HDMI module is displayed.

3130: RX-V3900

HDMI Product ID

HDMI モジュールに書き込まれている本機のプロダクト ID を表示します。

312F：DSP-AX3900




HDMI Vendor Name

The vendor name (YAMAHA) of this unit written in the HDMI module is displayed.

HDMI Vendor Name

HDMI モジュールに書き込まれている本機のベンダー名（YAMAHA）を表示します。



C5. EPROM CHECK

SPI-EPROM CHECK

C5. EPROM CHECK

SPI-EPROM CHECK

```
C5.EPROM CHECK
SPI EPROM:
```

– V: Video (Video system) –

V1. A-VIDEO P.C.B. CHECK

The video signal is converted and output as follows.

ANALOG BYPASS


ー V：Video（ビデオ系）ー

V1. A-VIDEO P.C.B. CHECK

映像信号が以下のように変換され、出力されます。

ANALOG BYPASS


```
V1.AVIDEO
ANALOG BYPASS
```



DIGITAL BYPASS


DIGITAL BYPASS






REC ZONE

REC ZONE





MUTE CHECK 1

MUTE signal “VMT” (92 pin) is output from the main microprocessor (FUNCTION P.C.B. IC402).

MUTE CHECK 1

メインマイコン（FUNCTION P.C.B. IC402）から MUTE 信号 “VMT”（92 pin）を出力します。



MUTE CHECK 2

MUTE signals “MON_N_VMT” (AE4) and “Z2_N_VMT” (AD4) are output from the NPGA (D-VIDEO P.C.B. IC114) and MUTE signals “/MTVR1 (18 pin)” and “/MTVR2 (17 pin)” from IC222 of the A-VIDEO P.C.B..


MUTE CHECK 2


NPGA（D-VIDEO P.C.B. IC114）から MUTE 信号 “MON_N_VMT”（AE4）、“Z2_N_VMT”（AD4）、IC222（A-VIDEO P.C.B.）から MUTE 信号 “/MTVR1”（18 pin）、“/MTVR2”（17 pin）を出力します。



OSD character pattern (0-127)


OSD character pattern (0-127)






OSD character pattern (128-255)

OSD character pattern (128-255)







TEST PATTERN

TEST PATTERN







VIDEO INFO

The information of video signals being input is displayed.

VIDEO INFO


入力されている映像信号の情報を表示します。



V2. D-VIDEO P.C.B. ROUTE CHECK


Check the image signal route as shown below.

HDMI loop-back test




TEST1

Loop-back check 1



TEST2

Loop-back check 2




V2. D-VIDEO P.C.B. ROUTE CHECK

以下の映像信号経路をチェックします。

HDMI loop-back test


TEST3

Test pattern 480p to 1080p (I/P Scalar check)



TEST4


Test pattern 480i to 1080p (FPGA check)



HDMI to HDMI_out1

HDMI to HDMI_out1






CVBS to DA and HDMI_out1

CVBS to DA and HDMI_out1





CVBS to DA and HDMI_out1 with DDR

Not applied to these models.

CVBS to DA and HDMI_out1 with DDR


このモデルには適用されません。

```
V2.VIDEO ROUTE
DIGITAL CVBS2
```

Y/C to DA and HDMI_out1

Y/C to DA and HDMI_out1


```
V2.VIDEO ROUTE
DIGITAL Y/C
```



Component_480p to DA and HDMI_out1


Component_480p to DA and HDMI_out1






Component_720p to HDMI_out1

Component_720p to HDMI_out1






YGV to DA and HDMI_out1

YGV to DA and HDMI_out1





– P: Power Supply (Power supply system) –

P1. SYSTEM MONITOR

This menu is used to display the A/D conversion value of the main microprocessor which detects panel keys of this unit and protection functions in using the sub-menu. Signal processing is maintained in the status before execution.

When K0/K1 menu is selected, keys become non-operable due to detection of the values of all keys. However, it is possible to advance to the next main menu by turning the PROGRAM knob of this unit.

* The figures in the diagram are given as reference only.

DC (Protection detection)

DC: DC detect protection value (Normal value: 5 to 34)

* If DC is out of the normal value range, the protection function works to turn off the power.

(Reference voltage: 5V=255)

– P：Power Supply（パワー系）–

P1. SYSTEM MONITOR

本機パネルキー、プロテクションなどを検出しているメインマイコンの A/D 変換の値を、サブメニューで表示します。信号処理は実行前の状態を維持します。K0/K1 のメニューにすると、全キーの値を検出するためキー操作はできなくなりますが、本機の PROGRAM ツマミを回すことにより、次のメインメニューに進めることができます。

※ 図中の数値は参考例です。

DC（プロテクションの検出）

DC： DC 検出プロテクションの値（正常値 5 ～ 34）

※ DC は正常値を外れるとプロテクションが働き、電源オフされます。

（基準電圧：5V=255）



PS1/PS2/PS3 (Protection detection)

Power supply voltage protection value
(Normal value: PS1: 43 to 66, PS2: 107 to 133, PS3: 140 to 179)

PS1: Detects ±B1, B2, ±12, ±RY, +5D2, +5I, +3.3HD.
PS2: Detects +2DSW, +3DSW, +4DSW, +6DSW, -VP.
PS3: Detects +5VA, -5VA, +9VA.

* If PS is out of the normal value range, the protection function works to turn off the power.

(Reference voltage: 5V=255)


PS1/PS2/PS3（電源電圧プロテクションの検出）

プロテクションの値
（正常値 PS1：40 ～ 69、PS2：103 ～ 133、PS3：140 ～ 179）

PS1： ± B1、B2、± 12、± RY、+5D2、+5I、+3.3HD を検出しています。
PS2： +2DSW、+3DSW、+4DSW、+6DSW、-VP を検出しています。
PS3： +5VA、-5VA、+9VA を検出しています。

※ PS は正常値を外れるとプロテクションが働き、電源オフされます。

（基準電圧：5V=255）



TM1/TM2 (Temperature detection)

Temperature detected value
(Normal value: 10 to 83)

TM1: Detects the temperature of the heat sink at the left side (power transformer side)

TM2: Detects the temperature of the heat sink at the right side (volume side)

(Reference voltage: 5V=255)


TM1/TM2（温度検出）

温度検出値（正常値 10 ～ 83）

TM1：ヒートシンク左側（電源トランス側）の温度を検出しています。

TM2：ヒートシンク右側（ボリューム側）の温度を検出しています。

（基準電圧：5V=255）



OUTLVL (Power limiter output level)

Total value of amplifier output of each channel
The voltage at 141 pin of IC402 is displayed with 5V/255 as a standard.

OUTLVL（パワーリミッターの出力）

各チャンネルのアンプ出力の合計値
IC402 の 141 ピンの電圧値を 5V/255 を基準にして表示します。



LMTCNT (Limiter control value)

The voltage at 3 pin of IC402 is displayed with 5V/255 as a standard.

LMTCNT（リミッター制御の値）

IC402 の 3 ピンの電圧値を 5V/255 を基準にして表示します。




AMPPOW (Amp. Power control)

Use the “PURE DIRECT” key to change the output of the power supply of the amplifier (RY250, RY251 MAIN (2) P.C.B.).

AMPPOW（Amp. Power control）

アンプ部電源リレー（RY250、RY251 MAIN（2）P.C.B.）の出力を “PURE DIRECT” キーで切り替えます。




AMPRELAY (Amp. Power relay control)

Use the "PURE DIRECT" key to change the output of the power supply of the amplifier (RY250, RY251 MAIN (2) P.C.B.).

AMPRELAY（Amp. Power relay control）

アンプ部電源リレー（RY250、RY251 MAIN（2）P.C.B.）の出力を "PURE DIRECT" キーで切り替えます。



VAR.: Variable
通常

LOW: RY250 ON, RY251 ON
RY250 オン、RY251 オン

MID: RY250 OFF, RY251 ON
RY250 オフ、RY251 オン

HIGH: RY250 OFF, RY251 OFF
RY250 オフ、RY251 オフ

MODEL


Model detection value

(Reference voltage: 5V=255)

MODEL

モデル検出の値

（基準電圧：5V=255）



Model	Value
RX-V3900/DSP-AX3900	192-255

DESTINATION


Destination detection value

(Reference voltage: 5V=255)

DESTINATION

仕向け検出の値

（基準電圧：5V=255）



Destination	Value
J	0 ± 4
U	27 ± 4
C	54 ± 4
R	81 ± 4
T	104 ± 4

Destination	Value
K	128 ± 4
A	152 ± 4
B, G, E	208 ± 4
L	228 ± 4

PANEL KEY (K0/K1)

(Panel key of this unit)

The key fails to function properly when its A/D conversion value deviates from standard value ±4. In this case, check the constant of partial pressure resistor, solder condition, etc. Refer to table.

(Reference voltage: 5V=255)

PANEL KEY (K0/K1)

（本機パネルキー）

キーは、その A/D 変換値が基準値± 4 から外れると、正常な動きをしません。下表をご覧になり、各キーの分圧抵抗の定数、ハンダ不良等の確認をしてください。

（基準電圧：5V=255）



RX-V3900 (U, C, R, T, K, A, B, G, E, L models)

Display	K0	K1
0±4	INFO	STRAIGHT / EFFECT
26±4	ZONE CONTROLS	ENTER
51±4	CATEGORY / BAND	TONE CONTROL / ▶
77±4	STEREO/MONO	MENU
104±4	SEARCH MODE	AUDIO SELECT/REC OUT / ◀
129±4	MEMORY	PURE DIRECT
154±4	PRESET/TUNING/CH ▶	–
179±4	PRESET/TUNING/CH ◀	–
205±4	ZONE ON/OFF / ZONE2	–
230±4	ZONE ON/OFF / ZONE3	–
255	KEY OFF	KEY OFF

DSP-AX3900 (J model)

Display	K0	K1
0±4	INFO	STRAIGHT / EFFECT
26±4	–	ENTER
51±4	BAND	TONE CONTROL / ▶
77±4	STEREO/MONO	MENU
104±4	SEARCH MODE	AUDIO SELECT/REC OUT / ◀
129±4	MEMORY	PURE DIRECT
154±4	PRESET/TUNING ▶	–
179±4	PRESET/TUNING ◀	–
205±4	–	–
230±4	–	–
255	KEY OFF	KEY OFF

P2. PROTECTION HIST.

The history of protection function is displayed.
After selecting the sub-menu, press the “STRAIGHT” key, and the history will be erased.

Last

Example

```
P2.PRTCT HIST.
1st:NONE
```

History1

Example

```
P2.PRTCT HIST.
2nd:Dc  034H
```

Protection name
プロテクション名

H: When the upper limit of the protection function is exceeded.
プロテクションの上限を超えた場合

L: When the lower limit of the protection function is exceeded.
プロテクションの下限を超えた場合

AD value when the protection function is activated.
プロテクション動作時の AD 値

History2

Example

```
P2.PRTCT HIST.
3rd:Dc  035H
```

P2. PROTECTION HIST.

プロテクション履歴を表示します。
サブメニューを選んだ後、“STRAIGHT” キーを押すと履歴は消去されます。

Last

History1

History2

– S: System (System setting confirmation item) –

S1. FIRM UPDATE

Not applied to these models.

CPU UPDATE : ALL



CPU UPDATE : VNP2



CPU UPDATE : M32C



CPU UPDATE : TI



S2. TOOL UPDATE

Not applied to these models.

UPDATE : CEC (J model)



UPDATE : HD-RADIO (U model)



ー S：System（システム設定確認項目）ー

S1. FIRM UPDATE

このモデルには適用されません。

CPU UPDATE：ALL

CPU UPDATE：VNP2

CPU UPDATE：M32C

CPU UPDATE：TI

S2. TOOL UPDATE

このモデルには適用されません。

UPDATE：CEC（J model）


UPDATE：HD-RADIO（U model）

S3. FACTORY PRESET

This menu is used to reserve and inhibit initialization of the back-up RAM. The signals are processed using EFFECT OFF. (The L/R signal is output using ANALOG MAIN BYPASS.)

S3. FACTORY PRESET

バックアップ用 RAM（音場プログラムのパラメーターやセットメニュー内容等）の初期化を予約 / 禁止します。
信号処理は EFFECT OFF と同じです。（ANALOG MAIN BYPASS で L/R を出力）



PRESET INHIBIT (Initialization inhibited) / PRESET INHIBIT（初期化禁止）
RAM initialization is not executed. Select this sub-menu to protect the values set by the user.
RAM の初期化は行われません。ユーザーの設定値を保護するときは、こちらを選択してください。

PRESET RESERVED (Initialization reserved) / PRESET RESERVED（初期化予約）
Initialization of the back-up RAM is reserved. (Actually, initialization is executed the next time that the power is turned on.) Select this sub-menu to reset to the original factory settings or to reset the RAM. Any protection history will be cleared.
バックアップ RAM の初期化が予約されます。（実際に初期化されるのは、次回の電源投入時です。）工場出荷時や RAM をリセットしたいときは、こちらを選択してください。

CAUTION: Before setting to the PRESET RESERVED, write down the existing preset memory content of the Tuner in a table as shown below. (This is because setting to the PRESET RESERVED will cause the user memory content to be erased.)

注意： PRESET RESERVED を選んで初期化をする前に、チューナーのユーザーメモリー内容を下表に書き写してください。（初期化をすると、ユーザーメモリーの内容は消えてしまいます。）

Preset group	P1	P2	P3	P4	P5	P6	P7	P8
A								
B								
C								
D								
E								

• PRESET STATIONS / プリセット局

STATION		FM FACTORY PRESET DATA (MHz)		
PAGE	NO.	U, C	R, T, K, A, B, G, E, L	J
A/C/E	1	87.5	87.50	76.0
	2	90.1	90.10	83.0
	3	95.1	95.10	84.0
	4	98.1	98.10	86.0
	5	107.9	108.00	90.0
	6	88.1	88.10	78.0
	7	106.1	106.10	88.0
	8	107.9	108.00	82.1


STATION		AM FACTORY PRESET DATA (kHz)		
PAGE	NO.	U, C, R, T, K	A, B, G, E, L	J
B/D	1	630	630	630
	2	1080	1080	1080
	3	1440	1440	1440
	4	530	531	531
	5	1710	1611	1611
	6	900	900	900
	7	1350	1350	1350
	8	1400	1404	1404

S4. ROM VER/SUM

The version and checksum are displayed. The signal is processed using EFFECT OFF. The checksum is obtained by adding the data at every 8 bits for each program area and expressing the result as a 4-figure hexadecimal data.

S4. ROM VER/SUM

プログラムのバージョン、チェックサムを表示します。
信号はエフェクト OFF です。チェックサムは、プログラムエリア別にデータを 8 ビットごとに加算していき、4 桁の 16 進データで現したものです。



VNP2 (Video Microprocessor) VERSION
The version of VNP2 (IC105 D-VIDEO P.C.B.) firmware is displayed.
VNP2（IC105 D-VIDEO P.C.B.）のファームウェアのバージョンを表示します。

VNP2 (Video Microprocessor) SUM
The checksum of VNP2 (IC105 D-VIDEO P.C.B.) is displayed.
VNP2（IC105 D-VIDEO P.C.B.）のチェックサムを表示します。

M32C (Main Microprocessor) VERSION
The version of Main microprocessor (IC402 FUNCTION P.C.B.) firmware is displayed.
メインマイコン（IC402 FUNCTION P.C.B.）のファームウェアのバージョンを表示します。

M32C (Main Microprocessor) SUM
The checksum of Main microprocessor (IC402 FUNCTION P.C.B.) is displayed.
メインマイコン（IC402 FUNCTION P.C.B.）のチェックサムを表示します。

DSP1 VERSION
The version of DSP1 (IC534 DSP P.C.B.) firmware is displayed.
DSP1（IC534 DSP P.C.B.）のファームウェアのバージョンを表示します。

DSP2 VERSION
The version of DSP2 (IC567 DSP P.C.B.) firmware is displayed.
DSP2（IC567 DSP P.C.B.）のファームウェアのバージョンを表示します。

DSP FLASH SUM (4Byte)
The checksum of DSP (IC540 DSP P.C.B.) is displayed.
DSP（IC540 DSP P.C.B.）のチェックサムを表示します。

GUI VERSION
The version of GUI (IC714 D-VIDEO P.C.B.) firmware is displayed.
GUI（IC714 D-VIDEO P.C.B.）のファームウェアのバージョンを表示します。

FPGA VERSION
The version of FPGA (IC737 D-VIDEO P.C.B.) firmware is displayed.
FPGA（IC737 D-VIDEO P.C.B.）のファームウェアのバージョンを表示します。

XM VERSION (U, C models)
The version of XM firmware is displayed.

SIRIUS VERSION (U, C models)
The version of SIRIUS firmware is displayed.

CEC VERSION (J model)
The version of CEC (IC100 D-VIDEO P.C.B.) firmware is displayed.
CEC（IC100 D-VIDEO P.C.B.）のファームウェアのバージョンを表示します。

BT VERSION (DOCK (YBA-10) is connected)
The version of DOCK (YBA-10) version is displayed.
DOCK（YBA-10）のファームウェアのバージョンを表示します。

S5. SET INFO.
The information on the model are displayed.

MODEL: RX-Z7, DSP-Z7
The model name is displayed.

S5. SET INFO.
モデル、仕向け等の情報を表示します。

MODEL: DSP-Z7
モデル名を表示します。

```
S5.SET INFO
MODEL:RX-V3900
```

DEST.: U, C, R, T, K, A, BGE, L, J
U, C, R, T, K, A, B, GE, L or J is displayed.

DEST.：U、C、R、T、K、A、BGE、L、J
U、C、R、T、K、A、B、GE、L、J のいずれかを表示します。

```
S5.SET INFO
DEST.:U
```

HARD :
Not applied to these models.

HARD：
このモデルには適用されません。

```
S5.SET INFO
HARD:PP V.xx
```


S6. SOFT SW
Not applied to these models.

S6. SOFT SW
このモデルには適用されません。

■ AMP ADJUSTMENT / アンプ部調整

Confirmation of Idling Current of Amp Unit

- Right after power is turned on, confirm that the voltage across the terminals of R467 (SURROUND BACK Rch), R468 (SURROUND Rch), R469 (FRONT Rch), R470 (CENTER), R471 (FRONT Lch), R472 (SURROUND Lch), R473 (SURROUND BACK Lch) are between 0.1mV and 10.0mV.
- If it exceeds 10.0mV, open (cut off) R432 (SURROUND BACK Rch), R433 (SURROUND Rch), R434 (FRONT Rch), R435 (CENTER), R436 (FRONT Lch), R437 (SURROUND Lch), R438 (SURROUND BACK Lch) and reconfirm the voltage.

  Attention
  If the measured voltage exceeds 10.0mV after an amplifier repair, first check for a defective component before cutting the bias resistor.


- Confirm that the voltage is 0.2 mV to 15.0 mV after 60 minutes.


アンプユニットのアイドリング電流の確認


- 電源投入直後、R467（SURROUND BACK Rch）、R468（SURROUND Rch）、R469（FRONT Rch）、R470（CENTER）、R471（FRONT Lch）、R472（SURROUND Lch）、R473（SURROUND BACK Lch）の端子間電圧を測定し、0.1mV から 10.0mV の間であることを確認してください。
- 電圧が 10mV を超えている場合は、R432（SURROUND BACK Rch）、R433（SURROUND Rch）、R434（FRONT Rch）、R435（CENTER）、R436（FRONT Lch）、R437（SURROUND Lch）、R438（SURROUND BACK Lch）をカットし、電圧を再確認してください。

  注意
  パワーアンプ修理後に 10.0mV を超えている場合は、抵抗をカットする前に故障箇所を調べてください。

- 60 分後、電圧が 0.2mV ～ 15.0mV であることを確認してください。








■ DISPLAY DATA

- **V9001: HNA-16ML15T (FL P.C.B.)**




- **PIN CONNECTION**


Pin No.	130	129	128	127	126	125	124	123	122	121	120	119	118	117	116	115	114	113	112	111	110	109	108	107	106	105	104	103	102	101	100	99
Connection	F1	F1	NP	NP	P35A	P34A	P33A	P32A	P31A	P30A	P29A	P28A	P27A	P26A	P25A	P24A	P23A	P22A	P21A	P20A	P19A	P18A	P17A	P16A	P15A	P14A	P13A	P12A	P11A	P10A	P9A	P8A
Pin No.	98	97	96	95	94	93	92	91	90	89	88	87	86	85	84	83	82	81	80	79	78	77	76	75	74	73	72	71	70	69	68	67	66
Connection	P7A	P6A	P5A	P4A	P3A	P2A	P1A	NX (IC)	NX	NX	NX	NX	NX	16GA	15GA	14GA	13GA	12GA	11GA	10GA	9GA	8GA	7GA	6GA	5GA	4GA	3GA	2GA	1GA	NP	NP	F2	F2
Pin No.	34	35	36	37	38	39	40	41	42	43	44	45	46	47	48	49	50	51	52	53	54	55	56	57	58	59	60	61	62	63	64	65	
Connection	P8B	P9B	P10B	P11B	P12B	P13B	P14B	P15B	P16B	P17B	P18B	P19B	P20B	P21B	P22B	P23B	P24B	P25B	P26B	P27B	P28B	P29B	P30B	P31B	P32B	P33B	P34B	P35B	NP	NP	F2	F2	
Pin No.	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27	28	29	30	31	32	33
Connection	F1	F1	NP	NP	1GB	2GB	3GB	4GB	5GB	6GB	7GB	8GB	9GB	10GB	11GB	12GB	13GB	14GB	15GB	NX (IC)	NX	NX	NX	NX	NX	NX	P1B	P2B	P3B	P4B	P5B	P6B	P7B

Note: 1) F1, F2 ..... Filament pin 2) 1GA to 16GA, 1GB to 15GB ..... Grid pin 3) P1A to P35A, P1B to P35B ..... Anode pin 4) NP ..... No pin
5) NX ..... No extended pin 6) NX (IC) ..... Pins are internally connected, are should be electrically opened on the PCB


- **GRID ASSIGNMENT**



(16GA)



(1GA~14GA)
(1GB~14GB)



(15GB)

- **ANODE CONNECTION**


	1GA-14GA	15GA	16GA
P1A	1-1A	neural	X1
P2A	2-1A	AAC	USB
P3A	3-1A	CSII	NET
P4A	4-1A	DSD	R
P5A	5-1A	PCM	XM
P6A	1-2A	WMA	X2
P7A	2-2A	MP3	DOCK
P8A	3-2A	FLAC	X3
P9A	4-2A		S1
P10A	5-2A	SILENT CINEMA	X4
P11A	1-3A	HDMI	X5
P12A	2-3A	IN	X6
P13A	3-3A	OUT1	X7
P14A	4-3A	OUT2	X8
P15A	5-3A	ENHANCER	X9
P16A	1-4A	DD DIGITAL	X10
P17A	2-4A	PLUS	X11
P18A	3-4A	DD PL	X12
P19A	4-4A	II	X13
P20A	5-4A	x	MULTI CH
P21A	1-5A	DD EX	X14
P22A	2-5A	DD TRUE HD	X15
P23A	3-5A	YPAO	SIRIUS
P24A	4-5A	PRESET	X16
P25A	5-5A	CINEMA DSP	HD
P26A	1-6A	3	TAG
P27A	2-6A	VIRTUAL	TUNED
P28A	3-6A	ADAPTIVE DRC	STEREO
P29A	4-6A	DISCRETE	AUTO
P30A	5-6A	MATRIX	MEMORY
P31A	1-7A	dts	CATEGORY
P32A	2-7A	HD	ALL
P33A	3-7A	ES	PTY
P34A	4-7A	96 24	HOLD
P35A	5-7A	MASTER AUDIO	EON


	1GB-14GB	15GB
P1B	1-1B	V1
P2B	2-1B	V2
P3B	3-1B	V3
P4B	4-1B	V4
P5B	5-1B	V5
P6B	1-2B	V6
P7B	2-2B	V7
P8B	3-2B	V8
P9B	4-2B	V9
P10B	5-2B	V10
P11B	1-3B	V11
P12B	2-3B	V12
P13B	3-3B	V13
P14B	4-3B	V14
P15B	5-3B	V15
P16B	1-4B	V16
P17B	2-4B	V17
P18B	3-4B	V18
P19B	4-4B	V19
P20B	5-4B	»
P21B	1-5B	SLEEP
P22B	2-5B	PRE AMP
P23B	3-5B	ZONE 2
P24B	4-5B	ZONE 3
P25B	5-5B	ZONE 4
P26B	1-6B	W1
P27B	2-6B	L
P28B	3-6B	C
P29B	4-6B	R
P30B	5-6B	SL
P31B	1-7B	LFE
P32B	2-7B	SR
P33B	3-7B	SBL
P34B	4-7B	SB
P35B	5-7B	SBR

■ IC DATA

IC534, 567: D70YE101BRFP266 (DSP P.C.B.)
Decoder/Post processor

*** No replacement part available. / サービス部品供給なし**






No.	Function Name (P.C.B.)	TYPE(1)	PULL(2)	GPIO(3)	Detail of Function
1	VSS				
2	AHCLKX0/AHCLKX2	IO	–	Y	McASP0 and McASP2 transmit master clock
3	AMUTE0	IO	–	Y	McASP0 mute output
4	AMUTE1	IO	–	Y	McASP1 mute output
5	AHCLKX1	IO	–	Y	McASP1 transmit master clock
6	VSS				
7	ACLKX1	IO	–	Y	McASP1 transmit bit clock
8	CVDD				
9	ACLKR1	IO	–	Y	McASP1 receive bit clock
10	DVDD				
11	AFSX1	IO	–	Y	McASP1 transmit frame Sync (L/R clock)
12	AFSR1	IO	–	Y	McASP1 receive frame Sync (L/R clock)
13	VSS				
14	RESET	IO	–	N	Device reset pin
15	VSS				
16	CVDD				
17	CLKIN	IO	–	N	Alternate clock input (3.3-V LVCMOS input)
18	VSS				
19	TMS	IO	IPU	N	Test mode select
20	CVDD				
21	TRST	IO	IPU	N	Test reset
22	OSCVSS	PWR	–	N	Oscillator Vss tap point (for filter only)
23	OSCIN	IO	–	N	1.2-V oscillator input
24	NC	O	–	N	
25	OSCVDD	PWR	–	N	Oscillator 1.2-V Vpp tap point (for filter only)
26	VSS				
27	PLLHV	PWR	–	N	PLL 3.3-V supply input (requires external filter)
28	TDI	IO	IPU	N	Test data in
29	TDO	OZ	IPU	N	Test data out
30	VSS				
31	DVDD				
32	EMU[0]	IO	IPU	N	Emulation pin 0
33	CVDD				
34	EMU[1]	IO	IPU	N	Emulation pin 1
35	TCK	IO	IPU	N	Test clock
36	Ground(Vss)				
37	EM_CAS	O	–	N	SDRAM column address strobe
38	EM_WE	O	–	N	SDRAM write enable
39	EM_WE_DQM[0]	O	–	N	Write enable or byte enable for EM_D [7:0]
40	VSS				
41	EM_D[7]	IO	–	N	EMIF data bus [lower 16-bits]
42	DVDD				
43	EM_D[6]	IO	–	N	EMIF data bus [lower 16-bits]
44	CVDD				
45	EM_D[5]	IO	–	N	EMIF data bus [lower 16-bits]
46	EM_D[4]	IO	–	N	EMIF data bus [lower 16-bits]
47	VSS				
48	EM_D[3]	IO	–	N	EMIF data bus [lower 16-bits]
49	EM_D[2]	IO	–	N	EMIF data bus [lower 16-bits]
50	DVDD				
51	EM_D[1]	IO	–	N	EMIF data bus [lower 16-bits]
52	EM_D[0]	IO	–	N	EMIF data bus [lower 16-bits]
53	CVDD				
54	VSS				
55	EM_D[15]	IO	–	N	EMIF data bus [lower 16-bits]
56	EM_D[14]	IO	–	N	EMIF data bus [lower 16-Bits]
57	CVDD				
58	EM_D[13]	IO	–	N	EMIF data bus [lower 16-Bits]
59	EM_D[12]	IO	–	N	EMIF data bus [lower 16-Bits]
60	DVDD				
61	EM_D[11]	IO	–	N	EMIF data bus [lower 16-Bits]


No.	Function Name (P.C.B.)	TYPE(1)	PULL(2)	GPIO(3)	Detail of Function
62	VSS				
63	EM_D[10]	IO	–	N	EMIF data bus [lower 16-Bits]
64	EM_D[9]	IO	–	N	EMIF data bus [lower 16-Bits]
65	CVDD				
66	EM_D[8]	IO	–	N	EMIF data bus [lower 16-bits]
67	EM_WE_DQM[1]	O	–	N	Write enable or byte enable for EM_D [15:8]
68	DVDD				
69	VSS				
70	EM_CLK	O	–	N	SDRAM clock
71	EM_CKE	O	–	N	SDRAM clock enable
72	VSS				
73	DVDD				
74	EM_A[11]	O	–	N	EMIF address bus
75	EM_A[9]	O	–	N	EMIF address bus
76	EM_A[8]	O	–	N	EMIF address bus
77	CVDD				
78	VSS				
79	EM_A[7]	O	–	N	EMIF address bus
80	EM_A[6]	O	–	N	EMIF address bus
81	DVDD				
82	VSS				
83	EM_A[5]	O	–	N	EMIF address bus
84	EM_A[4]	O	–	N	EMIF address bus
85	CVDD				
86	EM_A[3]	O	–	N	EMIF address bus
87	VSS				
88	EM_A[2]	O	–	N	EMIF address bus
89	EM_A[1]	O	–	N	EMIF address bus
90	CVDD				
91	EM_A[0]	O	–	N	EMIF address bus
92	DVDD				
93	EM_A[10]	O	–	N	EMIF address bus
94	EM_BA[1]	O	–	N	SDRAM bank address and asynchronous memory Low-Order address
95	VSS				
96	EM_BA[0]	O	–	N	SDRAM bank address and asynchronous memory Low-Order address
97	EM_CS[0]	O	–	N	SDRAM chip select
98	EM_RAS	O	–	N	SDRAM row address strobe
99	VSS				
100	EM_CS[2]	O	–	N	Asynchronous memory chip Select
101	CVDD				
102	NC	O	–	N	Asynchronous memory read/not write
103	DVDD				
104	EM_OE	O	–	N	SDRAM output enable
105	SPI0_ENA/I2C1_SDA	IO	–	Y	SPI0 enable (ready) or I2c1 serial data
106	VSS				
107	SPI0_ENA/I2C1_SCL	IO	–	Y	SPI0 enable (ready) or I2c1 serial clock
108	SPI0_CLK/I2C0_SCL	IO	–	Y	SPI0 serial clock or I2c0 serial clock
109	VSS				
110	SPIO_SIMO	IO	–	Y	SPI0 data pin slave in master out
111	SPIO_SOMI/I2C0_SDA	IO	–	Y	SPI0 data pin slave out master in or I2C0 serial data
112	DVDD				
113	AXR0[0]	IO	–	Y	McASP0 serial data 0
114	VSS				
115	AXR0[1]	IO	–	Y	McASP0 serial data 1
116	AXR0[2]	IO	–	Y	McASP0 serial data 2
117	AXR0[3]	IO	–	Y	McASP0 serial data 3
118	VSS				
119	AXR0[4]	IO	–	Y	McASP0 serial data 4
120	SPI1_SCS	IO	–	Y	McASP0 serial data 5 or SPI1 slave chip select
121	SPI1_ENA	IO	–	Y	McASP0 serial data 6 or SPI1 enable (ready)
122	SPI1_CLK	IO	–	Y	McASP0 serial data 7 or SPI1 serial clock

No.	Function Name (P.C.B.)	TYPE(1)	PULL(2)	GPIO(3)	Detail of Function
123	CVDD				
124	VSS				
125	DVDD				
126	/SPI1_SOMI	IO	–	Y	McASP0 serial data 8 or McASP1 serial data 5 or SPI1 data pin slave out master in
127	/SPI1_SIMO	IO	–	Y	McASP0 serial data 9 or McASP1 serial data 4 or SPI1 data pin slave in master out
128	CVDD				
129	VSS	IO	–	Y	
130	AXR0[10]	IO	–	Y	McASP0 serial data 10 or McASP1 serial data 3
131	AXR0[11]				McASP0 serial data 11 or McASP1 serial data 2
132	CVDD				
133	VSS	IO	–	Y	
134	AXR0[12]	IO	–	Y	McASP0 serial data 12 or McASP1 serial data 1
135	AXR0[13]				McASP0 serial data 13 or McASP1 serial data 0
136	DVDD	IO	–	Y	
137	AXR0[14]	IO	–	Y	McASP0 serial data 14 or McASP2 serial data 1
138	AXR0[15]	IO	–	Y	McASP0 serial data 15 or McASP2 serial data 0
139	ACLKR0				McASP0 receive bit clock
140	VSS	IO	–	Y	
141	AFSR0	IO	–	Y	McASP0 receive frame Sync (L/R clock)
142	ACLKX0	IO	–	Y	McASP0 transmit bit clock
143	AHCLKR0/AHCLKR1	IO	–	Y	McASP0 and McASP1 receive master clock
144	AFSX0				McASP0 transmit frame Sync (L/R clock)

IC402: M3087BFKBGP (FUNCTION P.C.B.)
Main microprocessor



NOTES:
1. Ports P11 to P15 are provided in the 144-pin package only.
2. Included in the 144-pin package only.
3. The supply voltage of M32C/84T (High-reliability version) must be $V_{CC1}=V_{CC2}$.



NOTES:
1. $P7_0$ / $TA0_{OUT}$ / TxD2 / SDA2 / $SRxD2$ / $INPC1_6$ / $OUTC1_6$
2. $P7_0$ and $P7_1$ are ports for the N-channel open drain output.
3. The supply voltage of M32C/84T must be $V_{CC1}=V_{CC2}$.

Pin No.	Port Name	Function Name (P.C.B.)	I/O					Detail of Function
			Power On	Standby	MCU Sleep [AC OFF]	CEC Standby [OFF]	Sleep	
1	TXD4	SIRTXD	SO	O			O	Asynchronous data output for SIRIUS (U, C models)
			O	O			O	Hardware connection is NC / Perform Low Fix treatment also when power on (R, T, K, A, B, G, E, L, J models)
2	P9_5	SCKN	O	O	O			Clock output for FL DRIVER IC / PT6302
			O	O	O			Clock output for EPROM IC / BR25L320F-W
			O	O	O			Clock output for expanded IC / LC709004A Max. 2MHz when using VDD=4.5 to 6V
3	P9-4	PRI	I	O	O			Current protection detection / 100k pull-down
4	DA1	LMTCNT	DA	O	O			Limiter control output
5	SDA3	–	O	O			O	Hardware connection is NC / Perform Low Fix treatment also when power on (U, C, R, T, K, A, B, G, E, L models)
		SDACEC	SIO			SIO	O	CEC microprocessor I2C_SDA port (open drain input/output) Set to “Low Fix” when 4.7k pull-up and CEC_PE=Low (ES only) Set to “L” before [CEC_PE, VPOWER]=[0, 0] and to “H” after [CEC_PE, VPOWER]≠[0, 0] (J model)
6	SCL3	–	O	O			O	Hardware connection is NC / Perform Low Fix treatment also when power on (U, C, R, T, K, A, B, G, E, L models)
		SCLCEC	SIO			SIO	O	CEC microprocessor I2C_SCL port (open drain input/output) Set to “Low Fix” when 4.7k pull-up and CEC_PE=Low (ES only) Set to “L” before [CEC_PE, VPOWER]=[0, 0] and to “H” after [CEC_PE, VPOWER]≠[0, 0] (J model)
7	TB0in	/VSYNC	TMR	O	O			Vertical sync pulse INT
8	P146	RSELDT0	O	O	O			Recout SW1 control (ROHM) data Clock speed: 20us, MSBF (U, C, R, T, K, A, B, G, E, L models)
		–	O	O			O	Hardware connection is NC because J model has no Zone 2, 3 Perform Low Fix treatment also when power on (J model)
9	P145	RSELCK0	O	O	O			Recout SW1 control (ROHM) clock (U, C, R, T, K, A, B, G, E, L models)
		–	O	O			O	Hardware connection is NC because J model has no Zone 2, 3 Perform Low Fix treatment also when power on (J model)
10	P144	ISELDT0	O	O	O			Recout SW1 control (ROHM) data / Clock speed: 20us, MSBF
11	P143	ISELCK0	O	O	O			Recout SW1 control (ROHM) clock
12	INPC1_6	HDIMT	IRQ	O			O	HDMI MUTE input
13	P141	/CSDAC1	O	O	O			Chip enable of 2shDAC (PCM1791A) *6
14	P140	–	O	O			O	Hardware connection is NC / Perform Low Fix treatment also when power on (U, C, R, T, K, A, B, G, E, L models)
		/INTCEC				TMR [O]	O	CEC command processing request interrupt input / 10k pull-up CEC_PUPWR (Pin113@M32C)=Hi-Z -> Low Fix (OUT) (J model)
15	BYTE	BYTE	MCU	MCU	MCU		MCU	External data bus width change: 16bit
16	CNVss	CNVss	MCU	MCU	MCU		MCU	Processor mode selection: Single chip mode / Hi: To flash built-in boot mode To boot mode with P50=H, P55=L, CNVss=H setting when resetting the hardware
17	P87	/ICD	O	O	O			DIR initial clear
18	P86	/CSTI	I	O	O			TI #1 SPI READY
19	RESET	RESET	MCU	MCU	MCU		MCU	
20	Xout	Xout	MCU	MCU	MCU		MCU	
21	Vss	Vss	MCU	MCU	MCU		MCU	
22	Xin	Xin	MCU	MCU	MCU		MCU	
23	Vcc	Vcc	MCU	MCU	MCU		MCU	
24	NMI	NMI	IRQ	I	I			
25	INT2	REM2	IRQ	IRQ	IRQ [O]			Remote control pulse input 2 / Remote control pulse input for Zone (U, C, R, T, K, A, B, G, E, L models)
			O	O			O	Hardware connection is NC Perform Low Fix treatment also when power on because there is no remote control input for Zone Perform Low Fix treatment also when power on (J model)
26	INT1	PDET	IRQ	IRQ	IRQ			Power detection / 100k pull-up to 5M2 on SUB TR P.C.B.
27	INT0	RXDR	IRQ	IRQ	IRQ [O]			RS232C · YDC reception detection
28	TA4in	iPDET	TMR	O	O			iPod detection
29	RXD5	HDRXD	SI	O			O	Asynchronous data input for HD-Radio (U model)
		PLLR	I	O	O			PLL reception for tuner / Reception clock 20us / LSB fast (C, A models)
		–	O	O			O	Hardware connection is NC / Perform Low Fix treatment also when power on (R, T, K, B, G, E, L, J models)

Pin No.	Port Name	Function Name (P.C.B.)	I/O					Detail of Function
			Power On	Standby	MCU Sleep [AC OFF]	CEC Standby [OFF]	Sleep	
30	CLK5	–	O	O			O	HD-Radio connection is NC / Perform Low Fix treatment also when power on (U model)
		TUCK	O	O	O			PLL clock output for tuner (C, A models)
		–	O	O			O	Hardware connection is NC / Perform Low Fix treatment also when power on (R, T, K, B, G, E, L, J models)
31	TXD5	HDTXD	SO	O			O	Asynchronous data output for HD-Radio (U model)
		TUDA	O	O	O			PLL data output for tuner / Transmission clock 4us / LSB fast (C, A models)
		–	O	O			O	Hardware connection is NC / Perform Low Fix treatment also when power on (R, T, K, B, G, E, L, J models)
32	TA2in	/INTTI	TMR	O	O			TI #0 / #1(DA70Y) interrupt
33	INPC1_1	–	O	O			O	Hardware connection is NC / Perform Low Fix treatment also when power on (U, C, R, T, K, A, B, G, E, L models)
		CEC-D	I			I [O]	O	CEC initialization request input / 10k pull-up CEC_PUPWR (Pin113@M32C)=Hi-Z -> Low Fix (OUT) (J model)
34	TA1in	/INTDIR	TMR	O	O			DIR interruption
35	P72/CLK2/TA1out	SPIRDY /SPIRDY /SPURDY0	I	O	O			TI DA70Y serial ready
			I	O	O			DIR WCK input (WCK input for CDDA writing)
36	P71/RxD2/SCL2	DRXM	SI	O			O	DABIC IC RxD (XM data reception) / 1.5k pull-up to +5SPC (U, C models)
		–	O	O			O	Hardware connection is NC / Perform Low Fix treatment also when power on (R, T, K, A, B, G, E, L, J models)
37	P70/TXD2/SDA2	DTXM	SO	SIO			O	DABIC IC TxD (open drain) / 1.5k pull-up to +5SPC (U, C models)
		–	O	O			O	Hardware connection is NC / Perform Low Fix treatment also when power on (R, T, K, A, B, G, E, L, J models)
38	P67/TxD1	TXDH (M to V)	SO	SO	O			Asynchronous data transmission to VIDEO_CPU usually RS-232C asynchronous communication data output Data transmission terminal for AF220
39	Vcc	Vcc	MCU	MCU	MCU		MCU	
40	P66/RxD1	RXDH (V to M)	SI	SI				Asynchronous data input to VIDEO_CPU usually RS-232C Asynchronous communication data input Data reception terminal for AF220
					SI			[RS232C ON]
					O			[RS232C OFF] Perform Low Fix treatment because the driver output becomes HiZ when 232C driver is OFF
41	Vss	Vss	MCU	MCU	MCU		MCU	
42	P65/CLK1	RTSH	SO	SO	O			D-VIDEO asynchronous communication RTS output usually RS-232C asynchronous communication RTS output
		CLKF	SO					Clock input for AF220
43	P64/CTS1/RTS1/	CTSH	I	I	[O]			D-VIDEO asynchronous communication CTS input usually RS-232C asynchronous communication CTS input
		YDCBUSY	O					BUSY output for AF220
44	P63/TxD0	TXDD	SO	O	O			To DIR, TI (DA70Y), DAC serial data output / DIR: 4M, LSBF TI: 1M, MSBF
45	P62/RxD0	RXDD	SI	O	O			To DIR, TI (DA70Y), DAC serial data reception / DIR: 4M, LSBF TI: 1M, MSBF
46	P61/CLK0	CLKD	SO	O	O			To DIR, TI (DA70Y), DAC serial clock output
47	P60/CTS0/RTS0	DMT	O	O	O			Digital FULL MUTE (HI=MUTE)
48	P137	CDDA/XLINK	I	O	O			CDDA writing for both DATA input / XMLINK ACTIVE
49	P136	/CSTI0	O	O	O			T1 #0 chip enable
50	P135	/CSTI1 /CSY	O	O	O			T1 #1 chip enable
51	P134	XMPWR	O	O	O			XM Radio power supply control (U, C models)
		–	O	O			O	Perform Low Fix treatment / NC for hardware (R, T, K, A, B, G, E, L, J models)
52	P57/RDY	–	O	O			O	Set to “High” before turning on the main power and to “Low” after turning it off (U model)
		/TMUTE	O	O	O			TUNER mute output / Logical inversion by Tr on FUNCTION P.C.B. (C, R, T, K, A, B, G, E, L, J models)
53	P56/RAS	–	I	O			O	Pull-down to GND when connected HD-Radio is connected (U model)
		TUNED	I	O	O			TUNER TUNED input / Pull-up to +5SPC (C, R, T, K, A, B, G, E, L, J models)
54	P55/HOLD	HD_PE	O	O			O	HD-Radio reset output (L+Reset) (U model)
		TUCE	O	O	O			PLL chip select for tuner (C, R, T, K, A, B, G, E, L, J models)

Pin No.	Port Name	Function Name (P.C.B.)	I/O					Detail of Function
			Power On	Standby	MCU Sleep [AC OFF]	CEC Standby [OFF]	Sleep	
55	P54/HLDA	–	I	O			O	Pull-down to GND when HD-Radio is connected (U model)
		/ST	I	O	O			TUNER STEREO detection input (C, R, T, K, A, B, G, E, L, J models) Pull-up to +5SPC
56	P133	CKZEV	O	O	O			T-CONT/EVOL IC serial transmission clock for ZONE NJW1194V (U, C, R, T, K, A, B, G, E, L models)
		–	O	O			O	Hardware connection is NC because J model has no Zone2, 3 Perform Low Fix treatment also when power on (J model)
57	Vss	Vss	MCU	MCU	MCU		MCU	
58	P132	DTZEV	O	O	O			T-CONT/EVOL IC chip select for ZONE (U, C, R, T, K, A, B, G, E, L models) NJW1194V
		–	O	O			O	Hardware connection is NC because J model has no Zone2, 3 Perform Low Fix treatment also when power on (J model)
59	Vcc	Vcc	MCU	MCU	MCU		MCU	
60	P131	/CEZEV0	O	O	O			T-CONT/EVOL IC serial transmission data for ZONE NJW1194V (U, C, R, T, K, A, B, G, E, L models)
		–	O	O			O	Hardware connection is NC because J model has no Zone2, 3 Perform Low Fix treatment also when power on (J model)
61	P130	/Z4MT	O	O	O [O]			Zone4 Mute control (U, C, R, T, K, A, B, G, E, L models)
		/MODE	I	I	I [O]			High: Normal mode / Low: Special mode (circuit board check, etc.) (J model)
62	P53/BCLK	/Z2MT	O	O	O [O]			Zone2 Mute control (U, C, R, T, K, A, B, G, E, L models)
		–	O	O			O	Hardware connection is NC because J model has no Zone2 Perform Low Fix treatment also when power on (J model)
63	P52/RD	/Z3MT	O	O	O [O]			Zone3 Mute control (U, C, R, T, K, A, B, G, E, L models)
		–	O	O			O	Hardware connection is NC because J has no Zone3 Perform Low Fix treatment also when power on (J model)
64	P51/WRH	/FMTF	O	O	O [O]			Full Mute FL/SBL/SBR
65	P50/WRL	–	O	O	O			
66	P127	/FMTS	O	O	O [O]			Full Mute SL/SR
67	P126	/FMTC	O	O	O [O]			Full Mute Center
68	P125	/FMTSW	O	O	O [O]			Full Mute SWL/SWR/SW MONO
69	P47/CS0	DTEV	O	O	O			EVOL IC serial transmission data for MAIN
70	P46/CS1	CKEV	O	O	O			EVOL IC serial transmission clock for MAIN
71	P45/CS2	/CEEV	O	O	O			EVOL CE for MAIN
72	P44/CS3	CEA	O	O	O			Chip select output for JRC audio select IC / NJU731xAM
73	P43/A19	SDTA	O	O	O			Data output for JRC Audio select IC NJU731xAM: Transmission clock 10us MSB fast
74	Vcc	Vcc	MCU	MCU	MCU		MCU	
75	P42/A18	SCKA	O	O	O			Clock output for JRC Audio select IC NJU731xAM: Transmission clock 10us MSB fast
76	Vss	Vss	MCU	MCU	MCU		MCU	
77	P41/A17	TRG2	O	O	O			DC TRIGGER output 2
78	P40/A16	TRG1	O	O	O			DC TRIGGER output 1
79	P37/A15	232PWR	O	O	O			Rear232C driver ON/OFF control
80	P36/A14	PRY	O	O	O			Power relay control
81	P35/A13	RYBL	O	O	O			POWER AMP B relay control for power supply control ON at Low power supply
82	P34/A12	RYBM	O	O	O			POWER AMP B relay control for power supply control ON at Mid. power supply
83	P33/A11	/CSEX	O	O	O			Chip select for expanded IC / LC709004A Max. 2MHz when using VDD=4.5 to 6V
84	P32/A10	/ICEX	O	O	O			Reset for expanded IC / LC709004A / Max. 2MHz when using VDD=4.5 to 6V
85	P31/A9	iPWR	O	O	O			iPod power supply control
86	P142	/CSDAC2	O	O	O			TI#1 initial clear
87	CTS6	CTSR	I	O			O	
88	RXD6	RXDR	SI	O	O			

Pin No.	Port Name	Function Name (P.C.B.)	I/O					Detail of Function
			Power On	Standby	MCU Sleep [AC OFF]	CEC Standby [OFF]	Sleep	
89	P121	RTSR	O	O			O	
90	TXD6	TXDR	SO	O	O			
91	Vcc		MCU	MCU	MCU		MCU	
92	P30/A8	VMT	O	O	O			Video output MUTE / This port is logically inverted at ON*Tr when Power ON/OFF and Pure Direct ON/OFF
93	Vss		MCU	MCU	MCU		MCU	
94	AN27/P27/A7	/EPROM	O	O			O	Chip select output for EPROM IC (Unused, High_Fix or Low_Fix) / BR25L320F-W
95	AN26/P26/A6	VPOWER	O					VIDEO power supply control (Low when VIDEO OFF) iPAP is received by VNP2
96	AN25/P25/A5	RSELDT1	O	O	O			Recout SW1 control (ROHM) data / Clock speed: 20us, MSBF (U, C, R, T, K, A, B, G, E, L models)
		–	O	O			O	Hardware connection is NC because J model has no Zone 2, 3 Perform Low Fix treatment also when power on (J model)
97	AN24/P24/A4	RSELCK1	O	O	O			Recout SW1 control (ROHM) clock (U, C, R, T, K, A, B, G, E, L models)
		–	O	O	O			Hardware connection is NC because J model has no Zone 2, 3 Perform Low Fix treatment also when power on (J model)
98	AN23/P23/A3	ISELDT1	O	O	O			Recout SW1 control (ROHM) data / Clock speed: 20us, MSBF
99	AN22/P22/A2	ISELCK1	O	O	O			Recout SW1 control (ROHM) clock
100	AN21/P21/A1	/ICFL	O	O	O			FL driver initial clear
101	AN20/P20/A0	CEF2	O	O	O			FL enable2
102	P17/D15/INT5	PSWDET	IRQ	IRQ	IRQ [O]			Main Zone 2, 3 power key interrupt
103	P16/D14/INT4	MSW	IRQ	IRQ	IRQ [O]			MASTER SW (Push lock SW)
104	P15/D13/INT3	REM1	IRQ	IRQ	IRQ [O]			Remote control pulse input 1
105	P14/D12	CEF1	O	O	O			FL enable 1
106	P13/D11	BT232C	I	I	O			RS232C Flash writing mode detection
		–	O	O	O			TI#0 Initial clear
107	P12/D10	–	O	O			O	Hardware connection is NC / Perform Low Fix treatment also when Power On (U, C, R, T, K, A, B, G, E, L models)
		CEC_PE	O	O	O			Power for CEC circuit ON/OFF (J model)
108	P11/D9	–	O	O			O	Hardware connection is NC / Perform Low Fix treatment also when Power On (U, C, R, T, K, A, B, G, E, L models)
		/ICCEC	OD	O	O			CEC microprocessor initial clear Open drain output (Pull-up to +3.3V on CEC side) (J model)
109	P10/D8	PSW2	I	I	O			Logical key discriminated after INT5: PSW input
110	P07/AN07/D7	PSW1	I	I	O			Logical key discriminated after INT5: PSW input
111	P06/AN06/D6	SPC	O	O	O [O]			• +5SPC Power ON/OFF control (L=ON, H=OFF: To reduce stand-by power) • Fixed to Low usually. Setting to HI after the stand-by related process reduces stand-by power (MCUSleep) (Neither expansion port nor expansion A/D does not operate when set to HI) • Keep “HighFix” as it is until Power ON signal is inputted when AC IN or MCU-Sleep is used
112	P05/AN05/D5	/HPMT	O	O	O [O]			Headphone Mute control
113	P04/AN04/D4	CEC_PUPWR				O [I]	I	Power supply for pull-up resistor of CEC microprocessor interface (12C, IRQ) OFF/ON Set to “Hi-Z” before [CEC_PE, VPOWER]=[0, 0] and to “L” after [CEC_PE, VPOWER]≠[0, 0] (To prevent +5V/+3.3V voltage from being applied to CEC microprocessor port when CEC microprocessor power is OFF) (J model)
		–	O	O			O	Hardware connection is NC because there is no CEC other than J model Perform Low Fix treatment also when Power On (U, C, R, T, K, A, B, G, E, L models)
114	P114	/ICEQ	O	O	O			HDMI Equalizer reset output
115	INPC1_3	H2MIRQ	IRQ	O	O			VIDEO_CPUI transfer request input
116	P112	EXDI	I	I			O	Data IN for expanded IC, EEPROM / LC709004A Max. 2MHz when using VDD=4.5 to 6V
117	P111/ISCLK1	HDMINT	TMR	O	O			HDMI interrupt input

Pin No.	Port Name	Function Name (P.C.B.)	I/O					Detail of Function
			Power On	Standby	MCU Sleep [AC OFF]	CEC Standby [OFF]	Sleep	
118	P110	SDTN	O	O	O			Data output for FL DRIVER IC / PT6302
			O	O	O			Data output for expanded IC / LC709004A Max. 2MHz when using VDD=4.5 to 6V
119	P03/AN03/D3	VRB	I	O	O			Volume rotary B
120	P02/AN02/D2	PDLED	O	O	O			Pure direct LED
121	P01/AN01/D1	/ICH	O	O	O			VIDEO_CPU reset
		–	O	O			O	
122	P00/AN00/D0	/ICXM	O	O			O	XMDT IC reset (U, C models)
		–	O	O			O	Hardware connection is NC Perform Low Fix treatment also when Power On (R, T, K, A, B, G, E, L, J models)
123	AN157	KEY1	AD	O	I [O]			KEY1 AD value taken in
124	AN156	KEY0	AD	O	I [O]			KEY0 AD value taken in
125	AN155	DOCK_ID	AD	O			O	DOCK_ID detection input: YBA or YDS or others ?
126	AN154	SIR_PE	AD	O	O			SIRIUS power enable (U, C models)
127	AN153	PRV2	AD	O			O	Power protection detection 2
128	AN152/P152/ISRXD0	M2HIRQ	O	O			O	MAIN_CPUI transfer request output
129	AN151/P151/ISCLK0	VRA	I	O	O			Volume rotary A
130	Vss	Vss	MCU	MCU	MCU		MCU	
131	AN150/P150/ISTXD0	/CSDIR	O	O	O			DIR chip enable
132	Vcc	Vcc	MCU	MCU	MCU		MCU	
133	P107/AN7	DEST	AD	AD	I [O]			Destination discrimination by AD value When AD is taken in at Power On, there is 1msec waiting time after AD input port setting
134	AN0_1	MODEL	AD	AD	I [O]			Model discrimination by AD value When AD is taken in at Power On, there is 1msec waiting time after AD input port setting
135	AN5	THM1	AD	O	I [O]			AD temperature detection 1
136	AN4	THM2	AD	O	I [O]			AD temperature detection 2
137	AN3	PRD	AD	O	O			Power amplifier DC protection detection
138	AN2	PRV1	AD	O	O			Power protection detection 1
139	AN1	PRVS (PRVP)	AD	O	O			Power protection detection 3 (Power turned off by Pure Direct)
140	Avss	AVSS	MCU	MCU	MCU		MCU	
141	AN0	OUTLVL	AD	O	O			AD power limiter output level detection
142	Vref	VREF	MCU	MCU	MCU		MCU	
143	Avcc	AVCC	MCU	MCU	MCU		MCU	
144	RXD4	SIRRXD	SI	O			O	Asynchronous data input for SIRIUS (U, C models)
		–	O	O			O	Hardware connection is NC / Perform Low Fix treatment also when Power On (R, T, K, A, B, G, E, L, J models)

Expansion of serial parameter / シリパラ拡張 (LC709004A)

Pin No.	Port Name	Function Name (P.C.B.)	I/O				Detail of Function
			Power On	Standby	MCU Sleep	OUTPUT	
24	P00	SPF	O				Front speaker relay control
23	P01	SPSR	O				Surround speaker relay control
22	P02	SPZ3	O				Z3 speaker relay control
21	P03	SPZ2	O				Z2 speaker relay control
20	P04	SPSB	O				Surround Back speaker relay control
19	P05	SPC	O				Center speaker relay control
18	P06	–				O	TUNER power ON/OFF (High=ON, Low=OFF)
17	P07					O	
15	P10	/MIC	I	O	O		MIC detection / 220k pull-down (U, C, R, T, K, A, B, G, E, F, L models)
14	P11	/HP	I	O	O		Headphone detection / 100k pull-up to +5SPC (U, C, R, T, K, A, B, G, E, F, L models)
13	P12					O	
12	P13					O	
11	P14					O	
10	P15					O	
9	P16					O	
8	P17					O	

RX-V3900 (U, C, R, T, K, A, B, G, E, L models)
Key input(A-D) pull-up resistance 10 k-ohms

Ohm *	0	+1.2k	+1.2k	+1.8k	+2.7k	+3.3k	+4.7k	+8.2k	+18.0k	+47.0k
V	-0.26	-0.75	-1.22	-1.76	-2.28	-2.75	-3.24	-3.75	-4.25	-4.72
KEY0 (124pin/AN156)	INFO	ZONE CONTROLS	CATEGORY / BAND	STEREO/ MONO	SEARCH MODE	MEMORY	PRESET/ TUNING >	PRESET/ TUNING <	ZONE ON/OFF ZONE2	ZONE ON/OFF ZONE3
KEY1 (123pin/AN157)	STRAIGHT / EFFECT	ENTER	TONE CONTROL	MENU	AUDIO SELECT / REC OUT	PURE DIRECT	–	–	–	–

* KEY0: R9022 to R9051 of FL (1) P.C.B., KEY1: R9017 to R9021 of FL (1) P.C.B. / R8004 of OPERATION (2) P.C.B.

DSP-AX3900 (J model)
Key input(A-D) pull-up resistance 10 k-ohms

Ohm *	0	+1.2k	+1.2k	+1.8k	+2.7k	+3.3k	+4.7k	+8.2k	+18.0k	+47.0k
V	-0.26	-0.75	-1.22	-1.76	-2.28	-2.75	-3.24	-3.75	-4.25	-4.72
KEY0 (124pin/AN156)	INFO	–	BAND	STEREO/MONO	SEARCH MODE	MEMORY	PRESET/ TUNING >	PRESET/ TUNING <	–	–
KEY1 (123pin/AN157)	STRAIGHT / EFFECT	ENTER	TONE CONTROL	MENU	AUDIO SELECT	PURE DIRECT	–	–	–	–

* KEY0: R9022 to R9051 of FL (1) P.C.B., KEY1: R9017 to R9021 of FL (1) P.C.B. / R8004 of OPERATION (2) P.C.B.


Destination for AD Port / 仕向け判別ポート
Pull-up resistance 10 k-ohms

Ohm *	0.0k	1.2k	2.7k	4.7k	6.8k	10.0k	15.0k	24.0k	47.0k	100.0k
V	0-0.2	0.3-0.8	0.9-1.3	1.4-1.8	1.8-2.2	2.3-2.7	2.8-3.2	3.3-3.8	3.9-4.3	4.4-4.7
A-D (5V=255)	0-13	14-40	41-68	69-92	93-115	116-140	141-167	168-195	196-221	222-243
DEST (AN7) 133pin	J	U	C	R	T	K	A	–	B, G, E	L

Model distinction for AD port / モデル判別ポート

Ohm	–
V	4.7-5.0
A-D (5V=255)	243-255
DEST (AN6) 134pin	RX-V3900/DSP-AX3900

IC105: YTD-446CZ (D-VIDEO P.C.B.)
VNP2 (Video and network processor)
*** No replacement part available. / サービス部品供給なし**



Pin No.	Port Name	Function Name (P.C.B.)	I/O	Detail of Function
M25	nRESET	VNP2_N_RST	MCU	System reset terminal
T25	XI_S		MCU	System clock crystal oscillation terminal
T24	XO_S		MCU	System clock crystal oscillation terminal
AE24	XI_A		MCU	Audio clock crystal oscillation terminal
AD24	XO_A		MCU	Audio clock crystal oscillation terminal
T22	TEST0	TEST0	MCU	System reset terminal
R23	TEST1		MCU	Test mode setting
T23	TEST2		MCU	Test mode setting
AA3	nTRST	VNP2_N_TRST	MCU	
AB1	TDI	VNP2_TDI	MCU	
AC1	TDO	VNP2_TDO	MCU	
AA2	TCK	VNP2_TCK	MCU	
AB3	TMS	TNP2_TMS	MCU	
AB2	RTCK		MCU	
L23	nSCS3		CS	Chip select 3 for accessing YGV619 MEM
L24	nSCS2		CS	Chip select 2 for accessing YGV619 REG
K23	nSCS1		CS	Chip select 1 for accessing Flash ROM
K24	nSCS0		CS	Chip select 0 for accessing NPGA
J23	nSLBE		BUS	Lower byte write enable
J24	nSUBE		BUS	Upper byte write enable
K25	nSWR		BUS	8bit device write enable
J25	nSRD		BUS	Read enable
**	SA[22:0]		BUS	SRAM address bus / CS0 space
				CS1 space
				CS2 space
				CS3 space
**	SD[15:0]		BUS	SRAM data bus
B1	SCLK0		BUS	SDRAM clock
C1	SCKE0		BUS	SDRAM clock enable
D1	SCLK1		BUS	SDRAM clock
E1	SCKE1		BUS	SDRAM clock enable
F1	nCS1		CS	SDRAM chip select 1
C2	nCS0		CS	SDRAM chip select 0
E3	nWE		BUS	SDRAM write enable
F2	nRAS		BUS	SDRAM row address strobe
E2	nCAS		BUS	SDRAM column address strobe
A9	DQM3		BUS	SDRAM data input/output mask 3
B9	DQM2		BUS	SDRAM data input/output mask 2
C9	DQM1		BUS	SDRAM data input/output mask 1
C10	DQM0		BUS	SDRAM data input/output mask 0
**	A[11:0]		BUS	SDRAM address bus
F3	A12		BUS	
J2	A13		BUS	
J1	A14		BUS	
**	D[31:0]		BUS	SDRAM data bus
L25	nINT0	VNP2_TCK	IRQ	
M24	nINT1	M2V_N_INT_3	IRQ	Interrupt input from main microprocessor
M23	nINT2	GA_N_INT	IRQ	Interrupt input from NPGA
AE7	TXD0/AGPIO[3]	DBG_TXD	SO	For debugging
AE8	RXD0/AGPIO[0]	DBG_RXD	SI	For debugging
AD7	nCTS0/AGPIO[4]	DBG_LED0	O	LED output 0 for debugging
AD8	nRTS0/AGPIO[1]	DBG_LED1	O	LED output 1 for debugging
AC8	EXTCLK0/AGPIO[2]	V2M_N_INT_3	O	Interrupt output from main microprocessor
AE5	TXD1/AGPIO[9]	VCPU_TXD_3	SO	Communication between microprocessors (Asynchronous)
AE6	RXD1/AGPIO[6]	VCPU_RXD	SI	Communication between microprocessors (Asynchronous)
AD5	nCTS1/AGPIO[10]	VCPU_N_CTS	SI	Communication between microprocessors (Asynchronous)
AD6	nRTS1/AGPIO[7]	VCPU_N_RTS_3	SO	Communication between microprocessors (Asynchronous)
AC6	nDCD1/AGPIO[8]	DEV_N_RST	O	System reset

Pin No.	Port Name	Function Name (P.C.B.)	I/O	Detail of Function
AD4	nDSR1/AGPIO[13]	USB_HIZ	O	H: USB disconnected, L: USB connected
AC5	nDTR1/AGPIO[11]	FLASH_N_WP	O	H: FLASH write enable L: FLASH write disable (Only top sector is effective)
AE4	EXTCLK1/AGPIO[12]	USB_N_FRONT	O	H: Rear USB terminal is effective L: Front USB terminal is effective
AC7	nRI1/AGPIO[5]	HDMI_INT	I	
AE2	TXD2/AGPIO[18]	IPD_TXD	O	TXD to iPOD DOC
AE3	RXD2/AGPIO[15]	IPD_RXD	I	RXD from iPOD DOC
AD2	nCTS2/AGPIO[19]	HTX1_N_PWEN	O	IC733 (HDMI OUT2) +5V enable
AD3	nRTS2/AGPIO[16]	PHY_N_100M	I	H: Ether 10Mbps L: Ether 100Mbps
AD1	EXTCLK2/AGPIO[20]	HTX2_N_PWEN	O	IC730 (HDMI OUT1) +5V enable
AC4	PARITY/AGPIO[14]	PHY_N_FDX	I	H: Ether half duplex L: Ether full duplex
AC3	SIMRST/AGPIO[17]	PHY_PD	O	H: Ether low power mode L: Ether normal mode
AA1	I2C_SDA/BGPIO[0]	HDMI_SDA	SIO	I2C SDA input/output for HDMI RX (SII9135A) I2C SDA input/output for HDMI TX#1 (SII9134) I2C SDA input/output for HDMI TX#2 (SII9134)
Y1	I2C_SCL/BGPIO[1]	HDMI_SCL	SO	I2C SCL output for HDMI RX (SII9135A) 300k I2C SCL output for HDMI TX#1 (SII9134) 300k I2C SCL output for HDMI TX#2 (SII9134) 300k
Y3	SPI_SCK/BGPIO[3]	OSD_N_SCK_3	SO	OSD serial CK
W3	SPI_CS0/BGPIO[6]	OSD_N_CS_3	O	OSD chip select
V1	SPI_CS1/BGPIO[7]	ABT_1.0_EN_C	O	
V2	SPI_CS2/BGPIO[8]	ABT_1.8_EN_C	O	
V3	SPI_CS3/BGPIO[9]	ABT_3.3_EN_C	O	
W1	SPI_SDI/BGPIO[4]	WIFI_N_RST	O	
W2	SPI_SDO/BGPIO[5]	OSD_MOSI_3	SO	OSD serial data transmission
N25	BGPIO[16]	VOL_RA	I	Volume rotary A
N24	BGPIO[17]	VOL_RB	I	Volume rotary B
N23	BGPIO[18]	ISEL_RA	I	Input selector rotary A
P25	BGPIO[19]	ISEL_RB	I	Input selector rotary B
P24	BGPIO[20]	PRG_RA	I	PROGRAM rotary A
P23	BGPIO[21]	PRG_RB	I	PROGRAM rotary B
Y2	BGPIO[2]	NUDAC_MUT	O	NET/USB DAC H: Mute on / L: MUTE off
R25	BGPIO[22]	IPAP_DET	I	iPod accessory power detection
R24	BGPIO[23]	Z7_DET	I	Model discrimination H: RX-Z7/DSP-Z7 / L: RX-V3900/DSP-3900 (Applicable only when testing P.C.B.)
R1	SDO_ABCK	VNP2_BCK	MCU	Bit clock output for audio
U2	SDO_BBCK/BGPIO[11]	–		
P1	SDO_AWCK	VNP2_LRCK	MCU	LR clock output for audio
U3	SDO_BWCK/BGPIO[12]	–	I	USB excess current detection spare
U1	SDO_MCK/BGPIO[10]	VNP2_MCK	MCU	Master clock output for audio
P2	SDO3		MCU	Data output 3 for audio
P3	SDO2		MCU	Data output 2 for audio
R2	SDO1		MCU	Data output 1 for audio
R3	SDO0	VNP2_SDO	MCU	Data output 0 for audio
N1	SDI_ABCK		MCU	Bit clock input for audio
T2	SDI_BBCK/BGPIO[14]	DBG_DIP0	I	Mode switching DIP SW for debugging
M1	SDI_AWCK		MCU	LR clock input for audio
T3	SDI_BWCK/BGPIO[15]	DBG_DIP1	I	Mode switching DIP SW for debugging
T1	SDI_MCK/BGPIO[13]	GA_AMCKO	MCU	Master clock input for audio
M2	SDI3		MCU	Data input 3 for audio
M3	SDI2		MCU	Data input 2 for audio
N2	SDI1		MCU	Data input 1 for audio
N3	SDI0		MCU	Data input 0 for audio
AE16	USBP		MCU	USB data +
AD16	USBM		MCU	USB data -
AB16	USB_PWREN		MCU	USB power enable

Pin No.	Port Name	Function Name (P.C.B.)	I/O	Detail of Function
AC17	USB_OC		MCU	USB excess current detection
AE12	MAC_REF_CLK		MCU	RMII clock output
AE13	MAC0_RXD0		MCU	RMII reception data
AD13	MAC0_RXD1		MCU	RMII reception data
AC13	MAC0_RXER		MCU	RMII reception error
AE14	MAC0_TXD0		MCU	RMII transmission data
AD14	MAC0_TXD1		MCU	RMII transmission data
AC14	MAC0_TXEN		MCU	RMII transmission enable
AD12	MAC0_CRS_DV		MCU	RMII carrier detection
AE15	MAC0_MDC		MCU	RMII MI clock
AD15	MAC0_MDIO		MCU	RMII MI data
AE10	MAC1_RXD0		MCU	MAC1 RMII (no used)
AD10	MAC1_RXD1		MCU	MAC1 RMII (no used)
AC10	MAC1_RXER		MCU	MAC1 RMII (no used)
AE11	MAC1_TXD0		MCU	MAC1 RMII (no used)
AD11	MAC1_TXD1		MCU	MAC1 RMII (no used)
AC11	MAC1_TXEN		MCU	MAC1 RMII (no used)
AC12	MAC1_CRS_DV		MCU	MAC1 RMII (no used)
AE9	MAC1_MDC		MCU	MAC1 RMII (no used)
AD9	MAC1_MDIO		MCU	MAC1 RMII (no used)
AE20	SD0_CLK		MCU	
AC21	SD0_CMD		MCU	
AD21	SD0_DATA3		MCU	
AE21	SD0_DATA2		MCU	
AD22	SD0_DATA1		MCU	
AE22	SD0_DATA0		MCU	
AC22	SD0_SDCD		MCU	
AE23	SD0_SDWP		MCU	
AE17	SD1_CLK		MCU	
AC18	SD1_CMD		MCU	
AD18	SD1_DATA3		MCU	
AE18	SD1_DATA2		MCU	
AD19	SD1_DATA1		MCU	
AE19	SD1_DATA0		MCU	
AC19	SD1_SDCD		MCU	
AD20	SD1_SDWP		MCU	

IC114: MB87L8760 (D-VIDEOP.C.B)
NPGA
*** No replacement part available. / サービス部品供給なし**


Pin No.	Port Name	Function Name (P.C.B.)	I/O	Detail of Function
1	VDD		MCU	
2	VSS		MCU	
3	PIO[0]	VDEC_N_INT	IRQ	Interrupt from ADV7800
4	PIO[1]	HTX1_N_INT	IRQ	Interrupt from SII9134 #1
5	PIO[2]	HTX2_N_INT	IRQ	Interrupt from SII9134 #2
6	PIO[3]	HRX_N_INT	IRQ	Interrupt from SII9135A
7	PIO[4]	HEQ0_N_INT_F	IRQ	Interrupt from SII9185A #0
8	PWM[0]	–		
9	VSS		MCU	
10	VDD		MCU	
11	SCL0	HEQ_SCL	SO	SII9185A control
12	SDA0	HEQ_SDA	SIO	SII9185A control
13	PIO[16]	IOEX_N_CS	O	I/O expanded device chip select
14	PIO[17]	VIPC_N_CS	O	
15	PIO[18]	CXB1442_CE	O	CXB1442 chip enable
16	PIO[19]	FPGA_N_CS	O	FPGA chip select
17	PIO[20]	FPGA_N_CFG	O	FPGA configuration
18	VDD		MCU	
19	VSS		MCU	
20	PIO[21]	FPGA_CDONE	I	FPGA configuration
21	PIO[22]	FPGA_N_STA	I	FPGA configuration
22	PIO[23]	HDMI_MUT_3	I	HDMI Mute input
23	PWM[1]	–		
24	PIO[5]	HEQ1_N_INT_F	IRQ	Interrupt from SII9185A #1
25	SCL1	DV_SCL	SO	Video Encoder/Decoder ABT2010 analog video device control
26	SDA1	DV_SDA	SIO	Video Encoder/Decoder ABT2010 analog video device control
27	SCL2	EEP_SCL	SO	EEPROM read/write
28	SDA2	EEP_SDL	SIO	EEPROM read/write
29	VDD		MCU	
30	VSS		MCU	
31	PIO[6]	PHY_N_INT	IRQ	Interrupt from PHY
32	SCK0	FPGA_SCK	SO	FGPA control
33	SO0	FPGA_MOSI	SO	FGPA control
34	SI0	FPGA_MISO	SI	FGPA control
35	PIO[7]	–		
36	PIO[8]	HTX1_N_RST	O	SII9134 #1 reset
37	VDD		MCU	
38	VSS		MCU	
39	PIO[24]	HTX_AUSEL	O	Source selector when updating HDMI conversion L: HDMI input / H: Analog input
40	SCK1	IOEX_N_SCK	SO	Serial clock for I/O expanded device chip
41	SO1	IOEX_MOSI	SO	Serial data for I/O expanded device chip
42	SI1	–		
43	SCK2	VIPC_N_SCK		
44	SO2	VIPC_MOSI		
45	VSS		MCU	
46	VDD		MCU	
47	SI2	VIPC_MISO		
48	TXD0	–		
49	RXD0	–		
50	PI4_XCTS0	–		
51	PO4_XRTS0	–		
52	PIO[25]	VDEC_FPGA_N_OE	O	Path from ADV7800 to FPGA ON/OFF (L: ON / H: OFF)
53	PIO[26]	LPF_HD	O	LPF switching L: when SD, PS signal is input H: when HD signal is input

Pin No.	Port Name	Function Name (P.C.B.)	I/O	Detail of Function
54	VDD		MCU	
55	VSS		MCU	
56	PIO[27]	MON_N_VMT_3	O	Video monitor signal mute L: Mute on / H: Mute off
57	TXD1	–		
58	RXD1	–		
59	PI5_XCTS1	–		
60	PO5_XRTS1	–		
61	PIO[9]	HTX2_N_RST	O	Resetting for SII9134 #2
62	PIO[10]	HRX_N_RST	O	Resetting for SII9135A
63	PIO[11]	HEQ_N_RST_F	O	Resetting for SII9185A
64	PIO[12]	VDEC_N_RST	O	Resetting for ADV7800
65	VDD		MCU	
66	VSS		MCU	
67	PIO[13]	YGV_N_RST	O	Resetting for YGV619
68	PIO[14]	VIPC_N_RST	O	Resetting for ABT2010
69	TXD2	–		
70	RXD2	–		
71	PI6_XCTS2	–		
72	PO6_XRTS2	–		
73	VDD		MCU	
74	VSS		MCU	
75	VCXI0	–		
76	VDD		MCU	
77	PI2_X0IN	–		
78	NC		MCU	
79	VCXO0	–		
80	PI3_X1IN	–		
81	VSS		MCU	
82	VDD		MCU	
83	VCXI1	–		
84	VSS		MCU	
85	XIC	DEV_N_RST	MCU	Hardware reset input for NPGA
86	NC			
87	VCXO1	–		
88	TEST0			For testing
89	CLKIN	GA_24M	I	NPGA system clock 24.576MHz
90	VDD		MCU	
91	VSS		MCU	
92	TEST1			For testing
93	TEST2			For testing
94	PO1_XLOCK	CEC_RY2	O	CEC line switching control
95	XPCO	–		
96	PCO	–		
97	PO2	(AVI2S_ON)	O	Set to “H” when turning on power to AVIDEO
98	PO3	–		
99	PO0_MCLKO	CEC_RY1	O	Switching control of CEC line
100	AMCKO	GA_AMCKO	O	Master clock for audio
101	VDD		MCU	
102	VSS		MCU	
103	AHCKI	45.1584MHz	PLL	45.158MHz clock input for generation of 11.2896MHz
104	A[7]	SA[7]	BUS	HOST I/F address bus
105	A[6]	SA[6]	BUS	HOST I/F address bus
106	A[5]	SA[5]	BUS	HOST I/F address bus
107	A[4]	SA[4]	BUS	HOST I/F address bus
108	VDD		MCU	
109	PI0_MCLKI	–		
110	VSS		MCU	
111	PI1_LRCK	–		
112	A[3]	SA[3]	BUS	HOST I/F address bus
113	A[2]	SA[2]	BUS	HHOST I/F address bus
114	A[1]	SA[1]	BUS	HHOST I/F address bus


Pin No.	Port Name	Function Name (P.C.B.)	I/O	Detail of Function
115	A[0]	SA[0]	BUS	HOST I/F address bus
116	XTCK		MCU	For testing
117	VSS		MCU	
118	VDD		MCU	
119	PIO[28]	Z2_N_VMT_3	O	Zone2 video mute
120	PIO[15]	IOEX_N_RST	O	Reset signal to IO expanded device
121	PIO[29]	SV_DET	I	S-Video detection signal
122	VSS		MCU	
123	PIO[30]			
124	XIRQ	GA_N_INT	O	Request for interrupt to microprocessor
125	PIO[31]			
126	VDD		MCU	
127	VSS		MCU	
128	D[0]	SD[0]	BUS	HOST I/F data bus
129	D[1]	SD[1]	BUS	HOST I/F data bus
130	D[2]	SD[2]	BUS	HOST I/F data bus
131	D[3]	SD[3]	BUS	HOST I/F data bus
132	VDD		MCU	
133	VSS		MCU	
134	D[4]	SD[4]	BUS	HOST I/F data bus
135	D[5]	SD[5]	BUS	HOST I/F data bus
136	D[6]	SD[6]	BUS	HHOST I/F data bus
137	D[7]	SD[7]	BUS	HOST I/F data bus
138	VSS		MCU	
139	VDD		MCU	
140	XWR	GA_N_WR	BUS	Write enable input
141	VSS		MCU	
142	XCS	GA_N_CS	BUS	Chip select input
143	XTST		MCU	For testing
144	XRD	GA_N_RD	BUS	Read enable input

■ BLOCK DIAGRAMS


AUDIO SECTION BLOCK DIAGRAM



VIDEO SECTION BLOCK DIAGRAM




D-VIDEO SECTION BLOCK DIAGRAM




D-VIDEO •See page 157-166 → SCHEMATIC DIAGRAM

POWER SECTION BLOCK DIAGRAM




CONTROL SECTION BLOCK DIAGRAM




■ PIN CONNECTION DIAGRAMS

• ICs


ADV7800BSTZ-80




ADM222ARZ




ADV7342BSTZ




Sil9134CTU




AK4384ET
CD4051BNSR




BA15218F




BD3841FS




BD6517F-E2




CS230003-CZZR




BD3508EKN-E2




BD9011EKN-E2




EP2C8F256C8N




D70YE101BRFP266
M3087BFKBGP




DSD1791DBR




F2621E-01-TR
YAC523-EVR2




K4S281632K-UC75000
M12L64164A-5TG




KIA7812API




KIA7912PI




LA7106M-TLM-E
LC72725KM-UY-TLM-E
MM74HC4051SJX
MM74HC4053SJX
PCM1781DBQR




LA73050-TLM-E
LA73053-TLM-E




LB1836M-TLM-E
NJM2581M
TC74VHCT08AFT
TC74VHCU04FT




LC709004A-TLM-E
LC74782JM-8A16-TLMC
YAC526-EZE2




LC89057W-VF4AD-E




LM61CIZ



M24256-BRDW6TP




IP101ALF



K4S641632K-UC75000




NJM2388F05
NJM2388F33




1. V_{IN}
2. V_{OUT}
3. GND
4. ON/OFF CONTROL

NJM2388F09




1. V_{IN}
2. V_{OUT}
3. GND
4. ON/OFF CONTROL


M3087BFKBGP
MB87L8760




MN103SFD7G




M12L64322A-7TG 0.1UM




NE5532DR




NJM2068MD-TE2
NJM5532M-D




NJM2566AV




NJM2867F3-05
TC7SET32FU




NJM2885DL1-33




NJM4565M




NJU7311AM
NJU7312AM
NJU7313AM




NJW1194V




NJW1321FP1




PCM1804DBR




PQ200WNA1ZPH




PT6302LQ-008




R1154H050B-T1-F
R1172H121D-T1-F




R3112N251A-TR
TC7SH00FU
TC7SH08FU
TC7SH125FU
TC7SZ02FU




R1172S121D-E2-F
R1172S181B-E2-F
R1172S331B-E2-F



Sil9135ACTU



Sil9185ACTU




S29AL016D70TFI020




S29GL128P90TFCR20




SN74AHCT00PWR




SN74AHCT08PWR
SN74LVC74APWR
TC74VHC125FT




SN74CB3Q3257PWR
SN74LS151NSR




SN74LV157APWR
TC74VHC153FT




SN74LV245APWR



SN74LVC245APWR
TC74VHCT245AFT




SN74LVU04APWR




SN74AHCT1G32DCKR




TA1318AF




TC4013BP




TC74HC4052AF




TK15420M




TC7WH08FK
TC7WH14FK
TC7WZ04FK




V59C1256164QAF25



YGV619




YTD446-CZ




• Diodes


1N4002S
MTZJ5.1C




1SS355
1SS380
MA8030-L
MA-8039-H
MA8047
MA8047-L
MA8051-M
MA8062-M
MA8068-M
MA8075-M
MA8100-M 10.0V
MA8130-M
MA8160-H 16.7V
MA8240-M
RB501V-40
RB160M-30
RB160M-60 TR
RB500V-40
UDZS5.6BTE-17




D2SBA20




D4SBS6-7101




D15XBN20




DB105




MA8024-(TX) 2.4V




RB051L-40



RLS245



RS203M-B-C-J80




RLZ5.1A 5.1V




• Diodes


2SA949
2SC1815
2SC2229
2SC2878




2SA2168
2SC5291




2SB1257
2SB1274
2SC3852
2SD2014



A2151/C6011



2SK3850



2SA1036KT146
2SA1037K
2SA1576A
2SC2412K
2SC3326
2SC3837K
2SC3906K
2SC4081
2SD1938F



2SK208
5HP01C-TB-E



DTA143EKA
DTC114EKA
DTC144EKA



1: GND
2: IN
3: OUT


KRA102S-RTK/P
KRA104S-RTK
KRC102S-RTK
KRC104S-RTK




KTA1504S
KTA1517S
KTC3875S
KTC3911S




KTA1046-Y-U/P



KRC102M-AT




2SA1708



3LN01C-TB-E



2SD1915F




HN4C06J



1. BASE 1 (B1)
2. EMITTER (E)
3. BASE 2 (B2)
4. COLLECTOR 2 (C2)
5. COLLECTOR 1 (G2)


SP8K2




1. SOURCE1
2. GATE1
3. SOURCE2
4. GATE2
5. DRAIN2
6. DRAIN2
7. DRAIN1
8. DRAIN1

■ PRINTED CIRCUIT BOARDS


DSP P.C.B. (Side A)



POINT (B-1) XL502 (Pin 29 of IC506)



POINT (D-2) XL501 (Pin 28 of IC503)




Circuit No.	U, C	R, T, K, A, B, G, E, L, J
R5077, 5102	X	O

X : NOT USED
O : USED/APPLICABLE

• Semiconductor Location

Ref No.	Location	Ref No.	Location
D5001	D2	IC542	F3
D5002	E2	IC543	D5
D5003	D2	IC544	G3
D5305	G3	IC545	E4
D5608	D5	IC546	H3
D5609	H5	IC560	E5
IC501	E2	IC561	E6
IC502	H2	IC562	E6
IC503	E3	IC563	E6
IC504	E3	IC564	D5
IC505	E3	IC565	D6
IC506	E4	IC566	F4
IC507	F4	IC567	G4
IC508	F4	IC569	F5
IC509	F4	IC570	G5
IC510	D3	IC571	G5
IC511	D4	IC573	H5
IC512	D3	IC574	H5
IC513	E3	IC575	F6
IC531	E3	IC576	G6
IC532	H3	IC577	G6
IC533	H4	IC579	H6
IC534	F3	IC580	H6
IC535	H4	IC581	F4
IC536	H3	IC582	F4
IC537	H3	IC583	G3
IC538	H3	IC585	H4
IC539	H3	IC587	F3
IC540	G3	IC588	H3
IC541	H3		

DSP P.C.B. (Side B)



Circuit No.	U, C	R, T, K, A, B, G, E, L, J
R5076, 5090	X	O

X : NOT USED
O : USED/APPLICABLE


• Semiconductor Location

Ref No.	Location
side B	H3
D5301	G3
D5302	F3
D5303	D4
D5306	D4
D5308	D4
D5309	G3
D5310	F3
D5311	E5
D5600	E5
D5601	E5
D5602	E5
D5603	E5
D5604	E5
D5605	E5
D5606	E5
D5607	E4
Q5001	E4
Q5002	D4
Q5301	

FUNCTION (1) P.C.B. (Side A)

Circuit No.	U	C, R, T, K, A, L	B, G, E	J
C4520, 4521, 4523, 4528	O	O	O	X
IC450	O	O	O	X
J4506, 4507, 4512, 4513	X	X	X	O
J4510, 4511	O	O	O	X
R4025	O	X	X	X
R4530, 4533	O	O	O	X
R4538, 4541, 4555-4558	O	O	O	X


X : NOT USED
O : USED/APPLICABLE



• Semiconductor Location

Ref No.	Location	Ref No.	Location	Ref No.	Location
D4001	G3	IC401	G4	IC451	E3
D4014	C3	IC402	C4	Q4002	G3
D4015	C3	IC403	C5	Q4009	E5
D4016	C3	IC407	G5	Q4021	H3
D4017	C3	IC450	F3		

FUNCTION (1) P.C.B. (Side B)




Circuit No.	U, C	R, T, K, A, B, G, E, L	J
C3601, 3610	O	O	X
IC310, 311	X	O	O
IC356	O	O	X
J3003-3006	O	X	X
J3544-3545, 3548, 3549	X	X	O
J3546, 3647	O	O	X
R3605, 3606, 3620, 3621	O	O	X

X : NOT USED
O : USED/APPLICABLE

• Semiconductor Location

Ref No.	Location
D4002	C4
D4003	C4
D4004	C4
D4005	C4
D4006	C3
D4007	C3
D4008	F5
D4009	F5
D4010	C3
D4012	E5
D4013	E5
Q4	D5
Q26	E6
Q27	D5
Q28	E6
Q29	D6
Q30	D6
Q31	D6
Q32	E6
Q33	D5
Q34	D5
Q35	D5
Q36	D5
Q37	D5
Q38	D5
Q39	D5
Q40	D5
Q4001	G4
Q4003	G3
Q4004	C3
Q4005	E5
Q4006	E5
Q4007	C5
Q4008	C3
Q4010	E5
Q4011	E5
Q4012	F5
Q4013	F5
Q4014	F5
Q4015	F5
Q4016	D5


FUNCTION (2) P.C.B. (Side A)



• Semiconductor Location

Ref No.	Location
D3000	E6
D3002	E6
D3004	E4
D3005	F4
D3500	C3
D3501	C3
D3502	H5
D3503	H5
IC300	C6
IC301	C6
IC302	C6
IC304	D6
IC305	D6
IC306	D5
IC307	E6
IC308	E6
IC309	E6
IC310	E6
IC311	E5
IC312	E5
IC313	G6
IC350	B3
IC351	D3
IC352	D3
IC355	B4
IC356	C4
IC357	G5
IC358	G5
IC359	G4
IC360	G4
Q3000	E3
Q3001	F3
Q3002	F5
Q3003	F5
Q3004	F6
Q3005	F6
Q3006	F6
Q3007	F6
Q3008	F5
Q3009	F5
Q3010	F5
Q3011	F5
Q3012	F6
Q3013	F6
Q3014	F6
Q3015	F6
Q3016	F5
Q3017	F5
Q3500	G3
Q3501	G3
Q3502	G3
Q3503	G3
Q3504	G3
Q3505	G3
Q3506	G3
Q3507	G3


FUNCTION (2) P.C.B. (Side B)




• Semiconductor Location

Ref No.	Location
D3001	E6
D3003	E6


OPERATION (1) P.C.B. (Side A)




OPERATION (4) P.C.B. (Side A)




OPERATION (6) P.C.B. (Side A)




OPERATION (2) P.C.B. (Side A)



OPERATION (5) P.C.B. (Side A)




OPERATION (7) P.C.B. (Side A)




• Semiconductor Location

Ref No.	Location
D8001	B6


OPERATION (1) P.C.B. (Side B)




OPERATION (2) P.C.B. (Side B)



OPERATION (4) P.C.B. (Side B)




OPERATION (7) P.C.B. (Side B)



• Semiconductor Location

Ref No.	Location
Q8001	B5


OPERATION (3) P.C.B. (Side A)



• Semiconductor Location

Ref No.	Location
D8010	C4
D8011	C4

OPERATION (3) P.C.B. (Side B)




• Semiconductor Location

Ref No.	Location
D8004	F4
D8005	F4
D8006	E3
D8007	E3
D8008	D3
D8009	C3
IC801	C3
IC802	G3
IC805	E4
Q8002	F4
Q8003	F4


MAIN (1) P.C.B. (Side A)

• Semiconductor Location

Ref No.	Location	Ref No.	Location	Ref No.	Location	Ref No.	Location	Ref No.	Location	Ref No.	Location	Ref No.	Location
D279	I4	Q279	I5	Q288	G4	Q296	F3	Q309A	G3	Q313A	C3	Q366	E3
D280	H4	Q280	H5	Q289	F4	Q297	E3	Q309C	G3	Q313C	B3	Q367	F3
D281	G4	Q281	G5	Q290	E4	Q298	D3	Q310A	F3	Q360	I3	Q368	D3
D282	F4	Q282	F5	Q291	D4	Q299	B3	Q310C	E3	Q361	I4	Q369	E3
D283	E4	Q283	E5	Q292	C5	Q307A	I3	Q311A	E3	Q362	H3	Q370	C3
D284	D4	Q284	E5	Q293	I3	Q307C	I3	Q311C	D3	Q363	H3	Q371	C4
D285	C5	Q286	I4	Q294	H3	Q308A	H3	Q312A	D3	Q364	F3	Q372	B4
Q278	I5	Q287	H4	Q295	G3	Q308C	H3	Q312C	C3	Q365	G3	Q373	C4




MAIN (1) P.C.B. (Side B)




• Semiconductor Location

Ref No.	Location	Ref No.	Location	Ref No.	Location	Ref No.	Location	Ref No.	Location	Ref No.	Location	Ref No.	Location	Ref No.	Location	Ref No.	Location	Ref No.	Location
D252	I5	D265	I4	D272	F4	D286	I4	D293	I4	D300	D5	Q256	D5	Q263	D5	Q276	D5	Q320	B5	Q345	C4
D253	H5	D266	I4	D273	E4	D287	G4	D294	H4	Q250	I5	Q257	I5	Q270	I5	Q314	I3	Q321	C5	Q346	C5
D254	G5	D267	H4	D274	E4	D288	F4	D295	G4	Q251	H5	Q258	H5	Q271	H5	Q315	H3	Q340	I4		
D255	G5	D268	H4	D275	D4	D289	E4	D296	F4	Q252	G5	Q259	H5	Q272	H5	Q316	G3	Q341	H4		
D256	F5	D269	G4	D276	D4	D290	D4	D297	D4	Q253	G5	Q260	G5	Q273	G5	Q317	E3	Q342	G4		
D257	E5	D270	G4	D277	C5	D291	B4	D298	C4	Q254	F5	Q261	F5	Q274	F5	Q318	D4	Q343	F4		
D258	D5	D271	F4	D278	C5	D292	B5	D299	B5	Q255	E5	Q262	E5	Q275	E5	Q319	C4	Q344	E4		


MAIN (2) P.C.B. (Side A)




MAIN (3) P.C.B. (Side A)




MAIN (2) P.C.B. (Side B)



MAIN (3) P.C.B. (Side B)




MAIN (4) P.C.B. (Side B)




• Semiconductor Location

Ref No.	Location	Ref No.	Location
D250	J2	D305	I2
D251	J2	D306	J4
D259	J3	D307	J4
D260	J3	D313	C4
D261	J3	D314	B4
D262	J3	Q264	J3
D264	J3	Q265	J2
D302	G5	Q268	J3
D303	G4	Q269	J2
D304	F2	Q277	J3

POWER (1) P.C.B. (Side A)



POWER (1) P.C.B. (Side B)




• Semiconductor Location

Ref No.	Location
D13	C4
D14	B3
D15	B3
D16	H3
D18	H3
D22	I3
D23	I3
D35	I3
D40	H3
D41	I3
Q4	I3
Q7	D4

POWER (2) P.C.B. (Side A)

R, L models




VOLTAGE SELECTOR

VOLTAGE SELECTOR

230-240V	1-2/5-6
220V	2-3/6-7
110V	3-4/7-8
120V	4-5/8-1


POWER (6) P.C.B. (Side A)




• Semiconductor Location

Ref No.	Location
IC13	I5
IC14	B5


POWER (5) P.C.B. (Side A)




POWER (5) P.C.B. (Side B)



POWER (3) P.C.B. (Side A)




POWER (3) P.C.B. (Side B)




• Semiconductor Location

Ref No.	Location
D19	B3
D20	B2
D21	C7
D27	E5
D30	C7
D33	F6
D36	D6
D37	D6
D38	E6
D43	G5
D44	C6
D46	E6
IC4	F2
IC5	H2
IC6	H2
IC7	E2
IC15	F2
IC16	F2
Q8	G5
Q9	G2
Q10	G6
Q11	G6
Q12	F6
Q13	E6
Q17	D6
Q18	D6
Q19	E6
Q20	D2
Q21	D2
Q22	E2
Q24	G7
Q41	G7
Q44	F6

POWER (4) P.C.B. (Side A)




POWER (4) P.C.B. (Side B)




• Semiconductor Location

Ref No.	Location
D1	H3
D2	H5
D3	H5
D4	H5
D5	H5
D6	H4
D7	H4
D8	H4
D9	H4
D10	C4
D11	C6
D12	H5
D17	H2
D45	H2
IC1	D4
IC2	D4
IC3	C4
Q1	H5
Q2	H3
Q3	H5
Q5	H3
Q6	C4

A-VIDEO P.C.B. (Side A)



POINT (A-2) XL202 (Pin 3 of IC224)




POINT (D-1) XL201 (Pin 9 of IC202)

• Semiconductor Location

Ref No.	Location	Ref No.	Location	Ref No.	Location	Ref No.	Location	Ref No.	Location	Ref No.	Location	Ref No.	Location
D2001	F3	D2008	F3	D2661	D5	IC207	H5	IC220	D4	Q2542	E3	Q2633	D4
D2002	F3	D2009	F3	D2662	D5	IC211	D3	IC221	B4	Q2543	E4	Q2634	E4
D2003	F3	D2061	H3	IC201	H4	IC213	D3	IC222	C5	Q2544	E3		
D2004	F3	D2062	H3	IC202	G4	IC215	E3	IC223	F5	Q2545	E3		
D2005	F3	D2611	F4	IC203	H3	IC217	C4	IC224	E5	Q2546	E3		
D2006	F3	D2612	F4	IC204	F3	IC218	C3	IC226	D5	Q2601	E4		
D2007	F3	D2631	D5	IC205	F3	IC219	B3	Q2541	E3	Q2631	D4		

A-VIDEO P.C.B. (Side B)



Circuit No.	U, C, R, T, K, A, B, G, E, L	J
C2501-2505	X	O
J2501-2505	O	X


X : NOT USED
O : USED/APPLICABLE

• Semiconductor Location

Ref No.	Location
D2561	C3
D2563	B3
D2581	B4
D2582	B4
D2632	D4
D2633	D4
D2634	D4

Ref No.	Location
IC212	D3
IC214	D3
IC216	E3
Q2632	D4
Q2641	D5
Q2642	D5

D-VIDEO P.C.B. (Side A)



• Semiconductor Location

Ref No.	Location
D1000	E3
D1001	C3
D1002	E4
D1003	E3
D1009	E3
D7005	J5
D7006	J5
D7007	J5
D7008	J5
D7009	J4
D7010	J4
D7011	J5
D7012	J5
D7016	J4
D7017	J4
D7018	J4
D7019	J4
D7020	J4
D7021	J4
D7022	J4

Ref No.	Location
D7023	J4
D7029	J3
D7030	J3
D7031	J3
D7032	J3
D7033	J3
D7034	J3
D7035	J3
D7036	J3
D7041	J3
D7042	J3
D7043	J3
D7044	J3
D7045	J3
D7046	J3
D7047	J3
D7048	J3
D7063	I6
D7064	I6
D7076	I5

Ref No.	Location
D7077	I5
D7080	H3
D7087	F3
D7088	H3
D7089	G6
D7091	F3
D7093	E6
D7095	E3
D7096	E3
D7099	H3
D7100	H3
D7101	G6
D7104	C4
D7105	E6
IC102	E4
IC104	C4
IC105	D4
IC107	E4
IC109	E4
IC110	E4

Ref No.	Location
IC111	E4
IC112	E3
IC113	F3
IC114	E4
IC115	F3
IC116	E3
IC117	D3
IC118	C4

Ref No.	Location
IC120	D3
IC121	I3
IC124	E3
IC125	C5
IC700	G3
IC701	G4
IC702	G3
IC714	D5

Ref No.	Location
IC716	E5
IC717	E5
IC718	E3
IC720	E5
IC722	B4
IC726	I4
IC727	H4
IC728	I3

Ref No.	Location
IC729	I6
IC730	I6
IC731	I3
IC732	I5
IC733	I5
IC734	H5
IC735	H4
IC737	H5

Ref No.	Location
IC740	H6
IC745	G6
IC751	G5
IC752	F6
IC753	G6


Ref No.	Location
IC754	E5
Q1005	F3
Q7000	H4
Q7009	I6
Q7010	I5

Ref No.	Location
Q7011	I3
Q7012	I3
Q7013	H3
Q7014	H3


D-VIDEO P.C.B. (Side B)

• Semiconductor Location


Ref No.	Location	Ref No.	Location	Ref No.	Location	Ref No.	Location	Ref No.	Location	Ref No.	Location	Ref No.	Location	Ref No.	Location	Ref No.	Location
D1004	E3	D7014	I4	D7037	I3	D7061	I6	D7082	H3	D7103	F3	IC705	H4	IC744	G6	Q7001	I4
D1006	F3	D7015	J4	D7038	I3	D7062	J6	D7083	G6	IC100	E3	IC707	G4	IC749	E6	Q7002	I4
D1008	F3	D7024	I4	D7040	J2	D7073	I5	D7084	G6	IC101	C3	IC715	D5	IC750	F3	Q7003	I4
D7000	G3	D7025	I4	D7049	I2	D7074	I5	D7090	G6	IC103	C5	IC719	G6	IC755	E5	Q7004	I4
D7003	I4	D7026	I4	D7050	I2	D7075	J5	D7094	F3	IC106	E3	IC721	F3	Q1004	F3	Q7005	I3
D7004	J5	D7027	J4	D7051	I2	D7079	H3	D7097	E5	IC122	F3	IC741	H3	Q1006	E4	Q7006	I3
D7013	I4	D7028	I3	D7060	I6	D7081	E3	D7102	F5	IC704	G4	IC743	H3	Q1007	E4	Q7007	I2



FL (1) P.C.B. (Side A)




FL (1) P.C.B. (Side B)




• Semiconductor Location

Ref No.	Location	Ref No.	Location
D9005	I3	Q9001	F3
D9006	I3	Q9002	F3
D9017	E5	Q9003	F3
D9021	E5	Q9004	F3
D9022	E5	Q9005	F3
D9023	E4	Q9006	F3
D9024	E4	Q9007	F3
D9025	E5	Q9008	F3
D9026	E4	Q9009	C3
IC901	G3	Q9010	E4
IC902	D3	Q9011	E4

FL (2) P.C.B. (Side A)




FL (2) P.C.B. (Side B)




• Semiconductor Location

Ref No.	Location
D9501	E3
IC951	F3
IC952	E3


FL (3) P.C.B. (Side A)



FL (4) P.C.B. (Side A)




FL (3) P.C.B. (Side B)



FL (4) P.C.B. (Side B)




FL (5) P.C.B. (Side A)




FL (5) P.C.B. (Side B)



FL (6) P.C.B. (Side A)



FL (6) P.C.B. (Side B)




• Semiconductor Location

Ref No.	Location
D9901	G6
D9902	G6
D9903	G6
D9904	G6
IC991	H6
Q9001	G3
Q9901	G3
Q9902	G6
Q9903	G3
Q9904	G6


CONNECT (1) P.C.B. (Side A)

U model



CONNECT (1) P.C.B. (Side B)

U model




• Semiconductor Location

Ref No.	Location
D900	G3
D901	G3
D904	I4
IC901	I3
Q900	G3

CONNECT (2) P.C.B. (Side A)


U, C models

SIRIUS



CONNECT (2) P.C.B. (Side B)


U, C models




• Semiconductor Location

Ref No.	Location
D950	H3
D952	H4
D953	I3
D954	I3
IC950	H4
IC951	I5
Q951	G3
Q952	C3

DCCNVT (1) P.C.B. (Side A)




DCCNVT (1) P.C.B. (Side B)



• Semiconductor Location


Ref No.	Location
D701	G3
D702	D3
D703	D4
D704	G4
D705	G5
D706	D5
D707	D6
D708	D5
D709	G6
D710	G4
IC71	C4
IC72	C4
IC74	C5
Q701	C3
Q702	C4
Q703	C4
Q704	C5
Q705	C6

DCCNVT (2) P.C.B. (Side A)



NETWORK

DCCNVT (2) P.C.B. (Side B)



MEMO

MEMO

■ SCHEMATIC DIAGRAMS
DSP 1/3

No replacement part available.
サービス部品供給なし

Page 148 J8 to FUNCTION (1)_CB411
Page 152 F2 to OPERATION (3)_CB805
Page 168 B8 to FL (2)_CB954
Page 168 E8 to FL (2)_CB974

DOCK

DUTY CORRECTOR

INPUT SELECT

REC OUT SELECT

DIR

PLL

XMDT

XM-Radio (U, C models)

XM

DIGITAL IN

ANALOG IN

to DSP 2/3

Control BUS in PWB(DSP)
Audio Data-Clock
Control.From CPU

NOTICE (model)
(J)····· JAPAN
(U)····· U.S.A
(C)····· CANADA
(R)····· GENERAL
(T)····· CHINA
(K)····· KOREA
(A)····· AUSTRALIA
(B)····· BRITISH
(G)····· EUROPE
(L)····· SINGAPORE
(E)····· SOUTH
(V)····· TAIWAN
(F)····· RUSSIAN

RESISTOR

REMARKS	PARTS NAME
NO MARK	CARBON FILM RESISTOR (P=5)
☐	CARBON FILM RESISTOR (P=10)
△	METAL OXIDE FILM RESISTOR
▲	METAL FILM RESISTOR
⊠	METAL PLATE RESISTOR
▨	FIRE PROOF CARBON FILM RESISTOR
□	CEMENT MOLDED RESISTOR
⊘	SEMI VARIABLE RESISTOR
■	CHIP RESISTOR

CAPACITOR

REMARKS	PARTS NAME
NO MARK	ELECTROLYTIC CAPACITOR
▽	TANTALUM CAPACITOR
NO MARK	CERAMIC CAPACITOR
◉	CERAMIC TUBULAR CAPACITOR
◎	POLYESTER FILM CAPACITOR
○	POLYSTYRENE FILM CAPACITOR
Ⓘ	MICA CAPACITOR
Ⓟ	POLYPROPYLENE FILM CAPACITOR
Ⓢ	SEMICONDUCTIVE CERAMIC CAPACITOR
Ⓢ	POLYPHENYLENE SULFIDE FILM CAPACITOR


Destination Part List

s××	LOC	J	UC	RTKA8GLE	
s1	CB502	x	WJ45032 ICAM-CB5032AB	x	
s2	IC503	x	YA070A0 S2658E-01-TR	x	
s3	D5001 D5002 D5003	x	WE67480 AVRL161A1R1NTB	x	
s4	L5010 L5011 L5006	x	V244990 BLM21PG600SN1D	x	
s5	C5042 C5041 C5035 C5043 C5044 C5010 C5022 C5024 C5045	x	US13510 0.1/16	x	
s6	R5009 R5008	x	RD35510 100	x	XM Radio
s7	R5016 R5017	x	RD35610 1K	x	
s8	R5033	x	RD35910 1M	x	
s9	R5040 R5039 R5034 R5069	x	RD35810 100K	x	
s10	C5056 C5047	x	US06080 8P(CH)	x	
s11	R5077 R5090 R5076 R5102	RD35810 100K	x	RD35810 100K	
s12	R5079 R5080	x	RD35647 4.7K	x	
s13	R5041 R5042	x	RD35847 470K	x	
s14	C5019	x	US06310 1000P(B)	x	
s15	C5044	x	UR83747 47/16	x	
s16	XL501	x	WH45530 45.1584MHZ	x	
s19	R5043	x	RD44433 33K4	x	
s20	R5026	x	RD35510 100	x	
s21	L5013	x	WA80150 1.5uH	x	
s22	C5092	x	US06310 1000P(B)	x	
s23	PJ501	WB82440 YKC21-4228V	WB49120 IRJ-1165.31-03001	WB49120 IRJ-1165.31-03001	J Gold Ex normal
s24	JS003 JS004	x	RD35000 0	x	

Interchangeable Parts at Manufacture-Stage

Mark	Reference Parts Number	Parts Name
&1	D5301-5303-5305-5306 5308-5311	1SS355 MA2J11100L KDS160-RTK/P
&2	Q5301	2SA1037AK(G/R/S) KTA1504S-Y,GR-RTK/P
&3	Q5002	2SC3326(A/B) 2SC3326(B) 2SD1938(F) 2SC5938A(A/B) 2SD2704(K) KTC3875-B
&4	Q5001	DTC114EKA KRC102S-RTK/P
&5	IC502	SN74AHCT00PWR TC74VHCT00AFT(EL-K)
&6	IC535	SN74AHCT08PWR TC74VHCT08AFT(EL-K)
&7	IC501	SN74LVU04APWR TC74VHCU04FT(EL)
&8	IC509-566-588	SN74LV157APWR TC74VHC157FT(EL-K) 74VHC157MTCX,-NF4G
&9	IC532-533-538	TC7SET32FU SN74AHCT1G32DCKR
&10	IC585-587	K4S641632K-UC75000 M12L6416A8-7TG
&11		
&12		
&13		


IC509: SN74LV157APWR
Quadruple 2-line to 1-line data selectors/multiplexers




Pin numbers shown are for the D, DB, DGV, J, NS, PW, and W packages.




IC507, 508: TC74VHC153FT
Dual 4-channel multiplexer




IC506: LC89057W-VF4AD-E
Digital audio interface transceiver




IC501: SN74LVU04APWR
Hex inverters




IC502: SN74AHCT00PWR
Quadruple 2-input NAND gate




IC504, 505: SN74LS151NSR
8-input multiplexer



IC510: NJM2068MD-TE2
Dual operational amplifier




IC511: TC74VHC125FT
high speed CMOS quad bus buffer




inputs		outputs
G	A	Y
H	X	Z
L	L	L
L	H	H

IC512: TC7SH08FU
2-input AND gate



IC513: CS230003-CZZR
Clock multiplier



★ All voltages are measured with a 10MΩ/V DC electronic voltmeter.
★ Components having special characteristics are marked ! and must be replaced with parts having specifications equal to those originally installed.
★ Schematic diagram is subject to change without notice.

● 電圧は、内部抵抗10MΩの電圧計で測定したものです。
● ! 印のある部品は、安全性確保部品を示しています。部品の交換が必要な場合、パーツリストに記載されている部品を使用してください。
● 本回路図は標準回路図です。改良のため予告なく変更することがございます。

DSP 2/3

Page 168 L5 to FL (5)_CB973
Page 168 N5 to FL (5)_CB959
Page 154 H5 to POWER (3)_CB16
Page 154 H6 to POWER (3)_CB17

NOTICE (model)
(J)····· JAPAN
(U)····· U.S.A
(C)····· CANADA
(A)····· GENERAL
(T)····· CHINA
(K)····· KOREA
(A)····· AUSTRALIA
(B)····· BRITISH
(G)····· EUROPE
(L)····· SINGAPORE
(E)····· SOUTH EUROPE
(V)····· TAIWAN
(F)····· RUSSIAN

CAPACITOR

REMARKS	PARTS NAME	
NO MARK	ELECTROLYTIC CAPACITOR	⊟
⊗	TANTALUM CAPACITOR	
NO MARK	CERAMIC CAPACITOR	⫼
◉	CERAMIC TUBULAR CAPACITOR	
◎	POLYESTER FILM CAPACITOR	
○	POLYSTYRENE FILM CAPACITOR	
ⓘ	MICA CAPACITOR	
ⓟ	POLYPROPYLENE FILM CAPACITOR	
◉	SEMICONDUCTIVE CERAMIC CAPACITOR	
Ⓢ	POLYPHENYLENE SULFIDE FILM CAPACITOR	

RESISTOR

REMARKS	PARTS NAME
NO MARK	CARBON FILM RESISTOR (P=5)
⊠	CARBON FILM RESISTOR (P=10)
△	METAL OXIDE FILM RESISTOR
◬	METAL FILM RESISTOR
⊠	METAL PLATE RESISTOR
▨	FIRE PROOF CARBON FILM RESISTOR
□	CEMENT MOLDED RESISTOR
⊘	SEMI VARIABLE RESISTOR
■	CHIP RESISTOR


Destination Part List


xxx	LOC	J	UC	RTK&BGLE	
s30	IC545	x	X79L440 PQ200WNA1ZPH	x	
s31	D5308 R5389	x	VB07000 1.8V	x	
s32	C5401 C5398	x	UR23810 100/16	x	
s33	C5400 C5402 C5399	x	US13510 0.1/16	x	
s34	R5387	x	RD35647 4.7K	x	
s35	D5309 D5306	x	VT33290 1SS355	x	
s36	R5395	x	RF35618 1.8K	x	
s37	R5396	x	RF35639 390	x	
s38	R5392	x	RD35610 1K	x	XM Radio
s39	R5394	x	RF35622 2.2K	x	
s40	R5393	x	RD35810 100K	x	
s41	D5301	x	VV55650 A1037AI(G/A/S)-1	x	
s42	R5400	x	RD35747 47K	x	
s43	C5403	x	UR21847 470/6.3	x	

(U, C models)

for XM Radito

IC540: S29AL016D70TFI020
16 M-bits CMOS 3.0 volt-only boot sector flash memory






DSP1

No replacement part available.
サービス部品供給なし


RAM

FLASH ROM

IC587: K4S641632K-UC75000
64 M synchronous DRAM




IC588: SN74LV157APWR
Quadruple 2-line to 1-line data selectors/multiplexers




Pin numbers shown are for the D, DB, DGV, J, NS, PW, and W packages.


IC534: D70YE101BRFP266
Floating-point digital signal processors



IC536: SN74LV245APWR
Octal bus transceiver with 3-state outputs




IC541, 542: R1172S121D-E2-F
Voltage regulator




Pin No.	Symbol	Description
1	VOUT	Output Pin of Voltage Regulator
2, 5	GND	Ground Pin
3	CE	Chip Enable Pin
4	NC	No Connection
6	VDD	Input Pin


IC543, 545: PQ200WNA1ZPH
Low power loss regulator




IC544: NJM2885DL1-33
Low dropout voltage regulator




IC531, 537, 539, 546: TC7SH08FU
2-input AND gate



IC532, 533, 538: TC7SET32FU
2-input OR gate



IC535: SN74AHCT08PWR
Quadruple 2-input positive-AND gates



★ All voltages are measured with a 10MΩ/V DC electronic voltmeter.
★ Components having special characteristics are marked ⚠ and must be replaced with parts having specifications equal to those originally installed.
★ Schematic diagram is subject to change without notice.

● 電圧は、内部抵抗10MΩの電圧計で測定したものです。
● ⚠印のある部品は、安全性確保部品を示しています。部品の交換が必要な場合、パーツリストに記載されている部品を使用してください。
● 本回路図は標準回路図です。改良のため予告なく変更することがございます。

DSP 3/3

Page 150 B5
to FUNCTION (2)_CB300

Page 151 C3
to FUNCTION (2)_W3503

Destination Part List					
xxx	LOC	J	UC	RTK49GLE	
x51	IC564	x	K6D1616 4K4384ET	x	
x52	IC565	x	K6R4804 NE5532DR	x	
x53	C5701 C5702 C5703 C5673 C5674	x	U02374 7 16	x	
x54	C5675 C5698 C5699	x	U03510 0.1 16	x	
x55	C5674 C5687 C5688	x	U02710 10 16	x	
x56	C5666 C5667	x	U05410 0.01B1	x	
x57	C5680 C5681 C5682 C5684	x	K-04020 270P	x	
x58	L5609	x	V24990 SLN4125SS10N10	x	
x59	R5667 R5668 R5670 R5671	x	R03547 47	x	
x60	R5708 R5709 R5711	x	HX75310 -	x	
x61	R5676 R5677 R5675	x	R03510 10K	x	
x62	R5678 R5677	x	R03515 1.5K	x	
x63	R5685 R5684	x	RF35633 1.3K	x	
x64	R5688 R5687	x	RF35620 2.2K	x	
x65	R5704 R5705	x	R03547 47K	x	
x66	R5707 R5706	x	R03510 10	x	
x68	R5682 R5683	x	R03518 1.8K	x	
x69	R5669	x	R03510 10	x	

NOTICE (model)
(J)..... JAPAN
(U)..... U.S.A
(C)..... CANADA
(R)..... GENERAL
(T)..... CHINA
(K)..... KOREA
(A)..... AUSTRALIA
(B)..... BRITISH
(G)..... EUROPE
(L)..... SINGAPORE
(E)..... SOUTH
(V)..... TAIWAN
(F)..... RUSSIAN


RESISTOR

REMARKS	PARTS NAME
NO MARK	CARBON FILM RESISTOR (B=5)
☑	CARBON FILM RESISTOR (B=10)
△	METAL OXIDE FILM RESISTOR
▲	METAL FILM RESISTOR
☒	METAL PLATE RESISTOR
◪	FIRE PROOF CARBON FILM RESISTOR
□	CEMENT MOLDED RESISTOR
⊘	SEMI VARIABLE RESISTOR
■	CHIP RESISTOR


CAPACITOR

REMARKS	PARTS NAME
NO MARK	ELECTROLYTIC CAPACITOR
⊗	TANTALUM CAPACITOR
NO MARK	CERAMIC CAPACITOR
◈	CERAMIC TUBULAR CAPACITOR
◎	POLYESTER FILM CAPACITOR
◯	POLYSTYRENE FILM CAPACITOR
Ⓜ	MICA CAPACITOR
Ⓟ	POLYPROPYLENE FILM CAPACITOR
ⓒ	SEMICONDUCTIVE CERAMIC CAPACITOR
Ⓢ	POLYPHENYLENE SULFIDE FILM CAPACITOR


IC585: K4S641632K-UC75000
64 M synchronous DRAM



IC567: D70YE101BRFP266
Floating-point digital signal processors




IC566: SN74LV157APWR
Quadruple 2-line to 1-line data selectors/multiplexers




Pin numbers shown are for the D, DB, DGV, J, NS, PW, and W packages.


IC569-571, 573, 574: DSD1791DBR
24-bit, 192 kHz sampling, advanced segment, audio stereo digital-to-analog converter




IC582: TC7SH00FU
Single 2-input positive-AND gate



IC581, 583: TC7SH08FU
2-input AND gate




IC560: PCM1804DBR
Stereo A/D converter




IC561-563, 579, 580: NJM2068MD-TE2
Dual operational amplifier



IC564: AK4384ET
D/A converter



IC565, 575-577: NE5532DR
Dual low-noise operational amplifiers



★ All voltages are measured with a 10MΩ/V DC electronic voltmeter.
★ Components having special characteristics are marked ⚠ and must be replaced with parts having specifications equal to those originally installed.
★ Schematic diagram is subject to change without notice.

● 電圧は、内部抵抗10MΩの電圧計で測定したものです。
● ⚠印のある部品は、安全性確保部品を示しています。部品の交換が必要な場合、パーツリストに記載されている部品を使用してください。
● 本回路図は標準回路図です。改良のため予告なく変更することがございます。

FUNCTION 1/4

Page 169 B7
to CONNECT (1)_CB903 (U model)
To AM/FM TUNER (C, R, T, K, A, B, G, E, L, J models)

AM/FM HD-Radio TUNER

(C, R, T, K, A, B, G, E, L, J models)

Serial/Parallel (Port Extend)

[RDS]

(B, G, E models)
RDS BSE Only

[TUNER]

[EPROM] [I/O Expander]

MICROPROCESSOR (MAIN)

IC402

MS1TTEN (0: YDA	BLANK	PARTS NAME
YA208A0	X901340	W30878FX85P

(U, C, R, T, K, A, B, G, E, L models)

REMOTE

NOTICE (model)
(J ····· JAPAN
(U ····· U.S.A
(C ····· CANADA
(R ····· GENERAL
(T ····· CHINA
(K ····· KOREA
(A ····· AUSTRALIA
(B ····· BRITISH
(G ····· EUROPE
(L ····· SINGAPORE
(E ····· SOUTH EUROPE
(V ····· TAIWAN
(F ····· RUSSIAN

RESISTOR

REMARKS	PARTS NAME
NO MARK	CARBON FILM RESISTOR (1/4S)
☑	CARBON FILM RESISTOR (1/10)
△	METAL OXIDE FILM RESISTOR
▲	METAL FILM RESISTOR
⊠	METAL PLATE RESISTOR
▤	FIRE PROOF CARBON FILM RESISTOR
□	CEMENT MOLDED RESISTOR
⊘	SEMI VARIABLE RESISTOR
■	CHIP RESISTOR

CAPACITOR

REMARKS	PARTS NAME
	ELECTROLYTIC CAPACITOR
⊘	TANTALUM CAPACITOR
NO MARK	CERAMIC CAPACITOR
◉	CERAMIC TUBULAR CAPACITOR
Ⓢ	POLYESTER FILM CAPACITOR
○	POLYSTYRENE FILM CAPACITOR
Ⓜ	MICA CAPACITOR
Ⓟ	POLYPROPYLENE FILM CAPACITOR
●	SEMICONDUCTIVE CERAMIC CAPACITOR
Ⓟ	POLYPHENYLENE SULFIDE FILM CAPACITOR

Interchangeable Parts at Manufacture-Stage

Mark	Reference Parts Number	Parts Name
▲1	S4004-4007	2SC3326(A/B) 2SD2704K(X) KTC3198 KTC4388 2SC3938(A/B) 2SD1938(F/S)*1
▲2	03000-3003-3502-3503 4002-4007-4009-4010-4013 4016-4017	1S1355 MA3J11150L KDS160-RTK/P
▲3	S4006-4008	A1037AX(S/R/S) KTA1504S(Y)-GR-RTK/P
▲4	S4009	C2878(A/B) KTC3874(A/B) 2SD1915F5A15(F1)
▲5	S4002	2SC1815(Y) KTC3198
▲6	S4001-4003	2SC3326(A/B) 2SD2704K(X) KTC3198 2SC3938(A/B) 2SD1938(F/S)*1
▲7		
▲8	S4021	2SC2412K(Q/R/S) 2SD601SR,SQ,SS*1
▲9	S4001	US2S5-5B MA2S05506PL
▲10	S27-28-31-32-35-36-39-40	KRA104S-RTK/P DTA144EKA
▲11	24-26-29-30-33-34-37-38	KRC104S-RTK/P DTC144EKA

Page 168 M6
to FL (5)_CB960
Page 168 L6
to FL (5)_CB972
Page 168 N8
to FL (3)_CB955
Page 168 M8
to FL (3)_CB952
Page 167 N3
to FL (6)_W9901
Page 154 J8
to POWER (4)_W1
Page 153 B1
to MAIN (4)_W272
Page 154 H7
to POWER (3)_CB18
Page 156 J2
to A-VIDEO_CB203
Page 145 F1
to DSP_CB504
Page 168 E7
to FL (2)_CB958
Page 168 G7
to FL (2)_CB962
Page 168 H7
to FL (2)_CB969


RX-V3900
FUNC(1)

FUNCTION (1)

Destination Part List (Y3900,Sht=1)


xxx	LOC	J	U	C	RTKL	A	B06
S18	S29 S34		X	MC43510 KRC104S-RTK/P	MC43510 KRC104S-RTK/P	MC43510 KRC104S-RTK/P	MC43510 KRC104S-RTK/P
S19	S31 S33		X	MC43490 KRA104S-RTK/P	MC43490 KRA104S-RTK/P	MC43490 KRA104S-RTK/P	MC43490 KRA104S-RTK/P
S21	R4063 R4064		X	RD35610 1K	RD35610 1K	RD35610 1K	RD35610 1K
S50	IC401						VB2356G LC72725KM-UY-TL
S51	XL401		X	X	X	X	V273310 4.332MHZ
S52	C4028 C4027		X	X	X	X	US5K127 27PJCH
S53	C4026 C4029 C4025		X	X	X	X	UR2J747 47JE
S54	R4021		X	X	X	X	RD35610 1K
S55	C4024		X	X	X	X	UR2J104 SE0100L
S56	C4023 C4030		X	X	X	X	UR1H101 5-1716
S57	R4019		X	X	X	X	RD35610 100K
S58	S4003		X	X	X	X	VD30370 D3326(A/B)
S59	C4022 C4033		X	X	X	X	US5K233 330PJSL1
S60	R4018		X	X	X	X	RD35733 33K
S61	R4020		X	X	X	X	RD35622 2.2K
S62	R4022		X	X	X	X	RD35722 22K
S63	R4023 R4024 R4070		X	X	X	X	RD35547 47K
S64	R4031		X	X	X	X	RD35710 10K
S65	L4001		X	X	X	X	VK36750 220UH
S67	D4015 D4014		X	V259820 S1R-50557447	V259820 S1R-50557447	V259820 S1R-50557447	V259820 S1R-50557447
S68	R4239 R4238		X	RD35710 10K	RD35710 10K	RD35710 10K	RD35710 10K
S69	R4234		X	RD35447 470K	RD35447 470K	RD35447 470K	RD35447 470K
S70	R4235		X	RD35610 100K	RD35610 100K	RD35610 100K	RD35610 100K
S71	JK402 JK403 JK404 JK405		X	V94357G MLJ-039-124PC	V94357G MLJ-039-124PC	V94357G MLJ-039-124PC	V94357G MLJ-039-124PC
S72	C4078 C4079 C4081 C4074 C4077 C4076		X	US5K310 1000F(B)	US5K310 1000F(B)	US5K310 1000F(B)	US5K310 1000F(B)
S73	D4017 D4016		X	V733290 1S1355	V733290 1S1355	V733290 1S1355	V733290 1S1355
S74	U4001		X	VB21020 GP1UD271XKDF	VB21020 GP1UD271XKDF	VB21020 GP1UD271XKDF	VB21020 GP1UD271XKDF
S75	C4073		X	UR21B10 100V-5-3	UR21B10 100V-5-3	UR21B10 100V-5-3	UR21B10 100V-5-3
S76	C4072		X	US13510 5-1716	US13510 5-1716	US13510 5-1716	US13510 5-1716
S82	D4011 D4012		X	MT76790 SHP01C-TB-E	MT76790 SHP01C-TB-E	MT76790 SHP01C-TB-E	MT76790 SHP01C-TB-E
S83	R4212 R4209 R4208 R4211		X	RD35610 100K	RD35610 100K	RD35610 100K	RD35610 100K
S84	R4219 R4218		X	RD35482 82	RD35482 82	RD35482 82	RD35482 82
S85	C4065 C4064		X	UR2B632 2.2/50	UR2B632 2.2/50	UR2B632 2.2/50	UR2B632 2.2/50
S86	Q4021		X	V2SD965 C2412K(R/S)	X	X	X
S87	R4269		X	RD35747 470K	RD35747 470K	RD35747 470K	RD35747 470K
S88	R4058		X	RD35710 10K	RD35710 10K	X	X
S89	R4187		X	RD39515 1.5K	RD39515 1.5K	X	X
S90	R4263 R4264		X	RD35710 10K	X	X	X
S91	R4206 R4207		X	RD35647 4.7K	X	X	X
S92	R4261		X	RD35747 470K	X	X	X
S93	R4265		X	RD35702 82K	X	X	X
S94	Q4008		X	VB21020 A1037AX(S/R/S)	X	X	X
S95	C4102 C4103 C4087 C4086 C4101		X	US0G210 100F(SL)	X	X	X
S96	R4168		X	RD39515 1.5K	RD39515 1.5K	X	X
S100	R4025		X	RD35000 0	X	X	X
S101	R4001		X	RD35810 100K	RD35810 100K	RD35810 100K	RD35810 100K
S102	R4002		X	RD35710 10K	RD35710 10K	RD35710 10K	RD35710 10K
S104	Q4001		X	VD30370 C3326(A/B)	VD30370 C3326(A/B)	VD30370 C3326(A/B)	VD30370 C3326(A/B)
S105	R4009 R4016		X	RD35622 2.2K	RD35622 2.2K	RD35622 2.2K	RD35622 2.2K
S106	D4002		X	IC18152 C1815(Y)	IC18152 C1815(Y)	IC18152 C1815(Y)	IC18152 C1815(Y)
S107	C4018		X	US0K410 5-0178*	US0K410 5-0178*	US0K410 5-0178*	US0K410 5-0178*
S109	R4017		X	RD35510 100	RD35510 100	RD35510 100	RD35510 100
S110	C4019		X	UR2B632 2.2/50	UR2B632 2.2/50	UR2B632 2.2/50	UR2B632 2.2/50
S111	D4001		X	UG20B-6B UG20B-6B	UG20B-6B UG20B-6B	UG20B-6B UG20B-6B	UG20B-6B UG20B-6B
S112	C4020		X	UA2E810 100/16	UA2E810 100/16	UA2E810 100/16	UA2E810 100/16
S113	CB451		X	VW68900 S2045	VW68900 S2045	VW68900 S2045	VW68900 S2045
S115	R4161 R4158		X	RD39810 100K	RD39710 10K	RD35710 10K	RD35710 10K
S117	C4134		X	US0K147 470PJ(H)	US0K147 470PJ(H)	X	X
S124	R4232		X	RD35747 47K	RD35747 47K	RD35747 47K	RD35747 47K
S125	R4035		X	RD35710 10K	RD35710 10K	RD35710 10K	RD35710 10K
S126	R4040		X	RD35710 10K	X	X	X
S127	R4002		X	RD35000 0	RD35000 0	RD35000 0	RD35000 0
S128	R4005		X	RD35410 1K	RD35410 1K	X	X

IC407: R1154H058B-T1-F
Voltage regulator




Pin No.	Symbol	Description
1	VOUT	Output Pin for Voltage Regulator
2	GND	Ground
3	CE	Chip Enable Pin (active at "H")
4	NC	No Connection
5	VCC	Power Supply Pin

IC402: M3087BFKBGP
Microprocessor




NOTES:
1. Ports P11 to P15 are provided in the 144-pin package only.
2. Included in the 144-pin package only.
3. The supply voltage of M30C/M8T (High-reliability version) must be Vcc=AVcc.


IC403: LC709004A-TLM-E
I/O-expander for microcontroller




IC401: LC72725KM-UY-TLM-E
RDS signal demodulation IC



POINT (A-1) XL402 (Pin 20 of IC402)




POINT (A-2)(A-3) ①/ Pin7, ②/ Pin8 of CB406



★ All voltages are measured with a 10MΩ/V DC electronic voltmeter.
★ Components having special characteristics are marked ⚠ and must be replaced with parts having specifications equal to those originally installed.
★ Schematic diagram is subject to change without notice.

● 電圧は、内部抵抗10MΩの電圧計で測定したものです。
● ⚠印のある部品は、安全性確保部品を示しています。部品の交換が必要な場合、パーツリストに記載されている部品を使用してください。
● 本回路図は標準回路図です。改良のため予告なく変更することがございます。


FUNCTION 2/4



Destination Part List (V3900_Sht-2)

sXX	LOC	J	U	C	RTKL	A	BGE
s450	C4523 C4521 C4520 C4528	X	UR23710 10/16	UR23710 10/16	UR23710 10/16	UR23710 10/16	UR23710 10/16
s451	IC450	X	X3547A0 BD3841FS-E2	X3547A0 BD3841FS-E2	X3547A0 BD3841FS-E2	X3547A0 BD3841FS-E2	X3547A0 BD3841FS-E2
s452	J4513 J4512 J4506 J4504 J4505 J4507 J4508 J4509	RD35000 0	X	X	X	X	X
s453	J4510 J4511 J4503 J4502	X	RD35000 0	RD35000 0	RD35000 0	RD35000 0	RD35000 0
s454	PJ450 PJ453	VV55150 RJ-1073-09-0551	VV30690 RJ-1073+09-0H51	VV30690 RJ-1073+09-0H51	VV30690 RJ-1073+09-0H51	VV30690 RJ-1073+09-0H51	VV30690 RJ-1073+09-0H51
s455	PJ451	VS63480 RJ-1074-09-0553	VV32540 RJ-1074+09-0H53	VV32540 RJ-1074+09-0H53	VV32540 RJ-1074+09-0H53	VV32540 RJ-1074+09-0H53	VV32540 RJ-1074+09-0H53
s456	R4541 R4538 R4555 R4558 R4556 R4557	X	RD35810 100K	RD35810 100K	RD35810 100K	RD35810 100K	RD35810 100K
s457	R4533 R4530	X	RD35710 10K	RD35710 10K	RD35710 10K	RD35710 10K	RD35710 10K
s458	PJ454	X	X	X	X	X	X
s459	CB451	X	VB39050 PHI	VB39050 PHI	X	X	X
S460	R4502 R4503	X	X	X	X	X	X
S461	R4517 R4516	X	X	X	X	X	X
S462	C4505 C4504	X	X	X	X	X	X
s463	R4570 R4571	RD35000 0	RD35000 0	RD35000 0	RD35000 0	RD35000 0	RD35000 0
s464	PJ452	VV55150 RJ-1073-09-0551	VV30690 RJ-1073+09-0H51	VV30690 RJ-1073+09-0H51	VV30690 RJ-1073+09-0H51	VV30690 RJ-1073+09-0H51	VV30690 RJ-1073+09-0H51
s465	C4541	X	US06222 220P(SL)	US06222 220P(SL)	X	X	X

IC450, 451: BD3841FS
Function switch



FUNCTION (1)

NOTICE (model)
(J)····· JAPAN
(U)····· U.S.A
(C)····· CANADA
(R)····· GENERAL
(T)····· CHINA
(K)····· KOREA
(A)····· AUSTRALIA
(B)····· BRITISH
(G)····· EUROPE
(L)····· SINGAPORE
(E)····· SOUTH EUROPE
(V)····· TAIWAN
(F)····· RUSSIAN

RESISTOR

REMARKS	PARTS NAME
NO MARK	CARBON FILM RESISTOR (P=5)
▨	CARBON FILM RESISTOR (P=10)
△	METAL OXIDE FILM RESISTOR
▲	METAL FILM RESISTOR
☒	METAL PLATE RESISTOR
▨	FIRE PROOF CARBON FILM RESISTOR
□	CEMENT MOLDED RESISTOR
⊘	SEMI VARIABLE RESISTOR
■	CHIP RESISTOR

CAPACITOR

REMARKS	PARTS NAME	
NO MARK	ELECTROLYTIC CAPACITOR	⫼
⊗	TANTALUM CAPACITOR	
NO MARK	CERAMIC CAPACITOR	‖
◉	CERAMIC TUBULAR CAPACITOR	
◎	POLYESTER FILM CAPACITOR	
○	POLYSTYRENE FILM CAPACITOR	
Ⓘ	MICA CAPACITOR	
Ⓟ	POLYPROPYLENE FILM CAPACITOR	
◉	SEMICONDUCTIVE CERAMIC CAPACITOR	
Ⓢ	POLYPHENYLENE SULFIDE FILM CAPACITOR	


RX-V3900

FUNC(1)

★ All voltages are measured with a 10MΩ/V DC electronic voltmeter.
★ Components having special characteristics are marked ! and must be replaced with parts having specifications equal to those originally installed.
★ Schematic diagram is subject to change without notice.

● 電圧は、内部抵抗10MΩの電圧計で測定したものです。
● !印のある部品は、安全性確保部品を示しています。部品の交換が必要な場合、パーツリストに記載されている部品を使用してください。
● 本回路図は標準回路図です。改良のため予告なく変更することがございます。

FUNCTION 3/4



RESISTOR

REMARKS	PARTS NAME
NO MARK	CARBON FILM RESISTOR (P=5)
☑	CARBON FILM RESISTOR (P=10)
△	METAL OXIDE FILM RESISTOR
▲	METAL FILM RESISTOR
☒	METAL PLATE RESISTOR
▨	FIRE PROOF CARBON FILM RESISTOR
□	CEMENT MOLDED RESISTOR
⊘	SEMI VARIABLE RESISTOR
■	CHIP RESISTOR

CAPACITOR

REMARKS	PARTS NAME	
NO MARK	ELECTROLYTIC CAPACITOR	⊣⊢
⊗	TANTALUM CAPACITOR	
NO MARK	CERAMIC CAPACITOR	⊣⊢
◉	CERAMIC TUBULAR CAPACITOR	
Ⓜ	POLYESTER FILM CAPACITOR	
○	POLYSTYRENE FILM CAPACITOR	
Ⓘ	MICA CAPACITOR	
Ⓟ	POLYPROPYLENE FILM CAPACITOR	
▣	SEMICONDUCTIVE CERAMIC CAPACITOR	
Ⓢ	POLYPHENYLENE SULFIDE FILM CAPACITOR	

NOTICE (model)
(J)····· JAPAN
(U)····· U.S.A
(C)····· CANADA
(R)····· GENERAL
(T)····· CHINA
(K)····· KOREA
(A)····· AUSTRALIA
(B)····· BRITISH
(G)····· EUROPE
(L)····· SINGAPORE
(E)····· SOUTH EUROPE
(V)····· TAIWAN
(F)····· RUSSIAN

RX-V3900 FUNC(2)

設計値
TOTAL 14dB

FRONT	0.0	12.5	1.5	14.0
CENTER	0.0	14.0	0.0	14.0
SURROUND	0.0	14.0	0.0	14.0
SURROUND BACK	0.0	14.0	0.0	14.0
SUB WOOFER	3.0	5.5	4.5	14.0
ZONE2 & ZONE3	0.0	14.0	0.0	14.0

→ +0.5dB:目然減寄連のため

定数計算値
TOTAL 14dB

FRONT	0.515	12.5	1.289	14.304
CENTER	0.584	14.0	0.0	14.584
SURROUND	0.584	14.0	0.0	14.584
SURROUND BACK	0.584	14.0	0.0	15.584
SUB WOOFER	3.418	5.5	4.619	14.537
ZONE2 & ZONE3	0.0	14.0	0.0	14.000

→ +0.5dB:目然減寄連のため

MIX部 設計値

P MIX FRONT	4.5
P MIX PRESENCE	-3.5
SUB WOOFER MIX	0.0

MIX部 定数計算値


P MIX FRONT	4.964
P MIX PRESENCE	2.979
SUB WOOFER MIX	0.446

→ +0.5dB:目然減寄連のため


★ All voltages are measured with a 10MΩ/V DC electronic voltmeter.
★ Components having special characteristics are marked ! and must be replaced with parts having specifications equal to those originally installed.
★ Schematic diagram is subject to change without notice.

● 電圧は、内部抵抗10MΩの電圧計で測定したものです。
● !印のある部品は、安全性確保部品を示しています。部品の交換が必要な場合、パーツリストに記載されている部品を使用してください。
● 本回路図は標準回路図です。改良のため予告なく変更することがございます。


IC300: NJU7312AM
Analog function switch




IC301: NJU7311AM
Analog function switch




IC302, 304-306: NJM2068MD-TE2
Dual operational amplifier




IC307: YAC526-EZE2
2-chnnel high grade digital volume LSI




IC309-312: NJM5532M-D
Dual low noise operational amplifier



IC313: NJU7313AM
Analog function switch




IC308: YAC523-EVR2
Digital volume



FUNCTION 4/4

Page 152 F3
to OPERATION (3)_CB806

Page 168 I7
to FL (2)_CB967



NOTICE (model)
(J)····· JAPAN
(U)····· U.S.A
(C)····· CANADA
(R)····· GENERAL
(T)····· CHINA
(K)····· KOREA
(A)····· AUSTRALIA
(B)····· BRITISH
(E)····· EUROPE
(L)····· SINGAPORE
(E)····· SOUTH EUROPE
(V)····· TAIWAN
(F)····· RUSSIAN

RESISTOR

REMARKS	PARTS NAME
NO MARK	CARBON FILM RESISTOR (P=5)
☑	CARBON FILM RESISTOR (P=10)
△	METAL OXIDE FILM RESISTOR
△	METAL FILM RESISTOR
⊠	METAL PLATE RESISTOR
◪	FIRE PROOF CARBON FILM RESISTOR
▭	CEMENT MOLDED RESISTOR
⊘	SEMI VARIABLE RESISTOR
■	CHIP RESISTOR


CAPACITOR

REMARKS	PARTS NAME
NO MARK	ELECTROLYTIC CAPACITOR
⊗	TANTALUM CAPACITOR
NO MARK	CERAMIC CAPACITOR
✱	CERAMIC TUBULAR CAPACITOR
Ⓟ	POLYESTER FILM CAPACITOR
○	POLYSTYRENE FILM CAPACITOR
Ⓜ	MICA CAPACITOR
Ⓟ	POLYPROPYLENE FILM CAPACITOR
◉	SEMICONDUCTIVE CERAMIC CAPACITOR
Ⓟ	POLYPHENYLENE SULFIDE FILM CAPACITOR


Destination Part List (V3900_Sht-4)

※※※	LOC	J	U	C	RTKL	A	BGE
s351	C3503 C3504	X	X	X	US06222 220F(SL)	US06222 220F(SL)	US06222 220F(SL)
s352	R3512 R3513	RD35447 47	RD35447 47	RD35447 47	RD35622 2.2K	RD35622 2.2K	RD35622 2.2K
s353	IC356	X	X35474A BD3841FS-E2	X35474A BD3841FS-E2	X35474A BD3841FS-E2	X35474A BD3841FS-E2	X35474A BD3841FS-E2
s354	J3547 J3520 J3546	X	RD35000 0	RD35000 0	RD35000 0	RD35000 0	RD35000 0
s355	J3544 J3549 J3548 J3545	RD35000 0	X	X	X	X	X
s356	C3601 C3610	X	UR23710 10/16	UR23710 10/16	UR23710 10/16	UR23710 10/16	UR23710 10/16
s357	R3606 R3620 R3605 R3621	X	RD35810 100K	RD35810 100K	RD35810 100K	RD35810 100K	RD35810 100K
s358	PJ350	V976390 RJ-1073F-09-055	V547870 RJ-1073F109-GH5	V547870 RJ-1073F109-GH5	V547870 RJ-1073F109-GH5	V547870 RJ-1073F109-GH5	V547870 RJ-1073F109-GH5
s360	PJ352	V976430 RJ-1074-B4-0353	V547890 RJ-1074-B4-0353	V547890 RJ-1074-B4-0353	V547890 RJ-1074-B4-0353	V547890 RJ-1074-B4-0353	V547890 RJ-1074-B4-0353
s361	PJ353	V563480 RJ-1074109-0553	V532540 RJ-1074109-0H53	V532540 RJ-1074109-0H53	V532540 RJ-1074109-0H53	V532540 RJ-1074109-0H53	V532540 RJ-1074109-0H53
s362	PJ354	X	WH22100 RJ-1074-B3-0353	WH22100 RJ-1074-B3-0353	WH22100 RJ-1074-B3-0353	WH22100 RJ-1074-B3-0353	WH22100 RJ-1074-B3-0353
s363	C3506 C3507 C3508 C3509	X	US06247 470F(SL)	US06247 470F(SL)	US06247 470F(SL)	US06247 470F(SL)	US06247 470F(SL)
s364	C3524 C3525	X	US06210 100F(SL)	US06210 100F(SL)	US06210 100F(SL)	US06210 100F(SL)	US06210 100F(SL)
s365	C3551 C3552 C3553 C3550	X	UJ26710 10/50	UJ26710 10/50	UJ26710 10/50	UJ26710 10/50	UJ26710 10/50
s366	C3579 C3578 C3580	X	UR26647 4.7/50	UR26647 4.7/50	UR26647 4.7/50	UR26647 4.7/50	UR26647 4.7/50
s367	C3591 C3588	X	UR24710 10/25	UR24710 10/25	UR24710 10/25	UR24710 10/25	UR24710 10/25
s369	C3570 C3571 C3616 C3623 C3624 C3569	X	UR03810 100/16	UR03810 100/16	UR03810 100/16	UR03810 100/16	UR03810 100/16
s370	C3617 C3615	X	UR24710 10/25	UR24710 10/25	UR24710 10/25	UR24710 10/25	UR24710 10/25
s372	VR1977 C3582 C3581 C3581	X	VR16830 0-1	VR16830 0-1	VR16830 0-1	VR16830 0-1	VR16830 0-1
s373	C3584 C3587 C3586 C3585	X	WJ60430 3300P	WJ60430 3300P	WJ60430 3300P	WJ60430 3300P	WJ60430 3300P
s374	C3619 C3632 C3634 C3633	X	US13510 0.1/16	US13510 0.1/16	US13510 0.1/16	US13510 0.1/16	US13510 0.1/16
s375	D3503 D3502	X	YT33290 1SS355	YT33290 1SS355	YT33290 1SS355	YT33290 1SS355	YT33290 1SS355
s377	IC360 IC359	X	XB3554A0 NJW1194VITE1	XB3554A0 NJW1194VITE1	XB3554A0 NJW1194VITE1	XB3554A0 NJW1194VITE1	XB3554A0 NJW1194VITE1
s378	Q3507 Q3504 Q3503 Q3502 Q3506 Q3503 Q3501	X	VZ7259D D1938(F)	VZ7259D D1938(F)	VZ7259D D1938(F)	VZ7259D D1938(F)	VZ7259D D1938(F)
s379	R3508 R3511 R3510	X	HF35547 1/2F470	HF35547 1/2F470	HF35547 1/2F470	HF35547 1/2F470	HF35547 1/2F470
s380	R3544 R3543	X	RD35475 75	RD35475 75	RD35475 75	RD35475 75	RD35475 75
s381	R3559 R3560 R3561 R3553 R3556 R3554	X	RD35647 470	RD35647 470	RD35647 470	RD35647 470	RD35647 470
s382	R3567 R3570 R3568 R3569 R3571 R3572 R3559	X	RD35710 10K	RD35710 10K	RD35710 10K	RD35710 10K	RD35710 10K
s383	R3583 R3584 R3581 R3582	X	RD35722 22K	RD35722 22K	RD35722 22K	RD35722 22K	RD35722 22K
s384	R3617	X	RD35322 2.2	RD35322 2.2	RD35322 2.2	RD35322 2.2	RD35322 2.2
s386	R3635 R3630 R3633 R3634	X	RD35647 4.7K	RD35647 4.7K	RD35647 4.7K	RD35647 4.7K	RD35647 4.7K
s389	W3500	X	WH53310 -	WH53310 -	WH53310 -	WH53310 -	WH53310 -
s390	R3630 R3627	X	RD35822 220K	RD35822 220K	RD35822 220K	RD35822 220K	RD35822 220K
s391	R3624 R3625	X	RD35810 100K	RD35810 100K	RD35810 100K	RD35810 100K	RD35810 100K
s392	R3622 R3626 R3628 R3629	X	RF35610 1.0K	RF35610 1.0K	RF35610 1.0K	RF35610 1.0K	RF35610 1.0K
s393	IC358 IC357	X	X35054G NJM2068MD-TE2	X35054G NJM2068MD-TE2	X35054G NJM2068MD-TE2	X35054G NJM2068MD-TE2	X35054G NJM2068MD-TE2
s394	C3589 C3590	X	UR24710 10/25	UR24710 10/25	UR24710 10/25	UR24710 10/25	UR24710 10/25
s395	C3502 C3505	X	X	X	X	X	X
s396	PJ355	X	X	X	X	X	X
s397	R3593 R3594	X	X	X	X	X	X
s398	PJ357	W019490 RJ-1060-09-0531	W236480 RJ-1060109-0441	W236480 RJ-1060109-0341	W236480 RJ-1060109-0341	W236480 RJ-1060109-0341	W236480 RJ-1060109-0341
s399	PJ356	W238530 RJ-1060F01-0531	W235410 RJ-1060F01-0331	W235410 RJ-1060F01-0331	W235410 RJ-1060F01-0331	W235410 RJ-1060F01-0331	W235410 RJ-1060F01-0331
s403	Q3508 Q3509 Q3510 Q3511	X	X	X	X	X	X


IC350-352: NJM2068MD-TE2
Dual operational amplifier



IC355, 356: BD3841FS
Function switch




IC359, 360: NJW1194V
2-channel electronic volume input selector and tone control





★ All voltages are measured with a 10MΩ/V DC electronic voltmeter.
★ Components having special characteristics are marked ⚠ and must be replaced with parts having specifications equal to those originally installed.
★ Schematic diagram is subject to change without notice.


● 電圧は、内部抵抗10MΩの電圧計で測定したものです。
● ⚠印のある部品は、安全性確保部品を示しています。部品の交換が必要な場合、パーツリストに記載されている部品を使用してください。
● 本回路図は標準回路図です。改良のため予告なく変更することがございます。


OPERATION














Interchangeable Parts at Manufacture-Stage

Mark	Reference Parts Number	Parts Name
&1	QB002, B003	2SD1938(F) 2SC3326(A/B) 2SC5938A(A/B) 2SD2704K
&2	DB004-B008, B010	1SS355 MA111 KDS160-RTK/P
&3	UB001	GP1FA513RZ0F GP1FA513RZ


Destinatin Part List

sXX	LOC	J	UCRTKABGEL
s1	CB039	US13510 0.1/16	X
s2	JB005	X	RD35000 0


NOTICE (model)

(J)····· JAPAN
(U)····· U.S.A
(C)····· CANADA
(R)····· GENERAL
(T)····· CHINA
(K)····· KOREA
(A)····· AUSTRALIA
(B)····· BRITISH
(G)····· EUROPE
(L)····· SINGAPORE
(E)····· SOUTH EUROPE
(V)····· TAIWAN


IC801: NJM4565M
Dual operational amplifier



IC802: SN74AHCT1G32DCKR
Single 2-input positive-OR gate



IC805: BA15218F
Dual high slew rate, low noise operational amplifier



RESISTOR

REMARKS	PARTS NAME
NO MARK	CARBON FILM RESISTOR (P=5)
⊘	CARBON FILM RESISTOR (P=10)
△	METAL OXIDE FILM RESISTOR
⊿	METAL FILM RESISTOR
⊠	METAL PLATE RESISTOR
▨	FIRE PROOF CARBON FILM RESISTOR
□	CEMENT MOLDED RESISTOR
⊘	SEMI VARIABLE RESISTOR
▩	CHIP RESISTOR

CAPACITOR

REMARKS	PARTS NAME	
NO MARK	ELECTROLYTIC CAPACITOR	⊣⊢
⊗	TANTALUM CAPACITOR	
NO MARK	CERAMIC CAPACITOR	⊣⊢
◉	CERAMIC TUBULAR CAPACITOR	
◎	POLYESTER FILM CAPACITOR	
○	POLYSTYRENE FILM CAPACITOR	
Ⓘ	MICA CAPACITOR	
Ⓟ	POLYPROPYLENE FILM CAPACITOR	
▩	SEMICONDUCTIVE CERAMIC CAPACITOR	


IMPREMENTATION:

INPUT SELECTOR
VOLUME
VIDEO-AUX
HEAD PHONE AMP
MIC AMP
PROGRAM SELECTOR
MASTER SWITCH
USB CONNECTOR

★ All voltages are measured with a 10MΩ/V DC electronic voltmeter.
★ Components having special characteristics are marked ! and must be replaced with parts having specifications equal to those originally installed.
★ Schematic diagram is subject to change without notice.

● 電圧は、内部抵抗10MΩの電圧計で測定したものです。
● !印のある部品は、安全性確保部品を示しています。部品の交換が必要な場合、パーツリストに記載されている部品を使用してください。
● 本回路図は標準回路図です。改良のため予告なく変更することがございます。

MAIN




Destination Part List

s-xx	LOC	J	UCRTA	KBGLE
s1	TE250	WK56100 MST-207V1-01	WK56100 MST-207V1-01	WK56110 MST-207V1-01
s2	TE252 TE251 TE254	WK56080 MST-204V1-01	WK56080 MST-204V1-01	WK56090 MST-204V1-01
s3	TE253	X	WK56080 MST-204V1-01	WK56090 MST-204V1-01
s4	C399 C400 C403	X	WJ62500 0.01	WJ62500 0.01
s5	C404 C398	X	WH16550 0.022/100	WH16550 0.022/100
s6	R595 R596	X	HV75347 4.7	HV75347 4.7
s7	RY254	X	WM95900 GSPA-2B-NC	WM95900 GSPA-2B-NC
s8	D313 D304	X	V733290 1SS355	V733290 1SS355
s12	RY250	X	WE64870 DH24D2-D-9	WE64870 DH24D2-D-9
s14	J258 J257	VW50000	X	X
s15	R558 R559	X	RD35627 270K	RD35627 270K
s17	R343	X	RD35347 4.7	RD35347 4.7
s18	R560 R561	RD35820 220K	RD35833 330K	RD35833 330K
s19	R562 R563	RD35827 270K	RD35839 390K	RD35839 390K
s30	C360 C364	WN16550 0.022/100	WP42100 0.047/100	WN16550 0.022/100

Interchangeable Parts at Manufacture-Stage

Mark	Reference Parts Number	Parts Name
k1	Q257-263-265-268-321	KTA1517S-GR 2SA1312GR-BL
k2	Q314-320-340-346-264 269-277	KTC3911S-GR-BL 2SC3324GR-BL
k3	D252-258-265-278 302-307-313-314	1SS355 MA3J111GSL KDS160-RTK/P
k4	Q267	2SB1274(R/S) 2SB1565(E/F) KTA1267
k5		
k6		



CAPACITOR

REMARKS	PARTS NAME	
NO MARK	ELECTROLYTIC CAPACITOR	B
⊗	TANTALUM CAPACITOR	
NO MARK	CERAMIC CAPACITOR	F
◉	CERAMIC TUBULAR CAPACITOR	
◎	POLYESTER FILM CAPACITOR	
○	POLYSTYRENE FILM CAPACITOR	
ⓘ	MICA CAPACITOR	
⊘	POLYPROPYLENE FILM CAPACITOR	
●	SEMICONDUCTIVE CERAMIC CAPACITOR	

NOTICE (mode1)
(J)····· JAPAN
(U)····· U.S.A
(C)····· CANADA
(R)····· GENERAL
(T)····· CHINA
(K)····· KOREA
(A)····· AUSTRALIA
(B)····· BRITISH
(G)····· EUROPE
(L)····· SINGAPORE
(E)····· SOUTH EUROPE
(V)····· TAIWAN
(F)····· RUSSIAN

RESISTOR

REMARKS	PARTS NAME
NO MARK	CARBON FILM RESISTOR (P=5)
☑	CARBON FILM RESISTOR (P=10)
△	METAL OXIDE FILM RESISTOR
▲	METAL FILM RESISTOR
⊠	METAL PLATE RESISTOR
◪	FIRE PROOF CARBON FILM RESISTOR
□	CEMENT MOLDED RESISTOR
⊘	SEMI VARIABLE RESISTOR
■	CHIP RESISTOR

★ All voltages are measured with a 10MΩ/V DC electronic voltmeter.
★ Components having special characteristics are marked ⚠ and must be replaced with parts having specifications equal to those originally installed.
★ Schematic diagram is subject to change without notice.

● 電圧は、内部抵抗10MΩの電圧計で測定したものです。
● ⚠印のある部品は、安全性確保部品を示しています。部品の交換が必要な場合、パーツリストに記載されている部品を使用してください。
● 本回路図は標準回路図です。改良のため予告なく変更することがございます。

POWER

Destination Part List

sXX	LOC	J	U	C	R	T	K	A	B	GE	L
s1	J6	X	X	X	VN50000	VN50000	VN50000	VN50000	VN50000	VN50000	VN50000
s2	C4	WJ36120 0.047/400	WJ36120 0.047/400	WJ36120 0.047/400	WD55420 0.047/630	WJ36180 0.022/630	WJ36180 0.022/630	WJ36180 0.022/630	WJ36180 0.022/630	WJ36180 0.022/630	WD55420 0.047/630
s3	C7	WB69630 0.1/400	WB69630 0.1/400	WB69630 0.1/400	WF08150 0.047/630	WF08150 0.047/630	WF08150 0.047/630	WF08150 0.047/630	WF08150 0.047/630	WF08150 0.047/630	WF08150 0.047/630
s4	F1	WG21120 10A125V	WG21120 10A125V	WG21120 10A125V	WG21120 10A125V	WB76060 6.3A250V	WB76060 6.3A250V	WB76060 6.3A250V	WB76060 6.3A250V	WB76060 6.3A250V	WG21120 10A125V
s5	F2	X	WG41030 4A125V	WG41030 4A125V	X	VT84290 2.5A250V	X	X	VT84290 2.5A250V	VT84290 2.5A250V	X
s6	J1	VN50000	X	X	VN50000	X	VN50000	VN50000	X	X	VN50000
s7	CB2 CB1	X	WN10300 TP00351-31	WN10300 TP00351-31	X	WN10300 TP00351-31	X	X	WN10300 TP00351-31	WN10300 TP00351-31	X
s8	T1	YA12940 YA2911	YA29140 YA2911	YA29140 YA2911	X7034A0 X7034	X7035A0 X7035	X7035A0 X7035	X7035A0 X7035	X7035A0 X7035	X7035A0 X7035	X7034A0 X7034
s9	TE1	VU54310 S2-7641-214	VU54310 S2-7641-214	VU54310 S2-7641-214	VS6740 AC-182-GB-115V	VS6740 AC-182-GB-115V	X	VT91500 S2-7737-210	VU54330 S2-7721-210	VU54340 S2-7621-214	VU54340 S2-7621-214
s11	R22	RD35000 0	RF35612 1-2K	RF35627 2.7K	RF35647 4.7K	RF35668 6.8K	RF35710 10K	RF35715 15K	RF35724 24K	RF35747 47K	RF35810 100K
s12	C10	UU24933 3300/25	UU24933 3300/25	UU24933 3300/25	WD04730 3300/50	UU24933 3300/25	UU24933 3300/25	UU24933 3300/25	UU24933 3300/25	UU24933 3300/25	WD04730 3300/50
s13	C47	UU24933 3300/25	X	X	X	UU24933 3300/25	UU24933 3300/25	UU24933 3300/25	UU24933 3300/25	UU24933 3300/25	X
s16	TE2	WB89330 R-3019012(F)	WB78260 R-3019012(E)	WB78260 R-3019012(E)	WB78260 R-3019012(E)	WB78260 R-3019012(E)	WB78260 R-3019012(E)	WB78260 R-3019012(E)	WB89330 R-3019012(F)	WB89330 R-3019012(F)	WB78260 R-3019012(E)
s17	J28	VN50000	X	VN50000	VN50000	VN50000	VN50000	VN50000	VN50000	VN50000	VN50000
s18	J29	X	VN50000	VN50000	X	X	X	X	X	X	X
s19	J27	VN50000	X	X	VN50000	VN50000	VN50000	VN50000	VN50000	VN50000	VN50000
s24	CB7	X	X	X	V937790 B4P75-VH	X	X	X	X	X	V937790 B4P75-VH
s25	J113 J2 J3	X	X	X	VN50000	X	X	X	X	X	VN50000
s26	W2B W2A	X	X	X	V941190 VV-ST	X	X	X	X	X	V941190 VV-ST
s27	CB6	X	X	X	V937780 B3P5S-VH	X	X	X	X	X	V937780 B3P5S-VH
s28	SW1	X	X	X	WB49370 RB140246	X	X	X	X	X	WB49370 RB140246
s29	CB10 CB9	X	X	X	WN10300 TP00351-31	X	X	X	X	X	WN10300 TP00351-31
s30	F3	X	X	X	WB76060 6.3A250V	X	X	X	X	X	WB76060 6.3A250V
s31	IC4	X	X624BA0 NJM2388F33	X624BA0 NJM2388F33	X	X	X	X	X	X	X
s32	R40	X	RD35610 1K	X	X	X	X	X	X	X	X
s33	C29	X	UR23810 100/16	UR23810 100/16	X	X	X	X	X	X	X
s34	D27	X	V237660 RB500V-40	V237660 RB500V-40	X	X	X	X	X	X	X
s35	C34	X	UR23810 100/16	UR23810 100/16	X	X	X	X	X	X	X
s36	D33	X	VU99050 MA8030-L	VU99050 MA8030-L	X	X	X	X	X	X	X
s37	Q12	X	WC43480 KRA102S-RTK/P	WC43480 KRA102S-RTK/P	X	X	X	X	X	X	X
s38	R51	X	WJ78750 1P0.22	WJ78750 1P0.22	X	X	X	X	X	X	X
s39	R50	X	RD35510 10Ω	RD35510 10Ω	X	X	X	X	X	X	X
s40	W8	X	WM66310 SCN-XH	X	X	X	X	X	X	X	X
s41	Q5	WC52940 KTC3875S-Y.GR-R	WC52940 KTC3875S-Y.GR-R	WC52940 KTC3875S-Y.GR-R	X	WC52940 KTC3875S-Y.GR-R	WC52940 KTC3875S-Y.GR-R	WC52940 KTC3875S-Y.GR-R	WC52940 KTC3875S-Y.GR-R	WC52940 KTC3875S-Y.GR-R	WC52940 KTC3875S-Y.GR-R
s42	R12	RD35747 47K	RD35747 47K	RD35747 47K	X	RD35747 47K	RD35747 47K	RD35747 47K	RD35747 47K	RD35747 47K	X
s43	D19 D14 D15	V426960 D2SBA20	WH48730 RS203M-B-C-J80	WH48730 RS203M-B-C-J80	WH48730 RS203M-B-C-J80	WH48730 RS203M-B-C-J80	WH48730 RS203M-B-C-J80	WH48730 RS203M-B-C-J80	V426960 D2SBA20	V426960 D2SBA20	WH48730 RS203M-B-C-J80

CAPACITOR

REMARKS	PARTS NAME
	ELECTROLYTIC CAPACITOR
⊗	TANTALUM CAPACITOR
NO MARK	CERAMIC CAPACITOR
◉	CERAMIC TUBULAR CAPACITOR
◎	POLYESTER FILM CAPACITOR
○	POLYSTYRENE FILM CAPACITOR
ⓘ	MICA CAPACITOR
Ⓟ	POLYPROPYLENE FILM CAPACITOR
◉	SEMICONDUCTIVE CERAMIC CAPACITOR
Ⓢ	POLYPHENYLENE SULFIDE FILM CAPACITOR

RESISTOR


REMARKS	PARTS NAME
NO MARK	CARBON FILM RESISTOR (P=5)
▽	CARBON FILM RESISTOR (P=10)
△	METAL OXIDE FILM RESISTOR
▲	METAL FILM RESISTOR
⊠	METAL PLATE RESISTOR
◪	FIRE PROOF CARBON FILM RESISTOR
□	CEMENT MOLDED RESISTOR
⊘	SEMI VARIABLE RESISTOR
■	CHIP RESISTOR

NOTICE (model)
(J)····· JAPAN
(U)····· U.S.A
(C)····· CANADA
(R)····· GENERAL
(T)····· CHINA
(K)····· KOREA
(A)····· AUSTRALIA
(B)····· BRITISH
(G)····· EUROPE
(L)····· SINGAPORE
(E)····· SOUTH
(V)····· TAIWAN
(F)····· RUSSIAN


Interchangeable Parts at Manufacture-Stage

Mark	Reference Parts Number	Parts Name
k1	Q12	KRA102S-RTK/P DTA114EKA
k2	G44	KRC102S-RTK/P DTC114EKA
k3	G1	KRC104S-RTK/P DTC144EKA
k4	G13-24	KRA104S-RTK/P DTA144EKA
k5	D1-5 8-12 16-18 21-30 45	1SS355 WAZJ1109L KDS160-RTK/P
k6	G6	K3B50-E 2SK3491-E
k7	D10-11	DB105 S1NB60
k8	Q2-3 5-11	KTC3875S-Y GR-RTK/P 2SD601AR/AQL(G.R.S) 2SC2412K(G/R/S)
k9	G8-10 41	KTA1504S-Y GR-RTK/P 2SA1037AK(G/R/S)
k10	Q9	KTA1046-Y-U/P 2SB1274 R-S ST 2SB1565 E-F ST
k11		
k12		


IC13, 14: LM61CIZ
Temperature sensor



IC15: KIA7812API
Voltage regulator





IC16: KIA7912PI
Voltage regulator




VOLTAGE SELECTOR


230-240V	1-2/5-6
220V	2-3/6-7
110V	3-4/7-8
120V	4-5/8-1








POINT Ⓓ ①/ C2, ②/ Q1




IC3: TC4013BP
Dual D-type flip flop




INPUTS				OUTPUTS	
RESET	SET	DATA	CK ▲	Qn + 1	Qn + 1
L	H	*	*	H	L
H	L	*	*	L	H
H	H	*	*	H	H
L	L	H	↑	H	L
L	L	L	↑	L	H
L	L	*	↓	Qn	Qn

▲ : Don't care
↑ : Level change
↓ : No change


IC4: NJM2388F33
Low dropout voltage regulator with ON/OFF control



IC5: NJM2388F09
Low dropout voltage regulator with ON/OFF control



IC6, 7: NJM2388F05
Low dropout voltage regulator with ON/OFF control




★ All voltages are measured with a 10MΩ/V DC electronic voltmeter.
★ Components having special characteristics are marked ⚠ and must be replaced with parts having specifications equal to those originally installed.
★ Schematic diagram is subject to change without notice.

● 電圧は、内部抵抗10MΩの電圧計で測定したものです。
● ⚠ 印のある部品は、安全性確保部品を示しています。部品の交換が必要な場合、パーツリストに記載されている部品を使用してください。
● 本回路図は標準回路図です。改良のため予告なく変更することがございます。

A-VIDEO 1/2

Page 157 A3
to D-VIDEO_CB701

Page 157 A2
to D-VIDEO_CB700



RESISTOR

REMARKS	PARTS NAME
NO MARK	CARBON FILM RESISTOR (P=5)
	CARBON FILM RESISTOR (P=10)
	METAL OXIDE FILM RESISTOR
	METAL FILM RESISTOR
	METAL PLATE RESISTOR
	FIRE PROOF CARBON FILM RESISTOR
	CEMENT MOLDED RESISTOR
	SEMI VARIABLE RESISTOR
	CHIP RESISTOR

NOTICE (model)
(U)····· JAPAN
(U)····· U.S.A
(C)····· CANADA
(R)····· GENERAL
(T)····· CHINA
(K)····· KOREA
(A)····· AUSTRALIA
(B)····· BRITISH
(G)····· EUROPE
(L)····· SINGAPORE
(E)····· SOUTH
(V)····· TAIWAN
(F)····· RUSSIAN


CAPACITOR

REMARKS	PARTS NAME
NO MARK	ELECTROLYTIC CAPACITOR
	TANTALUM CAPACITOR
NO MARK	CERAMIC CAPACITOR
	CERAMIC TUBULAR CAPACITOR
	POLYESTER FILM CAPACITOR
	POLYSTYRENE FILM CAPACITOR
	MICA CAPACITOR
	POLYPROPYLENE FILM CAPACITOR
	SEMICONDUCTIVE CERAMIC CAPACITOR
	POLYPHENYLENE SULFIDE FILM CAPACITOR


Destination Part List

S/XX	LOC	J	U-C-R-K	T-A-B-G-L-E	
s1	PJ201 PJ202 PJ203 PJ205	WD39840 YKF45-3011	X	X	
s2	R2001 R2002 R2003 R2004 R2005 R2006 R2007 R2008 R2009	RO35510 100	X	X	
s3	C2001 C2002 C2003 C2004 C2005 C2006 C2007 C2008 C2009 C2024 C2025 C2026	US06410 0.01	X	X	
s4	D2001 D2002 D2003 D2004 D2005 D2006 D2007 D2008 D2009	YT33290 155355	X	X	D Connector
s5	R2010 R2020	HY75310 1	X	X	
s6	C2010 C2011	US13510 0.1/16	X	X	
s7	IC204 IC205	XS79040 TC74HC4052AF	X	X	
s8	R2027 R2028 R2029	RO35475 75	X	X	
s9	C2021 C2022 C2023	US06080 8PCH	X	X	
s10	R2021 R2022 R2023	RO35710 10K	X	X	
s11	PJ204	WK38210 YLC21-3077V	WK38200 YKC21-4502V	WK38200 YKC21-4502V	
s12	PJ206	WK38190 YKC21-4200V	WK38180 YKC21-4199V	WK38180 YKC21-4199V	Ni or Au


IC201: NJW1321FP1
Wide band video switch with I²C bus




IC202: TA1318AF
SYNC processor, frequency counter IC for TV component signals



IC203: NJM2581M
Video amplifier




IC204, 205: TC74HC4052AF
Analog multiplexer/demultiplexer



INHIBIT	B	A	
0	0	0	0x, 0y
0	0	1	1x, 1y
0	1	0	2x, 2y
0	1	1	3x, 3y
1	X	X	NONE

IC207: NJM2566AV
6-channel video amplifier for DVD



Interchangeable Parts at Manufacture-Stage

Mark	Reference Parts Number	Parts Name
&1	D2001-2009-2061-2062-2561-2563-2581-2582-2611-2612-2631-2634-2661-2662	1SS355 MA2J1110GL
&2	Q2541-2546	DTC144EKA KRC104S-RTK/P
&3	IC220	TK15420MTL-G AS8656AR2
&4	IC211-214	MM74HC4051SJX,NL TC74HC4051AFEL-F1
&5	IC204-205	MM74HC4052SJX,NL TC74HC4052AFEL-F1
&6	IC217-221	MM74HC4053SJX,NL TC74HC4053AFEL-F1
&7	IC215-216	CD4051BNSR TC4051BFEL-N-F1

★ All voltages are measured with a 10MΩ/V DC electronic voltmeter.
★ Components having special characteristics are marked ! and must be replaced with parts having specifications equal to those originally installed.
★ Schematic diagram is subject to change without notice.

● 電圧は、内部抵抗10MΩの電圧計で測定したものです。
● ! 印のある部品は、安全性確保部品を示しています。部品の交換が必要な場合、パーツリストに記載されている部品を使用してください。
● 本回路図は標準回路図です。改良のため予告なく変更することがございます。

A-VIDEO 2/2

Page 152 F4
to OPERATION (3)_CB807

Page 148 I8
to FUNCTION (1)_CB410


Page 154 H4
to POWER (3)_CB23

Page 165 M3
to D-VIDEO_CB106

001.sht
to A-VIDEO 1/2

Page 151 C10
to FUNCTION (2)_W3500

001.sht
to A-VIDEO 1/2


BD/HD DVD IN
DVD IN
CBL/SAT IN
VIDEO IN
VCR DVR/VCR IN
VCR DVR/VCR OUT
MONITOR OUT
REC/ZONE SELECTOR
INPUT SELECTOR
CVBS REC/ZONE SELECTOR
Y REC/ZONE SELECTOR
C REC/ZONE SELECTOR
SOURCE/REC SELECTOR
CVBS INPUT SELECTOR
Y INPUT SELECTOR
C INPUT SELECTOR
SIGNAL DETECT
OSD IC
MUTE
L A73050-TLM-E
L A71056M-TLM-E
IC227 TC74VHCU04FT(EL
IC229 TC74VHC4051AFT(EL
IC2201 TK15420MTL-G
IC2202 TK15420MTL-G
IC2203 TK15420MTL-G
IC2204 TK15420MTL-G
IC2205 TK15420MTL-G
IC2206 TK15420MTL-G
IC2207 TK15420MTL-G
IC2208 TK15420MTL-G
IC2209 TK15420MTL-G
IC2210 TK15420MTL-G
IC2211 TK15420MTL-G
IC2212 TK15420MTL-G
IC2213 TK15420MTL-G
IC2214 TK15420MTL-G
IC2215 TK15420MTL-G
IC2216 TK15420MTL-G
IC2217 TK15420MTL-G
IC2218 TK15420MTL-G
IC2219 LA71056M-TLM-E
IC2220 LA71056M-TLM-E
IC2221 LA71056M-TLM-E
IC2222 LA71056M-TLM-E
IC2223 LA71056M-TLM-E
IC2224 LA71056M-TLM-E
IC2225 LA71056M-TLM-E
IC2226 LA71056M-TLM-E
IC2227 LA71056M-TLM-E
IC2228 LA71056M-TLM-E
IC2229 LA71056M-TLM-E
IC2230 LA71056M-TLM-E
IC2231 LA71056M-TLM-E
IC2232 LA71056M-TLM-E
IC2233 LA71056M-TLM-E
IC2234 LA71056M-TLM-E
IC2235 LA71056M-TLM-E
IC2236 LA71056M-TLM-E
IC2237 LA71056M-TLM-E
IC2238 LA71056M-TLM-E

D-VIDEO 1/10

DVIDEO-1

Page 155 G2 to A-VIDEO_CB202

Page 155 F2 to A-VIDEO_CB201

to A-VIDEO

to D-VIDEO 2/10

to D-VIDEO 3/10, 9/10

to D-VIDEO 6/10

to D-VIDEO 9/10

Video Encoder

IC702

ADV7342BSTZ

VIDEO ENCODER


Video Decoder

IC701


ADV7800BSTZ-80

VIDEO DECODER


IC701: ADV7800BSTZ-80
10-bit, SDTV/HDTV 3D comb filter, video decoder and graphics digitizer




IC702: ADV7342BSTZ
Multiformat video encoder



IC700: LA73053-TLM-E
Analog dual operational amplifier



IC704, 705, 707: SN74LVC245APWR
Octal bus transceivers with 3-state outputs



Interchangeable Parts at Manufacture-Stage

Mark	Reference Parts Number	Parts Name
k1	D1001-1004, 1006-1008 7064-7077, 7079-7084 7087-7091, 7093-7095 7097, 7100-7105	1SS355 MA2J111GL KDS160-R74/P
k2	IC104-125	K4S281632K-UC75000 M12L128168A-7TG
k3	T1000	H126DNLT 5558-5999-U7-F
k4	IC727	SI91354CTU SI91356CTU

RESISTOR

REMARKS	PARTS NAME
NO MARK	CARBON FILM RESISTOR (P=5)
◪	CARBON FILM RESISTOR (P=10)
△	METAL OXIDE FILM RESISTOR
▲	METAL FILM RESISTOR
⊠	METAL PLATE RESISTOR
◩	FIRE PROOF CARBON FILM RESISTOR
□	CEMENT MOLDED RESISTOR
⊘	SEMI VARIABLE RESISTOR
■	CHIP RESISTOR

CAPACITOR


REMARKS	PARTS NAME	
NO MARK	ELECTROLYTIC CAPACITOR	日
⊗	TANTALUM CAPACITOR	
NO MARK	CERAMIC CAPACITOR	
◉	CERAMIC TUBULAR CAPACITOR	
◍	POLYESTER FILM CAPACITOR	
○	POLYSTYRENE FILM CAPACITOR	日
ⓘ	MICA CAPACITOR	
◐	POLYPROPYLENE FILM CAPACITOR	
◉	SEMICONDUCTIVE CERAMIC CAPACITOR	

NOTICE (model)
(J)····· JAPAN
(U)····· U.S.A
(C)····· CANADA
(B)····· GENERAL
(T)····· CHINA
(K)····· KOREA
(A)····· AUSTRALIA
(B)····· BRITISH
(G)····· EUROPE
(L)····· SINGAPORE
(E)····· SOUTH EUROPE
(V)····· TAIWAN
(F)····· RUSSIAN

★ All voltages are measured with a 10MΩ/V DC electronic voltmeter.
★ Components having special characteristics are marked ! and must be replaced with parts having specifications equal to those originally installed.
★ Schematic diagram is subject to change without notice.

● 電圧は、内部抵抗10MΩの電圧計で測定したものです。
● !印のある部品は、安全性確保部品を示しています。部品の交換が必要な場合、パーツリストに記載されている部品を使用してください。
● 本回路図は標準回路図です。改良のため予告なく変更することがございます。


D-VIDEO 2/10




★ All voltages are measured with a 10MΩ/V DC electronic voltmeter.
★ Components having special characteristics are marked ⚠ and must be replaced with parts having specifications equal to those originally installed.
★ Schematic diagram is subject to change without notice.

● 電圧は、内部抵抗10MΩの電圧計で測定したものです。
● ⚠印のある部品は、安全性確保部品を示しています。部品の交換が必要な場合、パーツリストに記載されている部品を使用してください。
● 本回路図は標準回路図です。改良のため予告なく変更することがございます。


IC714: YGV619
OSD display controller




IC715: M12L64322A-7TG 0.1UM
512 k x 32-bit x 4 banks synchronous DRAM



IC716: TC7WZ04FK
Triple inverter



IC717: SN74LVC74APWR
Dual positive-edge-triggered D-type flip-flop



RESISTOR

REMARKS	PARTS NAME
NO MARK	CARBON FILM RESISTOR (P=5)
⚠	CARBON FILM RESISTOR (P=10)
△	METAL OXIDE FILM RESISTOR
▲	METAL FILM RESISTOR
⊠	METAL PLATE RESISTOR
◪	FIRE PROOF CARBON FILM RESISTOR
□	CEMENT MOLDED RESISTOR
⊘	SEMI VARIABLE RESISTOR
■	CHIP RESISTOR

CAPACITOR

REMARKS	PARTS NAME	
NO MARK	ELECTROLYTIC CAPACITOR	⊟
⊗	TANTALUM CAPACITOR	⊟
NO MARK	CERAMIC CAPACITOR	⊟
◉	CERAMIC TUBULAR CAPACITOR	⊟
Ⓜ	POLYESTER FILM CAPACITOR	⊟
Ⓢ	POLYSTYRENE FILM CAPACITOR	⊟
Ⓘ	MICA CAPACITOR	⊟
Ⓟ	POLYPROPYLENE FILM CAPACITOR	⊟
◉	SEMICONDUCTIVE CERAMIC CAPACITOR	⊟

NOTICE (model)
(J)····· JAPAN
(U)····· U.S.A
(C)····· CANADA
(R)····· GENERAL
(T)····· CHINA
(K)····· KOREA
(A)····· AUSTRALIA
(B)····· BRITISH
(G)····· EUROPE
(L)····· SINGAPORE
(E)····· SOUTH EUROPE
(V)····· TAIWAN
(F)····· RUSSIAN

D-VIDEO 3/10

DVIDEO-3

RESITOR

REMARKS	PARTS NAME
NO MARK	CARBON FILM RESISTOR (P=5)
☑	CARBON FILM RESISTOR (P=10)
△	METAL OXIDE FILM RESISTOR
▲	METAL FILM RESISTOR
☒	METAL PLATE RESISTOR
◪	FIRE PROOF CARBON FILM RESISTOR
□	CEMENT MOLDED RESISTOR
⊘	SEMI VARIABLE RESISTOR
■	CHIP RESISTOR

CAPACITOR

REMARKS	PARTS NAME	
⊗	ELECTROLYTIC CAPACITOR	H
	TANTALUM CAPACITOR	
NO MARK	CERAMIC CAPACITOR	
◉	CERAMIC TUBULAR CAPACITOR	
◎	POLYESTER FILM CAPACITOR	H
○	POLYSTYRENE FILM CAPACITOR	
Ⓘ	MICA CAPACITOR	
Ⓟ	POLYPROPYLENE FILM CAPACITOR	
●	SEMICONDUCTIVE CERAMIC CAPACITOR	

NOTICE (model)
(J)····· JAPAN
(U)····· U.S.A
(C)····· CANADA
(R)····· GENERAL
(T)····· CHINA
(K)····· KOREA
(A)····· AUSTRALIA
(B)····· BRITISH
(G)····· EUROPE
(L)····· SINGAPORE
(E)····· SOUTH
(V)····· TAIWAN
(F)····· RUSSIAN

VIDEO PROCESSOR
No replacement part available.
サービス部品供給なし

256M bit x 16
DDR2 SDRAM

IC752, 753: V59C1256164QAF25
256 M-bit DDR2 SDRAM

1	2	3		7	8	9
VDD	NC	VSS	A	VSSQ	DQS	VDDQ
NC	VSSQ	DM	B	DQS	VSSQ	NC
VDDQ	DQ1	VDDQ	C	VDDQ	DQ0	VDDQ
NC	VSSQ	DQ3	D	DQ2	VSSQ	NC
VDDL	VREF	VSS	E	VSSDL	CK	VDD
	CKE	WE	F	RAS	CK	ODT
NC	BA0	BA1	G	CAS	CS	
	A10	A1	H	A2	A0	VDD
VSS	A3	A5	J	A6	A4	
	A7	A9	K	A11	A8	VSS
VDD	A12	NC	L	NC	NC	

★ All voltages are measured with a 10MΩ/V DC electronic voltmeter.
★ Components having special characteristics are marked ! and must be replaced with parts having specifications equal to those originally installed.
★ Schematic diagram is subject to change without notice.

● 電圧は、内部抵抗10MΩの電圧計で測定したものです。
● ! 印のある部品は、安全性確保部品を示しています。部品の交換が必要な場合、パーツリストに記載されている部品を使用してください。
● 本回路図は標準回路図です。改良のため予告なく変更することがございます。

D-VIDEO 4/10

DVIDEO-4

HDMI

BD/HD DVD — HDMI IN-1 — HDMI IN-Front

DVD — HDMI IN-2

CBL/SAT — HDMI IN-3

DVR — HDMI IN-4

Differential impedance: 105 ohm

IC726
SII9185ACTU
HDMI SW

IC728
SII9185ACTU
HDMI SW

No replacement part available.
サービス部品供給なし


No replacement part available.
サービス部品供給なし

HDMI DUAL RECEIVER


IC727
SII9135ACTU
HDMI Dual Receiver

No replacement part available.
サービス部品供給なし

IC726, 728: SiI9185ACTU
3:1 HDMI 1.3 switch



IC727: SiI9135ACTU
HDMI receiver



RESISTOR

REMARKS	PARTS NAME
NO MARK	CARBON FILM RESISTOR (5%)
○	CARBON FILM RESISTOR (1%)
△	METAL OXIDE FILM RESISTOR
△	METAL FILM RESISTOR
⊠	METAL PLATE RESISTOR
▲	FIRE PROOF CARBON FILM RESISTOR
□	CEMENT MOLDED RESISTOR
◇	SEMI VARIABLE RESISTOR
■	CHIP RESISTOR

CAPACITOR

REMARKS	PARTS NAME
⊗	TANTALUM CAPACITOR
◉	CERAMIC TUBULAR CAPACITOR
◎	POLYESTER FILM CAPACITOR
○	POLYSTYRENE FILM CAPACITOR
⊙	MICA CAPACITOR
⊘	POLYPROPYLENE FILM CAPACITOR
◉	SEMICONDUCTIVE CERAMIC CAPACITOR

NOTICE (model)
(J)····· JAPAN
(U)····· U.S.A
(C)····· CANADA
(B)····· GENERAL
(T)····· CHINA
(K)····· KOREA
(A)····· AUSTRALIA
(B)····· BRITISH
(G)····· EUROPE
(L)····· SINGAPORE
(E)····· SOUTH EUROPE
(V)····· TAIWAN
(F)····· RUSSIAN

★ All voltages are measured with a 10MΩ/V DC electronic voltmeter.
★ Components having special characteristics are marked ! and must be replaced with parts having specifications equal to those originally installed.
★ Schematic diagram is subject to change without notice.

● 電圧は、内部抵抗10MΩの電圧計で測定したものです。
● ! 印のある部品は、安全性確保部品を示しています。部品の交換が必要な場合、パーツリストに記載されている部品を使用してください。
● 本回路図は標準回路図です。改良のため予告なく変更することがございます。

D-VIDEO 5/10


DVIDEO-5

HDMI


HDMI OUT1

HDMI OUT2


IC729, 732: SiI9134CTU
HDMI transmitter




IC730, 733: NJM2867F3-05
Low dropout voltage regulator




IC731: LB1836M-TLM-E
Motor driver IC



IC734: SN74CB3Q3257PWR
Low boltage high-bandwidth bus switch



IC735: SN74LVC245APWR
Octal bus transceivers with 3-state outputs



No replacement part available.
サービス部品供給なし

Page 168 B2
to FL (2)_CB953

RESISTOR

REMARKS	PARTS NAME
NO MARK	CARBON FILM RESISTOR (P=5)
☑	CARBON FILM RESISTOR (P=10)
△	METAL OXIDE FILM RESISTOR
▲	METAL FILM RESISTOR
☒	METAL PLATE RESISTOR
▨	FIRE PROOF CARBON FILM RESISTOR
□	CEMENT MOLDED RESISTOR
⊘	SEMI VARIABLE RESISTOR
■	CHIP RESISTOR

CAPACITOR

REMARKS	PARTS NAME	
NO MARK	ELECTROLYTIC CAPACITOR	▯
◇	TANTALUM CAPACITOR	
NO MARK	CERAMIC CAPACITOR	▯▯
◉	CERAMIC TUBULAR CAPACITOR	
◎	POLYESTER FILM CAPACITOR	
○	POLYSTYRENE FILM CAPACITOR	
ⓘ	MICA CAPACITOR	
ⓟ	POLYPROPYLENE FILM CAPACITOR	
◉	SEMICONDUCTIVE CERAMIC CAPACITOR	

NOTICE (model)
(J)····· JAPAN
(U)····· U.S.A
(C)····· CANADA
(R)····· GENERAL
(T)····· CHINA
(K)····· KOREA
(A)····· AUSTRALIA
(B)····· BRITISH
(G)····· EUROPE
(L)····· SINGAPORE
(E)····· SOUTH EUROPE
(V)····· TAIWAN
(F)····· RUSSIAN

★ All voltages are measured with a 10MΩ/V DC electronic voltmeter.
★ Components having special characteristics are marked ⚠ and must be replaced with parts having specifications equal to those originally installed.
★ Schematic diagram is subject to change without notice.

● 電圧は、内部抵抗10MΩの電圧計で測定したものです。
● ⚠印のある部品は、安全性確保部品を示しています。部品の交換が必要な場合、パーツリストに記載されている部品を使用してください。
● 本回路図は標準回路図です。改良のため予告なく変更することがございます。

D-VIDEO 6/10

No replacement part available.
サービス部品供給なし

No replacement part available.
サービス部品供給なし

No replacement part available.
サービス部品供給なし

No replacement part available.
サービス部品供給なし

RESISTOR

REMARKS	PARTS NAME
NO MARK	CARBON FILM RESISTOR (P=5)
☑	CARBON FILM RESISTOR (P=10)
△	METAL OXIDE FILM RESISTOR
▲	METAL FILM RESISTOR
⊠	METAL PLATE RESISTOR
◪	FIRE PROOF CARBON FILM RESISTOR
□	CEMENT MOLDED RESISTOR
⊘	SEMI VARIABLE RESISTOR
■	CHIP RESISTOR

CAPACITOR

REMARKS	PARTS NAME	
NO MARK	ELECTROLYTIC CAPACITOR	日
⊗	TANTALUM CAPACITOR	日
NO MARK	CERAMIC CAPACITOR	日
◉	CERAMIC TUBULAR CAPACITOR	日
◎	POLYESTER FILM CAPACITOR	日
○	POLYSTYRENE FILM CAPACITOR	日
Ⓘ	MICA CAPACITOR	日
Ⓟ	POLYPROPYLENE FILM CAPACITOR	日
●	SEMICONDUCTIVE CERAMIC CAPACITOR	日

NOTICE (model)
(J)····· JAPAN
(U)····· U.S.A
(C)····· CANADA
(R)····· GENERAL
(T)····· CHINA
(K)····· KOREA
(A)····· AUSTRALIA
(B)····· BRITISH
(G)····· EUROPE
(L)····· SINGAPORE
(E)····· SOUTH EUROPE
(V)····· TAIWAN
(F)····· RUSSIAN

IC718, 719, 721, 722, 755: R1172S331B-E2-F
CMOS-based positive-voltage regulator IC

Pin No.	Symbol	Description
1	VOUT	Output Pin of Voltage Regulator
2, 5	GND	Ground Pin
3	CE	Chip Enable Pin
4	NC	No Connection
6	VDD	Input Pin

IC720, 754: BD3508EKN-E2
1-channel series regulator driver IC

IC745: R1172S121D-E2-F
Voltage regulator

Pin No.	Symbol	Description
1	VOUT	Output Pin of Voltage Regulator
2, 5	GND	Ground Pin
3	CE	Chip Enable Pin
4	NC	No Connection
6	VDD	Input Pin

IC741, 743, 744, 749, 750: R1172S181B-E2-F
Voltage regulator

Pin No.	Symbol	Description
1	VOUT	Output Pin of Voltage Regulator
2, 5	GND	Ground Pin
3	CE	Chip Enable Pin
4	NC	No Connection
6	VDD	Input Pin

IC740: M12L64164A-5TG
1M x 16-bit x 4 banks synchronous DRAM


★ All voltages are measured with a 10MΩ/V DC electronic voltmeter.
★ Components having special characteristics are marked ! and must be replaced with parts having specifications equal to those originally installed.
★ Schematic diagram is subject to change without notice.

● 電圧は、内部抵抗10MΩの電圧計で測定したものです。
● !印のある部品は、安全性確保部品を示しています。部品の交換が必要な場合、パーツリストに記載されている部品を使用してください。
● 本回路図は標準回路図です。改良のため予告なく変更することがございます。

D-VIDEO 7/10

Destination Part List

sXX	LOC	J	U
s100	CB100	WA90070 07FMN-SMT-A-TF(I	X
s101	IC100	X9370D0 MN103SFD7GYAC	X
s102	XL100	WM22790 10MHZ	X
s105	D1000	V237660 RB500V-40	X
s106	L1001	V244990 BLM21PG600SN1D	X
s107	C1001	WG8BB30 10/6.3	X
s108	C1008 C1002	US12610 1/10	X
s109	C1011 C1005 C1012 C1009 C1010 C1006	US63510 0.1/16	X
s110	C1003 C1007	US06410 0.01(B)	X
s111	J1002 J1000	RD3500 0	X
s112	R1029 R1030 R1019 R1018 R1047 R1011 R1001 R1050 R1051 R1002	RD35422 22	X
s113	R1013 R1356 R1004 R1010 R1009 R1005 R1355 R1000	RD35647 4.7K	X
s114	R1026 R1034 R1033 R1028 R1027 R1007 R1032 R1012 R1017 R1031 R1014 R1035 R1020 R1036 R1038 R1049 R1024 R1025 R1045 R1044 R1043 R1039 R1040 R1041 R1037 R1022	RD35747 47K	X
s115	R1006	RF45727 27K	X
s116	R1003	RF45856 560K	X
s117	D1009	WE67480 AVRL161A1R1NTB	X
s118	Q1004 Q1005	WH44500 3LN01C-TB-E	X




RESISTOR	
REMARKS	PARTS NAME
NO MARK	CARBON FILM RESISTOR (P=5)
☑	CARBON FILM RESISTOR (P=10)
△	METAL OXIDE FILM RESISTOR
▲	METAL FILM RESISTOR
☒	METAL PLATE RESISTOR
▨	FIRE PROOF CARBON FILM RESISTOR
□	CEMENT MOLDED RESISTOR
⊘	SEMI VARIABLE RESISTOR
■	CHIP RESISTOR

CAPACITOR		
REMARKS	PARTS NAME	
NO MARK	ELECTROLYTIC CAPACITOR	‖
⊗	TANTALUM CAPACITOR	‖
NO MARK	CERAMIC CAPACITOR	=
◉	CERAMIC TUBULAR CAPACITOR	=
◎	POLYESTER FILM CAPACITOR	=
○	POLYSTYRENE FILM CAPACITOR	=
ⓘ	MICA CAPACITOR	=
⊛	POLYPROPYLENE FILM CAPACITOR	=
◉	SEMICONDUCTIVE CERAMIC CAPACITOR	=

NOTICE (model)
(J)····· JAPAN
(U)····· U.S.A
(C)····· CANADA
(R)····· GENERAL
(T)····· CHINA
(K)····· KOREA
(A)····· AUSTRALIA
(B)····· BRITISH
(G)····· EUROPE
(L)····· SINGAPORE
(E)····· SOUTH EUROPE
(V)····· TAIWAN
(F)····· RUSSIAN

IC100: MN103SFD7G
Microprocessor



DVIDEO-7

★ All voltages are measured with a 10MΩ/V DC electronic voltmeter.
★ Components having special characteristics are marked ⚠ and must be replaced with parts having specifications equal to those originally installed.
★ Schematic diagram is subject to change without notice.

● 電圧は、内部抵抗10MΩの電圧計で測定したものです。
● ⚠印のある部品は、安全性確保部品を示しています。部品の交換が必要な場合、パーツリストに記載されている部品を使用してください。
● 本回路図は標準回路図です。改良のため予告なく変更することがございます。

D-VIDEO 8/10

No replacement part available.
サービス部品供給なし

(for factory)

DEBUG

JTAG

SRAM

SDRAM

VNP2

UART

SPI

I2C

USB

SD

Ether

Audio Codec

SDIO

XB14340 IC105 YTD-446CZ

IC103 S29GL128P90TFCR20 YA121A0

No replacement part available.
サービス部品供給なし

No replacement part available.
サービス部品供給なし

DVIDEO 008

RESISTOR

REMARKS	PARTS NAME
NO MARK	CARBON FILM RESISTOR (P=5)
☑	CARBON FILM RESISTOR (P=10)
△	METAL OXIDE FILM RESISTOR
▲	METAL FILM RESISTOR
⊠	METAL PLATE RESISTOR
▣	FIRE PROOF CARBON FILM RESISTOR
□	CEMENT MOLDED RESISTOR
⊘	SEMI VARIABLE RESISTOR
▩	CHIP RESISTOR

NOTICE (model)


(J)····· JAPAN
(U)····· U.S.A
(C)····· CANADA
(R)····· GENERAL
(T)····· CHINA
(K)····· KOREA
(A)····· AUSTRALIA
(B)····· BRITISH
(E)····· EUROPE
(L)····· SINGAPORE
(E)····· SOUTH EUROPE
(V)····· TAIWAN
(F)····· RUSSIAN

CAPACITOR

REMARKS	PARTS NAME	
NO MARK	ELECTROLYTIC CAPACITOR	⊟
⊘	TANTALUM CAPACITOR	
NO MARK	CERAMIC CAPACITOR	⊣⊢
◉	CERAMIC TUBULAR CAPACITOR	
◎	POLYESTER FILM CAPACITOR	
ⓨ	POLYSTYRENE FILM CAPACITOR	
Ⓜ	MICA CAPACITOR	
Ⓟ	POLYPROPYLENE FILM CAPACITOR	
◉	SEMICONDUCTIVE CERAMIC CAPACITOR	
Ⓢ	POLYPHENYLENE SULFIDE FILM CAPACITOR	


Page 168 F2
to FL (1)_CB957

IC101: R1172S331B-E2-F
CMOS-based positive-voltage regulator IC




Pin No.	Symbol	Description
1	VOUT	Output Pin of Voltage Regulator
2, 5	GND	Ground Pin
3	CE	Chip Enable Pin
4	NC	No Connection
6	VDD	Input Pin

IC102: R1172H121D-T1-F
CMOS-based positive-voltage regulator IC




Pin No.	Symbol	Description
1	CE	Chip Enable Pin
2	GND	Ground Pin
3	NC	No Connection
4	VDD	Input Pin
5	VOUT	Output Pin of Voltage Regulator


IC106: TC74VHCT245AFT
Octal bus transceiver




IC107: TC7WH08FK
Dual 2-input AND gate



IC109: TC7WH14FK
Triple schmitt inverter




IC110: R3112N251A-TR
Voltage regulator




Pin No.	Symbol	Description
1	OUT	Output Pin ("L" at Detect, "H" at Released)
2	VDD	Input and power source for device itself
3	GND	Ground Pin
4	NC	No Connection
5	CD	Pin for external capacitor for setting output delay


IC104, 125: K4S281632K-UC75000
128 M synchronous DRAM




IC103: S29GL128P90TFCR20
128 M-bits CMOS 3.0 volt-only page mode flash memory



IC105: YTD446-CZ
Main microprocessor
Network audio equipment, and an equipment with network function




IC122: R1154H050B-T1-F
Voltage regulator



Pin No.	Symbol	Description
1	VOUT	Voltage Regulator Output Pin
2	GND	Ground Pin
3	CE	Chip Enable Pin
4	NC	No Connection
5	VDD	Input Pin


IC111: TC7SH125FU
Bus buffer



★ All voltages are measured with a 10MΩ/V DC electronic voltmeter.
★ Components having special characteristics are marked ! and must be replaced with parts having specifications equal to those originally installed.
★ Schematic diagram is subject to change without notice.

● 電圧は、内部抵抗10MΩの電圧計で測定したものです。
● !印のある部品は、安全性確保部品を示しています。部品の交換が必要な場合、パーツリストに記載されている部品を使用してください。
● 本回路図は標準回路図です。改良のため予告なく変更することがございます。


D-VIDEO 9/10




RESISTOR	
REMARKS	PARTS NAME
NO MARK	CARBON FILM RESISTOR (P=5)
⊠	CARBON FILM RESISTOR (P=10)
△	METAL OXIDE FILM RESISTOR
⚠	METAL FILM RESISTOR
⊠	METAL PLATE RESISTOR
▨	FIRE PROOF CARBON FILM RESISTOR
□	CEMENT MOLDED RESISTOR
⊘	SEMI VARIABLE RESISTOR
▤	CHIP RESISTOR

CAPACITOR		
REMARKS	PARTS NAME	
NO MARK	ELECTROLYTIC CAPACITOR	H
⊗	TANTALUM CAPACITOR	
NO MARK	CERAMIC CAPACITOR	H
⦿	CERAMIC TUBULAR CAPACITOR	
◎	POLYESTER FILM CAPACITOR	
○	POLYSTYRENE FILM CAPACITOR	
Ⓘ	MICA CAPACITOR	
Ⓟ	POLYPROPYLENE FILM CAPACITOR	
◉	SEMICONDUCTIVE CERAMIC CAPACITOR	
Ⓢ	POLYPHENYLENE SULFIDE FILM CAPACITOR	

IC112: NJM2867F3-05
Low dropout voltage regulator



IC113, 124: M24256-BRDW6TP
512k-bit and 256l-bit serial I²C bus EEPROM with three chip enable lines



IC115: TC74VHCT08AFT
Quad 2-input AND gate




IC121: TC7SH125FU
Bus buffer


★ All voltages are measured with a 10MΩ/V DC electronic voltmeter.
★ Components having special characteristics are marked ⚠ and must be replaced with parts having specifications equal to those originally installed.
★ Schematic diagram is subject to change without notice.


● 電圧は、内部抵抗10MΩの電圧計で測定したものです。
● ⚠印のある部品は、安全性確保部品を示しています。部品の交換が必要な場合、パーツリストに記載されている部品を使用してください。
● 本回路図は標準回路図です。改良のため予告なく変更することがございます。

D-VIDEO 10/10


J1064 0
J1065 0
J1066 0
J1067 0
FG3
ハナビラシド
DGND
J1068 0
J1069 0
J1070 0
J1071 0
FG4
ハナビラシド
DGND
no_use
J1060
J1061
no_use
J1057 0
J1058 0
HDMI Frame GND
FG2
ハナビラシド
DGND
PN100
PN101
Style Pin
DGND
TP1155
TP1156
TP1157
TP1171
TP1158
TP1159
TP1160
TP1161
TP1162
+6.5V
+2.8H
+2.8V
+2.8ABT
+4.3H
+4.3V
+4.3D
+2.0D
+2.0V
BLM21PG600SN1D
L1011
L1012
L1013
L1014
L1015
L1016
L1017
L1018
C1247 0.1/16
C1248 0.1/16
C1124 0.1/16
C1126 0.1/16
C1129 0.1/16
C1131 0.1/16
C1133 0.1/16
C1135 0.1/16
C1137 10/10
C1140 0.1/16
C1148 0.1/16
C1149 0.1/16
C1150 0.1/16
C1151 0.1/16
C1152 0.1/16
C1153 0.1/16
C1154 0.1/16
C1155 0.1/16
C1156 0.1/16
C1157 0.1/16
C1158 0.1/16
C1159 0.1/16
C1160 0.1/16
C1161 0.1/16
C1162 0.1/16
C1163 0.1/16
C1164 0.1/16
C1165 0.1/16
C1166 0.1/16
C1167 0.1/16

FL 1/2





Interchangeable Parts at Manufacture-Stage

Mark	Reference Parts Number	Parts Name
★1	D9017-9021-9026 9901-9904	1SS355 MA2J111GGL KDS160-RTK/P
★2	D9010-9011	DTC114EKA KRC102S-RTK/P
★3	D9902-9904	DTC144EKA KRC104S-RTK/P
★4	D9001-9009	KTC3B75S-Y-GR-RTK/P 2SC2412K(Q/R/S)
★5		

NOTICE (model)
(J)····· JAPAN
(U)····· U.S.A
(C)····· CANADA
(R)····· GENERAL
(T)····· CHINA
(K)····· KOREA
(A)····· AUSTRALIA
(B)····· BRITISH
(G)····· EUROPE
(L)····· SINGAPORE
(E)····· SOUTH EUROPE
(V)····· TAIWAN
(F)····· RUSSIAN

RESISTOR

REMARKS	PARTS NAME
NO MARK	CARBON FILM RESISTOR (P=5)
⊘	CARBON FILM RESISTOR (P=10)
△	METAL OXIDE FILM RESISTOR
⚠	METAL FILM RESISTOR
⊠	METAL PLATE RESISTOR
◪	FIRE PROOF CARBON FILM RESISTOR
□	CEMENT MOLDED RESISTOR
⊘	SEMI VARIABLE RESISTOR
■	CHIP RESISTOR

CAPACITOR

REMARKS	PARTS NAME	
NO MARK	ELECTROLYTIC CAPACITOR	⫼
⊗	TANTALUM CAPACITOR	⫼
NO MARK	CERAMIC CAPACITOR	⫼
◉	CERAMIC TUBULAR CAPACITOR	⫼
◎	POLYESTER FILM CAPACITOR	⫼
○	POLYSTYRENE FILM CAPACITOR	⫼
Ⓘ	MICA CAPACITOR	⫼
Ⓟ	POLYPROPYLENE FILM CAPACITOR	⫼
◉	SEMICONDUCTIVE CERAMIC CAPACITOR	⫼
Ⓢ	POLYPHENYLENE SULFIDE FILM CAPACITOR	⫼

RX-V3900 (U, C, R, T, K, A, B, G, E, L models)
Key input(A-D) pull-up resistance 10 k-ohms

Ohm *	0	+1.2k	+1.2k	+1.8k	+2.7k	+3.3k	+4.7k	+8.2k	+18.0k	+47.0k
V	-0.00	-0.75	-1.22	-1.76	-2.28	-2.75	-3.24	-3.75	-4.25	-4.72
KEY0 (124pin/AN156)	INFO	ZONE CONTROLS	CATEGORY / BAND	STEREO/ MONO	SEARCH MODE	MEMORY	PRESET/ TUNING >	PRESET/ TUNING <	ZONE ON/OFF ZONE2	ZONE ON/OFF ZONE3
KEY1 (123pin/AN157)	STRAIGHT / EFFECT	ENTER	TONE CONTROL	MENU	AUDIO SELECT / REC OUT	PURE DIRECT	–	–	–	–


* KEY0: R9022 to R9051 of FL (1) P.C.B., KEY1: R9017 to R9021 of FL (1) P.C.B. / R8004 of OPERATION (2) P.C.B.

DSP-AX3900 (J model)
Key input(A-D) pull-up resistance 10 k-ohms


Ohm *	0	+1.2k	+1.2k	+1.8k	+2.7k	+3.3k	+4.7k	+8.2k	+18.0k	+47.0k
V	-0.00	-0.26	-0.75	-1.22	-1.76	-2.28	-2.75	-3.24	-3.75	-4.25	-4.72
KEY0 (124pin/AN156)	INFO	–	BAND	STEREO/MONO	SEARCH MODE	MEMORY	PRESET/ TUNING >	PRESET/ TUNING <	–	–
KEY1 (123pin/AN157)	STRAIGHT / EFFECT	ENTER	TONE CONTROL	MENU	AUDIO SELECT	PURE DIRECT	–	–	–	–

* KEY0: R9022 to R9051 of FL (1) P.C.B., KEY1: R9017 to R9021 of FL (1) P.C.B. / R8004 of OPERATION (2) P.C.B.

IC991: ADM222ARZ
High speed RS-232 line drivers/receivers




IC901, 902: PT6302LQ-008
VFD driver/controller IC with character RAM




★ All voltages are measured with a 10MΩ/V DC electronic voltmeter.
★ Components having special characteristics are marked ⚠ and must be replaced with parts having specifications equal to those originally installed.
★ Schematic diagram is subject to change without notice.

● 電圧は、内部抵抗10MΩの電圧計で測定したものです。
● ⚠印のある部品は、安全性確保部品を示しています。部品の交換が必要な場合、パーツリストに記載されている部品を使用してください。
● 本回路図は標準回路図です。改良のため予告なく変更することがございます。


FL 2/2



IC951: PCM1781DBQR
Audio digital-to-analog converter



IC952: NJM4565M
Dual operational amplifier



RESISTOR

REMARKS	PARTS NAME
NO MARK	CARBON FILM RESISTOR (P=5)
	CARBON FILM RESISTOR (P=10)
	METAL OXIDE FILM RESISTOR
	METAL FILM RESISTOR
	METAL PLATE RESISTOR
	FIRE PROOF CARBON FILM RESISTOR
	CEMENT MOLDED RESISTOR
	SEMI VARIABLE RESISTOR
	CHIP RESISTOR

CAPACITOR

REMARKS	PARTS NAME	
NO MARK	ELECTROLYTIC CAPACITOR	‖
	TANTALUM CAPACITOR	‖
NO MARK	CERAMIC CAPACITOR	‖
	POLYESTER FILM CAPACITOR	‖
	POLYSTYRENE FILM CAPACITOR	‖
	MICA CAPACITOR	‖
	POLYPROPYLENE FILM CAPACITOR	‖
	SEMICONDUCTIVE CERAMIC CAPACITOR	‖


[部品ID]
*9501～9800
**951～980
(TP2001～2300)


NOTICE (model)
(J)····· JAPAN
(U)····· U.S.A.
(C)····· CANADA
(R)····· GENERAL
(T)····· CHINA
(K)····· KOREA
(A)····· AUSTRALIA
(B)····· BRITISH
(G)····· EUROPE
(L)····· SINGAPORE
(E)····· SOUTH EUROPE
(V)····· TAIWAN
(F)····· RUSSIAN

★ All voltages are measured with a 10MΩ/V DC electronic voltmeter.
★ Components having special characteristics are marked ⚠ and must be replaced with parts having specifications equal to those originally installed.
★ Schematic diagram is subject to change without notice.

● 電圧は、内部抵抗10MΩの電圧計で測定したものです。
● ⚠印のある部品は、安全性確保部品を示しています。部品の交換が必要な場合、パーツリストに記載されている部品を使用してください。
● 本回路図は標準回路図です。改良のため予告なく変更することがございます。

CONNECT





Destination Part List

sXX	LOC	U	C
s1	CB901	LB91903 XHL	X
s2	R908 R924	RD35647 4.7K	X
s3	R925	RD35633 3.3K	X
s4	R912 R923	RD35668 6.8K	X
s5	C914 C917	US06222 220P(SL)	X
s6	C912 C919 C913 C918	UM39710 10/16	X
s7	IC901	X7378A0 NJM4565M	X
s8	C920	US13510 0.1/16	X
s9	R921 R916	RD35810 100K	X
s10	W901	WQ08110 SAN-YDH	X
s11	ST900	V404050	X
s13	D901 D900	VT33290 1SS355	X
s14	C907 C905 C910 C903	US06210 100P(SL)	X
s15	Q900	WH44500 3LN01C-TB-E	X
s16	C901 C921	US13510 0.1/16	X
s17	C900	US06410 0.01(B)	X
s18	C916 C904	UM39747 47/16	X
s19	L901	WG53720 PZ2012U600-3R0T	X
s21	C975	US13510 0.1/16	X
s22	L902	WG53720 PZ2012U600-3R0T	X
s23	R909	RD35410 10	X
s24	R919	RD35633 3.3K	X
s25	CB903	VU44380 15PSL-JE	X
s27	R900	RD35000 0	X
s28	D904	VU99260 MA8051-M	X
s29	PN901	V963750 -	X
s30	R915	RD35000 0	X
s31	R914 R922	RD35810 100K	X
s32	R920 R917	RD35610 1K	X
s33	R905	RD35610 1K	X
s34	C902	UR21922 2200/6.3	X
NA No.		WP15650	WP15660
NC No.		X9907	

NOTICE (model)

(J)····· JAPAN
(U)····· U.S.A
(C)····· CANADA
(R)····· GENERAL
(T)····· CHINA
(K)····· KOREA
(A)····· AUSTRALIA
(B)····· BRITISH
(G)····· EUROPE
(L)····· SINGAPORE
(E)····· SOUTH EUROPE
(V)····· TAIWAN
(F)····· RUSSIAN

Interchangeable Parts at Manufacture-Stage

Mark	Reference Parts Number	Parts Name
&1	D900. 901. 953. 954	1SS355 MA2J1110GL KDS160-RTK/P


RESISTOR

REMARKS	PARTS NAME
NO MARK	CARBON FILM RESISTOR (P=5)
⊘	CARBON FILM RESISTOR (P=10)
△	METAL OXIDE FILM RESISTOR
⊿	METAL FILM RESISTOR
⊠	METAL PLATE RESISTOR
⊘	FIRE PROOF CARBON FILM RESISTOR
□	CEMENT MOLDED RESISTOR
⊘	SEMI VARIABLE RESISTOR
▤	CHIP RESISTOR


CAPACITOR

REMARKS	PARTS NAME	
NO MARK	ELECTROLYTIC CAPACITOR	⫫
⊗	TANTALUM CAPACITOR	
NO MARK	CERAMIC CAPACITOR	⫪
◉	CERAMIC TUBULAR CAPACITOR	
◎	POLYESTER FILM CAPACITOR	
○	POLYSTYRENE FILM CAPACITOR	
ⓘ	MICA CAPACITOR	
Ⓟ	POLYPROPYLENE FILM CAPACITOR	
ⓒ	SEMICONDUCTIVE CERAMIC CAPACITOR	
Ⓢ	POLYPHENYLENE SULFIDE FILM CAPACITOR	

IC901, 950: NJM4565M
Dual operational amplifier



IC951: TC7SET32FU
2-input OR gate




★ All voltages are measured with a 10MΩ/V DC electronic voltmeter.
★ Components having special characteristics are marked ! and must be replaced with parts having specifications equal to those originally installed.
★ Schematic diagram is subject to change without notice.

● 電圧は、内部抵抗10MΩの電圧計で測定したものです。
● ! 印のある部品は、安全性確保部品を示しています。部品の交換が必要な場合、パーツリストに記載されている部品を使用してください。
● 本回路図は標準回路図です。改良のため予告なく変更することがございます。

DCCNVT

Page 166 J3 to D-VIDEO_CB108
Page 166 J3 to D-VIDEO_CB109
Page 166 J2 to D-VIDEO_CB107

TO PCB-DVIDEO



Page 154 F6 to POWER (3)_CB14

DCCNVT (1)

DCCNVT 001

REF : 71 - 80, 701 - 800


RESISTOR

REMARKS	PARTS NAME
NO MARK	CARBON FILM RESISTOR (P=5)
▨	CARBON FILM RESISTOR (P=10)
△	METAL OXIDE FILM RESISTOR
▲	METAL FILM RESISTOR
⊠	METAL PLATE RESISTOR
▨	FIRE PROOF CARBON FILM RESISTOR
□	CEMENT MOLDED RESISTOR
⊘	SEMI VARIABLE RESISTOR
■	CHIP RESISTOR

CAPACITOR

REMARKS	PARTS NAME	
NO MARK	ELECTROLYTIC CAPACITOR	⫼
⊗	TANTALUM CAPACITOR	
NO MARK	CERAMIC CAPACITOR	⫼
◉	CERAMIC TUBULAR CAPACITOR	
Ⓜ	POLYESTER FILM CAPACITOR	
Ⓢ	POLYSTYRENE FILM CAPACITOR	
Ⓜ	MICA CAPACITOR	
Ⓟ	POLYPROPYLENE FILM CAPACITOR	
ⓒ	SEMICONDUCTIVE CERAMIC CAPACITOR	
Ⓢ	POLYPHENYLENE SULFIDE FILM CAPACITOR	

NOTICE (model)
(J)····· JAPAN
(U)····· U.S.A
(C)····· CANADA
(R)····· GENERAL
(T)····· CHINA
(K)····· KOREA
(A)····· AUSTRALIA
(B)····· BRITISH
(G)····· EUROPE
(L)····· SINGAPORE
(E)····· SOUTH EUROPE
(V)····· TAIWAN
(F)····· RUSSIAN




Page 166 J7 to D-VIDEO_CB112


DCCNVT 002

Lo:60-66 600-669

IC71, 74: BD9011EKN-E2
Dual synchronous DC/DC converter controller



IC72: TC7SZ02FU
2-input NOR gate



A	B	Y
L	L	H
L	H	L
H	L	L
H	H	L

★ All voltages are measured with a 10MΩ/V DC electronic voltmeter.
★ Components having special characteristics are marked ⚠ and must be replaced with parts having specifications equal to those originally installed.
★ Schematic diagram is subject to change without notice.

● 電圧は、内部抵抗10MΩの電圧計で測定したものです。
● ⚠印のある部品は、安全性確保部品を示しています。部品の交換が必要な場合、パーツリストに記載されている部品を使用してください。
● 本回路図は標準回路図です。改良のため予告なく変更することがございます。

■ REPLACEMENT PARTS LIST

• ELECTRICAL COMPONENT PARTS

WARNING

- Components having special characteristics are marked ⚠ and must be replaced with parts having specifications equal to those originally installed.
- The chip resistor is not supplied as a replacement part.
  * When a chip resistor is necessary, use the following part.
    AAX60720: CHIP RESISTOR SAMPLE BOOK
- ⚠印のある部分は、安全確保部品を示しています。部品の交換が必要な場合、パーツリストに記載されている部品を使用してください。
- チップ抵抗はサービス部品として供給しません。
  ※ チップ抵抗が必要な場合は、下記の部品をご利用ください。
  AAX60720：CHIP RESISTOR SAMPLE BOOK
- 部品価格ランクは、予告なく変更することがあります。

ABBREVIATIONS IN THIS LIST ARE AS FOLLOWS:

C.A.EL.CHP	: CHIP ALUMI.ELECTROLYTIC CAP
C.CE	: CERAMIC CAP
C.CE.ARRAY	: CERAMIC CAP ARRAY
C.CE.CHP	: CHIP CERAMIC CAP
C.CE.ML	: MULTILAYER CERAMIC CAP
C.CE.M.CHP	: CHIP MULTILAYER CERAMIC CAP
C.CE.SAFTY	: RECOGNIZED CERAMIC CAP
C.CE.TUBLR	: CERAMIC TUBULAR CAP
C.CE.SMI	: SEMI CONDUCTIVE CERAMIC CAP
C.EL	: ELECTROLYTIC CAP
C.MICA	: MICA CAP
C.ML.FLM	: MULTILAYER FILM CAP
C.MP	: METALLIZED PAPER CAP
C.MYLAR	: MYLAR FILM CAP
C.MYLAR.ML	: MULTILAYER MYLAR FILM CAP
C.PAPER	: PAPER CAPACITOR
C.PLS	: POLYSTYRENE FILM CAP
C.POL	: POLYESTER FILM CAP
C.POLY	: POLYETHYLENE FILM CAP
C.PP	: POLYPROPYLENE FILM CAP
C.TNTL	: TANTALUM CAP
C.TNTL.CHP	: CHIP TANTALUM CAP
C.TRIM	: TRIMMER CAP
CN	: CONNECTOR
CN.BS.PIN	: CONNECTOR,BASE PIN
CN.CANNON	: CONNECTOR,CANNON
CN.DIN	: CONNECTOR,DIN
CN.FLAT	: CONNECTOR,FLAT CABLE
CN.POST	: CONNECTOR,BASE POST
COIL.MX.AM	: COIL,AM MIX
COIL.AT.FM	: COIL,FM ANTENNA
COIL.DT.FM	: COIL,FM DETECT
COIL.MX.FM	: COIL,FM MIX
COIL,OUTPT	: OUTPUT COIL
DIOD.ARRAY	: DIODE ARRAY
DIODE.BRG	: DIODE BRIDGE
DIODE.CHP	: CHIP DIODE
DIODE.VAR	: VARACTOR DIODE
DIOD.Z.CHP	: CHIP ZENER DIODE
DIODE.ZENR	: ZENER DIODE
DSCR.CE	: CERAMIC DISCRIMINATOR
FER.BEAD	: FERRITE BEADS
FER.CORE	: FERRITE CORE
FET.CHP	: CHIP FET
FL.DSPLY	: FLUORESCENT DISPLAY
FLTR.CE	: CERAMIC FILTER
FLTR.COMB	: COMB FILTER MODULE
FLTR.LC.RF	: LC FILTER,EMI
GND.MTL	: GROUND PLATE
GND.TERM	: GROUND TERMINAL
HOLDER.FUS	: FUSE HOLDER
IC.PRTCT	: IC PROTECTOR
JUMPER.CN	: JUMPER CONNECTOR
JUMPER.TST	: JUMPER,TEST POINT
L.DTCT	: LIGHT DETECTING MODULE
L.EMIT	: LIGHT EMITTING MODULE
LED.DSPLY	: LED DISPLAY
LED.INFRD	: LED,INFRARED
MODUL.RF	: MODULATOR,RF
PHOT.CPL	: PHOTO COUPLER
PHOT.INTR	: PHOTO INTERRUPTER
PHOT.RFLCT	: PHOTO REFLECTOR
PIN.TEST	: PIN,TEST POINT
PLST.RIVET	: PLASTIC RIVET
R.ARRAY	: RESISTOR ARRAY
R.CAR.	: CARBON RESISTOR
R.CAR.CHP	: CHIP RESISTOR
R.CAR.FP	: FLAME PROOF CARBON RESISTOR
R.FUS	: FUSABLE RESISTOR
R.MTL.CHP	: CHIP METAL FILM RESISTOR
R.MTL.FLM	: METAL FILM RESISTOR
R.MTL.OXD	: METAL OXIDE FILM RESISTOR
R.MTL.PLAT	: METAL PLATE RESISTOR
RSNR.CE	: CERAMIC RESONATOR
RSNR.CRYS	: CRYSTAL RESONATOR
R.TW.CEM	: TWIN CEMENT FIXED RESISTOR
R.CEMENT	: CEMENT RESISTOR
SCR.BND.HD	: BIND HEAD B-TIGHT SCREW
SCR.BW.HD	: BW HEAD TAPPING SCREW
SCR.CUP	: CUP TIGHT SCREW
SCR.TERM	: SCREW TERMINAL
SCR.TR	: SCREW,TRANSISTOR
SUPRT.PCB	: SUPPORT,P.C.B.
SURG.PRTCT	: SURGE PROTECTOR
SW.TACT	: TACT SWITCH
SW.LEAF	: LEAF SWITCH
SW.LEVER	: LEVER SWITCH
SW.MICRO	: MICRO SWITCH
SW.PUSH	: PUSH SWITCH
SW.RT.ENC	: ROTARY ENCODER
SW.RT.MTR	: ROTARY SWITCH WITH MOTOR
SW.RT	: ROTARY SWITCH
SW.SLIDE	: SLIDE SWITCH
TERM.SP	: SPEAKER TERMINAL
TERM.WRAP	: WRAPPING TERMINAL
THRMST.CHP	: CHIP THERMISTOR
TR.CHP	: CHIP TRANSISTOR
TR.DGT	: DIGITAL TRANSISTOR
TR.DGT.CHP	: CHIP DIGITAL TRANSISTOR
TRANS	: TRANSFORMER
TRANS.PULS	: PULSE TRANSFORMER
TRANS.PWR	: POWER TRANSFORMER ASS'Y
TUNER.AM	: TUNER PACK,AM
TUNER.FM	: TUNER PACK,FM
TUNER.PK	: FRONT-ENDTUNER PACK
VR	: ROTARY POTENTIOMETER
VR.MTR	: POTENTIOMETER WITH MOTOR
VR.SW	: POTENTIOMETER WITH ROTARY SW
VR.SLIDE	: SLIDE POTENTIOMETER
VR.TRIM	: TRIMMER POTENTIOMETER

P.C.B. DSP

	Ref No.	Part No.	Description	Remarks	Markets	部 品 名	ﾗﾝｸ
*		WQ133200	P. C. B. DSP		J	ＰＣＢ　ＤＳＰ	
*		WQ133300	P. C. B. DSP		UC	ＰＣＢ　ＤＳＰ	
*		WQ133400	P. C. B. DSP		RTKABGEL	ＰＣＢ　ＤＳＰ	
*	CB502	WJ458700	CN. XM 4P, CAM-D96		UC	ＸＭコネクタ	
	CB503	V9356900	CN. JE 19P SE			ＪＥコネクタープラグ	
	CB504	VQ047100	CN. BS. PIN 7P			ＦＦＣコネクター	01
	CB505	VU443800	CN. JE 15P SE			ＪＥコネクタープラグ	01
	CB530	V8809800	CN. JE 9P SE			ＪＥコネクタープラグ	01
	CB536	V8875300	CN. JE 13P SE			ＪＥコネクタープラグ	01
	CB560	LB918020	CN. BS. PIN 2P			ベース付ポスト	01
	CB561	VQ048000	CN. BS. PIN 31P			ＦＦＣコネクター	02
	C5001-5003	US061220	C. CE. CHP 22pF 50V B			チップセラコン	01
	C5004-5009	US135100	C. CE. CHP 0. 1uF 16V			チップセラコン	01
	C5010-5011	US135100	C. CE. CHP 0. 1uF 16V		UC	チップセラコン	01
	C5012-5014	US135100	C. CE. CHP 0. 1uF 16V			チップセラコン	01
	C5015-5017	UR237220	C. EL 22uF 16V			ケミコン	
	C5018	US064100	C. CE. CHP 0. 01uF 50V B			チップセラコン	01
	C5019	US063100	C. CE. CHP 1000pF 50V B		UC	チップセラコン	01
	C5022	US135100	C. CE. CHP 0. 1uF 16V		UC	チップセラコン	01
	C5024	US135100	C. CE. CHP 0. 1uF 16V		UC	チップセラコン	01
	C5025	UR237470	C. EL 47uF 16V			ケミコン	01
	C5027	US064100	C. CE. CHP 0. 01uF 50V B			チップセラコン	01
	C5028	US135100	C. CE. CHP 0. 1uF 16V			チップセラコン	01
	C5030	US064100	C. CE. CHP 0. 01uF 50V B			チップセラコン	01
	C5031	US135100	C. CE. CHP 0. 1uF 16V			チップセラコン	01
	C5032	US062220	C. CE. CHP 220pF 50V B			チップセラコン	01
	C5033	UR237220	C. EL 22uF 16V			ケミコン	
	C5034	US062220	C. CE. CHP 220pF 50V B			チップセラコン	01
	C5035	US135100	C. CE. CHP 0. 1uF 16V		UC	チップセラコン	01
	C5036	UR237470	C. EL 47uF 16V			ケミコン	01
	C5037	US135100	C. CE. CHP 0. 1uF 16V			チップセラコン	01
	C5038	US062220	C. CE. CHP 220pF 50V B			チップセラコン	01
	C5039	US135100	C. CE. CHP 0. 1uF 16V			チップセラコン	01
	C5040	US062220	C. CE. CHP 220pF 50V B			チップセラコン	01
	C5041-5043	US135100	C. CE. CHP 0. 1uF 16V		UC	チップセラコン	01
	C5044	UR837470	C. EL 47uF 16V		UC	ケミコン	01
	C5045	US135100	C. CE. CHP 0. 1uF 16V		UC	チップセラコン	01
	C5046	UR238100	C. EL 100uF 16V			ケミコン	
	C5047	US060800	C. CE. CHP 8pF 50V B		UC	チップセラコン	01
	C5048-5049	US135100	C. CE. CHP 0. 1uF 16V			チップセラコン	01
	C5050	VE326000	C. MYLAR 0. 1uF 50V			マイラーコン	01
	C5051	VE326600	C. MYLAR 0. 33uF 50V			マイラーコン	01
	C5052	WJ605400	C. MYLAR 0. 022uF 50V J			マイラーコン	01
	C5053-5055	US135100	C. CE. CHP 0. 1uF 16V			チップセラコン	01
	C5056	US060800	C. CE. CHP 8pF 50V B		UC	チップセラコン	01
	C5057-5058	UR267100	C. EL 10uF 50V			ケミコン	
	C5059	US062100	C. CE. CHP 100pF 50V B			チップセラコン	01
	C5060	UU267470	C. EL 47uF 50V			ケミコン　ＦＷ	01
	C5061	US061470	C. CE. CHP 47pF 50V B			チップセラコン	01
	C5062	UU267470	C. EL 47uF 50V			ケミコン　ＦＷ	01
	C5063-5065	US135100	C. CE. CHP 0. 1uF 16V			チップセラコン	01
	C5066	US064100	C. CE. CHP 0. 01uF 50V B			チップセラコン	01

＊New Parts　＊新規部品

P.C.B. DSP

	Ref No.	Part No.	Description		Remarks	Markets	部 品 名	ﾗﾝｸ
	C5067	UR237470	C.EL	47uF 16V			ケミコン	01
	C5068-5069	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C5070	US062100	C.CE.CHP	100pF 50V B			チップセラコン	01
	C5071	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C5072-5073	US062100	C.CE.CHP	100pF 50V B			チップセラコン	01
	C5074-5075	US062220	C.CE.CHP	220pF 50V B			チップセラコン	01
	C5076	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C5077	US062100	C.CE.CHP	100pF 50V B			チップセラコン	01
*	C5078-5079	WP172700	C.MYLAR	390pF 50V			マイラーコン	
	C5080-5081	UR267100	C.EL	10uF 50V			ケミコン	
	C5082-5083	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C5084-5085	UR267100	C.EL	10uF 50V			ケミコン	
	C5086	UR237100	C.EL	10uF 16V			ケミコン	
	C5087	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C5092	US063100	C.CE.CHP	1000pF 50V B		UC	チップセラコン	01
	C5093	WD758300	C.CE.CHP	10uF 10V			チップセラコン	01
	C5094	US064100	C.CE.CHP	0.01uF 50V B			チップセラコン	01
	C5095	US035100	C.CE.CHP	0.1uF 16V B			チップセラコン	01
	C5098	US060500	C.CE.CHP	5pF 50V B			チップセラコン	01
	C5099	WD758300	C.CE.CHP	10uF 10V			チップセラコン	01
	C5100	US064100	C.CE.CHP	0.01uF 50V B			チップセラコン	01
	C5101	WD758300	C.CE.CHP	10uF 10V			チップセラコン	01
	C5102	US064100	C.CE.CHP	0.01uF 50V B			チップセラコン	01
	C5103	WD758300	C.CE.CHP	10uF 10V			チップセラコン	01
	C5301	US062100	C.CE.CHP	100pF 50V B			チップセラコン	01
	C5302-5303	UR238100	C.EL	100uF 16V			ケミコン	
	C5304	UR267100	C.EL	10uF 50V			ケミコン	
	C5305	US126100	C.CE.CHP	1uF 10V			チップセラコン	01
	C5307-5313	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C5314	UR237100	C.EL	10uF 16V			ケミコン	
	C5315-5322	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C5323-5334	US061470	C.CE.CHP	47pF 50V B			チップセラコン	01
	C5336	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C5338	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C5341-5343	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C5344	UR237100	C.EL	10uF 16V			ケミコン	
	C5345-5346	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C5348-5350	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C5355-5362	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C5363	UR237470	C.EL	47uF 16V			ケミコン	01
	C5364-5367	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C5368-5370	US063100	C.CE.CHP	1000pF 50V B			チップセラコン	01
	C5371-5372	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C5373-5375	US063100	C.CE.CHP	1000pF 50V B			チップセラコン	01
	C5376-5377	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C5378	UU238100	C.EL	100uF 16V			ケミコン	01
	C5379	WG251600	C.CE.CHP	4.7uF 6.3V			チップセラコン	01
	C5380	UU238100	C.EL	100uF 16V			ケミコン	01
	C5381	UR238100	C.EL	100uF 16V			ケミコン	
	C5382	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C5383-5384	WG251600	C.CE.CHP	4.7uF 6.3V			チップセラコン	01
	C5385	UR239100	C.EL	1000uF 16V			ケミコン	

＊New Parts ＊新規部品

P.C.B. DSP

Ref No.	Part No.	Description			Remarks	Markets	部 品 名	ﾗﾝｸ
C5386-5387	US135100	C.CE.CHP	0.1uF	16V			チップセラコン	01
C5388	UU238100	C.EL	100uF	16V			ケミコン	01
C5389	WG251600	C.CE.CHP	4.7uF	6.3V			チップセラコン	01
C5390	US135100	C.CE.CHP	0.1uF	16V			チップセラコン	01
C5391	WG251600	C.CE.CHP	4.7uF	6.3V			チップセラコン	01
C5392-5393	UR239100	C.EL	1000uF	16V			ケミコン	
C5394	US135330	C.CE.CHP	0.33uF	16V			チップセラコン	01
C5395	UR239100	C.EL	1000uF	16V			ケミコン	
C5396-5397	US064100	C.CE.CHP	0.01uF	50V B			チップセラコン	01
C5398	UR238100	C.EL	100uF	16V		UC	ケミコン	
C5399-5400	US135100	C.CE.CHP	0.1uF	16V		UC	チップセラコン	01
C5401	UR238100	C.EL	100uF	16V		UC	ケミコン	
C5402	US135100	C.CE.CHP	0.1uF	16V		UC	チップセラコン	01
C5403	UR218470	C.EL	470uF	6.3V		UC	ケミコン	
C5404-5406	US135100	C.CE.CHP	0.1uF	16V			チップセラコン	01
C5409-5429	US135100	C.CE.CHP	0.1uF	16V			チップセラコン	01
C5430-5432	US063100	C.CE.CHP	1000pF	50V B			チップセラコン	01
C5433-5442	US135100	C.CE.CHP	0.1uF	16V			チップセラコン	01
C5443	UR237100	C.EL	10uF	16V			ケミコン	
C5444	US135100	C.CE.CHP	0.1uF	16V			チップセラコン	01
C5601	US163100	C.CE.CHP	1000pF	50V			チップセラコン	01
C5602-5604	US064100	C.CE.CHP	0.01uF	50V B			チップセラコン	01
C5605	US135100	C.CE.CHP	0.1uF	16V			チップセラコン	01
C5607-5608	US135100	C.CE.CHP	0.1uF	16V			チップセラコン	01
C5609	UU267100	C.EL	10uF	50V			ケミコン　FW	01
C5610	US135100	C.CE.CHP	0.1uF	16V			チップセラコン	01
C5611	UU267100	C.EL	10uF	50V			ケミコン　FW	01
C5612	US135100	C.CE.CHP	0.1uF	16V			チップセラコン	01
C5613	US062100	C.CE.CHP	100pF	50V B			チップセラコン	01
C5614-5615	UR238100	C.EL	100uF	16V			ケミコン	
C5616	UR267100	C.EL	10uF	50V			ケミコン	
C5617	US126100	C.CE.CHP	1uF	10V			チップセラコン	01
C5618-5623	US135100	C.CE.CHP	0.1uF	16V			チップセラコン	01
C5624	UU267100	C.EL	10uF	50V			ケミコン　FW	01
C5625	US135100	C.CE.CHP	0.1uF	16V			チップセラコン	01
C5626	UU267100	C.EL	10uF	50V			ケミコン　FW	01
C5627	US064100	C.CE.CHP	0.01uF	50V B			チップセラコン	01
C5628	US135100	C.CE.CHP	0.1uF	16V			チップセラコン	01
C5629	US064100	C.CE.CHP	0.01uF	50V B			チップセラコン	01
C5630-5633	WJ602900	C.MYLAR	100pF	50V K			マイラーコン	01
C5634-5635	US135100	C.CE.CHP	0.1uF	16V			チップセラコン	01
C5636-5637	WJ605400	C.MYLAR	0.022uF	50V J			マイラーコン	01
C5638-5639	US135100	C.CE.CHP	0.1uF	16V			チップセラコン	01
C5640-5643	WJ603300	C.MYLAR	470pF	50V J			マイラーコン	01
C5644-5646	US135100	C.CE.CHP	0.1uF	16V			チップセラコン	01
C5647-5649	UU267100	C.EL	10uF	50V			ケミコン　FW	01
C5650-5652	US135100	C.CE.CHP	0.1uF	16V			チップセラコン	01
C5653	UU267100	C.EL	10uF	50V			ケミコン　FW	01
C5654-5656	US135100	C.CE.CHP	0.1uF	16V			チップセラコン	01
C5657-5658	UU267220	C.EL	22uF	50V			ケミコン　FW	01
C5659-5660	US135100	C.CE.CHP	0.1uF	16V			チップセラコン	01
C5661-5662	UR237470	C.EL	47uF	16V			ケミコン	01

※ New Parts　＊新規部品

P.C.B. DSP

	Ref No.	Part No.	Description		Remarks	Markets	部 品 名	ﾗﾝｸ
	C5663-5665	US135100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
	C5666-5667	US064100	C. CE. CHP	0. 01uF 50V B		UC	チップセラコン	01
	C5668-5672	US135100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
	C5673	UR237470	C. EL	47uF 16V		UC	ケミコン	01
	C5674	UR237100	C. EL	10uF 16V		UC	ケミコン	
	C5675	US135100	C. CE. CHP	0. 1uF 16V		UC	チップセラコン	01
	C5676	US135100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
	C5677-5678	UR237470	C. EL	47uF 16V		UC	ケミコン	01
	C5679	US135100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
	C5680-5681	WJ604200	C. MYLAR	2700pF 50V		UC	マイラーコン	01
	C5682-5683	US135100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
	C5684-5685	WJ604200	C. MYLAR	2700pF 50V		UC	マイラーコン	01
	C5686	US135100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
	C5687-5688	UR237100	C. EL	10uF 16V		UC	ケミコン	
	C5689	US063100	C. CE. CHP	1000pF 50V B			チップセラコン	01
	C5690-5697	US135100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
	C5698-5699	US135100	C. CE. CHP	0. 1uF 16V		UC	チップセラコン	01
	C5700-5701	UR237470	C. EL	47uF 16V		UC	ケミコン	01
	C5704-5705	US135100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
	C5708	US064100	C. CE. CHP	0. 01uF 50V B			チップセラコン	01
	C5709	UU238100	C. EL	100uF 16V			ケミコン	01
	C5710	US135100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
	C5712-5714	US163100	C. CE. CHP	1000pF 50V			チップセラコン	01
	C5715	US135100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
	C5716-5717	US163100	C. CE. CHP	1000pF 50V			チップセラコン	01
	C5718-5720	UR038100	C. EL	100uF 16V			ケミコン	
	C5721	US135100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
	C5722-5723	UR038100	C. EL	100uF 16V			ケミコン	
	C5724-5726	US135100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
	C5728-5729	US135100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
	C5730-5732	UR038100	C. EL	100uF 16V			ケミコン	
	C5734-5735	UR038100	C. EL	100uF 16V			ケミコン	
	C5736-5738	US135100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
	C5740-5744	US135100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
	C5746-5747	US135100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
	C5748-5750	UU267100	C. EL	10uF 50V			ケミコン FW	01
	C5752-5753	UU267100	C. EL	10uF 50V			ケミコン FW	01
*	C5754-5758	WJ603400	C. MYLAR	560pF 50V			マイラーコン	
*	C5759-5763	WJ604700	C. MYLAR	6800pF 50V			マイラーコン	
*	C5765	WJ605900	C. MYLAR	0. 056uF 50V			マイラーコン	
*	C5766-5769	WJ604700	C. MYLAR	6800pF 50V			マイラーコン	
*	C5770-5774	WP172700	C. MYLAR	390pF 50V			マイラーコン	
	C5775	UR237470	C. EL	47uF 16V			ケミコン	01
*	C5776	WJ605200	C. MYLAR	0. 015uF 50V			マイラーコン	
*	C5777-5785	WP172700	C. MYLAR	390pF 50V			マイラーコン	
	C5786	US135100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
*	C5787	WJ605200	C. MYLAR	0. 015uF 50V			マイラーコン	
*	C5788-5791	WP172700	C. MYLAR	390pF 50V			マイラーコン	
	C5797	US135100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
	C5803-5807	UU267100	C. EL	10uF 50V			ケミコン FW	01
	C5808	US135100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
	C5809-5813	UU267100	C. EL	10uF 50V			ケミコン FW	01

＊New Parts ＊新規部品

P.C.B. DSP

	Ref No.	Part No.	Description		Remarks	Markets	部 品 名	ﾗﾝｸ
	C5814-5825	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C5826-5831	UU237470	C.EL	47uF 16V			ケミコン FW	01
	C5834-5842	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C5844-5851	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C5852-5854	US063100	C.CE.CHP	1000pF 50V B			チップセラコン	01
	C5855-5856	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C5857-5859	US063100	C.CE.CHP	1000pF 50V B			チップセラコン	01
	C5860-5861	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C5900	US035100	C.CE.CHP	0.1uF 16V B			チップセラコン	01
	C5920-5922	US035100	C.CE.CHP	0.1uF 16V B			チップセラコン	01
	C5930-5931	US035100	C.CE.CHP	0.1uF 16V B			チップセラコン	01
	C5940-5945	US035100	C.CE.CHP	0.1uF 16V B			チップセラコン	01
*	C5946-5947	WJ603400	C.MYLAR	560pF 50V			マイラーコン	
	D5001-5003	WE674800	DIODE	AVRL161A1R1NTB		UC	チップバリスタ	01
	D5301-5303	VT332900	DIODE	1SS355			ダイオード	01
	D5305	VT332900	DIODE	1SS355			ダイオード	01
	D5306	VT332900	DIODE	1SS355		UC	ダイオード	01
	D5308	VT332900	DIODE	1SS355			ダイオード	01
	D5309	VT332900	DIODE	1SS355		UC	ダイオード	01
	D5310-5311	VT332900	DIODE	1SS355			ダイオード	01
	D5600-5609	VV220700	DIODE.SHOT	RB501V-40			ショットキーダイオード	01
	IC501	X3936A00	IC	SN74LVU04APWR			ロジックＩＣ	
	IC502	X3018A00	IC	SN74AHCT00PWR NAND			ロジックＩＣ	01
	IC504-505	XN518A00	IC	SN74LS151NSR 8-1 S			ロジックＩＣ	04
	IC506	X7746A00	IC	LC89057W-VF4AD-E			ＩＣ	07
	IC507-508	XV894A00	IC	TC74VHC153FT MULTI			ロジックＩＣ	03
	IC509	X6123A00	IC	SN74LV157APWR			ロジックＩＣ	02
	IC510	X3505A00	IC	NJM2068MD-TE2			アンプＩＣ	02
	IC511	XY074B00	IC	TC74VHC125FT(EL,K)			ロジックＩＣ	01
	IC512	XR680A00	IC	TC7SH08FU(TE85L,JF			ロジックＩＣ	01
*	IC513	X9798A00	IC	CS230003-CZZR			ＩＣデジタル	
	IC531	XR680A00	IC	TC7SH08FU(TE85L,JF			ロジックＩＣ	01
	IC532-533	XW814A00	IC	TC7SET32FU			ロジックＩＣ	01
	IC535	X3824A00	IC	SN74AHCT08PWR			ロジックＩＣ	01
	IC536	X3693A00	IC	SN74LV245APWR TRAN			ロジックＩＣ	
	IC537	XR680A00	IC	TC7SH08FU(TE85L,JF			ロジックＩＣ	01
	IC538	XW814A00	IC	TC7SET32FU			ロジックＩＣ	01
	IC539	XR680A00	IC	TC7SH08FU(TE85L,JF			ロジックＩＣ	01
*	IC540	YA400A00	IC.MEMORY	S29AL016D70TFI020	written		メモリＩＣ １６Ｍ	
	IC541-542	X7195A00	IC	R1172S121D-E2-F			電源ＩＣ	04
	IC543	X7964A00	IC	PQ200WNA1ZPH			電源ＩＣ	03
	IC544	X6869A00	IC	NJM2885DL1-33			電源ＩＣ	03
	IC545	X7964A00	IC	PQ200WNA1ZPH		UC	電源ＩＣ	03
	IC546	XR680A00	IC	TC7SH08FU(TE85L,JF			ロジックＩＣ	01
	IC560	X6872A00	IC	PCM1804DBR			Ａ／Ｄコンバーター	07
	IC561-563	X3505A00	IC	NJM2068MD-TE2			アンプＩＣ	02
*	IC564	X6231A00	IC	AK4384ET		UC	ＩＣ	
	IC565	X5482A00	IC	NE5532DR OP AMP		UC	アンプＩＣ	01
	IC566	X6123A00	IC	SN74LV157APWR			ロジックＩＣ	02
	IC569-571	X7947A00	IC	DSD1791DBR			Ｄ／Ａコンバーター	07
	IC573-574	X7947A00	IC	DSD1791DBR			Ｄ／Ａコンバーター	07
	IC575-577	X5482A00	IC	NE5532DR OP AMP			アンプＩＣ	01

＊New Parts ＊新規部品

P.C.B. DSP and P.C.B. FUNCTION

	Ref No.	Part No.	Description		Remarks	Markets	部 品 名	ﾗﾝｸ
	IC579-580	X3505A00	IC	NJM2068MD-TE2			アンプＩＣ	02
	IC581	XR680A00	IC	TC7SH08FU(TE85L,JF			ロジックＩＣ	01
	IC582	X7285A00	IC	TC7SH00FU(TE85L,F)			ロジックＩＣ	01
	IC583	XR680A00	IC	TC7SH08FU(TE85L,JF			ロジックＩＣ	01
	IC585	X2760C00	IC	K4S641632K-UC75000			メモリＩＣ６４Ｍ	07
	IC587	X2760C00	IC	K4S641632K-UC75000			メモリＩＣ６４Ｍ	07
	IC588	X6123A00	IC	SN74LV157APWR			ロジックＩＣ	02
	PJ501	WB824400	JACK.PIN	YKC21-4228N		J	ピンジャック　３Ｐ	04
*	PJ501	WB491200	JACK.PIN	3P RJ-1165_31-0300		UCRTKABGEL	ピンジャック	
	Q5001	VV655400	TR.DGT	DTC114EKA			デジタルトランジスタ	01
	Q5002	VD303700	TR	2SC3326 A,B			トランジスタ	01
	Q5301	VV556500	TR	2SA1037K Q,R,S		UC	トランジスタ	01
	R5010	HV753100	R.CAR.FP	1 Ω 1/4W			不燃化カーボン抵抗	01
	R5035	HV753100	R.CAR.FP	1 Ω 1/4W			不燃化カーボン抵抗	01
	R5070	HV753100	R.CAR.FP	1 Ω 1/4W			不燃化カーボン抵抗	01
	R5382	V8070000	R.MTL.FLM	1 Ω 1W			金属被膜抵抗	01
	R5383	WJ787500	R.MTL.FLM	0.22 Ω 1W			金属被膜抵抗	01
	R5384-5385	V8070000	R.MTL.FLM	1 Ω 1W			金属被膜抵抗	01
	R5388-5389	V8070000	R.MTL.FLM	1 Ω 1W		UC	金属被膜抵抗	01
	R5410	WJ787500	R.MTL.FLM	0.22 Ω 1W			金属被膜抵抗	01
*	R5655-5656	WQ072300	R.MTL.OXD	2.2 Ω 1W			酸化金属被膜抵抗	
	R5673	HV753100	R.CAR.FP	1 Ω 1/4W		UC	不燃化カーボン抵抗	01
	R5708-5709	HV753100	R.CAR.FP	1 Ω 1/4W		UC	不燃化カーボン抵抗	01
	R5727-5729	HV753470	R.CAR.FP	4.7 Ω 1/4W			不燃化カーボン抵抗	01
	R5731-5732	HV753470	R.CAR.FP	4.7 Ω 1/4W			不燃化カーボン抵抗	01
	R5780-5781	HF353100	R.CAR	1 Ω 1/2W			カーボン抵抗	
	R5783-5785	HF353100	R.CAR	1 Ω 1/2W			カーボン抵抗	
	ST530	V4040500	SCR.TERM	M3			スクリュー／ターミナル	01
	U5001-5002	WH536900	CN.PHOTO.T	1P GP1FAV51TK0F			光ファイバー送信器	04
	U5003-5006	WH169900	CN.PHOTO.R	1P GP1FAV51RK0F			光ファイバー受信器	04
*	XL501	WH455300	RSNR.CRYS	45.1584MHz		UC	水晶振動子	
	XL502	V6931900	RESONATOR	24.576MHz DS0751SV			水晶発振器	05
*		WQ136900	P.C.B.	FUNCTION		J	ＰＣＢ　ＦＵＮＣＴＩＯＮ	
*		WQ137000	P.C.B.	FUNCTION		U	ＰＣＢ　ＦＵＮＣＴＩＯＮ	
*		WQ137100	P.C.B.	FUNCTION		C	ＰＣＢ　ＦＵＮＣＴＩＯＮ	
*		WQ137200	P.C.B.	FUNCTION		RTKL	ＰＣＢ　ＦＵＮＣＴＩＯＮ	
*		WQ137200	P.C.B.	FUNCTION		RTL	ＰＣＢ　ＦＵＮＣＴＩＯＮ	
*		WQ137300	P.C.B.	FUNCTION		A	ＰＣＢ　ＦＵＮＣＴＩＯＮ	
*		WQ137400	P.C.B.	FUNCTION		BGE	ＰＣＢ　ＦＵＮＣＴＩＯＮ	
	CB300	VQ048000	CN.BS.PIN	31P			ＦＦＣコネクター	02
	CB301	V8809800	CN.JE	9P SE			ＪＥコネクタープラグ	01
	CB302	V8875300	CN.JE	13P SE			ＪＥコネクタープラグ	01
	CB303	VC166500	CN.BS.PIN	12P			コネクタベースポスト	01
	CB350	V8809800	CN.JE	9P SE			ＪＥコネクタープラグ	01
	CB351	V7827000	CN	20P TE TUC SERIES			コネクタープラグ	01
	CB401	VM859600	CN.BS.PIN	15P		JCRTKABGEL	ＦＦＣコネクター	01
	CB401	VU446000	CN.BS.PIN	15P TE		U	ＪＥ　コネクタ	02
	CB402-403	V8875300	CN.JE	13P SE			ＪＥコネクタープラグ	01
	CB404	V8809800	CN.JE	9P SE			ＪＥコネクタープラグ	01

＊New Parts　＊新規部品

P.C.B. FUNCTION

	Ref No.	Part No.	Description		Remarks	Markets	部 品 名	ﾗﾝｸ
	CB405	VB389600	CN.BS.PIN	11P			コネクタベースポスト	01
	CB406	VB858700	CN.BS.PIN	8P			ベースピン	01
	CB407	VK015400	CN.BS.PIN	13P			コネクタベースポスト	01
	CB409	VQ044700	CN.BS.PIN	16P			ＦＦＣコネクター	01
	CB410	VM859500	CN.BS.PIN	11P			ＦＦＣコネクター	01
	CB411	VQ044300	CN.BS.PIN	7P			ＦＦＣコネクター	01
	CB412-414	V9356900	CN.JE	19P SE			ＪＥコネクタープラグ	
	CB416	V8809800	CN.JE	9P SE			ＪＥコネクタープラグ	01
	CB451	VB390500	CN.BS.PIN	9P		UC	コネクタベースポスト	03
	CB453	V7828700	SOCKET	20P SE TUC SERIES			コネクターソケット	01
	C3000-3001	UR237100	C.EL	10uF 16V			ケミコン	
	C3002	US135220	C.CE.CHP	0.22uF 16V			チップセラコン	01
	C3003-3004	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C3005-3006	UR267470	C.EL	47uF 50V			ケミコン	01
	C3007-3008	UU237100	C.EL	10uF 16V			ケミコン ＦＷ	01
	C3009	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C3010-3011	UU237100	C.EL	10uF 16V			ケミコン ＦＷ	01
	C3013-3016	UU237100	C.EL	10uF 16V			ケミコン ＦＷ	01
	C3017-3018	UR238100	C.EL	100uF 16V			ケミコン	
	C3020-3023	UR238100	C.EL	100uF 16V			ケミコン	
	C3024-3025	US062100	C.CE.CHP	100pF 50V B			チップセラコン	01
	C3029	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C3030-3033	US062100	C.CE.CHP	100pF 50V B			チップセラコン	01
	C3035	UR266470	C.EL	4.7uF 50V			ケミコン	
	C3036-3037	UR267470	C.EL	47uF 50V			ケミコン	01
	C3038-3039	UR266470	C.EL	4.7uF 50V			ケミコン	
	C3040	UR237100	C.EL	10uF 16V			ケミコン	
	C3041-3042	UR266470	C.EL	4.7uF 50V			ケミコン	
	C3043-3044	UR266330	C.EL	3.3uF 50V			ケミコン	
	C3045-3050	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C3051	UR237470	C.EL	47uF 16V			ケミコン	01
	C3052	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C3053	UR247330	C.EL	33uF 25V			ケミコン	01
	C3054	UR267470	C.EL	47uF 50V			ケミコン	01
	C3055	UR267100	C.EL	10uF 50V			ケミコン	
	C3056	UR247330	C.EL	33uF 25V			ケミコン	01
	C3057	UR237470	C.EL	47uF 16V			ケミコン	01
	C3058	UR247330	C.EL	33uF 25V			ケミコン	01
	C3059	UR337100	C.EL	10uF 16V			ケミコン	03
	C3060	UR247330	C.EL	33uF 25V			ケミコン	01
	C3061	UR267470	C.EL	47uF 50V			ケミコン	01
	C3062-3064	UR247330	C.EL	33uF 25V			ケミコン	01
	C3065	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C3066-3067	UR267100	C.EL	10uF 50V			ケミコン	
	C3068	US062100	C.CE.CHP	100pF 50V B			チップセラコン	01
	C3069-3070	WJ602900	C.MYLAR	100pF 50V K			マイラーコン	01
*	C3071-3076	UR257100	C.EL	10uF 35V			ケミコン	
	C3077-3078	UR267470	C.EL	47uF 50V			ケミコン	01
	C3079	UR237220	C.EL	22uF 16V			ケミコン	
*	C3080-3081	UR257100	C.EL	10uF 35V			ケミコン	
	C3082	UR237220	C.EL	22uF 16V			ケミコン	
	C3083-3084	UR267470	C.EL	47uF 50V			ケミコン	01

※ New Parts ＊新規部品

P.C.B. FUNCTION

	Ref No.	Part No.	Description			Remarks	Markets	部 品 名	ﾗﾝｸ
	C3086	US135100	C. CE. CHP	0. 1uF	16V			チップセラコン	01
	C3088	US135100	C. CE. CHP	0. 1uF	16V			チップセラコン	01
	C3100-3101	UR237100	C. EL	10uF	16V			ケミコン	
	C3500-3501	US135100	C. CE. CHP	0. 1uF	16V			チップセラコン	01
	C3503	US062220	C. CE. CHP	220pF	50V B		RTKABGEL	チップセラコン	01
	C3504	US062220	C. CE. CHP	220pF	50V B		RTKABGEL	チップセラコン	01
	C3506	US062470	C. CE. CHP	470pF	50V B		UCRTKABGEL	チップセラコン	01
	C3507	US062470	C. CE. CHP	470pF	50V B		UCRTKABGEL	チップセラコン	01
	C3508	US062470	C. CE. CHP	470pF	50V B		UCRTKABGEL	チップセラコン	01
	C3509	US062470	C. CE. CHP	470pF	50V B		UCRTKABGEL	チップセラコン	01
	C3510-3511	US062220	C. CE. CHP	220pF	50V B			チップセラコン	01
	C3512-3513	WJ603100	C. MYLAR	220pF	50V			マイラーコン	01
	C3514-3515	US062220	C. CE. CHP	220pF	50V B			チップセラコン	01
	C3518	WJ603100	C. MYLAR	220pF	50V			マイラーコン	01
	C3519	WJ603300	C. MYLAR	470pF	50V J			マイラーコン	01
	C3520-3523	WJ603100	C. MYLAR	220pF	50V			マイラーコン	01
	C3524	US062100	C. CE. CHP	100pF	50V B		UCRTKABGEL	チップセラコン	01
	C3525	US062100	C. CE. CHP	100pF	50V B		UCRTKABGEL	チップセラコン	01
	C3526	WJ603300	C. MYLAR	470pF	50V J			マイラーコン	01
	C3527	VR169200	C. MYLAR	0. 47uF	50V			マイラーコン	01
	C3528-3533	WJ603300	C. MYLAR	470pF	50V J			マイラーコン	01
	C3536-3539	UR266220	C. EL	2. 2uF	50V			ケミコン	
	C3540-3541	UR218220	C. EL	220uF	6. 3V			ケミコン	
*	C3542-3543	WJ605600	C. MYLAR	0. 033uF	50V			マイラーコン	
*	C3544-3545	WJ604900	C. MYLAR	9100pF	50V			マイラーコン	
	C3546-3548	UR237100	C. EL	10uF	16V			ケミコン	
	C3550	UU267100	C. EL	10uF	50V		UCRTKABGEL	ケミコン　FW	01
	C3551	UU267100	C. EL	10uF	50V		UCRTKABGEL	ケミコン　FW	01
	C3552	UR237100	C. EL	10uF	16V			ケミコン	
	C3554	UU267100	C. EL	10uF	50V		UCRTKABGEL	ケミコン　FW	01
	C3555-3556	UR237100	C. EL	10uF	16V			ケミコン	
	C3557	UU267100	C. EL	10uF	50V		UCRTKABGEL	ケミコン　FW	01
	C3558	UR237100	C. EL	10uF	16V			ケミコン	
	C3559-3560	UR267470	C. EL	47uF	50V			ケミコン	01
*	C3561-3562	WJ603700	C. MYLAR	1000pF	50V			マイラーコン	
	C3563	UR237100	C. EL	10uF	16V			ケミコン	
	C3566	UR038100	C. EL	100uF	16V		UCRTKABGEL	ケミコン	
	C3569	UR038100	C. EL	100uF	16V		UCRTKABGEL	ケミコン	
	C3570	UR038100	C. EL	100uF	16V		UCRTKABGEL	ケミコン	
	C3572	UR038100	C. EL	100uF	16V		UCRTKABGEL	ケミコン	
	C3574-3575	UR267470	C. EL	47uF	50V			ケミコン	01
	C3576	UR266470	C. EL	4. 7uF	50V		UCRTKABGEL	ケミコン	
	C3577	VR168300	C. MYLAR	0. 1uF	50V		UCRTKABGEL	マイラーコン	01
	C3578	VR168300	C. MYLAR	0. 1uF	50V		UCRTKABGEL	マイラーコン	01
	C3579	UR266470	C. EL	4. 7uF	50V		UCRTKABGEL	ケミコン	
	C3580	UR266470	C. EL	4. 7uF	50V		UCRTKABGEL	ケミコン	
	C3581	VR168300	C. MYLAR	0. 1uF	50V		UCRTKABGEL	マイラーコン	01
	C3582	VR168300	C. MYLAR	0. 1uF	50V		UCRTKABGEL	マイラーコン	01
	C3583	UR266470	C. EL	4. 7uF	50V		UCRTKABGEL	ケミコン	
*	C3584	WJ604300	C. MYLAR	3300pF	50V		UCRTKABGEL	マイラーコン	
*	C3585	WJ604300	C. MYLAR	3300pF	50V		UCRTKABGEL	マイラーコン	
*	C3586	WJ604300	C. MYLAR	3300pF	50V		UCRTKABGEL	マイラーコン	

※ New Parts　＊新規部品

P.C.B. FUNCTION

	Ref No.	Part No.	Description		Remarks	Markets	部 品 名	ﾗﾝｸ
*	C3587	WJ604300	C.MYLAR	3300pF 50V		UCRTKABGEL	マイラーコン	
	C3588	UR247100	C.EL	10uF 25V		UCRTKABGEL	ケミコン	
	C3589	UR247100	C.EL	10uF 25V		UCRTKABGEL	ケミコン	
	C3590	UR247100	C.EL	10uF 25V		UCRTKABGEL	ケミコン	
	C3591	UR247100	C.EL	10uF 25V		UCRTKABGEL	ケミコン	
	C3598	UR237100	C.EL	10uF 16V			ケミコン	
	C3601	UR237100	C.EL	10uF 16V		UCRTKABGEL	ケミコン	
	C3603	UR038100	C.EL	100uF 16V		UCRTKABGEL	ケミコン	
	C3604	UR237100	C.EL	10uF 16V			ケミコン	
	C3605-3606	UR237470	C.EL	47uF 16V			ケミコン	01
	C3610	UR237100	C.EL	10uF 16V		UCRTKABGEL	ケミコン	
	C3615	UR247100	C.EL	10uF 25V		UCRTKABGEL	ケミコン	
	C3616	UR038100	C.EL	100uF 16V		UCRTKABGEL	ケミコン	
	C3617	UR247100	C.EL	10uF 25V		UCRTKABGEL	ケミコン	
	C3619	US135100	C.CE.CHP	0.1uF 16V		UCRTKABGEL	チップセラコン	01
	C3632	US135100	C.CE.CHP	0.1uF 16V		UCRTKABGEL	チップセラコン	01
	C3633	US135100	C.CE.CHP	0.1uF 16V		UCRTKABGEL	チップセラコン	01
	C3634	US135100	C.CE.CHP	0.1uF 16V		UCRTKABGEL	チップセラコン	01
	C3635	US135100	C.CE.CHP	0.1uF 16V		UCRTKABGEL	チップセラコン	01
	C3636-3639	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C4000	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C4018	US064100	C.CE.CHP	0.01uF 50V B		JCRTKABGEL	チップセラコン	01
	C4019	UR266220	C.EL	2.2uF 50V		JCRTKABGEL	ケミコン	
	C4020	UU238100	C.EL	100uF 16V		JCRTKABGEL	ケミコン	01
	C4021	US135100	C.CE.CHP	0.1uF 16V		BGE	チップセラコン	01
	C4022-4023	US062330	C.CE.CHP	330pF 50V B		BGE	チップセラコン	01
	C4024	US062560	C.CE.CHP	560pF 50V B		BGE	チップセラコン	01
	C4025-4026	UR237470	C.EL	47uF 16V		BGE	ケミコン	01
	C4027-4028	US061270	C.CE.CHP	27pF 50V B		BGE	チップセラコン	01
	C4029	UR237470	C.EL	47uF 16V		BGE	ケミコン	01
	C4030	US135100	C.CE.CHP	0.1uF 16V		BGE	チップセラコン	01
	C4031-4034	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C4036-4039	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C4040	UR239100	C.EL	1000uF 16V			ケミコン	
	C4041-4044	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C4045	US063100	C.CE.CHP	1000pF 50V B			チップセラコン	01
	C4046	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C4048-4049	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C4050	UR067100	C.EL	10uF 50V			ケミコン	01
	C4051	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C4052	WB165500	C.EL	0.33F 5.5V			ゴールドキャパシタ	04
	C4053-4055	UR219100	C.EL	1000uF 6.3V			ケミコン	
	C4056-4061	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C4063	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C4064	UR266220	C.EL	2.2uF 50V		UCRTKABGEL	ケミコン	
	C4065	UR266220	C.EL	2.2uF 50V		UCRTKABGEL	ケミコン	
	C4066-4070	UR266220	C.EL	2.2uF 50V			ケミコン	
	C4071	UR239100	C.EL	1000uF 16V			ケミコン	
	C4072	US135100	C.CE.CHP	0.1uF 16V		UCRTKABGEL	チップセラコン	01
	C4073	UR218100	C.EL	100uF 6.3V		UCRTKABGEL	ケミコン	
	C4074	US063100	C.CE.CHP	1000pF 50V B		UCRTKABGEL	チップセラコン	01
	C4075	US063100	C.CE.CHP	1000pF 50V B		UCRTKABGEL	チップセラコン	01

※ New Parts ＊新規部品

P.C.B. FUNCTION

Ref No.	Part No.	Description		Remarks	Markets	部 品 名	ﾗﾝｸ
C4076-4077	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
C4078	US063100	C.CE.CHP	1000pF 50V B		UCRTKABGEL	チップセラコン	01
C4079	US063100	C.CE.CHP	1000pF 50V B		UCRTKABGEL	チップセラコン	01
C4080	US063100	C.CE.CHP	1000pF 50V B		UCRTKABGEL	チップセラコン	01
C4081	US063100	C.CE.CHP	1000pF 50V B		UCRTKABGEL	チップセラコン	01
C4082-4084	US062100	C.CE.CHP	100pF 50V B			チップセラコン	01
C4085	US062100	C.CE.CHP	100pF 50V B		J	チップセラコン	01
C4086	US062100	C.CE.CHP	100pF 50V B			チップセラコン	01
C4087	US062100	C.CE.CHP	100pF 50V B		J	チップセラコン	01
C4088-4089	US062100	C.CE.CHP	100pF 50V B			チップセラコン	01
C4098-4099	US062100	C.CE.CHP	100pF 50V B			チップセラコン	01
C4100	US062100	C.CE.CHP	100pF 50V B		J	チップセラコン	01
C4101	US062100	C.CE.CHP	100pF 50V B			チップセラコン	01
C4102-4103	US062100	C.CE.CHP	100pF 50V B		J	チップセラコン	01
C4112	US062100	C.CE.CHP	100pF 50V B			チップセラコン	01
C4131	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
C4134	US061470	C.CE.CHP	47pF 50V B		UC	チップセラコン	01
C4500-4503	US062220	C.CE.CHP	220pF 50V B			チップセラコン	01
C4506-4507	US062220	C.CE.CHP	220pF 50V B			チップセラコン	01
C4508-4509	WJ603100	C.MYLAR	220pF 50V			マイラーコン	01
C4510-4511	US062220	C.CE.CHP	220pF 50V B			チップセラコン	01
C4512-4513	US062100	C.CE.CHP	100pF 50V B			チップセラコン	01
C4514-4515	US062220	C.CE.CHP	220pF 50V B			チップセラコン	01
C4516-4517	US062100	C.CE.CHP	100pF 50V B			チップセラコン	01
C4518-4519	UR237100	C.EL	10uF 16V			ケミコン	
C4520	UR237100	C.EL	10uF 16V		UCRTKABGEL	ケミコン	
C4521-4522	UR237100	C.EL	10uF 16V		UCRTKABGEL	ケミコン	
C4523-4527	UR237100	C.EL	10uF 16V		UCRTKABGEL	ケミコン	
C4528	UR237100	C.EL	10uF 16V		UCRTKABGEL	ケミコン	
C4529	UR237100	C.EL	10uF 16V			ケミコン	
C4530-4531	UR237470	C.EL	47uF 16V			ケミコン	01
C4532-4533	US062100	C.CE.CHP	100pF 50V B			チップセラコン	01
C4536-4539	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
C4541	US062220	C.CE.CHP	220pF 50V B		UC	チップセラコン	01
D3000-3003	VT332900	DIODE	1SS355			ダイオード	01
D3004-3005	VU993800	DIODE.ZENR	MA8068-M 6.8V			ツェナーダイオード	01
D3500-3501	VU992100	DIODE.ZENR	MA8047-L 4.6V			ツェナーダイオード	01
D3502	VT332900	DIODE	1SS355		UCRTKABGEL	ダイオード	01
D3503	VT332900	DIODE	1SS355		UCRTKABGEL	ダイオード	01
D4001	VU172000	DIODE.ZENR	UDZS5.6BTE-17 5.6V		JCRTKABGEL	ツェナーダイオード	01
D4002-4007	VT332900	DIODE	1SS355			ダイオード	01
D4008	VV833200	DIODE	1SS380			ダイオード	01
D4009	VT332900	DIODE	1SS355			ダイオード	01
D4010	VU992600	DIODE.ZENR	MA8051-M 5.1V			ツェナーダイオード	01
D4012-4013	VT332900	DIODE	1SS355			ダイオード	01
D4014	V2598200	LED	SIR-505ST		UCRTKABGEL	ＬＥＤ	01
D4015	V2598200	LED	SIR-505ST		UCRTKABGEL	ＬＥＤ	01
D4016	VT332900	DIODE	1SS355		UCRTKABGEL	ダイオード	01
D4017	VT332900	DIODE	1SS355		UCRTKABGEL	ダイオード	01
IC300	X5045A00	IC	NJU7312AM			アナログＩＣ	05
IC301	X5044A00	IC	NJU7311AM			アナログＩＣ	05
IC302	X3505A00	IC	NJM2068MD-TE2			アンプＩＣ	02

＊New Parts ＊新規部品

P.C.B. FUNCTION

	Ref No.	Part No.	Description		Remarks	Markets	部 品 名	ﾗﾝｸ
	IC304-306	X3505A00	IC	NJM2068MD-TE2			アンプＩＣ	02
	IC307	X5574A00	IC	YAC526-EZE2			ＩＣ アナログ	05
	IC308	X4325A00	IC	YAC523-EVR2			ＩＣ, アナログ	06
	IC309-312	X9127A00	IC	NJM5532M-D			アンプＩＣ	04
	IC313	X5043A00	IC	NJU7313AM			アナログＩＣ	05
	IC350-352	X3505A00	IC	NJM2068MD-TE2			アンプＩＣ	02
	IC355	X3547A00	IC	BD3841FS			ＩＣ	06
	IC356	X3547A00	IC	BD3841FS		UCRTKABGEL	ＩＣ	06
	IC357	X3505A00	IC	NJM2068MD-TE2		UCRTKABGEL	アンプＩＣ	02
	IC358	X3505A00	IC	NJM2068MD-TE2		UCRTKABGEL	アンプＩＣ	02
*	IC359	X8355A00	IC	NJW1194		UCRTKABGEL	ＩＣ アナログ	
*	IC360	X8355A00	IC	NJW1194		UCRTKABGEL	ＩＣ アナログ	
*	IC401	X8235A00	IC	LC72725KM		BGE	ＩＣ	
	IC402	X8013A00	IC.CPU	M3087BFKBGP CPU	unwritten		ＣＰＵ ＩＣ	
	IC403	X7779A00	IC	LC709004A-TLM-E			ロジックＩＣ	04
	IC407	X9428A00	IC	R1154H058B-T1-F			電源ＩＣ	03
	IC450	X3547A00	IC	BD3841FS		UCRTKABGEL	ＩＣ	06
	IC451	X3547A00	IC	BD3841FS			ＩＣ	06
	JK401	V9435700	JACK.MNI	MSJ-035-12APC		UCRTKABGEL	モノラル ミニジャック	01
	JK402	V9435700	JACK.MNI	MSJ-035-12APC		UCRTKABGEL	モノラル ミニジャック	01
	JK403	V9435700	JACK.MNI	MSJ-035-12APC		UCRTKABGEL	モノラル ミニジャック	01
	JK404	V9435700	JACK.MNI	MSJ-035-12APC		UCRTKABGEL	モノラル ミニジャック	01
	PJ350	V9763900	JACK.PIN	6P RJ-1073F-09-055		J	ピンジャック ４Ｐ	04
	PJ350	V5478700	JACK.PIN	4P RJ-1073F-09		UCRTKABGEL	ピンジャック	
	PJ352	V9764300	JACK.PIN	6P RJ-1074-84-0553		J	ピンジャック ６Ｐ	04
	PJ352	V5478900	JACK.PIN	RJ-1074-84-0353A		UCRTKABGEL	ピンジャック ６Ｐ	03
	PJ353	V5634800	JACK.PIN	6P		J	ピンジャック	04
	PJ353	VV325400	JACK.PIN	6P		UCRTKABGEL	ピンジャック	05
*	PJ354	WH221000	JACK.PIN	6P RJ-1074-83-0H53		UCRTKABGEL	ピンジャック	
*	PJ356	WQ380300	JACK.PIN	2P RJ-1060_01-0531		J	ピンジャック ２Ｐ	
*	PJ356	WQ354100	JACK.PIN	2P		UCRTKABGEL	ピンジャック	
*	PJ357	WD194900	JACK.PIN	RJ-1060_09-0531A		J	ピンジャック ２Ｐ	
*	PJ357	WQ364800	JACK.PIN	2P		UCRTKABGEL	ピンジャック	
	PJ450	VV551500	JACK.PIN	4P		J	ピンジャック	05
	PJ450	VV306900	JACK.PIN	4P		UCRTKABGEL	ピンジャック	02
	PJ451	V5634800	JACK.PIN	6P		J	ピンジャック	04
	PJ451	VV325400	JACK.PIN	6P		UCRTKABGEL	ピンジャック	05
	PJ452	VV551500	JACK.PIN	4P		J	ピンジャック	05
	PJ452-453	VV306900	JACK.PIN	4P		UCRTKABGEL	ピンジャック	02
	Q4	WC435100	TR.DGT	KRC104S-RTK			デジタルトランジスタ	01
	Q26	WC435100	TR.DGT	KRC104S-RTK			デジタルトランジスタ	01
	Q27-28	WC434900	TR.DGT	KRA104S-RTK			デジタルトランジスタ	01
	Q29	WC435100	TR.DGT	KRC104S-RTK		UCRTKABGEL	デジタルトランジスタ	01
	Q30	WC435100	TR.DGT	KRC104S-RTK			デジタルトランジスタ	01
	Q31	WC434900	TR.DGT	KRA104S-RTK		UCRTKABGEL	デジタルトランジスタ	01
	Q32	WC434900	TR.DGT	KRA104S-RTK			デジタルトランジスタ	01
	Q33	WC435100	TR.DGT	KRC104S-RTK			デジタルトランジスタ	01
	Q34	WC435100	TR.DGT	KRC104S-RTK		UCRTKABGEL	デジタルトランジスタ	01
	Q35	WC434900	TR.DGT	KRA104S-RTK			デジタルトランジスタ	01
	Q36	WC434900	TR.DGT	KRA104S-RTK		UCRTKABGEL	デジタルトランジスタ	01
	Q37-38	WC435100	TR.DGT	KRC104S-RTK			デジタルトランジスタ	01
	Q39-40	WC434900	TR.DGT	KRA104S-RTK			デジタルトランジスタ	01

＊New Parts ＊新規部品

P.C.B. FUNCTION and P.C.B. OPERATION

	Ref No.	Part No.	Description		Remarks	Markets	部 品 名	ﾗﾝｸ
	Q3000	WG408900	TR	2SC5291 S,T			トランジスタ	03
	Q3001	WG408800	TR	2SA2168 S,T			トランジスタ	03
	Q3002-3017	VZ725900	TR	2SD1938F S,T			トランジスタ	01
	Q3500	VZ725900	TR	2SD1938F S,T		UCRTKABGEL	トランジスタ	01
	Q3501-3502	VZ725900	TR	2SD1938F S,T		UCRTKABGEL	トランジスタ	01
	Q3503-3504	VZ725900	TR	2SD1938F S,T		UCRTKABGEL	トランジスタ	01
	Q3505-3506	VZ725900	TR	2SD1938F S,T		UCRTKABGEL	トランジスタ	01
	Q3507	VZ725900	TR	2SD1938F S,T		UCRTKABGEL	トランジスタ	01
	Q4001	VD303700	TR	2SC3326 A,B		JCRTKABGEL	トランジスタ	01
	Q4002	iC1815I0	TR	2SC1815 Y		JCRTKABGEL	トランジスタ	01
	Q4003	VD303700	TR	2SC3326 A,B		BGE	トランジスタ	01
	Q4004	VD303700	TR	2SC3326 A,B			トランジスタ	01
	Q4005	WD974200	TR	2SA1036KT146 P,Q,R			トランジスタ	01
	Q4006	VV556500	TR	2SA1037K Q,R,S			トランジスタ	01
	Q4007	VD303700	TR	2SC3326 A,B			トランジスタ	01
	Q4008	VV556500	TR	2SA1037K Q,R,S		J	トランジスタ	01
	Q4009	iC287820	TR	2SC2878 A,B			トランジスタ	01
	Q4010	WF767900	FET	5HP01C-TB-E		UCRTKABGEL	ＦＥＴ	01
	Q4011	WF767900	FET	5HP01C-TB-E		UCRTKABGEL	ＦＥＴ	01
	Q4012-4016	WF767900	FET	5HP01C-TB-E			ＦＥＴ	01
	Q4021	VV556400	TR	2SC2412K Q,R,S		UC	トランジスタ	01
	R3102	HF355680	R.CAR	680 Ω 1/2W			カーボン抵抗	
	R3508	HF355470	R.CAR	470 Ω 1/2W		UCRTKABGEL	カーボン抵抗	
	R3509	HF355470	R.CAR	470 Ω 1/2W		UCRTKABGEL	カーボン抵抗	
	R3510	HF355470	R.CAR	470 Ω 1/2W		UCRTKABGEL	カーボン抵抗	
	R3511	HF355470	R.CAR	470 Ω 1/2W		UCRTKABGEL	カーボン抵抗	
	R3526-3533	HF354470	R.CAR	47 Ω 1/2W			カーボン抵抗	
	R3597-3598	HV755100	R.CAR.FP	100 Ω 1/4W			不燃化カーボン抵抗	01
	R4065	V8070300	R.MTL.FLM	10 Ω 1W			金属被膜抵抗	
	U4001	V8210200	L.DTCT	GP1UD271XK		UCRTKABGEL	リモコン受光ユニット	03
*	XL401	V2731100	RSNR.CRYS	4.332M HC-49/U		BGE	水晶振動子	
	XL402	WF997400	RSNR.CE	20MHz			セラミック振動子	02
		WH567400	P.C.B.	OPERATION		J	ＰＣＢ ＯＰＥＲＡＴＩＯＮ	12
*		WH567500	P.C.B.	OPERATION		UCRTKABGEL	ＰＣＢ ＯＰＥＲＡＴＩＯＮ	
	CB801	VB858500	CN.BS.PIN	6P			ベースピン	01
	CB802	VQ047200	CN.BS.PIN	9P			ＦＦＣコネクター	01
	CB803	VM929900	CN.BS.PIN	15P			ＦＰＣコネクター	01
	CB804	V7825400	CN	4P TE TUC SERIES			コネクタープラグ	01
	CB805	VB389900	CN.BS.PIN	3P			ベースピン	01
	CB806	VB390500	CN.BS.PIN	9P			コネクタベースポスト	03
	CB807	VB390100	CN.BS.PIN	5P			ベースピン	01
	CB809	VB389800	CN.BS.PIN	2P			ベースピン	01
	CB810	V7827100	SOCKET	4P TE TUC SERIES			コネクターソケット	01
	CB811	WG668100	CN.USB	USB 4P SE			ＵＳＢコネクター	04
	CB812	VB858600	CN.BS.PIN	7P			ベースピン	01
	CB813	V7827200	SOCKET	5P TE TUC SERIES			コネクターソケット	
	CB814	VB858500	CN.BS.PIN	6P			ベースピン	01
	CB815	V7825500	CN	5P TE TUC SERIES			コネクタープラグ	01
	C8001	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01

＊New Parts ＊新規部品

P.C.B. OPERATION

Ref No.	Part No.	Description		Remarks	Markets	部 品 名	ﾗﾝｸ
C8002	US063100	C.CE.CHP	1000pF 50V B			チップセラコン	01
C8004	US063100	C.CE.CHP	1000pF 50V B			チップセラコン	01
C8005-8007	US061220	C.CE.CHP	22pF 50V B			チップセラコン	01
C8008	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
C8009-8012	US061220	C.CE.CHP	22pF 50V B			チップセラコン	01
C8013-8014	US063100	C.CE.CHP	1000pF 50V B			チップセラコン	01
C8015	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
C8016-8017	UM397220	C.EL	22uF 25V			ケミコン	01
C8018	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
C8020	WJ604300	C.MYLAR	3300pF 50V			マイラーコン	
C8021	UR237100	C.EL	10uF 16V			ケミコン	
C8022	US062100	C.CE.CHP	100pF 50V B			チップセラコン	01
C8024	US064100	C.CE.CHP	0.01uF 50V B			チップセラコン	01
C8025	WJ604300	C.MYLAR	3300pF 50V			マイラーコン	
C8026-8027	UR237100	C.EL	10uF 16V			ケミコン	
C8030	US061330	C.CE.CHP	33pF 50V B			チップセラコン	01
C8031	US063100	C.CE.CHP	1000pF 50V B			チップセラコン	01
C8032	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
C8033	UR237470	C.EL	47uF 16V			ケミコン	01
C8034-8035	US062470	C.CE.CHP	470pF 50V B			チップセラコン	01
C8036-8037	US062100	C.CE.CHP	100pF 50V B			チップセラコン	01
C8038	UR237470	C.EL	47uF 16V			ケミコン	01
C8039	US135100	C.CE.CHP	0.1uF 16V		J	チップセラコン	01
C8040-8042	US062100	C.CE.CHP	100pF 50V B			チップセラコン	01
C8043	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
C8044	US063100	C.CE.CHP	1000pF 50V B			チップセラコン	01
C8045-8046	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
C8047	UM397220	C.EL	22uF 25V			ケミコン	01
C8048-8049	UR237100	C.EL	10uF 16V			ケミコン	
C8050	US063100	C.CE.CHP	1000pF 50V B			チップセラコン	01
C8051	US062100	C.CE.CHP	100pF 50V B			チップセラコン	01
C8052	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
C8053	US063100	C.CE.CHP	1000pF 50V B			チップセラコン	01
C8054-8055	US061100	C.CE.CHP	10pF 50V B			チップセラコン	01
C8056	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
C8057	UR237100	C.EL	10uF 16V			ケミコン	
C8058-8059	WB553000	C.EL	1000uF 16V			ケミコン ＶＫ	
C8060-8062	US063100	C.CE.CHP	1000pF 50V B			チップセラコン	01
C8063-8064	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
D8001	WG760400	LED	SELK6E10C BLUE			ＬＥＤ	04
D8004-8008	VT332900	DIODE	1SS355			ダイオード	01
D8009	VU992600	DIODE.ZENR	MA8051-M 5.1V			ツェナーダイオード	01
D8010	VT332900	DIODE	1SS355			ダイオード	01
D8011	VV307700	DIODE	1N4002S			ダイオード	01
D8013	VV307700	DIODE	1N4002S			ダイオード	01
IC801	X7378A00	IC	NJM4565M(TE1)			アンプＩＣ	01
IC802	X2080A00	IC	SN74AHCT1G32DCKR			ロジックＩＣ	01
IC805	XS377A00	IC	BA15218F OP AMP			アンプＩＣ	01
JK801	V2589500	CN.DIN	1P			ミニＤＩＮコネクタ	02
JK802	V9408200	JACK.PHONE	MSJ-064-05B GR			ホーンジャック	03
JK803	WE260000	JACK.MNI	LGY6501-0900FC			モノラルミニジャック	02
PJ801	V6222800	JACK.PIN	3P			ピンジャック	04

＊New Parts ＊新規部品

P.C.B. OPERATION and P.C.B. MAIN

	Ref No.	Part No.	Description	Remarks	Markets	部 品 名	ﾗﾝｸ
	Q8001	WC529400	TR KTC3875S Y GR RTK			トランジスタ	01
	Q8002-8003	VZ725900	TR 2SD1938F S,T			トランジスタ	01
	R8026	HF355100	R.CAR 100 Ω 1/2W			カーボン抵抗	
	R8030	HF355100	R.CAR 100 Ω 1/2W			カーボン抵抗	
	R8044-8045	HL005220	R.MTL.OXD 220 Ω 1/2W			酸化金属被膜抵抗	
	SW801-802	V4757100	SW.TACT EVQ11A			タクトＳＷ	01
	SW803	V9281200	SW.RT.ENC EVEGC1F2512B			ロータリーエンコーダ	02
	SW805	V4757100	SW.TACT EVQ11A			タクトＳＷ	01
	SW806	V6578000	SW.RT.ENC RB161PVB20FHINA			ロータリーエンコーダ	04
	SW807	V9281200	SW.RT.ENC EVEGC1F2512B			ロータリーエンコーダ	02
	SW808	V9661700	SW.PUSH SY16-32-4(U99S2)/T			プッシュＳＷ	03
	U8001	WB547900	CN.PHOTO.R 1P GP1FA513RZ0F			光ファイバー受信器	03
*		WQ138600	P.C.B. MAIN		J	ＰＣＢ　ＭＡＩＮ	
*		WQ138700	P.C.B. MAIN		UCRTA	ＰＣＢ　ＭＡＩＮ	
*		WQ138800	P.C.B. MAIN		KBGEL	ＰＣＢ　ＭＡＩＮ	
	CB252	WB127100	CN.BS.PIN 3P			ベース付ポスト	
	CB253	LB932080	CN 8P			ベースポスト	01
	C250-256	WK041800	C.EL 10uF 16V			ケミコン	01
	C257-258	UR297470	C.EL 47uF 100V			ケミコン	01
	C259	WE100400	C.PP 47pF 630V			ＰＰコン	
	C260	WE100900	C.PP 220pF 630V			ＰＰコン	02
	C261	UR297220	C.EL 22uF 100V			ケミコン	
	C262	WE100400	C.PP 47pF 630V			ＰＰコン	
	C263	WE100900	C.PP 220pF 630V			ＰＰコン	02
	C264	UR297220	C.EL 22uF 100V			ケミコン	
	C265	WE100400	C.PP 47pF 630V			ＰＰコン	
	C266-267	WE100900	C.PP 220pF 630V			ＰＰコン	02
	C268	WE100400	C.PP 47pF 630V			ＰＰコン	
	C269	WE100900	C.PP 220pF 630V			ＰＰコン	02
	C271	WE100400	C.PP 47pF 630V			ＰＰコン	
	C272	WE100900	C.PP 220pF 630V			ＰＰコン	02
	C274	WE100400	C.PP 47pF 630V			ＰＰコン	
	C275	WE100900	C.PP 220pF 630V			ＰＰコン	02
	C277	WE100400	C.PP 47pF 630V			ＰＰコン	
	C278	WE100900	C.PP 220pF 630V			ＰＰコン	02
	C280-286	UR068100	C.EL 100uF 50V			ケミコン	01
	C287-293	WE100100	C.PP 15pF 630V			ＰＰコン	
	C294-300	WE102500	C.PP 4700pF 100V			ＰＰコン	01
	C303	UR267470	C.EL 47uF 50V			ケミコン	01
	C304-305	UR297220	C.EL 22uF 100V			ケミコン	
	C306	WE100500	C.PP 100pF 630V			ＰＰコン	
⚠	C307	UU297220	C.EL 22uF 100V			ケミコン	01
	C308-309	WE100500	C.PP 100pF 630V			ＰＰコン	
⚠	C310	UU297220	C.EL 22uF 100V			ケミコン	01
	C311-312	WE100500	C.PP 100pF 630V			ＰＰコン	
⚠	C313	UU297220	C.EL 22uF 100V			ケミコン	01
	C314-315	WE100500	C.PP 100pF 630V			ＰＰコン	
⚠	C316	UU297220	C.EL 22uF 100V			ケミコン	01
	C317-318	WE100500	C.PP 100pF 630V			ＰＰコン	

＊New Parts　＊新規部品

P.C.B. MAIN

	Ref No.	Part No.	Description		Remarks	Markets	部 品 名	ﾗﾝｸ
⚠	C319	UU297220	C.EL	22uF 100V			ケミコン	01
	C320-321	WE100500	C.PP	100pF 630V			ＰＰコン	
⚠	C322	UU297220	C.EL	22uF 100V			ケミコン	01
	C323-324	WE100500	C.PP	100pF 630V			ＰＰコン	
⚠	C325	UU297220	C.EL	22uF 100V			ケミコン	01
	C326	WE100500	C.PP	100pF 630V			ＰＰコン	
*	C327-333	WP421000	C.PP	0.047uF 100V			ＰＰコン	
	C341	UR296470	C.EL	4.7uF 100V			ケミコン	01
	C342	UR238220	C.EL	220uF 16V			ケミコン	01
	C343	UR067470	C.EL	47uF 50V			ケミコン	01
	C346-347	UR397100	C.EL	10uF 100V			ケミコン	03
	C350-351	UR397100	C.EL	10uF 100V			ケミコン	03
	C354-355	UR397100	C.EL	10uF 100V			ケミコン	03
*	C359	WQ239200	C.EL	18000 71.0V FOR.			ケミコン	
	C360	WN165500	C.PP	0.022uF 100V			ＰＰコン	01
*	C363	WQ239200	C.EL	18000 71.0V FOR.			ケミコン	
	C364	WN165500	C.PP	0.022uF 100V			ＰＰコン	01
	C368	WN165500	C.PP	0.022uF 100V			ＰＰコン	01
	C369	WJ605000	C.MYLAR	0.01uF 50V J			マイラーコン	01
	C371-374	WJ605000	C.MYLAR	0.01uF 50V J			マイラーコン	01
	C376	WN165500	C.PP	0.022uF 100V			ＰＰコン	01
	C377	WJ605000	C.MYLAR	0.01uF 50V J			マイラーコン	01
	C378	WN165500	C.PP	0.022uF 100V			ＰＰコン	01
	C383-384	WN165500	C.PP	0.022uF 100V			ＰＰコン	01
	C385-386	WJ605000	C.MYLAR	0.01uF 50V J			マイラーコン	01
	C389-393	WJ605000	C.MYLAR	0.01uF 50V J			マイラーコン	01
	C394-395	WN165500	C.PP	0.022uF 100V			ＰＰコン	01
	C396	WJ605000	C.MYLAR	0.01uF 50V J			マイラーコン	01
	C397	WN165500	C.PP	0.022uF 100V			ＰＰコン	01
	C398	WN165500	C.PP	0.022uF 100V		UCRTKABGEL	ＰＰコン	01
	C399	WJ605000	C.MYLAR	0.01uF 50V J		UCRTKABGEL	マイラーコン	01
	C400	WJ605000	C.MYLAR	0.01uF 50V J		UCRTKABGEL	マイラーコン	01
	C401	WJ605000	C.MYLAR	0.01uF 50V J			マイラーコン	01
	C402	WN165500	C.PP	0.022uF 100V			ＰＰコン	01
	C403	WJ605000	C.MYLAR	0.01uF 50V J		UCRTKABGEL	マイラーコン	01
	C404	WN165500	C.PP	0.022uF 100V		UCRTKABGEL	ＰＰコン	01
	D250-251	VH282500	DIODE	RLS245			ダイオード	01
	D252-258	VT332900	DIODE	1SS355			ダイオード	01
	D259-262	VH282500	DIODE	RLS245			ダイオード	01
	D264	VU992600	DIODE.ZENR	MA8051-M 5.1V			ツェナーダイオード	01
	D265-278	VT332900	DIODE	1SS355			ダイオード	01
⚠	D279-285	VG437500	DIODE.ZENR	MTZJ5.1C 5.1V			ツェナーダイオード	01
	D286-299	VH282500	DIODE	RLS245			ダイオード	01
	D300	VU992000	DIODE.ZENR	MA8047 4.7V			ツェナーダイオード	01
⚠	D301	WD890200	DIODE.BRG	D15XBN20 30A 200V			ダイオートブリッジ	06
	D302	VT332900	DIODE	1SS355			ダイオード	01
	D304	VT332900	DIODE	1SS355		UCRTKABGEL	ダイオード	01
	D305-307	VT332900	DIODE	1SS355			ダイオード	01
	D313	VT332900	DIODE	1SS355		UCRTKABGEL	ダイオード	01
	D314	VT332900	DIODE	1SS355			ダイオード	01
	G250	V5995800	PLATE.GND				アースプレート	
	Q250-256	WH199400	IC	HN4C06J			トランジスタアレイ	01

※ New Parts ＊新規部品

P.C.B. MAIN

	Ref No.	Part No.	Description		Remarks	Markets	部 品 名	ランク
	Q257-263	WH372100	TR	KTA1517S GR TP			トランジスタ	01
	Q264	WC139600	TR	KTC3911S GR BL			トランジスタ	01
	Q265	WH372100	TR	KTA1517S GR TP			トランジスタ	01
⚠	Q266	VC938500	TR	2SC3852			トランジスタ	02
⚠	Q267	VC614000	TR	2SB1274 Q,R,S			トランジスタ	02
	Q268	WH372100	TR	KTA1517S GR TP			トランジスタ	01
	Q269-277	WC139600	TR	KTC3911S GR BL			トランジスタ	01
	Q278-284	V3966800	TR	2SA949 O,Y			トランジスタ	02
⚠	Q286-292	VR325600	TR	2SC2229 O,Y			トランジスタ	01
⚠	Q293-299	VK432900	TR	2SD1915F S,T			トランジスタ	01
⚠	Q307-313	WD281200	TR.PAIR	A2151/C6011 O,P,Y			ペアトランジスタ	07
	Q314-320	WC139600	TR	KTC3911S GR BL			トランジスタ	01
	Q321	WH372100	TR	KTA1517S GR TP			トランジスタ	01
	Q340-346	WC139600	TR	KTC3911S GR BL			トランジスタ	01
	Q360	WG408900	TR	2SC5291 S,T			トランジスタ	03
⚠	Q361	WG408800	TR	2SA2168 S,T			トランジスタ	03
	Q362	WG408900	TR	2SC5291 S,T			トランジスタ	03
⚠	Q363	WG408800	TR	2SA2168 S,T			トランジスタ	03
	Q364	WG408900	TR	2SC5291 S,T			トランジスタ	03
⚠	Q365	WG408800	TR	2SA2168 S,T			トランジスタ	03
	Q366	WG408900	TR	2SC5291 S,T			トランジスタ	03
⚠	Q367	WG408800	TR	2SA2168 S,T			トランジスタ	03
	Q368	WG408900	TR	2SC5291 S,T			トランジスタ	03
⚠	Q369	WG408800	TR	2SA2168 S,T			トランジスタ	03
	Q370	WG408900	TR	2SC5291 S,T			トランジスタ	03
⚠	Q371	WG408800	TR	2SA2168 S,T			トランジスタ	03
	Q372	WG408900	TR	2SC5291 S,T			トランジスタ	03
⚠	Q373	WG408800	TR	2SA2168 S,T			トランジスタ	03
	R271-272	HV757270	R.CAR.FP	27K Ω 1/4W			不燃化カーボン抵抗	01
	R355-358	HV757270	R.CAR.FP	27K Ω 1/4W			不燃化カーボン抵抗	01
	R366	HV757100	R.CAR.FP	10K Ω 1/4W			不燃化カーボン抵抗	01
	R367	HV757160	R.CAR.FP	16K Ω 1/4W			不燃化カーボン抵抗	01
	R368	HV757200	R.CAR.FP	20K Ω 1/4W			不燃化カーボン抵抗	01
	R379	HV755100	R.CAR.FP	100 Ω 1/4W			不燃化カーボン抵抗	01
	R381	HV755100	R.CAR.FP	100 Ω 1/4W			不燃化カーボン抵抗	01
	R383	HV755100	R.CAR.FP	100 Ω 1/4W			不燃化カーボン抵抗	01
	R385	HV755100	R.CAR.FP	100 Ω 1/4W			不燃化カーボン抵抗	01
	R387	HV755100	R.CAR.FP	100 Ω 1/4W			不燃化カーボン抵抗	01
	R389	HV755100	R.CAR.FP	100 Ω 1/4W			不燃化カーボン抵抗	01
	R391	HV755100	R.CAR.FP	100 Ω 1/4W			不燃化カーボン抵抗	01
⚠	R401	HV754100	R.CAR.FP	10 Ω 1/4W			不燃化カーボン抵抗	01
⚠	R403	HV754100	R.CAR.FP	10 Ω 1/4W			不燃化カーボン抵抗	01
	R404	V3946100	R.MTL.OXD	2.7K Ω 1/2W			酸化金属被膜抵抗	01
	R405	V3945100	R.MTL.OXD	390 Ω 1/2W			酸化金属被膜抵抗	
	R406	V3945500	R.MTL.OXD	820 Ω 1/2W			酸化金属被膜抵抗	
⚠	R407	HV755120	R.CAR.FP	120 Ω 1/4W			不燃化カーボン抵抗	01
	R408	V3946100	R.MTL.OXD	2.7K Ω 1/2W			酸化金属被膜抵抗	01
	R409	V3945100	R.MTL.OXD	390 Ω 1/2W			酸化金属被膜抵抗	
	R410	V3945500	R.MTL.OXD	820 Ω 1/2W			酸化金属被膜抵抗	
⚠	R411	HV755120	R.CAR.FP	120 Ω 1/4W			不燃化カーボン抵抗	01
	R412	V3946100	R.MTL.OXD	2.7K Ω 1/2W			酸化金属被膜抵抗	01
	R413	V3945100	R.MTL.OXD	390 Ω 1/2W			酸化金属被膜抵抗	

＊New Parts ＊新規部品

P.C.B. MAIN

	Ref No.	Part No.	Description		Remarks	Markets	部 品 名	ランク
	R414	V3945500	R. MTL. OXD	820 Ω 1/2W			酸化金属被膜抵抗	
⚠	R415	HV755120	R. CAR. FP	120 Ω 1/4W			不燃化カーボン抵抗	01
	R416	V3946100	R. MTL. OXD	2. 7K Ω 1/2W			酸化金属被膜抵抗	01
	R417	V3945100	R. MTL. OXD	390 Ω 1/2W			酸化金属被膜抵抗	
	R418	V3945500	R. MTL. OXD	820 Ω 1/2W			酸化金属被膜抵抗	
⚠	R419	HV755120	R. CAR. FP	120 Ω 1/4W			不燃化カーボン抵抗	01
	R420	V3946100	R. MTL. OXD	2. 7K Ω 1/2W			酸化金属被膜抵抗	01
	R421	V3945100	R. MTL. OXD	390 Ω 1/2W			酸化金属被膜抵抗	
	R422	V3945500	R. MTL. OXD	820 Ω 1/2W			酸化金属被膜抵抗	
⚠	R423	HV755120	R. CAR. FP	120 Ω 1/4W			不燃化カーボン抵抗	01
	R424	V3946100	R. MTL. OXD	2. 7K Ω 1/2W			酸化金属被膜抵抗	01
	R425	V3945100	R. MTL. OXD	390 Ω 1/2W			酸化金属被膜抵抗	
	R426	V3945500	R. MTL. OXD	820 Ω 1/2W			酸化金属被膜抵抗	
⚠	R427	HV755120	R. CAR. FP	120 Ω 1/4W			不燃化カーボン抵抗	01
	R428	V3946100	R. MTL. OXD	2. 7K Ω 1/2W			酸化金属被膜抵抗	01
	R429	V3945100	R. MTL. OXD	390 Ω 1/2W			酸化金属被膜抵抗	
	R430	V3945500	R. MTL. OXD	820 Ω 1/2W			酸化金属被膜抵抗	
⚠	R431	HV755120	R. CAR. FP	120 Ω 1/4W			不燃化カーボン抵抗	01
	R432-438	V3945600	R. MTL. OXD	1K Ω 1/2W			酸化金属被膜抵抗	
⚠	R439-445	HV753470	R. CAR. FP	4. 7 Ω 1/4W			不燃化カーボン抵抗	01
⚠	R446-452	HV755220	R. CAR. FP	220 Ω 1/4W			不燃化カーボン抵抗	01
⚠	R453-466	HV753470	R. CAR. FP	4. 7 Ω 1/4W			不燃化カーボン抵抗	01
	R467-473	WG471300	R. WW	0. 22 Ω x2 5W	RF-5EGKR22		セメント抵抗	01
	R496-502	V8070200	R. MTL. FLM	4. 7 Ω 1W			金属被膜抵抗	
	R519-525	HV754100	R. CAR. FP	10 Ω 1/4W			不燃化カーボン抵抗	01
⚠	R550	V8070000	R. MTL. FLM	1 Ω 1W			金属被膜抵抗	01
⚠	R552	V8070000	R. MTL. FLM	1 Ω 1W			金属被膜抵抗	01
⚠	R554	V8070000	R. MTL. FLM	1 Ω 1W			金属被膜抵抗	01
	R571-573	HV753470	R. CAR. FP	4. 7 Ω 1/4W			不燃化カーボン抵抗	01
	R581	HV753470	R. CAR. FP	4. 7 Ω 1/4W			不燃化カーボン抵抗	01
	R583	HV753470	R. CAR. FP	4. 7 Ω 1/4W			不燃化カーボン抵抗	01
	R585-586	HV753470	R. CAR. FP	4. 7 Ω 1/4W			不燃化カーボン抵抗	01
	R593-594	HV753470	R. CAR. FP	4. 7 Ω 1/4W			不燃化カーボン抵抗	01
	R595	HV753470	R. CAR. FP	4. 7 Ω 1/4W		UCRTKABGEL	不燃化カーボン抵抗	01
	R596	HV753470	R. CAR. FP	4. 7 Ω 1/4W		UCRTKABGEL	不燃化カーボン抵抗	01
	RY250	WE648700	RELAY	DC DH24D2-O-Q		UCRTKABGEL	リレー ２４Ｖ	06
	RY251	WE648700	RELAY	DC DH24D2-O-Q			リレー ２４Ｖ	06
	RY252-253	V6322600	RELAY	DC DH24D2-OT(M)-SL			リレー ２４Ｖ	04
	RY254	WM959000	RELAY	DC24V G5PA-28-MC		UCRTKABGEL	リレー ２４Ｖ	
	RY255-257	V6322600	RELAY	DC DH24D2-OT(M)-SL			リレー ２４Ｖ	04
	TE250	WK561000	TERM. SP	6P MST-207V1-01 NC		JUCRTA	スピーカーターミナル	05
*	TE250	WK561100	TERM. SP	6P MST-207V1-01 WC		KBGEL	スピーカーターミナル	
	TE251	WK560800	TERM. SP	4P MST-204V1-01 NC		JUCRTA	スピーカーターミナル	04
*	TE251	WK560900	TERM. SP	4P MST-204V1-01 WC		KBGEL	スピーカーターミナル	
	TE252	WK560800	TERM. SP	4P MST-204V1-01 NC		JUCRTA	スピーカーターミナル	04
*	TE252	WK560900	TERM. SP	4P MST-204V1-01 WC		KBGEL	スピーカーターミナル	
	TE253	WK560800	TERM. SP	4P MST-204V1-01 NC		UCRTA	スピーカーターミナル	04
*	TE253	WK560900	TERM. SP	4P MST-204V1-01 WC		KBGEL	スピーカーターミナル	
	TE254	WK560800	TERM. SP	4P MST-204V1-01 NC		JUCRTA	スピーカーターミナル	04
*	TE254	WK560900	TERM. SP	4P MST-204V1-01 WC		KBGEL	スピーカーターミナル	
		WN440100	DAMPER	15x80 t=2			ダンパー	01
		VT669300	SCR. PW. HD	3x8-8 MFC2			ＰＷヘッドＢタイトネジ	01

※ New Parts ＊新規部品

P.C.B. POWER

	Ref No.	Part No.	Description		Remarks	Markets	部 品 名	ﾗﾝｸ
*		WQ134500	P. C. B.	POWER		J	ＰＣＢ　ＰＯＷＥＲ	
*		WQ134600	P. C. B.	POWER		U	ＰＣＢ　ＰＯＷＥＲ	
*		WQ134700	P. C. B.	POWER		C	ＰＣＢ　ＰＯＷＥＲ	
*		WQ134800	P. C. B.	POWER		R	ＰＣＢ　ＰＯＷＥＲ	
*		WQ134900	P. C. B.	POWER		T	ＰＣＢ　ＰＯＷＥＲ	
*		WQ135000	P. C. B.	POWER		K	ＰＣＢ　ＰＯＷＥＲ	
*		WQ135100	P. C. B.	POWER		A	ＰＣＢ　ＰＯＷＥＲ	
*		WQ135200	P. C. B.	POWER		B	ＰＣＢ　ＰＯＷＥＲ	
*		WQ135300	P. C. B.	POWER		GE	ＰＣＢ　ＰＯＷＥＲ	
*		WQ135400	P. C. B.	POWER		L	ＰＣＢ　ＰＯＷＥＲ	
	CB1	WN103000	CLIP. FUSE	TP00351-31		UCTBGE	ヒューズクリップ	01
	CB2	WN103000	CLIP. FUSE	TP00351-31		UCTBGE	ヒューズクリップ	01
	CB3-4	WN103000	CLIP. FUSE	TP00351-31			ヒューズクリップ	01
⚠	CB6	VG879900	CN. BS. PIN	2P			ベースピン	01
*	CB7	V9377900	CN. BS. PIN	4P		RL	ベース付ポスト	
*	CB8	V9377800	CN. BS. PIN	3P		RL	ベース付ポスト	
⚠	CB9	WN103000	CLIP. FUSE	TP00351-31		RL	ヒューズクリップ	01
⚠	CB10	WN103000	CLIP. FUSE	TP00351-31		RL	ヒューズクリップ	01
	CB11	LB919110	CN. BS. PIN	11P SE			ベースツキポスト	01
	CB12	VB858400	CN. BS. PIN	5P			ベースピン	01
*	CB14	VL954900	SOCKET	7P TE			ＪＬ　ソケット	01
	CB15	LB918060	CN. BS. PIN	6P			ベース付ポスト	01
	CB16	LB918100	CN. BS. PIN	10P			ベース付ポスト	02
	CB17	LB918060	CN. BS. PIN	6P			ベース付ポスト	01
	CB18	VM859700	CN. BS. PIN	16P			ＦＦＣコネクター	01
	CB19	VB389900	CN. BS. PIN	3P			ベースピン	01
	CB20	LB918040	CN. BS. PIN	4P			ベース付ポスト	01
	CB23	VB390000	CN. BS. PIN	4P			ベースピン	01
	CB24	LB918090	CN. BS. PIN	9P			ベース付ポスト	01
	CB25	VB858400	CN. BS. PIN	5P			ベースピン	01
	C1	UU266220	C. EL	2. 2uF　50V			ケミコン　ＦＷ	01
	C2	UR266220	C. EL	2. 2uF　50V			ケミコン	
	C3	WJ605000	C. MYLAR	0. 01uF　50V J			マイラーコン	01
	C4	WJ361200	C. POL. MTL	0. 047uF　400V		JUC	メタライズドポリコン	
	C4	WD054200	C. POL. MTL	0. 047uF　630V		RL	メタライズドポリコン	02
*	C4	WJ361800	C. POL. MTL	0. 022uF　630V		TKABGE	メタライズドポリコン	
	C5	UU266100	C. EL	1uF　50V			ケミコン	01
*	C6	WJ604500	C. MYLAR	4700pF　50V			マイラーコン	
	C7	WB696300	C. POL. MTL	0. 1uF　400V		JUC	メタライズドポリコン	
*	C7	WF081500	C. PP	0. 047uF　630V J		RTKABGEL	ＰＰコン	
*	C7	WF081500	C. PP	0. 047uF　630V J			ＰＰコン	
	C8	V6185300	C. CE. SAFTY	0. 01uF　275V			規格認定コンデンサ	01
	C9	WE102900	C. PP	0. 01uF　100V			ＰＰコン	
	C10	UU249330	C. EL	3300uF　25V		JUCTKABGE	ケミコン　ＦＷ	04
*	C10	WD047300	C. EL	3300uF　50V		RL	ケミコン　ＫＭＱ	
	C11	WN165500	C. PP	0. 022uF　100V			ＰＰコン	01
	C12	VR324700	C. MYLAR	0. 022uF　100V			マイラーコン	
	C13	WN165500	C. PP	0. 022uF　100V			ＰＰコン	01
	C14	UR068220	C. EL	220uF　50V			ケミコン	01
	C15	UR058220	C. EL	220uF　35V			ケミコン	01
	C16	UU23A150	C. EL	15000uF　16V			ケミコン　ＦＷ	06
* ⚠	C17	UR04A100	C. EL	10000uF　25V			ケミコン	

＊New Parts　＊新規部品

P.C.B. POWER

	Ref No.	Part No.	Description		Remarks	Markets	部 品 名	ﾗﾝｸ
	C18	UR03A100	C.EL	10000uF 16V			ケミコン	
	C19	UR078220	C.EL	220uF 63V			ケミコン	01
	C20	UR267100	C.EL	10uF 50V			ケミコン	
*	C21	UR04A100	C.EL	10000uF 25V			ケミコン	
	C22	UR068100	C.EL	100uF 50V			ケミコン	01
	C23	UR049100	C.EL	1000uF 25V			ケミコン	01
	C24	WA747600	C.MYLAR	1000pF 100V			マイラーコン	01
*	C25-28	WQ712000	C.EL	10uF 50V			ケミコン	
	C29	UR238100	C.EL	100uF 16V		UC	ケミコン	
	C30-31	WG218100	C.EL	100uF 16V			ケミコン	
	C32	UR266220	C.EL	2.2uF 50V			ケミコン	
	C33	WA747600	C.MYLAR	1000pF 100V			マイラーコン	01
	C34	UR038100	C.EL	100uF 16V		UC	ケミコン	
	C36	UR038100	C.EL	100uF 16V			ケミコン	
*	C40-41	WN164600	C.PP	1000pF 100V			ＰＰコン	01
	C42	WN165300	C.PP	0.01uF 100V			ＰＰコン	01
	C43	WA747600	C.MYLAR	1000pF 100V			マイラーコン	01
	C44	WG218100	C.EL	100uF 16V			ケミコン	
*	C45-46	WQ712000	C.EL	10uF 50V			ケミコン	
	C47	UU249330	C.EL	3300uF 25V		JTKABGE	ケミコン ＦＷ	04
	C48-49	UR058220	C.EL	220uF 35V			ケミコン	01
	C50	UR03A150	C.EL	15000uF 16V			ケミコン	05
	C54	UR049680	C.EL	6800uF 25V			ケミコン	
	C59	UR049680	C.EL	6800uF 25V			ケミコン	
	C60	UR049330	C.CE	3300uF 25V			ケミコン	
	C68-70	UR267100	C.EL	10uF 50V			ケミコン	
	C72	UR348100	C.EL	100uF 25V			ケミコン	01
	C73-74	UU238100	C.EL	100uF 16V			ケミコン	01
	C75	WA747600	C.MYLAR	1000pF 100V			マイラーコン	01
	C91-92	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C93	US035100	C.CE.CHP	0.1uF 16V B			チップセラコン	01
	D1-5	VT332900	DIODE	1SS355			ダイオード	01
	D6	VU993800	DIODE.ZENR	MA8068-M 6.8V			ツェナーダイオード	01
	D7	VU995400	DIODE.ZENR	MA8100-M 10V			ツェナーダイオード	
	D8	VT332900	DIODE	1SS355			ダイオード	01
	D9	VU994200	DIODE.ZENR	MA8075-M 7.5V			ツェナーダイオード	01
⚠	D10-11	WH471700	DIODE.BRG	DB105 1A 600V			ダイオートブリッジ	02
	D12	VT332900	DIODE	1SS355			ダイオード	01
* ⚠	D13	WP331500	DIODE.BRG	D20XBS6-7101 20A			ダイオードブリッジ	
⚠	D14	V4269600	DIODE.BRG	D2SBA20 1.5A200V		JBGE	ダイオードブリツジ	04
⚠	D14	WH487300	DIODE.BRG	RS203M 2.0A 200V		UCRTKAL	ダイオードブリッジ	02
⚠	D15	V4269600	DIODE.BRG	D2SBA20 1.5A200V		JBGE	ダイオードブリツジ	04
⚠	D15	WH487300	DIODE.BRG	RS203M 2.0A 200V		UCRTKAL	ダイオードブリッジ	02
	D16-18	VT332900	DIODE	1SS355			ダイオード	01
⚠	D19	V4269600	DIODE.BRG	D2SBA20 1.5A200V		JBGE	ダイオードブリツジ	04
⚠	D19	WH487300	DIODE.BRG	RS203M 2.0A 200V		UCRTKAL	ダイオードブリッジ	02
⚠	D20	WN629800	DIODE.BRG	4A 60V D4SBS6-7101			ダイオードブリッジ	05
	D21	VT332900	DIODE	1SS355			ダイオード	01
⚠	D22-23	VU997600	DIODE.ZENR	MA8160-H 16.7V			ツェナーダイオード	01
	D27	V2376600	DIODE.SHOT	RB500V-40		UC	ショットキーダイオード	01
	D30	VT332900	DIODE	1SS355			ダイオード	01
	D33	VU990500	DIODE.ZENR	MA8030-L 2.9V		UC	ツェナーダイオード	01

＊New Parts ＊新規部品

P.C.B. POWER

		Ref No.	Part No.	Description		Remarks	Markets	部 品 名	ﾗﾝｸ
	⚠	D35	VH282500	DIODE	RLS245			ダイオード	01
		D36	VU993400	DIODE.ZENR	MA8062-M 6.2V			ツェナーダイオード	01
		D37-38	VU996600	DIODE.ZENR	MA8130-M 13V			ツェナーダイオード	01
	⚠	D39-41	VH282500	DIODE	RLS245			ダイオード	01
		D43	VU999100	DIODE.ZENR	MA8240-M 24V			ツェナーダイオード	01
		D44	VU993400	DIODE.ZENR	MA8062-M 6.2V			ツェナーダイオード	01
		D45	VT332900	DIODE	1SS355			ダイオード	01
		D46	VU990500	DIODE.ZENR	MA8030-L 2.9V			ツェナーダイオード	01
*	⚠	F1	WQ211200	FUSE	10A 125V		JUCRL	ヒューズ	
	⚠	F1	WB760600	FUSE	T6.3A 250V		TKABGE	ヒューズ	01
	⚠	F2	WG410300	FUSE	4A 125V		UC	ヒューズ	01
	⚠	F2	VT942900	FUSE	T2.5A 250V		TBGE	ヒューズ	01
	⚠	F3	WB760600	FUSE	T6.3A 250V		RL	ヒューズ	01
	⚠	IC1-2	WJ688100	PHOT.CPL	EL816(B)			フォトカプラ	01
	⚠	IC3	iG001180	IC	TC4013BP FF			ロジックＩＣ	05
	⚠	IC4	X6248A00	IC	NJM2388F33		UC	電源ＩＣ	04
	⚠	IC5	X8274A00	IC	NJM2388F09			電源ＩＣ	04
	⚠	IC6-7	X6143A00	IC	NJM2388F05 5.0V			電源ＩＣ	04
*	⚠	IC13-14	X0515B00	IC	LM61CIZ THERMAL			電源ＩＣ	
	⚠	IC15	X4153A00	IC	KIA7812API			電源ＩＣ	02
	⚠	IC16	X4154A00	IC	KIA7912PI			電源ＩＣ	
		PN1-7	V9637500	PIN	L=70 #18			スタイルピン	
		Q1	WC435100	TR.DGT	KRC104S-RTK			デジタルトランジスタ	01
		Q2-3	WC529400	TR	KTC3875S Y GR RTK			トランジスタ	01
	⚠	Q4	VR043100	FET	2SK208 Y			チップＦＥＴ	01
		Q5	WC529400	TR	KTC3875S Y GR RTK		JUCTKABGE	トランジスタ	01
	⚠	Q6	WC741200	FET	2SK3850			ＦＥＴ	03
	⚠	Q7	WG408800	TR	2SA2168 S,T			トランジスタ	03
	⚠	Q8	WC529500	TR	KTA1504S Y GR RTK			トランジスタ	
	⚠	Q9	WG538600	TR	KTA1046-Y-U/P			トランジスタ	02
	⚠	Q10	WC529500	TR	KTA1504S Y GR RTK			トランジスタ	
	⚠	Q11	WC529400	TR	KTC3875S Y GR RTK			トランジスタ	01
		Q12	WC434800	TR.DGT	KRA102S-RTK/P		UC	デジタルトランジスタ	01
		Q13	WC434900	TR.DGT	KRA104S-RTK			デジタルトランジスタ	01
		Q17-19	VR043100	FET	2SK208 Y			チップＦＥＴ	01
	⚠	Q20-21	WF691400	TR	2SD2014			トランジスタ	03
		Q22	WF691300	TR	2SB1257			トランジスタ	03
		Q24	WC434900	TR.DGT	KRA104S-RTK			デジタルトランジスタ	01
		Q41	WC529500	TR	KTA1504S Y GR RTK			トランジスタ	
		Q44	WC435000	TR.DGT	KRC102S-RTK			デジタルトランジスタ	01
		R13	HF356220	R.CAR	2.2K Ω 1/2W			カーボン抵抗	
	⚠	R27	HL002220	R.MTL.OXD	0.22 Ω 1/2W			酸化金属被膜抵抗	01
	⚠	R28	HV754220	R.CAR.FP	22 Ω 1/4W			不燃化カーボン抵抗	01
	⚠	R29	HL002220	R.MTL.OXD	0.22 Ω 1/2W			酸化金属被膜抵抗	01
	⚠	R31	HV755100	R.CAR.FP	100 Ω 1/4W			不燃化カーボン抵抗	01
	⚠	R32	HV753100	R.CAR.FP	1 Ω 1/4W			不燃化カーボン抵抗	01
		R33	HF353470	R.CAR	4.7 Ω 1/2W			カーボン抵抗	
	⚠	R34	HV754100	R.CAR.FP	10 Ω 1/4W			不燃化カーボン抵抗	01
		R35	HV755100	R.CAR.FP	100 Ω 1/4W			不燃化カーボン抵抗	01
	⚠	R37	HL002220	R.MTL.OXD	0.22 Ω 1/2W			酸化金属被膜抵抗	01
		R42	HV755100	R.CAR.FP	100 Ω 1/4W			不燃化カーボン抵抗	01
	⚠	R43	V8070000	R.MTL.FLM	1 Ω 1W			金属被膜抵抗	01

＊New Parts ＊新規部品

P.C.B. POWER and P.C.B. A-VIDEO

	Ref No.	Part No.	Description	Remarks	Markets	部 品 名	ﾗﾝｸ
⚠	R51	WJ787500	R.MTL.FLM 0.22 Ω 1W		UC	金属被膜抵抗	01
⚠	R65-67	HV753470	R.CAR.FP 4.7 Ω 1/4W			不燃化カーボン抵抗	01
⚠	R71-73	HV755100	R.CAR.FP 100 Ω 1/4W			不燃化カーボン抵抗	01
⚠	RY1	V9366900	RELAY DLS9D1-0(M)0.25W			リレー ９Ｖ ＴＶ－８	05
	ST1-3	WG095100	SCR.TERM M3			スクリューターミナル	01
	ST4-5	WA246200	SCR.TERM 3.5			スクリューターミナル	
	ST6	V4040500	SCR.TERM M3			スクリュー／ターミナル	01
＊ ⚠	SW1	WB493700	VOLT.SELCT R8140246		RL	電圧切替器	
＊ ⚠	T1	YA129A00	TRANS.PWR		J	電源トランス	
＊ ⚠	T1	YA291A00	TRANS.PWR		UC	電源トランス	
＊ ⚠	T1	X7034A00	TRANS.PWR		RL	電源トランス	
＊ ⚠	T1	X7035A00	TRANS.PWR		TKABGE	電源トランス	
⚠	TE1	VU543100	OUTLET.AC 2P		JUC	ＡＣアウトレット	03
⚠	TE1	V5867400	OUTLET.AC 2P		RT	ＡＣアウトレット	03
⚠	TE1	VT915000	OUTLET.AC 1P		A	ＡＣアウトレット	06
⚠	TE1	VU543300	OUTLET.AC 1P		B	ＡＣアウトレット	05
⚠	TE1	VU543400	OUTLET.AC 2P		GEL	ＡＣアウトレット	05
⚠	TE2	WB893300	AC INLET R-30190		JBGE	ＡＣインレット ２Ｐ	03
⚠	TE2	WB782600	AC INLET R-30190(26)		UCRTKAL	ＡＣインレット ２Ｐ	
⚠	TH1	VV458400	SW.POLY RUEF600 6.00A 30V			ポリスイッチ	04
		WA143800	DAMPER 55x24x2			ダンパー	
		VT669300	SCR.PW.HD 3x8-8 MFC2			ＰＷヘッドＢタイトネジ	01
＊		WQ139800	P.C.B. A-VIDEO		J	ＰＣＢ Ａ－ＶＩＤＥＯ	
＊		WQ139900	P.C.B. A-VIDEO		UCRK	ＰＣＢ Ａ－ＶＩＤＥＯ	
＊		WQ140000	P.C.B. A-VIDEO		TABGEL	ＰＣＢ Ａ－ＶＩＤＥＯ	
	CB201-202	V8875300	CN.JE 13P SE			ＪＥコネクタープラグ	01
	CB203	VQ044500	CN.BS.PIN 11P			ＦＦＣコネクター	01
	CB204	VP113500	CN.BS.PIN 10P			ＦＦＣコネクター	01
	CB209	VB858200	CN.BS.PIN 3P		UCRTKABGEL	ベースピン	01
	C2001-2009	US064100	C.CE.CHP 0.01uF 50V B		J	チップセラコン	01
	C2010-2011	US135100	C.CE.CHP 0.1uF 16V		J	チップセラコン	01
	C2021-2023	US060800	C.CE.CHP 8pF 50V B		J	チップセラコン	01
	C2024-2026	US064100	C.CE.CHP 0.01uF 50V B		J	チップセラコン	01
	C2027-2029	US060800	C.CE.CHP 8pF 50V B			チップセラコン	01
	C2031	US135100	C.CE.CHP 0.1uF 16V			チップセラコン	01
	C2032	UR237470	C.EL 47uF 16V			ケミコン	01
	C2033	US135100	C.CE.CHP 0.1uF 16V			チップセラコン	01
	C2034	UR237470	C.EL 47uF 16V			ケミコン	01
	C2035	US135100	C.CE.CHP 0.1uF 16V			チップセラコン	01
	C2036-2037	UR237470	C.EL 47uF 16V			ケミコン	01
	C2038	US135100	C.CE.CHP 0.1uF 16V			チップセラコン	01
	C2041	US135100	C.CE.CHP 0.1uF 16V			チップセラコン	01
	C2042	UR237470	C.EL 47uF 16V			ケミコン	01
	C2043	US135100	C.CE.CHP 0.1uF 16V			チップセラコン	01
	C2044	UR237470	C.EL 47uF 16V			ケミコン	01
	C2045	US135100	C.CE.CHP 0.1uF 16V			チップセラコン	01
	C2046-2047	UR237470	C.EL 47uF 16V			ケミコン	01
	C2048	US135100	C.CE.CHP 0.1uF 16V			チップセラコン	01
	C2051	US135100	C.CE.CHP 0.1uF 16V			チップセラコン	01

＊New Parts ＊新規部品

P.C.B. A-VIDEO

Ref No.	Part No.	Description			Remarks	Markets	部 品 名	ランク
C2052	UR237470	C. EL	47uF	16V			ケミコン	01
C2053	US135100	C. CE. CHP	0. 1uF	16V			チップセラコン	01
C2054	UR237470	C. EL	47uF	16V			ケミコン	01
C2055	US135100	C. CE. CHP	0. 1uF	16V			チップセラコン	01
C2056-2057	UR237470	C. EL	47uF	16V			ケミコン	01
C2058	US135100	C. CE. CHP	0. 1uF	16V			チップセラコン	01
C2061	US135100	C. CE. CHP	0. 1uF	16V			チップセラコン	01
C2062	UR237470	C. EL	47uF	16V			ケミコン	01
C2063	US135100	C. CE. CHP	0. 1uF	16V			チップセラコン	01
C2064	UR237470	C. EL	47uF	16V			ケミコン	01
C2065	US135100	C. CE. CHP	0. 1uF	16V			チップセラコン	01
C2066	UR237470	C. EL	47uF	16V			ケミコン	01
C2067	UR238330	C. EL	330uF	16V			ケミコン	01
C2068-2069	US135100	C. CE. CHP	0. 1uF	16V			チップセラコン	01
C2070-2071	UR238330	C. EL	330uF	16V			ケミコン	01
C2072	US135100	C. CE. CHP	0. 1uF	16V			チップセラコン	01
C2073	UR266100	C. EL	1uF	50V			ケミコン	01
C2075-2077	US060100	C. CE. CHP	1pF	50V C			チップセラコン	01
C2081	UR266220	C. EL	2. 2uF	50V			ケミコン	
C2082	UR238100	C. EL	100uF	16V			ケミコン	
C2083	US135100	C. CE. CHP	0. 1uF	16V			チップセラコン	01
C2084	US064100	C. CE. CHP	0. 01uF	50V B			チップセラコン	01
C2086	US126100	C. CE. CHP	1uF	10V			チップセラコン	01
C2109	UR238100	C. EL	100uF	16V			ケミコン	
C2111	US135100	C. CE. CHP	0. 1uF	16V			チップセラコン	01
C2112-2113	US126100	C. CE. CHP	1uF	10V			チップセラコン	01
C2131	US135100	C. CE. CHP	0. 1uF	16V			チップセラコン	01
C2132	US126100	C. CE. CHP	1uF	10V			チップセラコン	01
C2133	US135100	C. CE. CHP	0. 1uF	16V			チップセラコン	01
C2137-2138	US135100	C. CE. CHP	0. 1uF	16V			チップセラコン	01
C2140-2141	US135100	C. CE. CHP	0. 1uF	16V			チップセラコン	01
C2142	UR238100	C. EL	100uF	16V			ケミコン	
C2143-2148	UR238470	C. EL	470uF	16V			ケミコン	
C2501-2505	US135100	C. CE. CHP	0. 1uF	16V		J	チップセラコン	01
C2521-2523	US062100	C. CE. CHP	100pF	50V B			チップセラコン	01
C2524	US135100	C. CE. CHP	0. 1uF	16V			チップセラコン	01
C2525-2527	US062100	C. CE. CHP	100pF	50V B			チップセラコン	01
C2528	US135100	C. CE. CHP	0. 1uF	16V			チップセラコン	01
C2531-2533	US062270	C. CE. CHP	270pF	50V B			チップセラコン	01
C2534	US135100	C. CE. CHP	0. 1uF	16V			チップセラコン	01
C2541-2546	US135100	C. CE. CHP	0. 1uF	16V			チップセラコン	01
C2547-2548	UR238220	C. EL	220uF	16V			ケミコン	01
C2549-2552	US135100	C. CE. CHP	0. 1uF	16V			チップセラコン	01
C2553-2554	UR238220	C. EL	220uF	16V			ケミコン	01
C2555	US135100	C. CE. CHP	0. 1uF	16V			チップセラコン	01
C2561-2564	UR237470	C. EL	47uF	16V			ケミコン	01
C2571-2572	UR238100	C. EL	100uF	16V			ケミコン	
C2573-2574	US135100	C. CE. CHP	0. 1uF	16V			チップセラコン	01
C2581-2582	UR237470	C. EL	47uF	16V			ケミコン	01
C2583	US062220	C. CE. CHP	220pF	50V B			チップセラコン	01
C2585	US062220	C. CE. CHP	220pF	50V B			チップセラコン	01
C2601-2602	UR237470	C. EL	47uF	16V			ケミコン	01

＊New Parts　＊新規部品

P.C.B. A-VIDEO

Ref No.	Part No.	Description		Remarks	Markets	部 品 名	ﾗﾝｸ
C2603	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
C2611	UR238470	C.EL	470uF 16V			ケミコン	
C2612	US064100	C.CE.CHP	0.01uF 50V B			チップセラコン	01
C2613	US062120	C.CE.CHP	120pF 50V B			チップセラコン	01
C2614	US062220	C.CE.CHP	220pF 50V B			チップセラコン	01
C2615	UR237100	C.EL	10uF 16V			ケミコン	
C2616	UR237470	C.EL	47uF 16V			ケミコン	01
C2617	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
C2631	UR237100	C.EL	10uF 16V		UCRTKABGEL	ケミコン	
C2632	UR266470	C.EL	4.7uF 50V		UCRTKABGEL	ケミコン	
C2633	UR238100	C.EL	100uF 16V		UCRTKABGEL	ケミコン	
C2634	UR238330	C.EL	330uF 16V		UCRTKABGEL	ケミコン	01
C2641	UR238100	C.EL	100uF 16V		UCRTKABGEL	ケミコン	
C2642	UR238100	C.EL	100uF 16V		UCRTKABGEL	ケミコン	
C2643	US135100	C.CE.CHP	0.1uF 16V		UCRTKABGEL	チップセラコン	01
C2644	US060800	C.CE.CHP	8pF 50V B		UCRK	チップセラコン	01
C2644	US060300	C.CE.CHP	3pF 50V B		TABGEL	チップセラコン	01
C2645	US060500	C.CE.CHP	5pF 50V B		UCRK	チップセラコン	01
C2645	US060300	C.CE.CHP	3pF 50V B		TABGEL	チップセラコン	01
C2646	US060500	C.CE.CHP	5pF 50V B		UCRK	チップセラコン	01
C2646	US060200	C.CE.CHP	2pF 50V B		TABGEL	チップセラコン	01
C2647-2648	US061240	C.CE.CHP	24pF 50V B		UCRTKABGEL	チップセラコン	01
C2649	UR266100	C.EL	1uF 50V		UCRTKABGEL	ケミコン	01
C2650	US062470	C.CE.CHP	470pF 50V B		UCRTKABGEL	チップセラコン	01
C2651	UR266100	C.EL	1uF 50V		UCRTKABGEL	ケミコン	01
C2652	US063120	C.CE.CHP	1200pF 50V B		UCRTKABGEL	チップセラコン	01
C2653	US135100	C.CE.CHP	0.1uF 16V		UCRTKABGEL	チップセラコン	01
C2661	UR237470	C.EL	47uF 16V		UCRTKABGEL	ケミコン	01
C2662-2663	US135100	C.CE.CHP	0.1uF 16V		UCRTKABGEL	チップセラコン	01
C2664-2665	UR238100	C.EL	100uF 16V		UCRTKABGEL	ケミコン	
C2691-2692	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
C2699-2701	US062180	C.CE.CHP	180pF 50V B			チップセラコン	01
D2001-2009	VT332900	DIODE	1SS355		J	ダイオード	01
D2061-2062	VT332900	DIODE	1SS355			ダイオード	01
D2561	VT332900	DIODE	1SS355			ダイオード	01
D2563	VT332900	DIODE	1SS355			ダイオード	01
D2581-2582	VT332900	DIODE	1SS355			ダイオード	01
D2611-2612	VT332900	DIODE	1SS355			ダイオード	01
D2631	VT332900	DIODE	1SS355		UCRTKABGEL	ダイオード	01
D2632-2633	VT332900	DIODE	1SS355		UCRTKABGEL	ダイオード	01
D2634	VT332900	DIODE	1SS355		UCRTKABGEL	ダイオード	01
D2661	VT332900	DIODE	1SS355		UCRTKABGEL	ダイオード	01
D2662	VT332900	DIODE	1SS355		UCRTKABGEL	ダイオード	01
IC201	X6757A00	IC	NJW1321FP1			ＩＣ	08
IC202	X2484A00	IC	TA1318AF			ＩＣ	07
IC203	X2904A00	IC	NJM2581M VIDEO AMP			アンプＩＣ	06
IC204-205	XS790A00	IC	TC74HC4052AF MPX		J	ロジックＩＣ	02
IC207	X7780A00	IC	NJM2566AV(TE1)			ビデオドライバー	07
IC211-214	XY550A00	IC	MM74HC4051SJX			ロジックＩＣ	01
IC215-216	X4321A00	IC	CD4051BNSR			ロジックＩＣ	01
IC217	XY877A00	IC	MM74HC4053SJX			ロジックＩＣ	01
IC218	X6742A00	IC	LA73050-TLM-E			アンプＩＣ	04

＊New Parts ＊新規部品

P.C.B. A-VIDEO

Ref No.	Part No.	Description		Remarks	Markets	部 品 名	ﾗﾝｸ
IC219	X6741A00	IC	LA7106M-TLM-E			アンプＩＣ	05
IC220	XW939A00	IC	TK15420M VIDEO AMP			アンプＩＣ	03
IC221	XY877A00	IC	MM74HC4053SJX			ロジックＩＣ	01
IC222	X7779A00	IC	LC709004A-TLM-E			ロジックＩＣ	04
IC223	XZ509A00	IC	TC74VHCU04FT INVER			ロジックＩＣ	01
IC224	X7818A00	IC	LC74782JM-8A16-TLM		UCRTKABGEL	ＩＣ	07
IC226	X6741A00	IC	LA7106M-TLM-E		UCRTKABGEL	アンプＩＣ	05
JK201	WD396200	JACK.PIN	LAP5100-1805FC		J	ピンジャック ＋ S	05
JK201	WD396100	JACK.PIN	LAP5100-1801FC		UCRTKABGEL	ピンジャック ＋ S	04
JK202	WD396400	JACK.PIN	LAP5100-1605FC		J	ピンジャック ＋ S	05
JK202-203	WD396300	JACK.PIN	LAP5100-1601FC		UCRTKABGEL	ピンジャック ＋ S	04
JK203	WD396300	JACK.PIN	LAP5100-1601FC		UCRTKABGEL	ピンジャック ＋ S	04
PJ201-203	WD398400	CN.DIN	14P YKF45-3011		J	ＤＩＮコネクタ	05
PJ204	WH382100	JACK.PIN	9P G,B,R		J	ピンジャック ９Ｐ	10
PJ204	WH382000	JACK.PIN	9P G,B,R		UCRTKABGEL	ピンジャック ９Ｐ	05
PJ205	WD398400	CN.DIN	14P YKF45-3011		J	ＤＩＮコネクタ	05
PJ206	WH381900	JACK.PIN	3P G,B,R		J	ピンジャック ３Ｐ	
PJ206	WH381800	JACK.PIN	3P G,B,R		UCRTKABGEL	ピンジャック ３Ｐ	03
Q2541-2546	VV655700	TR.DGT	DTC144EKA			デジタルトランジスタ	01
Q2601	VV556400	TR	2SC2412K Q,R,S			トランジスタ	01
Q2631	WF550000	TR	2SC3837K T146 N,P		UCRTKABGEL	トランジスタ	01
Q2632	VV556500	TR	2SA1037K Q,R,S		UCRTKABGEL	トランジスタ	01
Q2633	WF549900	TR	2SC3906K T146 R,S		UCRTKABGEL	トランジスタ	01
Q2634	VZ725900	TR	2SD1938F S,T		UCRTKABGEL	トランジスタ	01
Q2641-2642	VV556400	TR	2SC2412K Q,R,S		UCRTKABGEL	トランジスタ	01
R2010	HV753100	R.CAR.FP	1 Ω 1/4W		J	不燃化カーボン抵抗	01
R2020	HV753100	R.CAR.FP	1 Ω 1/4W		J	不燃化カーボン抵抗	01
R2068-2069	HV753100	R.CAR.FP	1 Ω 1/4W			不燃化カーボン抵抗	01
R2071	HV753100	R.CAR.FP	1 Ω 1/4W			不燃化カーボン抵抗	01
R2086	HV753100	R.CAR.FP	1 Ω 1/4W			不燃化カーボン抵抗	01
R2104	HV753100	R.CAR.FP	1 Ω 1/4W			不燃化カーボン抵抗	01
R2551-2552	HV753100	R.CAR.FP	1 Ω 1/4W			不燃化カーボン抵抗	01
R2571-2572	HV753100	R.CAR.FP	1 Ω 1/4W			不燃化カーボン抵抗	01
R2608	HV756470	R.CAR.FP	4.7K Ω 1/4W			不燃化カーボン抵抗	01
R2611	HV753220	R.CAR.FP	2.2 Ω 1/4W			不燃化カーボン抵抗	01
R2630	HV753220	R.CAR.FP	2.2 Ω 1/4W		UCRTKABGEL	不燃化カーボン抵抗	01
R2635	HV755470	R.CAR.FP	470 Ω 1/4W		UCRTKABGEL	不燃化カーボン抵抗	01
R2637	HV755470	R.CAR.FP	470 Ω 1/4W		UCRTKABGEL	不燃化カーボン抵抗	01
R2639	HV755470	R.CAR.FP	470 Ω 1/4W		UCRTKABGEL	不燃化カーボン抵抗	01
R2641	HV753100	R.CAR.FP	1 Ω 1/4W		UCRTKABGEL	不燃化カーボン抵抗	01
R2642	HV753100	R.CAR.FP	1 Ω 1/4W		UCRTKABGEL	不燃化カーボン抵抗	01
R2651	HV755470	R.CAR.FP	470 Ω 1/4W		UCRTKABGEL	不燃化カーボン抵抗	01
R2664	HV753100	R.CAR.FP	1 Ω 1/4W		UCRTKABGEL	不燃化カーボン抵抗	01
R2665	HV753100	R.CAR.FP	1 Ω 1/4W		UCRTKABGEL	不燃化カーボン抵抗	01
R2708	HV753100	R.CAR.FP	1 Ω 1/4W			不燃化カーボン抵抗	01
R2711-2712	HV753100	R.CAR.FP	1 Ω 1/4W			不燃化カーボン抵抗	01
XL201	V5345200	RSNR.CE	CSBLA503KECZF30-B0			セラミック振動子	01
XL202	WD280800	RSNR.CRYS	14.31818MHz		UCRK	水晶振動子	03
* XL202	WD280900	RSNR.CRYS	17.734475MHz		TABGEL	水晶振動子	

＊New Parts ＊新規部品

P.C.B. D-VIDEO

	Ref No.	Part No.	Description		Remarks	Markets	部 品 名	ﾗﾝｸ
*		WQ132100	P.C.B.	D-VIDEO		J	ＰＣＢ　Ｄ－ＶＩＤＥＯ	
*		WQ132200	P.C.B.	D-VIDEO		UCRTKABGEL	ＰＣＢ　Ｄ－ＶＩＤＥＯ	
	CB100	WA900700	CN.FMN	7P SE FMN		J	ＦＭＮコネクター	02
*	CB102	WA903700	CN	37P SE			ＦＭＮコネクター	
	CB103	VT388300	CN.BS.PIN	2P			ベース付ポスト	
*	CB104	WA901000	CN	10P SE			ＦＭＮコネクター	
	CB106	VP113500	CN.BS.PIN	10P			ＦＦＣコネクター	01
	CB107	WD018200	CN.BS.PIN	6P SE			ＸＨベースピン	02
	CB108	V9192700	CN.BS.PIN	4P			ベース付ポスト	01
	CB109	WJ789500	CN.BS.PIN	3P SE			ＸＨベースピン	02
	CB110	VR134300	CN.BS.PIN	6P			ベース付ポスト	01
	CB112	VT619100	CN.BS.PIN	5P			ベース付ポスト	01
	CB700-701	V8875600	CN	13P TE			ＪＥコネクター	02
	CB704-709	WH641400	CN.HDMI	19P SE			ＨＤＭＩコネクター	03
	CB710	WC199500	CN	20P TE			ＦＦＣ／ＦＰＣコネクタ	01
	C1001	WG888300	C.CE.M.CHP	10uF 6.3V		J	チップ積層セラコン	01
	C1002	US126100	C.CE.CHP	1uF 10V		J	チップセラコン	01
	C1003	US064100	C.CE.CHP	0.01uF 50V B		J	チップセラコン	01
	C1005-1006	US635100	C.CE.CHP	0.1uF 16V		J	チップセラコン	01
	C1007	US064100	C.CE.CHP	0.01uF 50V B		J	チップセラコン	01
	C1008	US126100	C.CE.CHP	1uF 10V		J	チップセラコン	01
	C1009-1012	US635100	C.CE.CHP	0.1uF 16V		J	チップセラコン	01
	C1014-1015	UF417220	C.EL.CHP	22uF 6.3V			チップケミコン	01
	C1016-1019	WG888300	C.CE.M.CHP	10uF 6.3V			チップ積層セラコン	01
	C1020-1021	UF417220	C.EL.CHP	22uF 6.3V			チップケミコン	01
	C1022-1026	US635100	C.CE.CHP	0.1uF 16V			チップセラコン	01
*	C1027-1028	WK978200	C.NbO	100uF 4V			酸化ニオブコンデンサ	
	C1029-1034	US635100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C1036-1045	US635100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C1046-1047	US061220	C.CE.CHP	22pF 50V B			チップセラコン	01
	C1048-1051	US635100	C.CE.CHP	0.1uF 16V			チップセラコン	01
*	C1052	WK978200	C.NbO	100uF 4V			酸化ニオブコンデンサ	
	C1053-1054	US635100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C1055	US126100	C.CE.CHP	1uF 10V			チップセラコン	01
	C1056	US635100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C1057	US126100	C.CE.CHP	1uF 10V			チップセラコン	01
	C1058-1066	US635100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C1067	US126100	C.CE.CHP	1uF 10V			チップセラコン	01
	C1068	US063680	C.CE.CHP	6800pF 50V B			チップセラコン	01
	C1069-1071	WG888300	C.CE.M.CHP	10uF 6.3V			チップ積層セラコン	01
	C1072-1074	US635100	C.CE.CHP	0.1uF 16V			チップセラコン	01
*	C1075	WK978200	C.NbO	100uF 4V			酸化ニオブコンデンサ	
	C1076	US635100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C1077	WG888300	C.CE.M.CHP	10uF 6.3V			チップ積層セラコン	01
	C1078	US635100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C1079	US126100	C.CE.CHP	1uF 10V			チップセラコン	01
	C1080	US635100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C1081	US126100	C.CE.CHP	1uF 10V			チップセラコン	01
	C1082	US635100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C1083	US126100	C.CE.CHP	1uF 10V			チップセラコン	01
	C1084	US635100	C.CE.CHP	0.1uF 16V			チップセラコン	01

＊New Parts　＊新規部品

P.C.B. D-VIDEO

Ref No.	Part No.	Description		Remarks	Markets	部 品 名	ﾗﾝｸ
C1085	US126100	C. CE. CHP	1uF 10V			チップセラコン	01
C1086-1087	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C1088-1089	US062100	C. CE. CHP	100pF 50V B			チップセラコン	01
C1090-1091	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C1092	WD758300	C. CE. CHP	10uF 10V			チップセラコン	01
C1093-1112	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C1113	UF417220	C. EL. CHP	22uF 6. 3V			チップケミコン	01
C1114-1115	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C1116	UF437100	C. EL. CHP	10uF 16V			チップケミコン	01
C1117-1118	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C1119-1120	WC891400	C. EL. CHP	220uF 10V			チップケミコン	01
C1121-1122	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C1123-1125	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C1126-1128	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C1129-1130	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C1131-1132	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C1133-1134	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C1135-1136	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C1137	WD758300	C. CE. CHP	10uF 10V			チップセラコン	01
C1138	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C1139-1141	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C1142	US063100	C. CE. CHP	1000pF 50V B			チップセラコン	01
C1143	UF417220	C. EL. CHP	22uF 6. 3V			チップケミコン	01
C1144	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C1145	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C1146	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C1147	US126100	C. CE. CHP	1uF 10V			チップセラコン	01
C1148	US063100	C. CE. CHP	1000pF 50V B			チップセラコン	01
C1149	WC891400	C. EL. CHP	220uF 10V			チップケミコン	01
C1150-1151	UF438100	C. EL. CHP	100uF 16V			チップケミコン	01
C1152	WC891400	C. EL. CHP	220uF 10V			チップケミコン	01
C1153-1157	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C1158	US063100	C. CE. CHP	1000pF 50V B			チップセラコン	01
C1159-1160	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C1161-1162	WC890600	C. EL	330uF 6. 3V			ケミコン　ＰＵＲＥ	01
C1163	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C1164	US063100	C. CE. CHP	1000pF 50V B			チップセラコン	01
C1165	WC890600	C. EL	330uF 6. 3V			ケミコン　ＰＵＲＥ	01
C1166	UF438100	C. EL. CHP	100uF 16V			チップケミコン	01
C1167	WC890600	C. EL	330uF 6. 3V			ケミコン　ＰＵＲＥ	01
C1168-1169	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C1170	US063100	C. CE. CHP	1000pF 50V B			チップセラコン	01
C1171	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C1172	V9878800	C. CE. CHP	1000pF			チップセラコン	01
C1173	WC890600	C. EL	330uF 6. 3V			ケミコン　ＰＵＲＥ	01
C1174	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C1175	WC890600	C. EL	330uF 6. 3V			ケミコン　ＰＵＲＥ	01
C1176-1177	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C1178-1179	US063100	C. CE. CHP	1000pF 50V B			チップセラコン	01
C1180-1197	US061220	C. CE. CHP	22pF 50V B			チップセラコン	01
C1195-1196	US062100	C. CE. CHP	100pF 50V B			チップセラコン	01
C1197	US061220	C. CE. CHP	22pF 50V B			チップセラコン	01

＊New Parts　＊新規部品

P.C.B. D-VIDEO

Ref No.	Part No.	Description		Remarks	Markets	部 品 名	ﾗﾝｸ
C1199-1214	US061220	C.CE.CHP	22pF 50V B			チップセラコン	01
C1215	US635100	C.CE.CHP	0.1uF 16V			チップセラコン	01
C1216-1225	US061220	C.CE.CHP	22pF 50V B			チップセラコン	01
C1226	WD758300	C.CE.CHP	10uF 10V			チップセラコン	01
C1227	US635100	C.CE.CHP	0.1uF 16V			チップセラコン	01
C1228	US126100	C.CE.CHP	1uF 10V			チップセラコン	01
C1229	UF437100	C.EL.CHP	10uF 16V			チップケミコン	01
C1230	US635100	C.CE.CHP	0.1uF 16V			チップセラコン	01
C1231	US126100	C.CE.CHP	1uF 10V			チップセラコン	01
C1239	US635100	C.CE.CHP	0.1uF 16V			チップセラコン	01
C1246	US635100	C.CE.CHP	0.1uF 16V			チップセラコン	01
C1247	WG888300	C.CE.M.CHP	10uF 6.3V			チップ積層セラコン	01
C1248	US635100	C.CE.CHP	0.1uF 16V			チップセラコン	01
C1250	US635100	C.CE.CHP	0.1uF 16V			チップセラコン	01
C7000-7001	US635100	C.CE.CHP	0.1uF 16V			チップセラコン	01
C7002-7003	US064100	C.CE.CHP	0.01uF 50V B			チップセラコン	01
C7004	UF438100	C.EL.CHP	100uF 16V			チップケミコン	01
C7005-7006	US635100	C.CE.CHP	0.1uF 16V			チップセラコン	01
C7007	UF438100	C.EL.CHP	100uF 16V			チップケミコン	01
C7008-7010	US635100	C.CE.CHP	0.1uF 16V			チップセラコン	01
C7011-7012	WG888300	C.CE.M.CHP	10uF 6.3V			チップ積層セラコン	01
C7013-7014	US635100	C.CE.CHP	0.1uF 16V			チップセラコン	01
C7015-7016	WG888300	C.CE.M.CHP	10uF 6.3V			チップ積層セラコン	01
C7017-7019	US064100	C.CE.CHP	0.01uF 50V B			チップセラコン	01
C7020-7024	US635100	C.CE.CHP	0.1uF 16V			チップセラコン	01
C7025-7026	US064100	C.CE.CHP	0.01uF 50V B			チップセラコン	01
C7027-7028	WD758300	C.CE.CHP	10uF 10V			チップセラコン	01
C7029-7036	US635100	C.CE.CHP	0.1uF 16V			チップセラコン	01
C7037-7038	US063100	C.CE.CHP	1000pF 50V B			チップセラコン	01
C7039	US034390	C.CE.CHP	0.039uF 16V B			チップセラコン	01
C7040-7041	US064100	C.CE.CHP	0.01uF 50V B			チップセラコン	01
C7042	VZ243400	C.CE.CHP	0.33uF 16V			チップセラコン	01
C7043	VZ281900	C.CE.CHP	0.47uF 16V K			チップセラ	01
C7044	US034820	C.CE.CHP	0.082uF 16V K			チップセラコン	01
C7045	US064100	C.CE.CHP	0.01uF 50V B			チップセラコン	01
C7046	US635100	C.CE.CHP	0.1uF 16V			チップセラコン	01
C7047-7048	UF417220	C.EL.CHP	22uF 6.3V			チップケミコン	01
C7050-7051	UF417220	C.EL.CHP	22uF 6.3V			チップケミコン	01
C7052	UF438100	C.EL.CHP	100uF 16V			チップケミコン	01
C7053-7054	US635100	C.CE.CHP	0.1uF 16V			チップセラコン	01
C7055	US135150	C.CE.CHP	0.15uF 16V			チップセラコン	01
C7056	US635100	C.CE.CHP	0.1uF 16V			チップセラコン	01
C7057	US063820	C.CE.CHP	8200pF 50V B			チップセラコン	01
C7058-7061	US635100	C.CE.CHP	0.1uF 16V			チップセラコン	01
C7062	US063220	C.CE.CHP	2200pF 50V B			チップセラコン	01
C7063	US063390	C.CE.CHP	3900pF 50V B			チップセラコン	01
C7064-7066	US635100	C.CE.CHP	0.1uF 16V			チップセラコン	01
C7067	US063220	C.CE.CHP	2200pF 50V B			チップセラコン	01
C7068-7072	US635100	C.CE.CHP	0.1uF 16V			チップセラコン	01
C7073	WG888300	C.CE.M.CHP	10uF 6.3V			チップ積層セラコン	01
C7074	US635100	C.CE.CHP	0.1uF 16V			チップセラコン	01
C7075	WG888300	C.CE.M.CHP	10uF 6.3V			チップ積層セラコン	01

＊New Parts ＊新規部品

P.C.B. D-VIDEO

Ref No.	Part No.	Description		Remarks	Markets	部 品 名	ﾗﾝｸ
C7076	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7077	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C7078	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7079	US064100	C. CE. CHP	0. 01uF 50V B			チップセラコン	01
C7080	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C7081-7083	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7084	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C7085	US063390	C. CE. CHP	3900pF 50V B			チップセラコン	01
C7086	US661100	C. CE. CHP	10pF 50V D			チップセラコン	01
C7087	US063820	C. CE. CHP	8200pF 50V B			チップセラコン	01
C7088-7089	US661100	C. CE. CHP	10pF 50V D			チップセラコン	01
C7090	US135150	C. CE. CHP	0. 15uF 16V			チップセラコン	01
C7091	US661100	C. CE. CHP	10pF 50V D			チップセラコン	01
C7092-7095	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7096	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C7097	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7098	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C7100-7108	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7113	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7115	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7119	UF417220	C. EL. CHP	22uF 6. 3V			チップケミコン	01
C7120-7121	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C7122	UF417220	C. EL. CHP	22uF 6. 3V			チップケミコン	01
C7123-7130	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7131	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C7132	US063100	C. CE. CHP	1000pF 50V B			チップセラコン	01
C7133	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7134	US063100	C. CE. CHP	1000pF 50V B			チップセラコン	01
C7135-7137	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7138	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C7139-7156	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7157	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C7158-7163	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7164	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C7165	UF438100	C. EL. CHP	100uF 16V			チップケミコン	01
C7166-7173	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7174	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C7175-7180	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7181	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C7182-7202	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7203-7204	UF417220	C. EL. CHP	22uF 6. 3V			チップケミコン	01
C7205-7207	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7208-7209	UF417220	C. EL. CHP	22uF 6. 3V			チップケミコン	01
C7210-7219	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7220-7221	UF417220	C. EL. CHP	22uF 6. 3V			チップケミコン	01
C7222-7224	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7228	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C7229-7232	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7233-7236	US661100	C. CE. CHP	10pF 50V D			チップセラコン	01
C7237	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7238	US064100	C. CE. CHP	0. 01uF 50V B			チップセラコン	01
C7239	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01

＊New Parts ＊新規部品

P.C.B. D-VIDEO

Ref No.	Part No.	Description		Remarks	Markets	部 品 名	ﾗﾝｸ
C7240-7241	US661100	C. CE. CHP	10pF 50V D			チップセラコン	01
C7242-7245	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7246-7247	US661100	C. CE. CHP	10pF 50V D			チップセラコン	01
C7248-7249	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7250-7253	US661100	C. CE. CHP	10pF 50V D			チップセラコン	01
C7254	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C7255	US661100	C. CE. CHP	10pF 50V D			チップセラコン	01
C7256-7258	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7259	US063100	C. CE. CHP	1000pF 50V B			チップセラコン	01
C7260-7262	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7263	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C7264-7267	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7268	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C7269-7270	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7271	US063100	C. CE. CHP	1000pF 50V B			チップセラコン	01
C7272-7278	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7279	US063100	C. CE. CHP	1000pF 50V B			チップセラコン	01
C7280-7283	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7284	US063100	C. CE. CHP	1000pF 50V B			チップセラコン	01
C7285-7287	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C7288-7291	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7292	US064100	C. CE. CHP	0. 01uF 50V B			チップセラコン	01
C7293	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C7294-7297	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7298-7301	US661100	C. CE. CHP	10pF 50V D			チップセラコン	01
C7304-7312	US661100	C. CE. CHP	10pF 50V D			チップセラコン	01
C7313-7317	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7318	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C7319-7322	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7323	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C7326	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C7327-7329	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7330-7331	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C7332	US063100	C. CE. CHP	1000pF 50V B			チップセラコン	01
C7333	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C7334-7341	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7342	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C7343	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7344	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C7345	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7346	WD758300	C. CE. CHP	10uF 10V			チップセラコン	01
C7347	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7348	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C7349-7351	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7352	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C7353-7355	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7356-7357	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C7358	US063100	C. CE. CHP	1000pF 50V B			チップセラコン	01
C7359	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C7360-7367	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7368	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C7369	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01

※ New Parts ＊新規部品

P.C.B. D-VIDEO

Ref No.	Part No.	Description		Remarks	Markets	部 品 名	ﾗﾝｸ
C7370	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C7371	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7372	WD758300	C. CE. CHP	10uF 10V			チップセラコン	01
C7373-7394	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7396	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7397	UF438100	C. EL. CHP	100uF 16V			チップケミコン	01
C7398-7399	UF417220	C. EL. CHP	22uF 6. 3V			チップケミコン	01
C7400-7401	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7402-7403	US063100	C. CE. CHP	1000pF 50V B			チップセラコン	01
C7404-7406	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7407	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C7408-7413	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7415-7416	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C7417	UF438100	C. EL. CHP	100uF 16V			チップケミコン	01
C7418	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C7419	UF417220	C. EL. CHP	22uF 6. 3V			チップケミコン	01
C7420-7421	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C7422-7425	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7426	WD758300	C. CE. CHP	10uF 10V			チップセラコン	01
C7427-7428	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7430	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7431	WD758300	C. CE. CHP	10uF 10V			チップセラコン	01
C7433	UF417220	C. EL. CHP	22uF 6. 3V			チップケミコン	01
C7434	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C7435-7437	UF417220	C. EL. CHP	22uF 6. 3V			チップケミコン	01
C7438-7441	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C7442	UF417220	C. EL. CHP	22uF 6. 3V			チップケミコン	01
C7444-7445	UF417220	C. EL. CHP	22uF 6. 3V			チップケミコン	01
C7446	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7447	UF438100	C. EL. CHP	100uF 16V			チップケミコン	01
C7449-7453	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C7454	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7455-7457	UF417220	C. EL. CHP	22uF 6. 3V			チップケミコン	01
C7458	US064100	C. CE. CHP	0. 01uF 50V B			チップセラコン	01
C7461-7462	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C7463	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7464	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C7466-7467	UF417220	C. EL. CHP	22uF 6. 3V			チップケミコン	01
C7468-7470	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7471	US063100	C. CE. CHP	1000pF 50V B			チップセラコン	01
C7472-7497	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7498	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C7499-7519	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7520	UF438100	C. EL. CHP	100uF 16V			チップケミコン	01
C7521	US064100	C. CE. CHP	0. 01uF 50V B			チップセラコン	01
C7523	US635100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C7524	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C7525-7526	US126100	C. CE. CHP	1uF 10V			チップセラコン	01
C7527-7528	UF417220	C. EL. CHP	22uF 6. 3V			チップケミコン	01
C7529-7532	WG888300	C. CE. M. CHP	10uF 6. 3V			チップ積層セラコン	01
C7533-7534	UF417220	C. EL. CHP	22uF 6. 3V			チップケミコン	01
C7535-7546	US661100	C. CE. CHP	10pF 50V D			チップセラコン	01

＊New Parts ＊新規部品

P.C.B. D-VIDEO

	Ref No.	Part No.	Description		Remarks	Markets	部 品 名	ﾗﾝｸ
	C7549-7552	WG888300	C.CE.M.CHP	10uF 6.3V			チップ積層セラコン	01
	C7553-7616	US635100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C7617	US661100	C.CE.CHP	10pF 50V D			チップセラコン	01
	C7618	US635100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C7619	US126100	C.CE.CHP	1uF 10V			チップセラコン	01
	C7620	US064100	C.CE.CHP	0.01uF 50V B			チップセラコン	01
	C7628-7635	US635100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	D1000	V2376600	DIODE.SHOT	RB500V-40		J	ショットキーダイオード	01
	D1001-1004	VT332900	DIODE	1SS355			ダイオード	01
	D1006	VT332900	DIODE	1SS355			ダイオード	01
	D1008	VT332900	DIODE	1SS355			ダイオード	01
	D1009	WE674800	DIODE	AVRL161A1R1NTB		J	チップバリスタ	01
	D7000	V8960900	DIODE.ZENR	MA8024-(TX) 2.4V			ツェナーダイオード	01
	D7003-7004	WE674800	DIODE	AVRL161A1R1NTB			チップバリスタ	01
*	D7005-7012	WP385600	PESD	PESD0603-240			ポリマーＥＳＤ	
	D7013-7015	WE674800	DIODE	AVRL161A1R1NTB			チップバリスタ	01
*	D7016-7023	WP385600	PESD	PESD0603-240			ポリマーＥＳＤ	
	D7024-7028	WE674800	DIODE	AVRL161A1R1NTB			チップバリスタ	01
*	D7029-7036	WP385600	PESD	PESD0603-240			ポリマーＥＳＤ	
	D7037-7038	WE674800	DIODE	AVRL161A1R1NTB			チップバリスタ	01
	D7040	WE674800	DIODE	AVRL161A1R1NTB			チップバリスタ	01
*	D7041-7048	WP385600	PESD	PESD0603-240			ポリマーＥＳＤ	
	D7049-7051	WE674800	DIODE	AVRL161A1R1NTB			チップバリスタ	01
	D7060-7062	WE674800	DIODE	AVRL161A1R1NTB			チップバリスタ	01
	D7063	V2376600	DIODE.SHOT	RB500V-40			ショットキーダイオード	01
	D7064	VT332900	DIODE	1SS355			ダイオード	01
	D7073-7075	WE674800	DIODE	AVRL161A1R1NTB			チップバリスタ	01
	D7076	V2376600	DIODE.SHOT	RB500V-40			ショットキーダイオード	01
	D7077	VT332900	DIODE	1SS355			ダイオード	01
	D7079-7084	VT332900	DIODE	1SS355			ダイオード	01
	D7087-7091	VT332900	DIODE	1SS355			ダイオード	01
	D7093-7095	VT332900	DIODE	1SS355			ダイオード	01
	D7096	WC549600	DIODE.CHP	RB160M-30 TR			チップダイオード	04
	D7097	VT332900	DIODE	1SS355			ダイオード	01
	D7099	WC549600	DIODE.CHP	RB160M-30 TR			チップダイオード	04
	D7100-7105	VT332900	DIODE	1SS355			ダイオード	01
	F7000-7001	V2997600	SW.POLY	SMDC050-02			ポリスイッチ	01
	IC100	X9370D00	IC.CEC	MN103SFD7GYAC CPU	written	J	ＩＣ　ＣＥＣ	11
	IC101	X8897A00	IC	R1172S331B-E2-F			電源ＩＣ	03
	IC102	X9292A00	IC	R1172H121D-T1-F 1.			電源ＩＣ	01
*	IC103	YA190B00	IC.MEMORY	S29GL128P90TFCR20	written		メモリＩＣ	
	IC104	X3585E00	IC.MEMORY	K4S281632K-UC75000			メモリＩＣ　１２８Ｍ	05
	IC106	XT744B00	IC	TC74VHCT245AFT E,K			ロジックＩＣ	02
	IC107	X8382A00	IC	TC7WH08FK(TE85L,F)			ロジックＩＣ	01
	IC109	X8386A00	IC	TC7WH14FK(TE85L,F)			ロジックＩＣ	01
	IC110	X7717A00	IC	R3112N251A-TR			リセットＩＣ	01
	IC111	X8378A00	IC	TC7SH125FU(TE85L,F			ロジックＩＣ	01
	IC112	X7741A00	IC	NJM2867F3-05(TE1)			電源ＩＣ	02
	IC113	X9063A00	IC	M24256-BRDW6TP			メモリＩＣ	05
	IC114	X8813A00	IC	MB87L8760			ＩＣ　デジタル	08
	IC115	X3586B00	IC	TC74VHCT08AFT EL,K			ロジックＩＣ	01
	IC116	X7964A00	IC	PQ20OWNA1ZPH			電源ＩＣ	03

＊New Parts　＊新規部品

P.C.B. D-VIDEO and P.C.B. FL

	Ref No.	Part No.	Description		Remarks	Markets	部 品 名	ランク
	IC117	X8386A00	IC	TC7WH14FK(TE85L,F)			ロジックＩＣ	01
	IC118	X9174A00	IC	IP101ALF			ＩＣ　デジタル	07
	IC120	X7951A00	IC	BD6517F-E2			電源ＩＣ	04
	IC121	X8378A00	IC	TC7SH125FU(TE85L,F			ロジックＩＣ	01
	IC122	X8944A00	IC	R1154H050B-T1-F			電源ＩＣ	03
	IC124	X9063A00	IC	M24256-BRDW6TP			メモリＩＣ	05
	IC125	X3585E00	IC.MEMORY	K4S281632K-UC75000			メモリＩＣ　１２８Ｍ	05
	IC700	X6848A00	IC	LA73053-TLM-E			アンプＩＣ	05
	IC701	X9393A00	IC	ADV7800BSTZ-80			ＩＣビデオデコーダ	13
	IC702	X8838A00	IC	ADV7342BSTZ			ＩＣビデオエンコーダ	11
	IC704-705	XZ287A00	IC	SN74LVC245APWR			ロジックＩＣ	02
	IC707	XZ287A00	IC	SN74LVC245APWR			ロジックＩＣ	02
	IC714	X2479A00	IC	YGV619			ＩＣ	12
	IC715	X4627C00	IC	M12L64322A-7TG0.11			メモリＩＣ　６４Ｍ	06
	IC716	X8527A00	IC	TC7WZ04FK			ロジックＩＣ	01
	IC717	X5731A00	IC	SN74LVC74APWR			ロジックＩＣ	02
	IC718-719	X8897A00	IC	R1172S331B-E2-F			電源ＩＣ	03
	IC721-722	X8897A00	IC	R1172S331B-E2-F			電源ＩＣ	03
	IC730	X7741A00	IC	NJM2867F3-05(TE1)			電源ＩＣ	02
	IC731	X2482A00	IC	LB1836M-TE-L			ＩＣ	03
	IC733	X7741A00	IC	NJM2867F3-05(TE1)			電源ＩＣ	02
	IC734	X7743A00	IC	SN74CB3Q3257PWR			ロジックＩＣ	04
	IC735	XZ287A00	IC	SN74LVC245APWR			ロジックＩＣ	02
	IC740	X9625A00	IC	M12L64164A-5TG			メモリＩＣ　６４Ｍ	07
	IC741	X7887A00	IC	R1172S181B-E2-F			電源ＩＣ	03
	IC743-744	X7887A00	IC	R1172S181B-E2-F			電源ＩＣ	03
	IC745	X7195A00	IC	R1172S121D-E2-F			電源ＩＣ	04
	IC749-750	X7887A00	IC	R1172S181B-E2-F			電源ＩＣ	03
	IC755	X8897A00	IC	R1172S331B-E2-F			電源ＩＣ	03
	PN100	V9637500	PIN	L=70 #18			スタイルピン	
	Q1004-1005	WH445000	FET	3LN01C-TB-E		J	ＦＥＴ	01
	Q1006-1007	VQ986700	TR	2SC4081 T106			トランジスタ	01
	Q7000-7012	VQ986700	TR	2SC4081 T106			トランジスタ	01
	Q7013	VR936300	TR	2SA1576A T106			トランジスタ	01
	Q7014	VQ986700	TR	2SC4081 T106			トランジスタ	01
	RY700	WN307700	RELAY	DC4.5V UB2-4.5SNUN			リレー	07
	XL100	WM227900	RSNR.CE	10MHz		J	セラミック振動子	03
	XL101	WH714200	RESONATOR	24.576MHz DSO321SR			水晶発振器	05
	XL102	WD046100	RSNR.CRYS	5.00MHz			水晶振動子	
	XL103	WK456400	RSNR.CRYS	45.1584MHz DSO321S			水晶振動子	05
	XL700	WK841300	RESONATOR	28.63636MHz			水晶発振器	05
	XL701	WK841200	RESONATOR	27MHz DSO321SRAB			水晶発振器	05
*	XL702	WQ047800	RESONATOR	30.000M DSO321SRAB			水晶発振器	
*		WQ134200	P.C.B.	FL			ＰＣＢ　ＦＬ	
	CB901	V6313400	CN.BS.PIN	27P TE			ＦＭＮコネクター	
	CB951-952	V8810200	CN	9P TE			ＪＥコネクター	02
	CB953	V7667200	CN.BS.PIN	20P TE			ＦＦＣコネクター	
	CB954	V9357000	CN	19P TE			ＪＥコネクター	
	CB955-956	V8875600	CN	13P TE			ＪＥコネクター	02

＊New Parts　＊新規部品

P.C.B. FL

Ref No.	Part No.	Description		Remarks	Markets	部 品 名	ﾗﾝｸ
CB957	WE221200	CN. BS. PIN	FMN 37P TE			ＦＭＮコネクター	04
CB958	V9357000	CN	19P TE			ＪＥコネクター	
CB959-960	V8875600	CN	13P TE			ＪＥコネクター	02
CB962	V9357000	CN	19P TE			ＪＥコネクター	
CB963	V7827000	CN	20P TE TUC SERIES			コネクタープラグ	01
CB964	VQ044400	CN. BS. PIN	9P			ＦＦＣコネクター	01
CB965	V7828700	SOCKET	20P SE TUC SERIES			コネクターソケット	01
CB967	V8810200	CN	9P TE			ＪＥコネクター	02
CB969	V9357000	CN	19P TE			ＪＥコネクター	
CB970	V6313500	CN. BS. PIN	27P SE			ＦＭＮコネクター	
CB971	VM929900	CN. BS. PIN	15P			ＦＰＣコネクター	01
CB972-973	V8810200	CN	9P TE			ＪＥコネクター	02
CB974	VU446000	CN. BS. PIN	15P TE			ＪＥ　コネクタ	02
CB991	V6509500	SOCKET	9P SE 3170			コネクターソケット	04
C9001	UR267470	C. EL	47uF 50V			ケミコン	01
C9003-9004	US064100	C. CE. CHP	0. 01uF 50V B			チップセラコン	01
C9008	US064100	C. CE. CHP	0. 01uF 50V B			チップセラコン	01
C9010	US064100	C. CE. CHP	0. 01uF 50V B			チップセラコン	01
C9011	UM388100	C. EL	100uF 10V			ケミコン	01
C9012-9013	US064100	C. CE. CHP	0. 01uF 50V B			チップセラコン	01
C9014	US135100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C9015	US064100	C. CE. CHP	0. 01uF 50V B			チップセラコン	01
C9016	UR218330	C. EL	330uF 6. 3V			ケミコン	
C9017	US135100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C9019	US064100	C. CE. CHP	0. 01uF 50V B			チップセラコン	01
C9020	US062100	C. CE. CHP	100pF 50V B			チップセラコン	01
C9021	US061470	C. CE. CHP	47pF 50V B			チップセラコン	01
C9022	US135100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C9023	UR218330	C. EL	330uF 6. 3V			ケミコン	
C9024	US062100	C. CE. CHP	100pF 50V B			チップセラコン	01
C9030	US064100	C. CE. CHP	0. 01uF 50V B			チップセラコン	01
C9501	US064100	C. CE. CHP	0. 01uF 50V B			チップセラコン	01
C9502	UR237100	C. EL	10uF 16V			ケミコン	
C9503	US163100	C. CE. CHP	1000pF 50V			チップセラコン	01
C9504	UR237100	C. EL	10uF 16V			ケミコン	
C9505	US064100	C. CE. CHP	0. 01uF 50V B			チップセラコン	01
C9506	WD758300	C. CE. CHP	10uF 10V			チップセラコン	01
C9507	US135100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C9509	UR238100	C. EL	100uF 16V			ケミコン	
C9510	US135100	C. CE. CHP	0. 1uF 16V			チップセラコン	01
C9511	US163100	C. CE. CHP	1000pF 50V			チップセラコン	01
C9512-9513	UR237100	C. EL	10uF 16V			ケミコン	
C9514	UR237470	C. EL	47uF 16V			ケミコン	01
C9515	US163100	C. CE. CHP	1000pF 50V			チップセラコン	01
C9516	US064100	C. CE. CHP	0. 01uF 50V B			チップセラコン	01
C9518	UR237100	C. EL	10uF 16V			ケミコン	
C9519	US163100	C. CE. CHP	1000pF 50V			チップセラコン	01
C9520	UR237470	C. EL	47uF 16V			ケミコン	01
C9521	US163100	C. CE. CHP	1000pF 50V			チップセラコン	01
C9522	US064100	C. CE. CHP	0. 01uF 50V B			チップセラコン	01
C9524	US064100	C. CE. CHP	0. 01uF 50V B			チップセラコン	01
C9901	US064100	C. CE. CHP	0. 01uF 50V B			チップセラコン	01

※ New Parts ＊新規部品

P.C.B. FL and P.C.B. CONNECT

	Ref No.	Part No.	Description		Remarks	Markets	部 品 名	ﾗﾝｸ
	C9902	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	C9903	UR237470	C.EL	47uF 16V			ケミコン	01
	C9904-9909	US135100	C.CE.CHP	0.1uF 16V			チップセラコン	01
	D9005-9006	VU991500	DIODE.ZENR	MA8039-H 4V			ツェナーダイオード	01
	D9017	VT332900	DIODE	1SS355			ダイオード	01
	D9021-9026	VT332900	DIODE	1SS355			ダイオード	01
	D9501	VV658000	DIODE.ZENR	RLZ5.1A 5.1V			ツェナーダイオード	01
	D9901-9904	VT332900	DIODE	1SS355			ダイオード	01
	IC901-902	X7821A00	IC	PT6302LQ-008(L)			ＩＣ	07
	IC951	X7375A00	IC	PCM1781DBQR			ＩＣ	04
	IC952	X7378A00	IC	NJM4565M(TE1)			アンプＩＣ	01
	IC991	X6876A00	IC	ADM222ARZ			ＩＣ	06
	JK991-992	V9435700	JACK.MNI	MSJ-035-12APC			モノラル ミニジャック	01
	PN902	V9637500	PIN	L=70 #18			スタイルピン	
	PN951-953	V9637500	PIN	L=70 #18			スタイルピン	
	Q9001-9009	WC529400	TR	KTC3875S Y GR RTK			トランジスタ	01
	Q9010-9011	VV655400	TR.DGT	DTC114EKA			デジタルトランジスタ	01
	Q9901	VP872600	TR	2SA1708 S,T			トランジスタ	01
	Q9902	VV655700	TR.DGT	DTC144EKA			デジタルトランジスタ	01
	Q9903	VP872600	TR	2SA1708 S,T			トランジスタ	01
	Q9904	VV655700	TR.DGT	DTC144EKA			デジタルトランジスタ	01
	R9002	HL005100	R.MTL.OXD	100 Ω 1/2W			酸化金属被膜抵抗	
	R9004	HL005100	R.MTL.OXD	100 Ω 1/2W			酸化金属被膜抵抗	
	R9503	VP940500	R.MTL.OXD	150 Ω 1W			酸化金属被膜抵抗	01
	R9907-9908	HF354270	R.CAR	27 Ω 1/2W J			カーボン抵抗	
	SW901-905	V4757100	SW.TACT	EVQ11A			タクトＳＷ	01
	SW907-917	V4757100	SW.TACT	EVQ11A			タクトＳＷ	01
	U9001	V8210200	L.DTCT	GP1UD271XK			リモコン受光ユニット	03
*	V9001	WP195500	FL.DSPLY	HNA-16ML15T			螢光表示管	
		V6007000	SHEET				シート／ＦＬ	03
		V3747400	SPACER.FL	T4x6x18			スペーサ／ＦＬ	01
		WF649700	SUPRT				サポート／ＦＬ	01
*		WP156500	P.C.B.	CONNECT		U	ＰＣＢ ＣＯＮＮＥＣＴ	
*		WP156600	P.C.B.	CONNECT		C	ＰＣＢ ＣＯＮＮＥＣＴ	
	CB901	LB919030	CN.BS.PIN	3P		U	ベース付ポスト	01
	CB903	VU443800	CN.JE	15P SE		U	ＪＥコネクタープラグ	01
	C900	US064100	C.CE.CHP	0.01uF 50V B		U	チップセラコン	01
	C901	US135100	C.CE.CHP	0.1uF 16V		U	チップセラコン	01
*	C902	UR219220	C.EL	2200uF 6.3V		U	ケミコン	
	C903	US062100	C.CE.CHP	100pF 50V B		U	チップセラコン	01
	C904	UM397470	C.EL	47uF 16V		U	ケミコン	01
	C905	US062100	C.CE.CHP	100pF 50V B		U	チップセラコン	01
	C907	US062100	C.CE.CHP	100pF 50V B		U	チップセラコン	01
	C910	US062100	C.CE.CHP	100pF 50V B		U	チップセラコン	01
	C912-913	UM397100	C.EL	10uF 16V		U	ケミコン	01
	C914	US062220	C.CE.CHP	220pF 50V B		U	チップセラコン	01
	C916	UM397470	C.EL	47uF 16V		U	ケミコン	01
	C917	US062220	C.CE.CHP	220pF 50V B		U	チップセラコン	01
	C918-919	UM397100	C.EL	10uF 16V		U	ケミコン	01

＊New Parts ＊新規部品

P.C.B. CONNECT and P.C.B. DCCNVT

	Ref No.	Part No.	Description		Remarks	Markets	部 品 名	ﾗﾝｸ
	C920	US135100	C.CE.CHP	0.1uF 16V		U	チップセラコン	01
	C921	US135100	C.CE.CHP	0.1uF 16V		UC	チップセラコン	01
	C950	US062220	C.CE.CHP	220pF 50V B		UC	チップセラコン	01
	C951	US063100	C.CE.CHP	1000pF 50V B		UC	チップセラコン	01
	C952-956	US062220	C.CE.CHP	220pF 50V B		UC	チップセラコン	01
	C957	UM397470	C.EL	47uF 16V		UC	ケミコン	01
	C959	US063100	C.CE.CHP	1000pF 50V B		UC	チップセラコン	01
	C960	US062220	C.CE.CHP	220pF 50V B		UC	チップセラコン	01
	C961	UM397470	C.EL	47uF 16V		UC	ケミコン	01
	C962-964	US062220	C.CE.CHP	220pF 50V B		UC	チップセラコン	01
	C965	UM397100	C.EL	10uF 16V		UC	ケミコン	01
	C966	UM397470	C.EL	47uF 16V		UC	ケミコン	01
	C967-969	UM397100	C.EL	10uF 16V		UC	ケミコン	01
	C970	US135100	C.CE.CHP	0.1uF 16V		UC	チップセラコン	01
	C975	US135100	C.CE.CHP	0.1uF 16V		U	チップセラコン	01
	C976	UM397470	C.EL	47uF 16V		UC	ケミコン	01
	D900-901	VT332900	DIODE	1SS355		U	ダイオード	01
	D904	VU992600	DIODE.ZENR	MA8051-M 5.1V		U	ツェナーダイオード	01
	D950	VU992600	DIODE.ZENR	MA8051-M 5.1V		UC	ツェナーダイオード	01
	D952	VU992600	DIODE.ZENR	MA8051-M 5.1V		UC	ツェナーダイオード	01
	D953-954	VT332900	DIODE	1SS355		UC	ダイオード	01
	IC901	X7378A00	IC	NJM4565M(TE1)		U	アンプＩＣ	01
	IC950	X7378A00	IC	NJM4565M(TE1)		UC	アンプＩＣ	01
	IC951	XW814A00	IC	TC7SET32FU		UC	ロジックＩＣ	01
*	JK950	WP418600	JACK.DIN	8P TCS7927-6821177		UC	ミニＤＩＮコネクター	
	Q900	WH445000	FET	3LN01C-TB-E		U	ＦＥＴ	01
	Q951	VV655200	TR.DGT	DTA143EKA		UC	デジタルトランジスタ	01
	Q952	WC529200	TR.DGT	KRC102M-AT		UC	デジタルトランジスタ	01
*		WQ140900	P.C.B.	DCCNVT			ＰＣＢ ＤＣＣＮＶＴ	
	CB61	VT619100	CN.BS.PIN	5P			ベース付ポスト	01
*	CB63	WN905300	CN	SS-6488S-A-PG4-BA			モジュラーコネクタ	
*	CB71	VL956100	CN.BS.PINP	7P SE			ＪＬ ベースポスト	
	C602	V9878800	C.CE.CHP	1000pF			チップセラコン	01
	C701	WE772500	C.EL.CHP	120uF 6.3V			チップＯＳケミコン	02
	C702	V5333500	C.CE.CHP	10uF 6.3V			チップセラコン	01
	C703	US063220	C.CE.CHP	2200pF 50V B			チップセラコン	01
	C704	US061680	C.CE.CHP	68pF 50V B			チップセラコン	01
	C705	US064150	C.CE.CHP	0.015uF 50V B			チップセラコン	01
	C706	US046100	C.CE.CHP	1uF 25V			チップセラコン	01
	C707	WE773800	C.CE.M.CHP	1uF 10V B			チップ積層セラコン	01
	C708	WJ343900	C.CE.CHP	0.33uF 10V			チップセラコン	01
	C709	US035100	C.CE.CHP	0.1uF 16V B			チップセラコン	01
	C710	US062470	C.CE.CHP	470pF 50V B			チップセラコン	01
	C711	WF547900	C.CE.CHP	10uF 25V			チップセラ	01
	C712-713	WM098400	C.EL.CHP	470uF 25V			チップケミコン	02
	C714	US062470	C.CE.CHP	470pF 50V B			チップセラコン	01
	C715	WF547900	C.CE.CHP	10uF 25V			チップセラ	01
	C716	US035100	C.CE.CHP	0.1uF 16V B			チップセラコン	01
	C717	WJ343900	C.CE.CHP	0.33uF 10V			チップセラコン	01

＊New Parts ＊新規部品

P.C.B. DCCNVT

Ref No.	Part No.	Description		Remarks	Markets	部 品 名	ﾗﾝｸ
C720	WE773800	C. CE. M. CHP	1uF 10V B			チップ積層セラコン	01
C721	US061330	C. CE. CHP	33pF 50V B			チップセラコン	01
C722	US063150	C. CE. CHP	1500pF 50V B			チップセラコン	01
C723	V5333500	C. CE. CHP	10uF 6. 3V			チップセラコン	01
C724	WE772500	C. EL. CHP	120uF 6. 3V			チップＯＳケミコン	02
C725	US062100	C. CE. CHP	100pF 50V B			チップセラコン	01
C726	US035100	C. CE. CHP	0. 1uF 16V B			チップセラコン	01
C727	WE476800	C. EL	330uF 10V			ケミコン	03
C728	V5333500	C. CE. CHP	10uF 6. 3V			チップセラコン	01
C729	US063220	C. CE. CHP	2200pF 50V B			チップセラコン	01
C730	US061510	C. CE. CHP	51pF 50V			チップセラコン	01
C731	US064150	C. CE. CHP	0. 015uF 50V B			チップセラコン	01
C732	US046100	C. CE. CHP	1uF 25V			チップセラコン	01
C733	WE773800	C. CE. M. CHP	1uF 10V B			チップ積層セラコン	01
C734	WJ343900	C. CE. CHP	0. 33uF 10V			チップセラコン	01
C735	US062100	C. CE. CHP	100pF 50V B			チップセラコン	01
C736	US035100	C. CE. CHP	0. 1uF 16V B			チップセラコン	01
C737	US062470	C. CE. CHP	470pF 50V B			チップセラコン	01
C738	WF547900	C. CE. CHP	10uF 25V			チップセラ	01
C739-740	US062220	C. CE. CHP	220pF 50V B			チップセラコン	01
C741	US062470	C. CE. CHP	470pF 50V B			チップセラコン	01
C742	WF547900	C. CE. CHP	10uF 25V			チップセラ	01
C743	US035100	C. CE. CHP	0. 1uF 16V B			チップセラコン	01
C744	WJ343900	C. CE. CHP	0. 33uF 10V			チップセラコン	01
C745	WE773800	C. CE. M. CHP	1uF 10V B			チップ積層セラコン	01
C746	US063680	C. CE. CHP	6800pF 50V B			チップセラコン	01
C747	WE773800	C. CE. M. CHP	1uF 10V B			チップ積層セラコン	01
C748	US061220	C. CE. CHP	22pF 50V B			チップセラコン	01
C749	US063150	C. CE. CHP	1500pF 50V B			チップセラコン	01
C750	WD758300	C. CE. CHP	10uF 10V			チップセラコン	01
C751	WE772500	C. EL. CHP	120uF 6. 3V			チップＯＳケミコン	02
C752-753	US046100	C. CE. CHP	1uF 25V			チップセラコン	01
C755	WF547900	C. CE. CHP	10uF 25V			チップセラ	01
C756	US035100	C. CE. CHP	0. 1uF 16V B			チップセラコン	01
C757	US062220	C. CE. CHP	220pF 50V B			チップセラコン	01
C758	WD758300	C. CE. CHP	10uF 10V			チップセラコン	01
C759-761	V5333500	C. CE. CHP	10uF 6. 3V			チップセラコン	01
C762	US062220	C. CE. CHP	220pF 50V B			チップセラコン	01
C766	US035100	C. CE. CHP	0. 1uF 16V B			チップセラコン	01
C767	US145100	C. CE. CHP	0. 1uF 25V			チップセラコン	01
C768-769	US064100	C. CE. CHP	0. 01uF 50V B			チップセラコン	01
C770	US035100	C. CE. CHP	0. 1uF 16V B			チップセラコン	01
D701	WK272200	DIODE. CHP	RB160M-60 TR			チップダイオード	01
D702-703	V6267600	DIODE	RB051L-40			ダイオード	01
D704-705	WK272200	DIODE. CHP	RB160M-60 TR			チップダイオード	01
D706-707	V6267600	DIODE	RB051L-40			ダイオード	01
D708	WK272200	DIODE. CHP	RB160M-60 TR			チップダイオード	01
D709-710	VU993800	DIODE. ZENR	MA8068-M 6. 8V			ツェナーダイオード	01
IC72	X8533A00	IC	TC7SZ02FU			ロジックＩＣ	01
Q701-702	WH948500	FET. ARRAY	SP8K2			ＦＥＴアレイ	04
Q703	WC434800	TR. DGT	KRA102S-RTK/P			デジタルトランジスタ	01
Q704-705	WH948500	FET. ARRAY	SP8K2			ＦＥＴアレイ	04

＊New Parts ＊新規部品

Carbon Resistors

Value	**1/4W** Type Part No.	**1/6W** Type Part No.	Value	**1/4W** Type Part No.	**1/6W** Type Part No.
1.0 Ω	HJ35 3100	HF85 3100	11 kΩ	HF45 7110	HF45 7110
1.8 Ω	HJ35 3180	＊	12 kΩ	HJ35 7120	HF85 7120
2.2 Ω	HJ35 3220	HF85 3220	13 kΩ	HF45 7130	HF45 7130
3.3 Ω	HJ35 3330	HF85 3330	15 kΩ	HF45 7150	HF45 7150
4.7 Ω	HJ35 3470	HF85 3470	18 kΩ	HF45 7180	HF45 7180
5.6 Ω	HJ35 3560	HF85 3560	22 kΩ	HF45 7220	HF45 7220
10 Ω	HF45 4100	HF45 4100	24 kΩ	HF45 7240	HF45 7240
15 Ω	HJ35 4150	HF85 4150	27 kΩ	HJ35 7270	HF85 7270
22 Ω	HF45 4220	HF45 4220	30 kΩ	HF45 7300	HF45 7300
27 Ω	HJ35 4270	HF85 4270	33 kΩ	HF45 7330	HF45 7330
33 Ω	HF45 4330	HF45 4330	36 kΩ	HF45 7360	HF45 7360
39 Ω	HJ35 4470	HF85 4390	39 kΩ	HF45 7390	HF45 7390
47 Ω	HF45 4470	HF45 4470	47 kΩ	HF45 7470	HF45 7470
56 Ω	HF45 4560	HF45 4560	51 kΩ	HF45 7510	HF45 7510
68 Ω	HF45 4680	HF45 4680	56 kΩ	HF45 7560	HF45 7560
75 Ω	HF45 4750	HF45 4750	62 kΩ	HF45 7620	HF45 7620
82 Ω	HF45 4820	HF45 4820	68 kΩ	HF45 7680	HF45 7680
91 Ω	HF45 4910	HF45 4910	82 kΩ	HF45 7820	HF45 7820
100 Ω	HF45 5100	HF45 5100	91 kΩ	HF45 7910	HF45 7910
110 Ω	HJ35 5110	HF85 5110	100 kΩ	HF45 8100	HF45 8100
120 Ω	HF45 5120	HF45 5120	110 kΩ	HF45 8110	HF45 8110
150 Ω	HF45 5150	HF45 5150	120 kΩ	HF45 8120	HF45 8120
160 Ω	HJ35 5160	＊	150 kΩ	HF45 8150	HF45 8150
180 Ω	HF45 5180	HF45 5180	180 kΩ	HF45 8180	HF45 8180
200 Ω	HF45 5200	HF45 5200	220 kΩ	HJ35 8220	HF85 8220
220 Ω	HF45 5220	HF45 5220	270 kΩ	HF45 8270	HF45 8270
270 Ω	HF45 5270	HF45 5270	300 kΩ	HF45 8300	HF45 8300
330 Ω	HF45 5330	HF45 5330	330 kΩ	HF45 8330	HF45 8330
390 Ω	HF45 5390	HF45 5390	390 kΩ	HJ35 8390	HF85 8390
430 Ω	HF45 5430	HF45 5430	470 kΩ	HF45 8470	HF45 8470
470 Ω	HF45 5470	HF45 5470	560 kΩ	HJ35 8560	HF85 8560
510 Ω	HF45 5510	HF45 5510	680 kΩ	HJ35 8680	HF85 8680
560 Ω	HF45 5560	HF45 5560	820 kΩ	HJ35 8820	HF85 8820
680 Ω	HF45 5680	HF45 5680	1.0 MΩ	HF45 9100	HF45 9100
820 Ω	HF45 5820	HF45 5820	1.2 MΩ	HJ35 9120	＊
910 Ω	HF45 5910	HF45 5910	1.5 MΩ	HJ35 9150	HF85 9150
1.0 k	HF45 6100	HF45 6100	1.8 MΩ	HJ35 9180	HF85 9180
1.2 kΩ	HF45 6120	HF45 6120	2.2 MΩ	HJ35 9220	HF85 9220
1.5 kΩ	HF45 6150	HF45 6150	3.3 MΩ	HJ35 9330	HF85 9330
1.8 kΩ	HF45 6180	HF45 6180	3.9 MΩ	HJ35 9390	＊
2.0 kΩ	HJ35 6200	HF85 6200	4.7 MΩ	HJ35 9470	HF85 9470
2.2 kΩ	HF45 6220	HF45 6220			
2.4 kΩ	HJ35 6240	HF85 6240			
2.7 kΩ	HF45 6270	HF45 6270			
3.0 kΩ	HF45 6300	HF45 6300			
3.3 kΩ	HF45 6330	HF45 6330			
3.6 kΩ	HJ35 6360	HF85 6360			
3.9 kΩ	HF45 6390	HF45 6390			
4.7 kΩ	HF45 6470	HF45 6470			
5.1 kΩ	HF45 6510	HF45 6510			
5.6 kΩ	HF45 6560	HF45 6560			
6.8 kΩ	HF45 6680	HF45 6680			
8.2 kΩ	HF45 6820	HF45 6820			
9.1 kΩ	HF45 6910	HF45 6910			
10 kΩ	HF45 7100	HF45 7100			


1/4W Type
HJ35○○○○
10mm

1/4W Type
HF45○○○○

1/6W Type
HF85○○○○
5mm

＊: Not available

- **OVERALL ASS'Y**




	Ref No.	Part No.	Description		Remarks	Markets	部 品 名	ランク
*	4	WQ134500	P.C.B. ASS'Y	POWER		J	ＰＣＢ ＰＯＷＥＲ	
*	4	WQ134600	P.C.B. ASS'Y	POWER		U	ＰＣＢ ＰＯＷＥＲ	
*	4	WQ134700	P.C.B. ASS'Y	POWER		C	ＰＣＢ ＰＯＷＥＲ	
*	4	WQ134800	P.C.B. ASS'Y	POWER		R	ＰＣＢ ＰＯＷＥＲ	14
*	4	WQ134900	P.C.B. ASS'Y	POWER		T	ＰＣＢ ＰＯＷＥＲ	
*	4	WQ135000	P.C.B. ASS'Y	POWER		K	ＰＣＢ ＰＯＷＥＲ	
*	4	WQ135100	P.C.B. ASS'Y	POWER		A	ＰＣＢ ＰＯＷＥＲ	
*	4	WQ135200	P.C.B. ASS'Y	POWER		B	ＰＣＢ ＰＯＷＥＲ	05
*	4	WQ135300	P.C.B. ASS'Y	POWER		GE	ＰＣＢ ＰＯＷＥＲ	
*	4	WQ135400	P.C.B. ASS'Y	POWER		L	ＰＣＢ ＰＯＷＥＲ	
*	5	WQ133200	P.C.B. ASS'Y	DSP		J	ＰＣＢ ＤＳＰ	
*	5	WQ133300	P.C.B. ASS'Y	DSP		UC	ＰＣＢ ＤＳＰ	06
*	5	WQ133400	P.C.B. ASS'Y	DSP		RTKABGEL	ＰＣＢ ＤＳＰ	
*	6	WQ136900	P.C.B. ASS'Y	FUNCTION		J	ＰＣＢ ＦＵＮＣＴＩＯＮ	
*	6	WQ137000	P.C.B. ASS'Y	FUNCTION		U	ＰＣＢ ＦＵＮＣＴＩＯＮ	
*	6	WQ137100	P.C.B. ASS'Y	FUNCTION		C	ＰＣＢ ＦＵＮＣＴＩＯＮ	01
*	6	WQ137200	P.C.B. ASS'Y	FUNCTION		RTKL	ＰＣＢ ＦＵＮＣＴＩＯＮ	
*	6	WQ137300	P.C.B. ASS'Y	FUNCTION		A	ＰＣＢ ＦＵＮＣＴＩＯＮ	
*	6	WQ137400	P.C.B. ASS'Y	FUNCTION		BGE	ＰＣＢ ＦＵＮＣＴＩＯＮ	
*	7	WQ139800	P.C.B. ASS'Y	AVIDEO		J	ＰＣＢ ＡＶＩＤＥＯ	
*	7	WQ139900	P.C.B. ASS'Y	AVIDEO		UCRK	ＰＣＢ ＡＶＩＤＥＯ	
*	7	WQ140000	P.C.B. ASS'Y	AVIDEO		TABGEL	ＰＣＢ ＡＶＩＤＥＯ	
*	8	WQ132100	P.C.B. ASS'Y	DVIDEO		J	ＰＣＢ ＤＶＩＤＥＯ	
*	8	WQ132200	P.C.B. ASS'Y	DVIDEO		UCRTKABGEL	ＰＣＢ ＤＶＩＤＥＯ	
*	9	WQ134200	P.C.B. ASS'Y	FL			ＰＣＢ ＦＬ	
*	10	WQ140900	P.C.B. ASS'Y	DCCNVT			ＰＣＢ ＤＣＣＮＶＴ	
	11	WD048200	AM/FM TUNER	FAE385-J01F		J	ＡＭ／ＦＭ チューナー	12
*	11	WP979800	HD RADIO TUNER	HDRMUHFSOOPTD		U	ＨＤチューナー	
	11	WD048300	AM/FM TUNER	FAE385-A01F		CRTL	ＡＭ／ＦＭ チューナー	
	11	WD048400	AM/FM TUNER	FAE485-E01F		KABGE	ＡＭ／ＦＭ チューナー	01
*	12	WP156500	P.C.B. ASS'Y	CONNECT		U	ＰＣＢ ＣＯＮＮＥＣＴ	
*	12	WP156600	P.C.B. ASS'Y	CONNECT		C	ＰＣＢ ＣＯＮＮＥＣＴ	
* ⚠	14	YA130A00	POWER TRANSFORMER			J	電源トランス	
* ⚠	14	YA131A00	POWER TRANSFORMER			UC	電源トランス	04
* ⚠	14	YA132A00	POWER TRANSFORMER			RL	電源トランス	
* ⚠	14	YA133A00	POWER TRANSFORMER			TK	電源トランス	01
* ⚠	14	YA134A00	POWER TRANSFORMER			A	電源トランス	01
* ⚠	14	YA135A00	POWER TRANSFORMER			BGE	電源トランス	01
	24	MF107070	FLEXIBLE FLAT CABLE	7P 70mm P=1.25			カード電線	01
*	25	WQ208100	FLEXIBLE FLAT CABLE	10P 160mm P=1.25			カード電線	01
	26	MF111070	FLEXIBLE FLAT CABLE	11P 70mm P=1.25			カード電線	01
*	27	WP510300	FLEXIBLE FLAT CABLE	16P 100mm P=1.25			カード電線	
*	28	WP505200	FLEXIBLE FLAT CABLE	15P 140mm P=1.25		JCRTKABGEL	カード電線	
*	29	WP510600	FLEXIBLE FLAT CABLE	37P 70mm P=1.0			カード電線	01
*	30	WP510400	FLEXIBLE FLAT CABLE	31P 180mm P=1.25			カード電線	
*	31	WQ082300	FLEXIBLE FLAT CABLE	20P 140mm P=1.0			カード電線	
*	101	WN985100	TOP COVER		GD		トップカバー	01
*	101	WN985000	TOP COVER		BL		トップカバー	
*	101	WN985200	TOP COVER		TI		トップカバー	
*	103	WN989100	REAR PANEL			J	リアパネル	
*	103	WN987800	REAR PANEL			U	リアパネル	
*	103	WN988000	REAR PANEL			C	リアパネル	
*	103	WN988300	REAR PANEL			R	リアパネル	


＊New Parts ＊新規部品


	Ref No.	Part No.	Description		Remarks	Markets	部 品 名	ランク
*	103	WN988400	REAR PANEL			T	リアパネル	
*	103	WN988600	REAR PANEL			K	リアパネル	
*	103	WN988700	REAR PANEL			A	リアパネル	
*	103	WN988800	REAR PANEL			B	リアパネル	
*	103	WN988900	REAR PANEL			GE	リアパネル	
*	103	WN989200	REAR PANEL			L	リアパネル	
*	116	WN997600	SUPPORT SC				サポートＳＣ	
	120	WK556500	LEG	D60xH22 Z11	GD,BL	JT	レッグ	08
	120	VO042500	LEG	D60xH21	GD	RK	レッグ	03
	120	VS025000	LEG	D60xH21	BL,TI	UCRABGEL	レッグ	02
	132	WF060100	KNOB D15	PROGRAM	GD		ノブＤ１５	01
	132	WF060000	KNOB D15	PROGRAM	BL		ノブＤ１５	01
	132	WF060200	KNOB D15	PROGRAM	TI		ノブＤ１５	
*	133	WN992000	KNOB D48	VOLUME	GD		ノブＤ４８	
*	133	WN991900	KNOB D48	VOLUME	BL		ノブＤ４８	
*	133	WN992100	KNOB D48	VOLUME	TI		ノブＤ４８	
*	134	WN992800	KNOB D24	INPUT	GD		ノブＤ２４	
*	134	WN992700	KNOB D24	INPUT	BL		ノブＤ２４	
*	134	WN992900	KNOB D24	INPUT	TI		ノブＤ２４	
	135	WJ053800	RIVET TOP			CRTKABGE	リベットトップ	
	136	VQ368600	PUSH RIVET	P3555-B			プッシュリベット	01
	142	V6742300	DAMPER	3/30/60			ダンパー	
*	143	WN997400	PLATE SIDE		GD		プレート／サイド	
*	143	WN997300	PLATE SIDE		BL		プレート／サイド	
*	143	WN997500	PLATE SIDE		TI		プレート／サイド	
	144	V9597500	DAMPER BASE	36x20x3			ダンパー ベース	
	146	VZ117100	DAMPER T2	50x10x2			ダンパー Ｔ２	01
	147	WJ069300	DAMPER TRANS	55x15x5			ダンパー トランス	04
	148	V8080600	CUSHION	10x20x3			クッション	01
	151	V7716700	DAMPER	5x5x15			ダンパー	01
	161	WE774100	BIND HEAD BONDING B-T. SCREW	3x8 MFZN2B3			ボンディングＢタイトネジ	01
	163	WE774300	BIND HEAD B-TIGHT SCREW	3x8 MFZN2W3			バインドＢタイトネジ	01
	164	WE998100	BIND HEAD B-TIGHT SCREW	3x12 MFZN2B3			バインドＢタイトネジ	01
	165	WE774700	BIND HEAD S-TIGHT SCREW	4x10 MFZN2W3			バインドＳタイトネジ	01
	166	WE774600	SCREW IC	3x18 MFZN2W3		JT	スクリュー ＩＣ	01
	167	WF002600	PW HEAD B-TIGHT SCREW	3x8 MFZN2W3			ＰＷヘッドＢタイトネジ	01
	169	VZ893000	SPECIAL S-TIGHT SCREW	4x8-10 MFNI33	GD,TI		化粧ネジＳタイト	02
	169	VK522100	SPECIAL S-TIGHT SCREW	4x8-10 MFC2BL	BL		化粧ネジＳタイト	01
	170	AA627310	GROUND TERMINAL				ＧＮＤターミナル	01
	171	VD069600	PW HEAD S-TIGHT SCREW	4x8-10 MFNI33	GD,TI		ＰＷヘッドＳタイトネジ	01
	171	VH313200	PW HEAD S-TIGHT SCREW	4x8-10 MFNI3BL	BL		ＰＷヘッドＳタイトネジ	01
	174	WE774800	BIND HEAD P-TIGHT SCREW	3x8 MFZN2W3			バインドＰタイトネジ	01
	175	V6509600	JACK SCREW	SS6-A47511848			ジャックスクリュー	01
	180	WJ045200	SHEET BARRIER			UCRTKAL	シートバリアー	01
	181	WJ053900	SHEET TOP			CRTKABGE	シートトップ	
	182	WG160000	DAMPER	T2x40x100		JBGE	ダンパー	04


＊New Parts ＊新規部品

• ACCESSORIES






























	Ref No.	Part No.	Description		Remarks	Markets	部 品 名	ランク
*	200	WN984100	REMOTE CONTROL	RAV387		J	リモコン	
*	200	WN984000	REMOTE CONTROL	RAV386		UC	リモコン	
*	200	WN984200	REMOTE CONTROL	RAV388		RTKABGEL	リモコン	
*	200-1	AAX90660	BATTERY COVER		F71-7320-02001		電池蓋	
*	201	WP337200	SIMPLIFIED REMOTE CONTROL	RAV36		UCRTKABGEL	簡易リモコン	
*	201-1	WQ785800	BATTERY HOLDER	CG4335 Black color	10030-0042400	UCRTKABGEL	電池ホルダー	
	202	V6267000	INDOOR FM ANTENNA	1.4m 1pc		JUCRTL	ＦＭ簡易アンテナ	03
	202	VQ147100	INDOOR FM ANTENNA	1.4m 1pc		KABGE	ＦＭ簡易アンテナ	02
	203	VR248500	AM LOOP ANTENNA	1.0m 1pc		JCRTKABGEL	ＡＭループアンテナ	03
	203	WE746800	AM LOOP ANTENNA	1.2m 1pc		U	ＡＭ　ループアンテナ	
⚠	204	V8466900	POWER CABLE	2m 1pc		J	電源コード	10
⚠	204	V7704800	POWER CABLE	2m 1pc		UC	電源コード	05
⚠	204	WK391000	POWER CABLE	2m 1pc		R	電源コード	
⚠	204	V9358400	POWER CABLE	2m 1pc		T	電源コード	05
⚠	204	WH641300	POWER CABLE	2m 1pc		K	電源コード	
⚠	204	WB750900	POWER CABLE	2m 1pc		A	電源コード	07
⚠	204	WB751000	POWER CABLE	2m 1pc		B	電源コード	08
⚠	204	V7704900	POWER CABLE	2m 1pc		GE	電源コード	06
* ⚠	204	WQ577000	POWER CABLE	2m 1pc		L	電源コード	
⚠	205	V7704900	POWER CABLE	2m 1pc		L	電源コード	06
	206	WB929200	OPTIMIZER MICROPHONE	6m 1pc	EMX-251		オプティマイザーマイク	08
*	207	WQ600800	FERRITE CORE for AM LOOP ANT.	1pc	ZCAT1518-0730-BK	U	クランプフィルタ	
	208	VU590000	BINDING TIE for AM LOOP ANT.	100mm Black 1pc	CBTD001B	U	インシュロックタイ	01
			BATTERY	LR03, AAA, UM-4 4pcs			乾電池	
			LITHIUM BATTERY	CR2025 1pc		UCRTKABGEL	リチウム電池	
			SERVICE TOOLS				サービス用部品	
		MF115300	FLEXIBLE FLAT CABLE	15P 300mm P=1.25			カード電線	
*		WQ662700	FLEXIBLE FLAT CABLE	27P 320mm P=1.0			カード電線	
		WM785100	FLEXIBLE FLAT CABLE	20P 300mm P=1.0			カード電線	
		MF111300	FLEXIBLE FLAT CABLE	11P 300mm P=1.25			カード電線	
*		WQ724300	FLEXIBLE FLAT CABLE	37P 340mm P=1.0			カード電線	

※ New Parts　＊新規部品


• FRONT PANEL and SUB CHASSIS UNIT



	Ref No.	Part No.	Description		Remarks	Markets	部 品 名	ランク
*	1-1	WN990800	FRONT PANEL		GD	J	フロントパネル	
*	1-1	WN990600	FRONT PANEL		GD	RTK	フロントパネル	
*	1-1	WP295400	FRONT PANEL		BL	J	フロントパネル	
*	1-1	WN990500	FRONT PANEL		BL	UCRTABGEL	フロントパネル	
*	1-1	WN990700	FRONT PANEL		TI		フロントパネル	
	1-2	WF121100	BUTTON LENS				ボタンレンズ	01
	1-3	WH186000	ESCUTCHEON D5		GD		エスカッションＤ５	06
	1-3	WH185800	ESCUTCHEON D5		BL		エスカッションＤ５	06
	1-3	WH186100	ESCUTCHEON D5		TI		エスカッションＤ５	
	1-4	WH384900	ESCUTCHEON PJ		GD		エスカッションＰＪ	01
	1-4	WH384800	ESCUTCHEON PJ		BL		エスカッションＰＪ	
	1-4	WH385000	ESCUTCHEON PJ		TI		エスカッションＰＪ	
	1-7	V6034200	EMBLEM		GD		エンブレム	03
	1-7	V6034100	EMBLEM		BL,TI		エンブレム	03
	2-1	WH567400	P.C.B. ASS'Y	OPERATION		J	ＰＣＢ ＯＰＥＲＡＴＩＯＮ	12
	2-1	WH567500	P.C.B. ASS'Y	OPERATION		UCRTKABGEL	ＰＣＢ ＯＰＥＲＡＴＩＯＮ	
*	2-14	WP505200	FLEXIBLE FLAT CABLE	15P 140mm P=1.25			カード電線	
*	2-15	WM784800	FLEXIBLE FLAT CABLE	27P 100mm P=1.0 BL			カード電線	03
*	2-22	WQ714100	SUB PANEL		GD	J	サブパネル	
*	2-22	WQ713300	SUB PANEL		GD	RTK	サブパネル	
*	2-22	WP323700	SUB PANEL		BL	J	サブパネル	
*	2-22	WQ713200	SUB PANEL		BL	UCRTABGEL	サブパネル	
*	2-22	WQ713400	SUB PANEL		TI		サブパネル	
	2-23	V9126500	SHAFT				シャフト	01
*	2-24	WN996900	WINDOW PANEL LID				ウインドウ	
*	2-25	WN997900	ESCUTCHEON VI		GD	J	エスカッションＶＩ	
*	2-25	WN997800	ESCUTCHEON VI		GD	RTK	エスカッションＶＩ	
*	2-25	WP280900	ESCUTCHEON VI		BL	J	エスカッションＶＩ	
*	2-25	WN997700	ESCUTCHEON VI		BL	UCRTABGEL	エスカッションＶＩ	
*	2-25	WN998000	ESCUTCHEON VI		TI		エスカッションＶＩ	
	2-26	V6002000	BUTTON D5		GD		ボタンＤ５	01
	2-26	V6001900	BUTTON D5		BL		ボタンＤ５	01
	2-26	WG290000	BUTTON D5		TI		ボタンＤ５	
*	2-28	WP001700	PANEL LID		GD	J	パネルリッド	
*	2-28	WP001600	PANEL LID		GD	RTK	パネルリッド	
*	2-28	WP295900	PANEL LID		BL	J	パネルリッド	
*	2-28	WP001400	PANEL LID		BL	U	パネルリッド	
*	2-28	WP392200	PANEL LID		BL	C	パネルリッド	
*	2-28	WP001500	PANEL LID		BL	RTABGEL	パネルリッド	
*	2-28	WP001800	PANEL LID		TI		パネルリッド	
*	2-29	WP002200	PLATE SP		GD	J	プレートＳＰ	
*	2-29	WP002100	PLATE SP		GD	RTK	プレートＳＰ	
*	2-29	WP296000	PLATE SP		BL	J	プレートＳＰ	
*	2-29	WP001900	PLATE SP		BL	UC	プレートＳＰ	
*	2-29	WP002000	PLATE SP		BL	RTABGEL	プレートＳＰ	
*	2-29	WP002300	PLATE SP		TI		プレートＳＰ	
*	2-30	WQ432100	HINGE L		GD		ヒンジＬ	
*	2-30	WQ432000	HINGE L		BL		ヒンジＬ	
*	2-30	WQ432200	HINGE L		TI		ヒンジＬ	
	2-31	V6005400	HINGE R		GD		ヒンジＲ	01
	2-31	V6005300	HINGE R		BL		ヒンジＲ	
	2-31	V6005500	HINGE R		TI		ヒンジＲ	
	2-32	V4593300	SPRING LID				スプリングＬＩＤ	01
	2-33	V9124600	DAMPER GEAR				ダンパーギヤ	03
	2-36	VY940400	CUSHION LID	T=0.8			クッションＬＩＤ	01
	2-38	WC144500	CUSHION	5x10			クッション	
	2-52	WE774800	BIND HEAD P-TIGHT SCREW	3x8 MFZN2W3			バインドＰタイトネジ	01
	2-53	WE973700	BIND HEAD P-TIGHT SCREW	2.6x6 MFZN2W3			バインドＰタイトネジ	01
	2-55	WG959600	PW HEAD TAPPING B-T. SCREW	3x6-8 MFZN2W3			ＰＷヘッドＢタイトネジ	01
	2-56	WM220800	HEXAGONAL HEAD B-TIGHT SCREW	3x15 SP MFZN2W3			６角Ｂタイトネジ	01
*	9	WQ134200	P.C.B. ASS'Y	FL			ＰＣＢ ＦＬ	

＊New Parts ＊新規部品

- **AMP UNIT**




	Ref No.	Part No.	Description		Remarks	Markets	部 品 名	ランク
*	3-1	WQ138600	P.C.B. ASS'Y	MAIN		J	ＰＣＢ　ＭＡＩＮ	
*	3-1	WQ138700	P.C.B. ASS'Y	MAIN		UCRTA	ＰＣＢ　ＭＡＩＮ	
*	3-1	WQ138800	P.C.B. ASS'Y	MAIN		KBGEL	ＰＣＢ　ＭＡＩＮ	
	3-17	WG432400	SUPPORT TR-6				サポートＴＲ－６	03
*	3-22	WP952300	RADIATION SHEET	TC-20EG			シート　放熱	
	3-25	VQ368600	PUSH RIVET	P3555-B			プッシュリベット	01
	3-32	WM220800	HEXAGONAL HEAD B-TIGHT SCREW	3x15 SP MFZN2W3			６角Ｂタイトネジ	01
	3-33	WF002600	PW HEAD B-TIGHT SCREW	3x8 MFZN2W3			ＰＷヘッドＢタイトネジ	01
	3-34	WE774100	BIND HEAD BONDING B-T. SCREW	3x8 MFZN2B3			ボンディングＢタイトネジ	01
	3-35	WE774300	BIND HEAD B-TIGHT SCREW	3x8 MFZN2W3			バインドＢタイトネジ	01
	3-107	WC879400	DAMPER	360x10 t=1			ダンパー	
*	4	WQ134500	P.C.B. ASS'Y	POWER		J	ＰＣＢ　ＰＯＷＥＲ	
*	4	WQ134600	P.C.B. ASS'Y	POWER		U	ＰＣＢ　ＰＯＷＥＲ	
*	4	WQ134700	P.C.B. ASS'Y	POWER		C	ＰＣＢ　ＰＯＷＥＲ	
*	4	WQ134800	P.C.B. ASS'Y	POWER		R	ＰＣＢ　ＰＯＷＥＲ	
*	4	WQ134900	P.C.B. ASS'Y	POWER		T	ＰＣＢ　ＰＯＷＥＲ	
*	4	WQ135000	P.C.B. ASS'Y	POWER		K	ＰＣＢ　ＰＯＷＥＲ	
*	4	WQ135100	P.C.B. ASS'Y	POWER		A	ＰＣＢ　ＰＯＷＥＲ	
*	4	WQ135200	P.C.B. ASS'Y	POWER		B	ＰＣＢ　ＰＯＷＥＲ	
*	4	WQ135300	P.C.B. ASS'Y	POWER		GE	ＰＣＢ　ＰＯＷＥＲ	
*	4	WQ135400	P.C.B. ASS'Y	POWER		L	ＰＣＢ　ＰＯＷＥＲ	
*	10	WQ140900	P.C.B. ASS'Y	DCCNVT			ＰＣＢ　ＤＣＣＮＶＴ	

＊New Parts　＊新規部品


■ REMOTE CONTROL

● RAV386 (RX-V3900: U, C models), RAV388 (RX-V3900: R, T, K, A, B, G, E, L models), RAV387 (DSP-AX3900: J model)

SCHEMATIC DIAGRAMS 1/2




SCHEMATIC DIAGRAMS 2/2




PANELS


RAV386
RX-V3900
(U, C models)




RAV388
RX-V3900
(R, T, K, A, B, G, E, L models)



RAV387
DSP-AX3900
(J model)



KYE NO. LAYOUT



KEY CODE

NO.	Label	MODE	LEARN	MACRO operation	BACK LIGHT	AMP ID1 (default) MAIN	AMP ID1 (default) ZONE2	AMP ID1 (default) ZONE3	AMP ID1 (default) ZONE4	AMP ID2 MAIN	AMP ID2 ZONE2	AMP ID2 ZONE3	AMP ID2 ZONE4				LCD display 5 letters	LCD display 3 letters	Preset code Library	Preset code Brand	Preset code Brand No.
MACRO mode														OFF	ON						
3	STANDBY	1	YES	YES	YES	7E-7F	7E-BB	7A-EE	7A-7C	7E-7F81	7E-BB45	7A-EE10	7A-7C82	Power STANDBY	Macro feature			STB			
4	POWER	1	YES	YES	YES	7E-7E	7E-BA	7A-ED	7A-7B	7E-7E80	7E-BA44	7A-ED13	7A-7B85	Power ON	Macro feature			PWR			
5	MULTI CH IN	1	YES	YES	YES	7A-87	–	–	–	7A-8779	–	–	–				MULTI	MLT	DVD	YAMAHA1	04306
6	V-AUX	1	YES	YES	YES	7A-55	7A-D8	7A-F0	7A-7D	7A-55AB	7A-D826	7A-F00E	7A-7D83				V-AUX	AUX	–	–	00000
7	PHONO	1	YES	YES	YES	7A-14	7A-D0	7A-F1	7A-7E	7A-14EA	7A-D02E	7A-F10F	7A-7E80				PHONO	PHO	–	–	00000
8	DOCK	1	YES	YES	YES	7F01-4A	7F01-4B	7F01-4C	7F01-4D	7F01-4AB4	7F01-4BB5	7F01-4CB2	7F01-4DB3				DOCK	DCK	SOURCE	YAMAHA	00012
9	BD/HD DVD	1	YES	YES	YES	7A-C8	7A-CE	7A-FB	7A-28	7A-C836	7A-CE30	7A-FB05	7A-28D6				BD/HD	BD	BD	YAMAHA1	04706
10	DVD	1	YES	YES	YES	7A-C1	7A-CD	7A-FC	7A-29	7A-C13F	7A-CD33	7A-FC02	7A-29D7				DVD	DVD	DVD	YAMAHA1	04306
11	CD	1	YES	YES	YES	7A-15	7A-D1	7A-F2	7A-7F	7A-15EB	7A-D12F	7A-F20C	7A-7F81	Output IR signal & change Device mode			CD	CD	CD	YAMAHA2	01205
12	MD/CD-R	1	YES	YES	YES	7A-19	7A-D4	7A-F5	7A-22	7A-19E7	7A-D42A	7A-F50B	7A-22DC				CD-R	CDR	CD-R	YAMAHA	01405
13	CBL/SAT	1	YES	YES	YES	7A-C0	7A-CC	7A-F7	7A-24	7A-C03E	7A-CC32	7A-F709	7A-24DA				CBSAT	SAT	–	–	00000
14	TV	1	YES	YES	YES	7A-54	7A-D9	7A-F6	7A-23	7A-54AA	7A-D927	7A-F608	7A-23DD				TV	TV	–	–	00000
15	DVR	1	YES	YES	YES	7A-13	7A-D7	7A-FA	7A-27	7A-13ED	7A-D729	7A-FA04	7A-27D9		Macro feature & change Device mode		DVR	DVR	DVR	YAMAHA	00707
16	VCR	1	YES	YES	YES	7A-0F	7A-D6	7A-F9	7A-26	7A-0FF1	7A-D628	7A-F907	7A-26D8				VCR	VCR	–	–	00000
17	TUNER	1	YES	YES	YES	7A-16	7A-D2	7A-F3	7A-20	7A-16E8	7A-D22C	7A-F30D	7A-20DE				TUNER	TUN	SOURCE	YAMAHA	00012
18	XM	1	YES	YES	YES	7A-B4	7A-B8	7A-B9	7A-2A	7A-B44A	7A-B846	7A-B947	7A-2AD4				XM	XM	SOURCE	YAMAHA	00012
	A	1	YES	YES	YES	–	–	–	–	–	–	–	–	Change Device mode			A	A	–	–	00000
19	SIRIUS	1	YES	YES	YES	7A-39	7A-3A	7A-3B	7A-3C	7A-39C7	7A-3AC4	7A-3BC5	7A-3CC2	Output IR signal & change Device mode			SSR	SSR	SOURCE	YAMAHA	00012
	B	1	YES	YES	YES	–	–	–	–	–	–	–	–	Change Device mode			B	B	–	–	00000
20	A	1	YES	YES	YES	–	–	–	–	–	–	–	–				A	A	–	–	00000
	USB	1	YES	YES	YES	7F01-3F	7F01-40	7F01-41	7F01-49	7F01-3FC1	7F01-40BE	7F01-41BF	7F01-49B7	Output IR signal & change Device mode			USB	USB	SOURCE	YAMAHA	00012
	NET/USB	1	YES	YES	YES	7F01-3F	7F01-40	7F01-41	7F01-49	7F01-3FC1	7F01-40BE	7F01-41BF	7F01-49B7				NET	NET	SOURCE	YAMAHA	00012
21	INPUT SELECT down	1	–	–	–	–	–	–	–	–	–	–	–	Select mode(down)							
22	INPUT SELECT up	1	–	–	–	–	–	–	–	–	–	–	–	Select mode(up)							
23	SETUP	1	–	–	–	–	–	–	–	–	–	–	–	Setup on/off							
24	ID	1	–	–	–	–	–	–	–	–	–	–	–	Change ID (ID1/ID2)							
25	MACRO	1	–	–	–	–	–	–	–	–	–	–	–	Macro on/off							
26	ZONE	1	–	–	–	–	–	–	–	–	–	–	–	Change Zone (Main/Zone2/Zone3/Zone4)							
27	MEMORY1	1	YES	–	YES	7A-007F	7A-017E	7A-027D	7A-1867	7A-007E	7A-017F	7A-027C	7A-1866								
28	MEMORY2	1	YES	–	YES	7A-037C	7A-047B	7A-057A	7A-1966	7A-037D	7A-047A	7A-057B	7A-1967	Output IR signal & change Device mode							
29	MEMORY3	1	YES	–	YES	7A-0679	7A-0778	7A-0877	7A-1A65	7A-0678	7A-0779	7A-0876	7A-1A64								
30	MEMORY4	1	YES	–	YES	7A-0976	7A-0A75	7A-0B74	7A-1B64	7A-0977	7A-0A74	7A-0B75	7A-1B65								

AMP/TV/SOURCE switch Device mode						AMP								TV	SOURCE MULTI	V-AUX	PHONO	MD/TAPE	BD/HDDVD	DVD	CD	CD-R	DOCK	DTV/CBL	DVR	VCR	TUNER	XM	A	SIRIUS	B	A	USB	NET/USB	OPTN1	OPTN2
1	TV POWER	20	YES	–	YES	Punch to TV								–	Punch to TV																				
2	AV POWER	20	YES	–	YES	Punch to SOURCE									7C-80	–	–	–	–	7C-80	79-60	7F-80	7F01-50	–	048. 012	–	7F01-50	7F01-50	–	7F01-50	–	–	7F01-50	7F01-50	–	–
31	TITLE	20	YES	–	YES	7A-433C	7A-3A45	7A-3D42	7A-403F	7A-433D	7A-3A44	7A-3D43	7A-403E	–	7C-B1	–	–	–	–	7C-B1	–	–	7F01-5D	–	048. 200	–	7F01-5D	7F01-5D	–	7F01-5D	–	–	7F01-5D	7F01-5D	–	–
32	UP	20	YES	–	YES	7A-9D	7A-2B54	7A-304F	7A-354A	7A-9D63	7A-2B55	7A-304E	7A-354B	–	7C-B4	–	–	–	–	7C-B4	–	–	7F01-61	–	048. 088	–	7F01-61	7F01-61	–	7F01-61	–	–	7F01-61	7F01-61	–	–
33	MENU	20	YES	–	YES	7A-84	7A-3B44	7A-443B	7A-413E	7A-847A	7A-3B45	7A-443A	7A-413F	–	7C-B2	–	–	–	–	7C-B2	–	–	7F01-5E	–	048. 084	–	7F01-5E	7F01-5E	–	7F01-5E	–	–	7F01-5E	7F01-5E	–	–
34	VOL UP	1	YES	–	YES	7A-1A	7A-DA	7A-FD	7A-2B	7A-1AE4	7A-DA24	7A-FD03	7A-2BD5		Punch to AMP																					
35	LEFT	20	YES	–	YES	7A-9F	7A-2D52	7A-324D	7A-3748	7A-9F61	7A-2D53	7A-324C	7A-3749	–	7C-B5	–	–	–	–	7C-B5	–	–	7F01-62	–	048. 090	–	7F01-62	7F01-62	–	7F01-62	–	–	7F01-62	7F01-62	–	–
36	ENTER	20	YES	–	YES	7A-DE	7A-2F50	7A-344B	7A-3946	7A-DE20	7A-2F51	7A-344A	7A-3947	–	7C-B8	–	–	–	–	7C-B8	–	–	7F01-63	–	048. 092	–	7F01-63	7F01-63	–	7F01-63	–	–	7F01-63	7F01-63	–	–
37	RIGHT	20	YES	–	YES	7A-9E	7A-2E51	7A-334C	7A-3847	7A-9E60	7A-2E50	7A-334D	7A-3846	–	7C-B6	–	–	–	–	7C-B6	–	–	7F01-64	–	048. 091	–	7F01-64	7F01-64	–	7F01-64	–	–	7F01-64	7F01-64	–	–
38	VOL DOWN	1	YES	–	YES	7A-1B	7A-DB	7A-FE	7A-2C	7A-1BE5	7A-DB25	7A-FE00	7A-2CD2		Punch to AMP																					
39	RETURN	20	YES	–	YES	7A-AA	7A-3C43	7A-3F40	7A-423D	7A-AA54	7A-3C42	7A-3F41	7A-423C	–	7C-B7	–	–	–	–	7C-B7	–	–	7F01-5F	–	048. 131	–	7F01-5F	7F01-5F	–	7F01-5F	–	–	7F01-5F	7F01-5F	–	–
40	DOWN	20	YES	–	YES	7A-9C	7A-2C53	7A-314E	7A-3649	7A-9C62	7A-2C52	7A-314F	7A-3648	–	7C-B3	–	–	–	–	7C-B3	–	–	7F01-65	–	048. 089	–	7F01-65	7F01-65	–	7F01-65	–	–	7F01-65	7F01-65	–	–
41	DISPLAY	20	YES	–	YES	7A-C2	7A-36	7A-37	7A-38	7A-C23C	7A-36C8	7A-37C9	7A-38C6	–	7C-A6	–	–	79-A5	–	7C-A6	79-0A	7F-9E	7F01-60	–	048. 015	–	7F01-60	7F01-60	–	7F01-60	–	–	7F01-60	7F01-60	–	–
42	MUTE	1	YES	–	YES	7A-1C	7A-DC	7A-FF	7A-2D	7A-1CE2	7A-DC22	7A-FF01	7A-2DD3		Punch to AMP																					
43	REC	20	YES	–	YES	Punch to SOURCE									7C-8B	–	–	79-AF	–	7C-8B	79-4F	–	7F01-66	–	048. 055	–	7F01-66	7F01-66	–	7F01-66	–	–	7F01-66	7F01-66	–	–
44	PAUSE	20	YES	–	YES										7C-83	–	–	79-A9	–	7C-83	79-55	7F-83	7F01-67	–	048. 048	–	7F01-67	7F01-67	–	7F01-67	–	–	7F01-67	7F01-67	–	–
45	PLAY	20	YES	–	YES										7C-82	–	–	79-A8	–	7C-82	79-02	7F-82	7F01-68	–	048. 044	–	7F01-68	7F01-68	–	7F01-68	–	–	7F01-68	7F01-68	–	–
46	STOP	20	YES	–	YES										7C-85	–	–	79-AA	–	7C-85	79-56	7F-84	7F01-69	–	048. 049	–	7F01-69	7F01-69	–	7F01-69	–	–	7F01-69	7F01-69	–	–
47	REW(SEARCH)	20	YES	–	YES										7C-86	–	–	79-AC	–	7C-86	79-05	7F-88	7F01-6A	–	048. 041	–	7F01-6A	7F01-6A	–	7F01-6A	–	–	7F01-6A	7F01-6A	–	–
48	FF(SEARCH)	20	YES	–	YES										7C-87	–	–	79-AD	–	7C-87	79-06	7F-89	7F01-6B	–	048. 040	–	7F01-6B	7F01-6B	–	7F01-6B	–	–	7F01-6B	7F01-6B	–	–
49	CHP/SKIP-	20	YES	–	YES										7C-B9	–	–	79-AB	–	7C-B9	79-04	7F-86	7F01-6C	–	048. 033	–	7F01-6C	7F01-6C	–	7F01-6C	–	–	7F01-6C	7F01-6C	–	–
50	CHP/SKIP+	20	YES	–	YES										7C-BA	–	–	79-AE	–	7C-BA	79-07	7F-87	7F01-6D	–	048. 032	–	7F01-6D	7F01-6D	–	7F01-6D	–	–	7F01-6D	7F01-6D	–	–
51	1	20	YES	–	–	7A-88	–	–	–	7A-8876	–	–	–	–	7C-94	–	–	79-85	–	7C-94	79-11	7F-91	7F01-51	–	048. 001	–	7F01-51	7F01-51	–	7F01-51	–	–	7F01-51	7F01-51	–	–
52	2	20	YES	–	–	7A-89	–	–	–	7A-8977	–	–	–	–	7C-95	–	–	79-86	–	7C-95	79-12	7F-92	7F01-52	–	048. 002	–	7F01-52	7F01-52	–	7F01-52	–	–	7F01-52	7F01-52	–	–
53	3	20	YES	–	–	7A-8A	–	–	–	7A-8A74	–	–	–	–	7C-96	–	–	79-87	–	7C-96	79-13	7F-93	7F01-53	–	048. 003	–	7F01-53	7F01-53	–	7F01-53	–	–	7F01-53	7F01-53	–	–
54	4	20	YES	–	–	7A-8B	–	–	–	7A-8B75	–	–	–	–	7C-97	–	–	79-88	–	7C-97	79-14	7F-94	7F01-54	–	048. 004	–	7F01-54	7F01-54	–	7F01-54	–	–	7F01-54	7F01-54	–	–
55	5	20	YES	–	–	7A-8C	–	–	–	7A-8C72	–	–	–	–	7C-98	–	–	79-89	–	7C-98	79-15	7F-95	7F01-55	–	048. 005	–	7F01-55	7F01-55	–	7F01-55	–	–	7F01-55	7F01-55	–	–
56	6	20	YES	–	–	7A-94	–	–	–	7A-946A	–	–	–	–	7C-99	–	–	79-8A	–	7C-99	79-16	7F-96	7F01-56	–	048. 006	–	7F01-56	7F01-56	–	7F01-56	–	–	7F01-56	7F01-56	–	–
57	7	20	YES	–	–	7A-8D	–	–	–	7A-8D73	–	–	–	–	7C-9A	–	–	79-8B	–	7C-9A	79-17	7F-97	7F01-57	–	048. 007	–	7F01-57	7F01-57	–	7F01-57	–	–	7F01-57	7F01-57	–	–
58	8	20	YES	–	–	7A-56	–	–	–	7A-56A8	–	–	–	–	7C-9B	–	–	79-8C	–	7C-9B	79-18	7F-98	7F01-58	–	048. 008	–	7F01-58	7F01-58	–	7F01-58	–	–	7F01-58	7F01-58	–	–
59	9	20	YES	–	–	7A-8F	–	–	–	7A-8F71	–	–	–	–	7C-9C	–	–	79-8D	–	7C-9C	79-19	7F-99	7F01-59	–	048. 009	–	7F01-59	7F01-59	–	7F01-59	–	–	7F01-59	7F01-59	–	–
60	0	20	YES	–	–	7A-35	–	–	–	7A-35CB	–	–	–	–	7C-93	–	–	79-8E	–	7C-93	79-10	7F-90	7F01-5A	–	048. 000	–	7F01-5A	7F01-5A	–	7F01-5A	–	–	7F01-5A	7F01-5A	–	–
61	+10	20	YES	–	–	7A-97	–	–	–	7A-9769	–	–	–	–	7C-9D	–	–	79-8F	–	7C-9D	79-1A	7F-9A	7F01-5B	–	–	–	7F01-5B	7F01-5B	–	7F01-5B	–	–	7F01-5B	7F01-5B	–	–
62	ENT	20	YES	–	–	7A-DD	–	–	–	7A-DD23	–	–	–	–	7C-9E	–	–	–	–	7C-9E	79-0B	7F-8A	7F01-5C	–	–	–	7F01-5C	7F01-5C	–	7F01-5C	–	–	7F01-5C	7F01-5C	–	–
63	TV VOL UP	20	YES	–	–	7A-2758	7A-2857	7A-2956	7A-2A55	7A-2759	7A-2856	7A-2957	7A-2A54	–	Punch to TV																					
64	TV CH UP	20	YES	–	–	7A-86	–	–	–	7A-8678	–	–	–	–																					
65	TV MUTE	20	YES	–	–	7A-30	7A-31	7A-32	7A-33	7A-30CE	7A-31CF	7A-32CC	7A-33CD	–																					
66	AUDIO	20	YES	–	–	7A-C3	–	–	–	7A-C33D	–	–	–	–	7C-AD	–	–	–	–	7C-AD	–	–	7F01-6E	–	048. 078	–	7F01-6E	7F01-6E	–	7F01-6E	–	–	7F01-6E	7F01-6E	–	–
67	TV VOL DOWN	20	YES	–	–	–	–	–	–	–	–	–	–	–	Punch to TV																					
68	TV CH DOWN	20	YES	–	–	–	–	–	–	–	–	–	–	–																					
69	TV INPUT	20	YES	–	–	7A-34	7A-34	7A-34	7A-34	7A-34CA	7A-34CA	7A-34CA	7A-34CA	–																					
70	3D	20	YES	–	–	7A-96	–	–	–	7A-9668	–	–	–	–	–	–	–	–	–	–	–	–	–	–	–	–	–	–	–	–	–	–	–	–	–	–

Macro default

NO.	MACRO	1	2	3	4 – 10	NO.	MACRO	1	2	3	4 – 10
3	STANDBY	K3	–	–	–	14	TV	K4	K14	–	–
4	POWER	K4	K1	–	–	15	DVR	K4	K15	–	–
5	MULTI CH IN	K4	K5	–	–	16	VCR	K4	K16	–	–
6	V-AUX	K4	K6	–	–	17	TUNER	K4	K17	–	–
7	PHONO	K4	K7	–	–	18	XM	K4	K18	–	–
8	DOCK	K4	K8	–	–		A	K4	K18	–	–
9	BD/HD DVD	K4	K9	–	–	19	SIRIUS	K4	K19	–	–
10	DVD	K4	K10	–	–		B	K4	K19	–	–
11	CD	K4	K11	–	–	20	A	K4	K20	–	–
12	MD/CD-R	K4	K12	–	–		USB	K4	K20	–	–
13	CBL/SAT	K4	K13	–	–		NET/USB	K4	K20	–	–

* Punch to AMP : Punch through to AMP mode
* Punch to SOURCE : Punch through to SOURCE mode
* Punch to TV : Punch through to TV mode

<Protocol>

16bit NEC (Custom), 16bit NEC (Data), 16bit NEC (Custom and Data)
All timings are identical with standard NEC protocol except data configuration.

Standard NEC protocol
Leader code
Custom code (8bit)
/Custom code (8bit reverse data)
Data code (8bit)
/Data code (8bit reverse data)
EX) 7A-00


16bit NEC (Custom)
Leader code
Custom code (16bit, no 8bit reverse data)
Data code (8bit)
/Data code (8bit reverse data)
EX) 7F01-00

16bit NEC (Data)
Leader code
Custom code (8bit)
/Custom code (8bit reverse data)
Data code (16bit, no 8bit reverse data)
EX) 7F-0000


16bit NEC (Custom and Data)
Leader code
Custom code (16bit, no 8bit reverse data)
Data code (16bit, no 8bit reverse data)
EX) 7F01-0000

● RAV36 (RX-V3900: U, C, R, T, K, A, B, G, E, L models)


SCHEMATIC DIAGRAM



PANEL



KEY NO. LAYOUT



KEY CODE

Key No.	Key name	Code							
		ID1				ID2			
		MAIN	ZONE2	ZONE3	ZONE4	MAIN	ZONE2	ZONE3	ZONE4
1	STANDBY	7E-7F	7E-BB	7A-EE	7A-7C	7E-7F81	7E-BB45	7A-EE10	7A-7C82
2	POWER	7E-7E	7E-BA	7A-ED	7A-7B	7E-7E80	7E-BA44	7A-ED13	7A-7B85
6	SYSTEM MEMORY 1	7A-007F	7A-017E	7A-027D	7A-1867	7A-007E	7A-017F	7A-027C	7A-1866
7	SYSTEM MEMORY 2	7A-037C	7A-047B	7A-057A	7A-1966	7A-037D	7A-047A	7A-057B	7A-1967
8	SYSTEM MEMORY 3	7A-0679	7A-0778	7A-0877	7A-1A65	7A-0678	7A-0779	7A-0876	7A-1A64
9	SYSTEM MEMORY 4	7A-0976	7A-0A75	7A-0B74	7A-1B64	7A-0977	7A-0A74	7A-0B75	7A-1B65
11	INPUT ◁	7A-235C	7A-245B	7A-255A	7A-2659	7A-235D	7A-245A	7A-255B	7A-2658
13	INPUT ▷	7A-1F60	7A-205F	7A-215E	7A-225D	7A-1F61	7A-205E	7A-215F	7A-225C
15	STATUS	7A-433C	7A-3A45	7A-3D42	7A-403F	7A-433D	7A-3A44	7A-3D43	7A-403E
16	▲ (up)	7A-9D	7A-2B54	7A-304F	7A-354A	7A-9D63	7A-2B55	7A-304E	7A-354B
17	MENU	7A-84	7A-3B44	7A-3E41	7A-413E	7A-847A	7A-3B45	7A-3E40	7A-413F
18	VOLUME +	7A-1A	7A-DA	7A-FD	7A-2B	7A-1AE4	7A-DA24	7A-FD03	7A-2BD5
19	◀ (left)	7A-9F	7A-2D52	7A-324D	7A-3748	7A-9F61	7A-2D53	7A-324C	7A-3749
20	ENTER	7A-DE	7A-2F50	7A-344B	7A-3946	7A-DE20	7A-2F51	7A-344A	7A-3947
21	▶ (right)	7A-9E	7A-2E51	7A-334C	7A-3847	7A-9E60	7A-2E50	7A-334D	7A-3846
22	VOLUME -	7A-1B	7A-DB	7A-FE	7A-2C	7A-1BE5	7A-DB25	7A-FE00	7A-2CD2
23	RETURN / SUBMENU	7A-AA	7A-3C43	7A-3F40	7A-423D	7A-AA54	7A-3C42	7A-3F41	7A-423C
24	▼ (down)	7A-9C	7A-2C53	7A-314E	7A-3649	7A-9C62	7A-2C52	7A-314F	7A-3648
25	DISPLAY	7A-C2	7A-36	7A-37	7A-38	7A-C23C	7A-36C8	7A-37C9	7A-38C6
26	MUTE	7A-1C	7A-DC	7A-FF	7A-2D	7A-1CE2	7A-DC22	7A-FF01	7A-2DD3

ID SETTING

Key No.	Key name		Key No.	Key name		SETTING
19	◀ (left)	with	6	SYSTEM MEMORY 1	more then 3 sec. ➡	ID1
			7	SYSTEM MEMORY 2		ID2

ZONE SETTING

Key No.	Key name		Key No.	Key name		SETTING
21	▶ (right)	with	6	SYSTEM MEMORY 1	more then 3 sec. ➡	MAIN
			7	SYSTEM MEMORY 2		ZONE2
			8	SYSTEM MEMORY 3		ZONE3
			9	SYSTEM MEMORY 4		ZONE4

Advanced setup

This unit has additional menus that are displayed in the front panel display. The advanced setup menu offers additional operations to adjust and customize the way this unit operates. Change the initial settings (indicated in bold under each parameter) to reflect the needs of your listening environment.

Notes

- Only Ⓐ**MASTER ON/OFF**, Ⓝ**STRAIGHT** and the Ⓜ**PROGRAM** selector are effective while you are using the advanced setup menu.
- All the other operations cannot be made while you are using the advanced setup menu.
- The advanced setup menu is only available in the front panel display.

Using the advanced setup menu

1 Press Ⓐ MASTER ON/OFF on the front panel to release it outward to the OFF position to turn off this unit.

2 Press and hold Ⓝ STRAIGHT and then press Ⓐ MASTER ON/OFF inward to the ON position to turn on this unit.

This unit turns on, and "ADVANCED SETUP" appears in the front panel display.



3 Rotate the Ⓜ PROGRAM selector to select the parameter you want to adjust.

4 Press Ⓝ STRAIGHT repeatedly to change the selected parameter setting.

5 Press Ⓐ MASTER ON/OFF to release it outward to the OFF position to save the new setting and turn off this unit.

The settings you made are reflected next time you turn on this unit.

■ Speaker impedance SPEAKER IMP.

Use this feature to set the speaker impedance of this unit so that it matches that of your speakers.

Choice	Descriptions
8ΩMIN	Select this setting to set the speaker impedance to 8 Ω. The impedance of each speaker must be 8 Ω or higher.
6ΩMIN	Select this setting to set the speaker impedance to 6 Ω. The impedance of each speaker must be 6 Ω or higher (front speakers only: 4 Ω or higher).

■ Remote sensor REMOTE SENSOR

Use this feature to activate or deactivate the signal-receiving capability of the remote control sensor on the front panel of this unit.

Choice	Descriptions
ON	Select this setting if you want to activate the signal-receiving capability of the remote control sensor.
OFF	Select this setting if you want to deactivate the signal-receiving capability of the remote control sensor.

Note

We recommend setting the parameter to "ON" in most cases.

■ Wake on RS-232C access RS232C STANDBY

Use this feature to set this unit to transmit data via the RS-232C interface when this unit is in the standby mode.

Choice	Functions
YES	Select this setting to set this unit to transmit data via the RS-232C interface.
NO	Select this setting to set this unit not to transmit data via the RS-232C interface.

Initial setting:
[U.S.A. and Canada models]: YES
[Other models]: NO

■ Remote control ID setting REMOTE CON AMP

Use this feature to set the remote control ID of this unit for remote control recognition.


Choice	Descriptions
ID1	Select this setting when the ID of the remote control is set to "ID1"
ID2	Select this setting when the ID of the remote control is set to "ID2"

Setting remote control ID

Use this feature to set the remote control ID. This feature is useful when you control multiple Yamaha AV receiver or amplifier with using the remote control.

Press ⑰ID repeatedly using a ballpoint pen or similar object on the remote control to select the desired remote control ID.

Each time you press ⑰**ID**, the remote control ID indicator changes as shown below.



To set the remote control ID of the simplified remote control.

■ SIRIUS Satellite Radio Parental Lock code number reset SIRIUS PIN (U.S.A. and Canada models only)

Use this feature to set the code number for the SIRIUS Satellite Radio Parental Lock feature to the initial factory setting.

Choice	Descriptions
RESET	Sets the code number to the initial factory setting.
CANCEL	Cancels the reset of the code number.

■ Tuner frequency step TUNER FRQ STEP (Asia and General models only)

Use this feature to set the tuner frequency step according to the frequency spacing in your area.

Choice	Descriptions
AM10/ FM100	Select this setting for North, Central and South America.
AM9/FM50	Select this setting for all other countries.

■ Bi-amplifier mode BI-AMP

Use this feature to activate or deactivate the bi-amplifier function.

Choice	Descriptions
ON	Select this setting if you want to activate the bi-amplifier function.
OFF	Select this setting if you want to deactivate the bi-amplifier function.

Note

When “BI-AMP” is set to “ON”, the SURROUND BACK terminals cannot be used to connect surround back speakers in that the terminals are already used for the bi-amplifier connection.

■ Recovery and backup of the system settings RECOV./BACKUP

Use this feature to save and restore the settings of this unit.

Choice	Descriptions
RECOVERY	Restoring the saved setting of this unit.
BACKUP	Saves the current settings of this unit.
CANCEL	Cancels the recovery or backup of the settings of this unit.

Notes

- This unit does not save the FM/AM preset stations, preset USB/ network items, and system memory settings.
- If no settings are saved, you cannot select “RECOVERY”.

■ Parameter initialization INITIALIZE

Use this feature to reset the parameters of this unit to the initial factory settings. You can select the category of parameters to be initialized.

Choice	Descriptions
DSP PARAM	Select this setting to initialize all the parameters of the sound field parameters.
VIDEO	Select this setting to initialize all the parameters in “Video” and “Display Set” (except “Short Message” and “Playback Screen”).
NETWORK	Select this setting to initialize all the parameters in “Network” and MusicCAST information stored in this unit.
ALL	Select this setting to initialize all the parameters of this unit.
CANCEL	Select this setting to cancel the initialization procedure.

To initialize the parameters of each sound field program, use “Initialize” in “Stereo/Surround”.

■ MAC address filter MAC FILTER

Use this feature to filter the access to this unit via LAN to control this unit by the MAC address of the accessing PC.

Choice	Descriptions
ON	Only allows to accept the access from the PC whose MAC address is registered to this unit.
OFF	Allows to accept the access from any PC.

You can register the MAC address that is allowed to access when “MAC FILTER” is set to “ON” by using the Web browser.

■ TV format TV FORMAT

Use this feature to set the color encoding format of your television.
Choices: NTSC, PAL
Initial setting:
[U.S.A., Canada, General and Korea models]: NTSC
[Other models]: PAL

■ HDMI monitor check MONITOR CHECK

Use this feature to activate or deactivate the monitor check function of this unit.

Choice	Descriptions
YES	This unit receives the information of the available video signal resolutions from the video monitor connected via HDMI and you can only select the resolutions supported by the video monitor in "Resolution".
SKIP	You can select any resolution in "Resolution".

■ Language LANGUAGE

Use this feature to select the language of your choice that appears in the GUI (graphical user interface) menu, OSD display in the zone monitor and the messages that appear in the front panel display.
Choices: **ENGLISH** (English), JAPANESE (Japanese), FRENCH (French), GERMAN (German), SPANISH (Spanish), RUSSIAN (Russian)

You can also select the display language with the GUI menu

LANGUAGE	GUI menu	Front panel display	Zone OSD
RUSSIAN	O	O	—
JAPANESE	O	—	—
Other languages	O	O	O

O ··· The selected language is displayed.
— ··· The selected language is not displayed. The menu items and messages are displayed in English.

■ Firmware update FIRM UPDATE

Use this feature to update the firmware of this unit. For details on how to update the firmware, refer to information supplied with updates.

Choice	Descriptions
USB	Updates the firmware of this unit using a USB memory.
NETWORK	Updates the firmware of this unit via network.

To start updating the firmware, rotate the Ⓜ**PROGRAM** selector to select "USB" or "NETWORK" and then press Ⓓ**MENU**.

Notes

- Do not use this feature unless you need to update the firmware.
- Be sure to read information supplied with updates before performing firmware updates.

■ Firmware version VERSION

Use this feature to check the version of the firmware currently installed on this unit.

Resetting the system

Use this feature to reset all the parameters of this unit to the initial factory settings.

Notes

- This procedure completely resets all the parameters of this unit including the "GUI menu" parameters.
- The initial factory settings are activated next time you turn on this unit.

To cancel the initialization procedure at any time without making any changes, press Ⓐ**MASTER ON/OFF** on the front panel to release it outward to the OFF position.

1 Press Ⓐ MASTER ON/OFF on the front panel to release it outward to the OFF position to turn off this unit.

2 Press and hold Ⓝ STRAIGHT and then press Ⓐ MASTER ON/OFF inward to the ON position to turn on this unit.

This unit turns on, and "ADVANCED SETUP" appears in the front panel display.



3 Rotate the Ⓜ PROGRAM selector to select "INITIALIZE".



4 Press Ⓝ STRAIGHT repeatedly to select "ALL".



Select "CANCEL" to cancel the initialization procedure without making any changes.

5 Press Ⓐ MASTER ON/OFF to release it outward to the OFF position to confirm your selection and turn off this unit.

本機の設定を変更する（ADVANCED SETUP）

フロントパネルディスプレイに表示されるメニューを見ながらさまざまな項目を設定します。アドバンストセットアップメニューでは、本機の設定を初期設定に戻したりリモコン ID を変更したりすることができます。お好みに合わせて、設定を変更してください。各項目の初期設定は太字で記載しています。

ご注意

- アドバンストセットアップメニューの操作中は、本体の ⒶMASTER ON/OFF スイッチ、ⓃSTRAIGHT キー、ⓂPROGRAM セレクター以外は機能しません。
- アドバンストセットアップメニューの操作中は他の操作はできません。
- アドバンストセットアップメニューはフロントパネルディスプレイでのみ操作できます。

アドバンストセットアップメニューの操作手順

1 本体の ⒶMASTER ON/OFF スイッチを押して本機の電源をオフにする。

2 ⓃSTRAIGHT キーを押しながらもう一度 ⒶMASTER ON/OFF スイッチを押す。

本機の電源がオンになり、アドバンストセットアップメニューがフロントパネルディスプレイに表示されます。



3 ⓂPROGRAM セレクターを回して、設定したいメニューを選ぶ。

4 ⓃSTRAIGHT キーを繰り返し押して、設定したい項目を選ぶ。

5 ⒶMASTER ON/OFF スイッチを押して本機の電源をオフにし、変更した設定を保存する。

☼
変更した設定は、次回電源を入れたときから有効になります。

■ リモコンセンサー設定 REMOTE SENSOR

リモコンでの本体操作を有効にするか無効にするかを設定します。

選択項目	説明
ON	リモコンの操作を有効にします。本機をリモコンで操作できます。通常はこの設定でお使いください。
OFF	リモコンの操作を無効にします。本機をリモコンで操作できません。

ご注意

通常は「ON」に設定することをおすすめします。

■ RS-232C 通信設定 RS232C STANDBY

本機がスタンバイのときに、RS-232C 端子からのデータを受信するか、受信しないかを設定します。

選択項目	説明
YES	RS-232C 端子からのデータを受信します。
NO	RS-232C 端子からのデータを受信しません。


■ リモコン ID 設定 REMOTE CON AMP

本体操作用のリモコン ID をリモコンの操作用コードに合わせて変更します。

選択項目	説明
ID1	リモコンの操作用コードを「ID1」に設定しているときに選びます。
ID2	リモコンの操作用コードを「ID2」に設定しているときに選びます。

リモコンの操作用コードを設定する
リモコンの操作用コードを設定します。複数のヤマハ製アンプをリモコンを使って操作する場合に、本機とは別のアンプが動作するのを防止します。

ボールペンなどで ⑰ID ボタンを押して ID を切り替える。
⑰ID ボタンを押すごとに、ID インジケーターが以下のように表示されます。



■ バイアンプ設定 BI-AMP
バイアンプ機能を設定します。

選択項目	説明
ON	バイアンプ機能をオンにします。
OFF	バイアンプ機能をオフにします。

ご注意

「BI-AMP」を「ON」に設定すると SURROUND BACK 端子はバイアンプ用として使われるので、サラウンドバックスピーカー接続用としては使えません。

■ 設定の保存／呼び出し RECOV./BACKUP
本機の設定を保存したり、呼び出したりします。

選択項目	説明
RECOVERY	本機の設定を呼び出します。
BACKUP	本機の現在の設定を保存します。
CANCEL	設定の保存／呼び出しを中止します。

ご注意

- プリセットした FM/AM 放送局や USB デバイス／ネットワークオーディオの音楽ファイル、システムメモリーの内容は保存しません。
- 設定を保存していない場合、「RECOVERY」は選べません。

■ 初期設定に戻す INITIALIZE
変更した設定を初期設定に戻します。初期設定に戻す項目を選んでください。

選択項目	説明
DSP PARAM	すべての音場プログラムパラメーターを初期設定に戻します。
VIDEO	すべての「映像の設定」、および「表示設定」（「ショートメッセージ」、「プレイバック表示」を除く）の内容を初期設定に戻します。
NETWORK	すべての「ネットワーク設定」の内容を初期設定に戻します。
ALL	本機のすべての設定を初期設定に戻します。
CANCEL	初期設定に戻しません。

音場プログラムごとに音場パラメーターを初期設定に戻すには、「サラウンド選択」の「初期化」で設定してください。

■ MAC フィルター設定 MAC FILTER
ネットワークからの接続を、特定の MAC アドレスのパソコンからに制限するか制限しないかを設定します。

選択項目	説明
ON	特定の MAC アドレスのパソコンからに制限します。
OFF	MAC アドレスによる制限をしません。

「MAC FILTER」を「ON」に設定した場合に制御できるパソコンの MAC アドレスは Web メニューで設定できます。

■ 映像信号方式設定 TV FORMAT
テレビの信号方式に合わせて、本機の MONITOR OUT 端子、および HDMI OUT 端子から出力される壁紙の信号方式を切り替えます。
選択項目：**NTSC**、PAL

■ HDMI モニターチェック設定 MONITOR CHECK
本機のモニターチェック機能のオン、オフを設定します。

選択項目	説明
YES	HDMI 接続したモニターが対応している解像度の情報を自動的にチェックします。「解像度」で、モニターが一対応している解像度のみ選べます。
SKIP	「解像度」のすべての解像度を選べます。

本機の設定を変更する（ADVANCED SETUP）

■ 表示言語設定 LANGUAGE

モニター画面やフロントパネルディスプレイに表示する文字の言語を設定します。

選択項目：**JAPANESE**（日本語）、FRENCH（フランス語）、GERMAN（ドイツ語）、SPANISH（スペイン語）、RUSSIAN（ロシア語）、ENGLISH（英語）

セットメニューでも表示言語を設定できます。

ご注意

「JAPANESE」を選んだ場合でもフロントパネルディスプレイには英語で表示されます。

■ ファームウェアの更新 FIRM UPDATE

本機のファームウェアを更新するときに使用します。ファームウェアの更新方法について詳しくはファームウェアと共に提供される情報をご覧ください。

選択項目	説明
USB	USB メモリーを使って本機のファームウェアを更新します。
NETWORK	ネットワークを経由して本機のファームウェアを更新します。

ファームウェアの更新を開始するには、**ⓂPROGRAM** セレクターを回して「USB」、または「NETWORK」を選び、**ⒹMENU** キーを押してください。

ご注意

- ファームウェアを更新する必要がない場合は本機能を操作しないでください。
- ファームウェアを更新する前に、ファームウェアと共に提供される情報をご確認ください。

■ ファームウェアのバージョン確認 VERSION

現在本機にインストールされているファームウェアのバージョンを表示します。

すべての設定を初期設定に戻す

変更したセットメニューの設定や音場パラメーター、プリセットした FM ／ AM 放送局などをすべて初期設定に戻します。

ご注意

- セットメニューを含む本機のすべての設定が初期化されます。
- 変更した設定は、次回電源を入れたときから有効になります。

初期化操作を中止するにはフロントパネルの **ⒶMASTER ON/OFF** スイッチを押して本機の電源をオフにしてください。

1 ⒶMASTER ON/OFF スイッチを押して本機の電源をオフにする。

2 ⓃSTRAIGHTキーを押しながらⒶMASTER ON/OFF スイッチを押して本機の電源をオンにする。


本機の電源がオンになり、フロントパネルディスプレイにアドバンストセットアップメニューが表示されます。



3 ⓂPROGRAM セレクターを回して「INITIALIZE」を選ぶ。



4 ⓃSTRAIGHT キーを繰り返し押して「ALL」を選ぶ。



初期設定に戻さない場合は「CANCEL」を選んでください。

5 ⒶMASTER ON/OFF スイッチを押して本機の電源をオフにする。

すべての設定が初期設定に戻ります。

MEMO

RX-V3900/DSP-AX3900

YAMAHA