Pioneer sound.vision.soul

Service Manual



SC-09TX

ORDER NO.
RRV3711

AUDIO/VIDEO MULTI-CHANNEL RECEIVER

SC-09TX

THIS MANUAL IS APPLICABLE TO THE FOLLOWING MODEL(S) AND TYPE(S).

Model	Type	Power Requirement	Remarks
SC-09TX	KUXJ/CA	AC 120 V	

This service manual should be used together with the following manual(s):

Model	Order No.	Remarks
SC-09TX/KUXJ/CA	RRV3708	BLOCK DIAGRAM, DIAGNOSIS, EXPLODED VIEWS, etc.

For details, refer to "Important Check Points for good servicing".

PIONEER CORPORATION 4-1, Meguro 1-chome, Meguro-ku, Tokyo 153-8654, Japan
PIONEER ELECTRONICS (USA) INC. P.O. Box 1760, Long Beach, CA 90801-1760, U.S.A.
PIONEER EUROPE NV Haven 1087, Keetberglaan 1, 9120 Melsele, Belgium
PIONEER ELECTRONICS ASIACENTRE PTE. LTD. 253 Alexandra Road, #04-01, Singapore 159936
ⓒ**PIONEER CORPORATION 2008**

T-ZZV MAR. 2008 Printed in Japan

SAFETY INFORMATION

[Important Check Points for Good Servicing]

In this manual, procedures that must be performed during repairs are marked with the below symbol.
Please be sure to confirm and follow these procedures.

1. Product safety

Please conform to product regulations (such as safety and radiation regulations), and maintain a safe servicing environment by following the safety instructions described in this manual.

① Use specified parts for repair.

Use genuine parts. Be sure to use important parts for safety.

② Do not perform modifications without proper instructions.

Please follow the specified safety methods when modification(addition/change of parts) is required due to interferences such as radio/TV interference and foreign noise.

③ Make sure the soldering of repaired locations is properly performed.

When you solder while repairing, please be sure that there are no cold solder and other debris.
Soldering should be finished with the proper quantity. (Refer to the example)

④ Make sure the screws are tightly fastened.

Please be sure that all screws are fastened, and that there are no loose screws.

⑤ Make sure each connectors are correctly inserted.

Please be sure that all connectors are inserted, and that there are no imperfect insertion.

⑥ Make sure the wiring cables are set to their original state.

Please replace the wiring and cables to the original state after repairs.
In addition, be sure that there are no pinched wires, etc.

⑦ Make sure screws and soldering scraps do not remain inside the product.

Please check that neither solder debris nor screws remain inside the product.

⑧ There should be no semi-broken wires, scratches, melting, etc. on the coating of the power cord.

Damaged power cords may lead to fire accidents, so please be sure that there are no damages.
If you find a damaged power cord, please exchange it with a suitable one.

⑨ There should be no spark traces or similar marks on the power plug.

When spark traces or similar marks are found on the power supply plug, please check the connection and advise on secure connections and suitable usage. Please exchange the power cord if necessary.

⑩ Safe environment should be secured during servicing.

When you perform repairs, please pay attention to static electricity, furniture, household articles, etc. in order to prevent injuries.
Please pay attention to your surroundings and repair safely.

2. Adjustments

To keep the original performance of the products, optimum adjustments and confirmation of characteristics within specification.
Adjustments should be performed in accordance with the procedures/instructions described in this manual.

3. Lubricants, Glues, and Replacement parts

Use grease and adhesives that are equal to the specified substance.
Make sure the proper amount is applied.

4. Cleaning

For parts that require cleaning, such as optical pickups, tape deck heads, lenses and mirrors used in projection monitors, proper cleaning should be performed to restore their performances.

5. Shipping mode and Shipping screws

To protect products from damages or failures during transit, the shipping mode should be set or the shipping screws should be installed before shipment. Please be sure to follow this method especially if it is specified in this manual.

CONTENTS

SAFETY INFORMATION 2
10. SCHEMATIC DIAGRAM 6
10.1 OVERALL WIRING DIAGRAM (1/2) 6
10.2 OVERALL WIRING DIAGRAM (2/2) 8
10.3 REFERENCE MARK LIST 9
10.4 A-AUDIO ASSY 10
10.5 V-AUDIO ASSY 12
10.6 AUDIO BRIDGE 1,2,3,4 ASSYS 14
10.7 REC SEL ASSY 16
10.8 MULTI CH IN ASSY (1/2) 18
10.9 MULTI CH IN ASSY (2/2) 20
10.10 VOLUME ASSY (1/2) 22
10.11 VOLUME ASSY (2/2) 24
10.12 FRONT USB and FRONT INPUT ASSYS 26
10.13 DIGI BRIDGE and BUFF ASSYS 28
10.14 USB ASSY 30
10.15 NEW ITEM ASSY (1/2) 32
10.16 NEW ITEM ASSY (2/2) 34
10.17 MAIN DIGITAL ASSY (1/8) 36
10.18 MAIN DIGITAL ASSY (2/8) 38
10.19 MAIN DIGITAL ASSY (3/8) 40
10.20 MAIN DIGITAL ASSY (4/8) 42
10.21 MAIN DIGITAL ASSY (5/8) 44
10.22 MAIN DIGITAL ASSY (6/8) 46
10.23 MAIN DIGITAL ASSY (7/8) 48
10.24 MAIN DIGITAL ASSY (8/8) 50
10.25 SUB DIGITAL ASSY (1/2) 52
10.26 SUB DIGITAL ASSY (2/2) 54
10.27 DSP ASSY (1/3) (Guide page) 56
10.28 DSP ASSY (2/3) 62
10.26 DSP ASSY (3/3) (Guide page) 74
10.30 DAC ASSY (1/4) 70
10.31 DAC ASSY (2/4) 72
10.32 DAC ASSY (3/4) 74
10.33 DAC ASSY (4/4) 76
10.34 HN MODULE ASSY (1/6) 78
10.35 HN MODULE ASSY (2/6) 80
10.36 HN MODULE ASSY (3/6) 82
10.37 HN MODULE ASSY (4/6) 84
10.38 HN MODULE ASSY (5/6) 86
10.39 HN MODULE ASSY (6/6) 88
10.40 PREOUT ASSY (1/2) 90
10.41 PREOUT ASSY (2/2) 92
10.42 MOTHER 1 ASSY (1/3) 94
10.43 MOTHER 1 ASSY (2/3) 96
10.44 MOTHER 1 ASSY (3/3) 98
10.45 ICE INTERFACE ASSY 100
10.46 COMPOSITE ASSY (1/2) 102
10.47 COMPOSITE ASSY (2/2) 104
10.48 S-VIDEO ASSY 106
10.49 COMPONENT ASSY 108
10.50 VIDEO BRIDGE ASSY 110
10.51 IR 232C ASSY (1/2) 112
10.52 IR 232C ASSY (2/2) 114
10.53 MOTHER 2 ASSY (1/2) 116
10.54 MOTHER 2 ASSY (2/2) 118
10.55 HDMI ASSY (1/8) (Guide page) 120
10.56 HDMI ASSY (2/8) (Guide page) 126
10.57 HDMI ASSY (3/8) (Guide page) 132
10.58 HDMI ASSY (4/8) 138
10.59 HDMI ASSY (5/8) 140
10.60 HDMI ASSY (6/8) (Guide page) 142
10.61 HDMI ASSY (7/8) 148
10.62 HDMI ASSY (8/8) 150

10.63 DISPLAY, ICE BLUE, PERCH FFC, PERCH DISP and PERCH PS ASSYS....152
10.64 5.1 TFT MODULE....154
10.65 TACT,POWER SW and VOL ENCODER ASSYS....156
10.66 ICE REG, ICE 5 and ICE 12 ASSYS....158
10.67 DD DSP,DSP DIODE & HN DIODE ASSYS....160
10.68 DD DISP and FAN-12V ASSYS....162
10.69 DD HDMI and HDMI DIODE ASSYS....164
10.70 2CH DD ASSY....166
10.71 A-REG and DA DIODE ASSYS....168
10.72 PRIMARY and ICE INPUT 4CH ASSYS....170
10.73 ICE INPUT 6CH ASSY....172
10.74 PFC and INLET ASSYS....174
11. PCB CONNECTION DIAGRAM....176
11.1 A-AUDIO, AUDIO BRIDGE 1 and AUDIO BRIDGE 2 ASSYS....178
11.2 V-AUDIO and REC SEL ASSYS....182
11.3 AUDIO BRIDGE 3, AUDIO BRIDGE 4 and MULTI CH IN ASSYS....186
11.4 VOLUME ASSY....190
11.5 FRONT USB and HN MODULE ASSYS....192
11.6 FRONT INPUT and FRONT BUFF ASSYS....196
11.7 USB and NEW ITEM ASSYS....200
11.8 MAIN DIGITAL ASSY....204
11.9 SUB DIGITAL ASSY....208
11.10 DSP and DIGI BRIDGE ASSYS....210
11.11 DAC ASSY....214
11.12 PREOUT, ICE INPUT 4CH and ICE INPUT 6CH ASSYS....218
11.13 MOTHER 1 ASSY....222
11.14 S-VIDEO, ICE INTERFACE and VIDEO BRIDGE ASSYS....226
11.15 COMPOSITE and COMPONENT ASSYS....230
11.16 IR 232C ASSY....234
11.17 MOTHER 2 ASSY....236
11.18 HDMI ASSY....240
11.19 DISPLAY,ICEBLUE,PERCH FFC,PERCH DISP and PERCH PS ASSYS....244
11.20 TACT,POWER SW,VOL ENCODER and FUNC ENCODER ASSYS....248
11.21 ICE REG, ICE 5 and ICE 12 ASSYS....252
11.22 DD DSP, DSP DIODE and HN DIODE ASSYS....254
11.23 FAN-12V and DD DISP ASSYS....256
11.24 DD HDMI, HDMI DIODE and 2CH DD ASSYS....258
11.25 A-REG and DA DIODE ASSYS....262
11.26 PRIMARY, PFC and INLET ASSYS....266
12. PCB PARTS LIST....270

A

B

C

D

E

F

10. SCHEMATIC DIAGRAM

10.1 OVERALL WIRING DIAGRAM (1/2)




AN
VOL ENCODER ASSY (AWX8754)
AK
5.1 TFT MODULE (AWV7006)
AO
FUNC ENCODER ASSY (AWX8753)
AF DISPLAY ASSY (AWX8777)
AG ICE BLUE ASSY (AWX8780)
AL TACT ASSY (AWX8730)
AM
POWER SW ASSY (AWX8755)
AD
MOTHER 2 ASSY (AWX8776)
K FRONT INPUT ASSY (AWX8774)
L
FRONT BUFF ASSY (AWX8775)
AH
PERCH FFC ASSY (AWX8782)
AI
PERCH DISP ASSY (AWX8783)
AJ
PERCH PS ASSY (AWX8785)
BC
PRIMARY ASSY (AWX8756)
BB
DA DIODE ASSY (AWX8965)
AA
VIDEO BRIDGE ASSY (AWX8743)
G
REC SEL ASSY (AWX8740)
X
COMPOSITE ASSY (AWX8778)
Y
S-VIDEO ASSY (AWX8725)
Z
COMPONENT ASSY (AWX8726)
AC
IR 232C ASSY (AWX8746)
A
A-AUDIO ASSY (AWX8745)
B
V-AUDIO ASSY (AWX8744)
BRIDGE 2 (AWX8765)
CN5081
CN5006
CN5001
CN8011
CN5009 (STBY)
CN5004
CN5008
CN5071
CN5003
CN5101
CN5002
CN5007
CN5085
CN5191
CN4751
CN4752
CN23
CN22
CN5091
CN5082
CN6502
CN5092
CN5093
CN5202
CN5201
CN5302
CN5301
CN5304
CN5303
CN5305
CN4121
CN8514
CN6501
CN6503
CN24
CN4004
CN4012
CN4002
CN4007
CN4001
CN8513
CN4005
CN8512
CN3411
CN3006
CN3421
CN3010
CN3108
CN3855
CN3110
CN3009
CN3852
CN3007
CN3851
CN3854
CN3109
CN8021
CN8023
CN8022
CN8024
CN3005
CN8025
CN3004
CN8026
CN3106
CN8027
CN3105
CN8028
CN8029
CN8501
CN8030
CN8502
CN8031
CN8503
CN2005
CN2004
CN2003
CN8504
CN2002
CN8505
CN2001
CN601
CN2501
CN2502
CN2203
CN2403
CN2405
CN2202
CN8506
CN2201
CN602
CN2402
CN8507
CN2401
CN603
CN6406
CN6405
CN6407
CN6408
CN6401
CN8508
CN6402
CN8509
CN6403
CN8510
CN6404
CN8511
CN6409
CN251
CN8051
CN8052
JP4121
JP4102
J1936 ADX7646-
J1937 ADX7644-
J1940 ADX7593-
ADD7630-
ADD7557
ADD7631-
ADD7562-
ADD7629-
ADD7558-
ADD7632-
ADX7544-
ADX7617-
ADX7611
ADX7580-
ADD7593-
ADD7592-
ADD7581-
ADD7569-
ADD7589-
ADD7590-
ADD7591-
ADD7616-
PF04PG0520
J1913 28/120
J1918 3/70
J1919 3/150
J1916 7/120
J1917 4/100
J1933 4/80
J1936 ADX7646-
J1938 ADX7645-
J1924 5/100
J1925 9/100
J1927 24100
J1928 26125
J1929 30150
J1930 8/210
J1931 14450
J1932 12460
J1934
J5201
J5005 8150
D20PYY0820E
5005
5102
5081
YELLOW
WHITE
WHITE
RED
FU3 : REK1149 (4 A/125 V)
FU4 : REK1145 (2 A/125 V)
(OVERALL WIRING DIAGRAM 2/2) TO MAIN ASSY (V/A J1 1) ADX7560-
(OVERALL WIRING DIAGRAM 2/2) TO MAIN ASSY (V/A J1 3,18) ADX7545-
WALL PAPER uCOM
i.Link uCOM
HDMI uCOM
DISP-LAY uCOM
EVENT uCOM

10.2 OVERALL WIRING DIAGRAM (2/2)



When ordering service parts, be sure to refer to "EXPLODED VIEWS and PARTS LIST" or "PCB PARTS LIST".
The ⚠ mark found on some component parts indicates the importance of the safety factor of the part. Therefore, when replacing, be sure to use parts of identical designation.
: The power supply is shown with the marked box.

10.3 REFERENCE MARK LIST

Ref. Mark	Assy Name	Ref. Mark	Assy Name	Ref. Mark	Assy Name
A	A-AUDIO ASSY	AA	VIDEO BRIDGE ASSY	BA	A-REG ASSY
B	V-AUDIO ASSY			BB	DA DIODE ASSY
C	AUDIO BRIDGE 1 ASSY	AC	IR 232C ASSY	BC	PRIMARY ASSY
D	AUDIO BRIDGE 2 ASSY	AD	MOTHER 2 ASSY	BD	ICE INPUT 4CH ASSY
E	AUDIO BRIDGE 3 ASSY	AE	HDMI ASSY	BE	ICE INPUT 6CH ASSY
F	AUDIO BRIDGE 4 ASSY	AF	DISPLAY ASSY	BF	PFC ASSY
G	REC SEL ASSY	AG	ICEBLUE ASSY	BG	INLET ASSY
H	MULTI CH IN ASSY	AH	PERCH FFC ASSY		ICEPOWER AMP ASSY
I	VOLUME ASSY	AI	PERCH DISP ASSY		ICEPOWER SMPS ASSY
J	FRONT USB ASSY	AJ	PERCH PS ASSY		FM/AM TUNER UNIT
K	FRONT INPUT ASSY	AK	5.1 TFT MODULE		
L	FRONT BUFF ASSY	AL	TACT ASSY		
M	USB ASSY	AM	POWER SW ASSY		
N	NEW ITEM ASSY	AN	VOL ENCODER ASSY		
O	MAIN DIGITAL ASSY	AO	FUNC ENCODER ASSY		
P	SUB DIGITAL ASSY	AP	ICE REG ASSY		
Q	DSP ASSY	AQ	ICE 5 ASSY		
R	DIGI BRIDGE ASSY	AR	ICE 12 ASSY		
S	DAC ASSY	AS	DD DSP ASSY		
T	HN MODULE ASSY	AT	DSP DIODE ASSY		
U	PREOUT ASSY	AU	HN DIODE ASSY		
V	MOTHER 1 ASSY	AV	FAN-12V ASSY		
W	ICE INTERFACE ASSY	AW	DD DISP ASSY		
X	COMPOSITE ASSY	AX	DD HDMI ASSY		
Y	S-VIDEO ASSY	AY	HDMI DIODE ASSY		
Z	COMPONENT ASSY	AZ	2CH DD ASSY		

10.4 A-AUDIO ASSY




G CN3852
CN3009
CKS1764-A
REC L
GNDSEP
REC R
Z3OUT R
GNDZ3
GNDZ3
Z3OUT L
Z3SEL L
GNDSEP
Z3SEL R
GNDD
INCLK
INDT
Z3IST
GNDSEP
Z2SEL L
GNDSEP
Z2SEL R
GNDSEP
V+15A
CN3010
CKS1764-A
Z3OUT L
GNDZ3
GNDZ3
Z3OUT R
V-15A
V-15A
V+15A
V+15A
GNDSEP
MULTI FR
GNDSEP
MULTI FL
GNDSEP
MAINOUT L
GNDA
GNDA
GNDA
GNDA
GNDA
MAINOUT R
D CN3421
GNDZ3
V-15A
(L)
(R)
Rch
R3052 220
R3057 220
R3058 220
R3054 220
R3055 220
IC3053 TC9273CFG-004-TBB <ZONE3>
IC3052 TC9273CFG-004-TBB <ZONE2>
Vdd
STB
DATA
Vss
GND
CK
C3055 0.01
C3056 0.01
C3053 0.01
C3054 0.01
C3057 100p CH
Lch
R3069 220
C3058 100p CH
R3056 220
C3059 100p CH
GNDD
CN3006
XKP3080-A
GNDA
iPod R
GNDA
GNDA
iPod L
V+15A
SIRIUS R
GNDSEP
SIRIUS L
GNDSEP
TUNER R
GNDSEP
TUNER L
V+15A
V+15A
GNDA
GNDA
V-15A
V-15A
C CN3411
CN3005
XKP3079-A
GNDA
GNDA
Z3 D/A R
GNDA
Z3 D/A L
GNDA
Z2 D/A R
GNDA
Z2 D/A L
GNDA
GNDD
GNDD
INCLK
INDT
Z3AIST
Z2AIST
MAIST
V 3/3 CN8025
CN3004
CKS1753-A
V-15A
V-15A
V-15A
GNDA
GNDA
GNDA
V+15A
V+15A
V 3/3 CN8026

10.5 V-AUDIO ASSY



NOTES

1.RESISTORS
Unit: k-kΩ, M-MΩ or Ω unless otherwise noted.
Rated power: 1/16W unless otherwise noted.
Tolerance: ±5%(J) unless otherwise noted.

2.CAPACITORS
No marked Capacitors are CEAT or CKSRYB.
Unit: p-pF or μF unless otherwise noted.
Rated Voltage: shown as
"Capacity(μF)/Voltage(V)",
or 50V unless otherwise noted.

3.DIODES
No marked Diodes are 1SS352.

※Parts or parts block marked by "STBY" are standby.

B


G CN3855
CN3110
CKS1759-A
GNDZ2
Z3SEL L
GNDZ2
Z3SEL R
GNDZ2
Z2SEL L
GNDZ2
Z2SEL R
GNDZ2
GNDZ2
Z2R
GNDZ2
GNDZ2
Z2L
Rch
Lch
IC3152 TC9273CFG-004-TBB <ZONE3>
IC3153 TC9273CFG-004-TBB <ZONE2>
Vdd
Vss
STB
DATA
GND
CK
C3153
C3154
C3155
C3156
C3157
C3158
C3159
100p CH
R3152
R3153
R3154
R3155
R3156
R3157
R3158
R3159
220
CN3108
KM200NA15
(MIC)
MIC
GNDA
V+15A
GNDA
GNDA
V-15A
HP RY
(FVR)
FV R
GNDA
(FVL)
FV L
GNDA
HP L
(HPL)
GHP
HP R
(HPR)
GHP
L CN5304
GNDD
GHP
CN3106
XKP3077-A
GNDD
INCLK
INDT
Z3VIST
Z2VIST
MVIST
GHP
GHP
HP L
GHP
HP R
GHP
HP RY
V 3/3 CN8027
GNDZ2
Z2L

10.6 AUDIO BRIDGE 1,2,3,4 ASSYS





C F

E AUDIO BRIDGE 3 ASSY (AWX8767)



D AUDIO BRIDGE2 ASSY (AWX8765)



NOTES

1.RESISTORS
Unit: k-k Ω , M-M Ω or Ω unless otherwise noted.
Rated power: 1/16W unless otherwise noted.
Tolerance: ±5%(J) unless otherwise noted.

2.CAPACITORS
No marked Capacitors are CEAT or CKSRYB.
Unit: p-pF or μF unless otherwise noted.
Rated Voltage: shown as
"Capacity(μF)/Voltage(V)",
or 50V unless otherwise noted.

3.DIODES
No marked Diodes are 1SS352.

※Parts or parts block marked by "STBY" are standby.

D E

10.7 REC SEL ASSY

G REC SEL ASSY (AWX8740)




B CN3109
B CN3110
CN3854
CKS1727-A
CN3855
CKS1725-A
V+15A
V+15A
MAINSEL L
GNDA
GNDA
GNDA
MAINSEL R
V-15A
V-15A
GNDSEP
VREC1 L
GNDSEP
VREC1 R
GNDSEP
VREC2 L
GNDSEP
VREC2 R
GNDZ2
Z3SEL L
GNDZ2
Z3SEL R
GNDZ2
Z2SEL L
GNDZ2
Z2SEL R
GNDZ2
GNDZ2
Z2R
GNDZ2
GNDZ2
GNDZ2
Z2L
GNDZ2S
GNDZ2
ZONE2
IC3881
TC9162CFG-TBB
Vdd
Vss
DATA
CK
STB
GND
C3881 0.01
C3882 0.01
R3882 220
R3881 220
R3883 220
C3885 100p
GNDD
C3861 1u
R3861 220
Lch
IC3861
(1/2)
BA4560RF-TBB
R3867 0
C3867 22/25
R3899 0
C3869 STBY
R3669 470k
R3863 470k
C3863 STBY
C3865 0.01
R3865 STBY
R3949 STBY
R3950 STBY
C3870 STBY
R3870 470k
R3864 470k
C3864 STBY
R3900 0
C3866 0.01
R3866 STBY
C3862 1u
R3862 220
Rch
R3868 0
C3868 22/25
IC3861(2/2)
BA4560RF-TBB

10.8 MULTI CH IN ASSY (1/2)

H 1/2 MULTI CH IN ASSY (AWX8739)





NOTES

1.RESISTORS
Unit: k-k Ω , M-M Ω or Ω unless otherwise noted.
Rated power: 1/16W unless otherwise noted.
Tolerance: ±5%(J) unless otherwise noted.

2.CAPACITORS
No marked Capacitors are CEAT or CKSRYB.
Unit: p-pF or μF unless otherwise noted.
Rated Voltage: shown as
"Capacity(μF)/Voltage(V)",
or 50V unless otherwise noted.

3.DIODES
No marked Diodes are 1SS352.

※ Parts or parts block marked by "STBY" are standby.

H 1/2

10.9 MULTI CH IN ASSY (2/2)

H 2/2 MULTI CH IN ASSY (AWX8739)





NOTES

1.RESISTORS
Unit: k-k Ω , M-M Ω or Ω unless otherwise noted.
Rated power: 1/16W unless otherwise noted.
Tolerance: ±5%(J) unless otherwise noted.

2.CAPACITORS
No marked Capacitors are CEAT or CKSRYB.
Unit: p-pF or μF unless otherwise noted.
Rated Voltage: shown as
"Capacity(μF)/Voltage(V)",
or 50V unless otherwise noted.

3.DIODES
No marked Diodes are 1SS352.

※Parts or parts block marked by "STBY" are standby.

10.10 VOLUME ASSY (1/2)




NOTES
1.RESISTORS
Unit: k-k Ω , M-M Ω or Ω unless otherwise noted.
Rated power: 1/16W unless otherwise noted.
Tolerance: ±5%(J) unless otherwise noted.
2.CAPACITORS
No marked Capacitors are CEAT or CKSRYB.
Unit: p-pF or μF unless otherwise noted.
Rated Voltage: shown as
"Capacity(μF)/Voltage(V)",
or 50V unless otherwise noted.
3.DIODES
No marked Diodes are 1SS352.
※Parts or parts block marked by "STBY" are standby.
3901
VEF1040-A
3902
VEF1040-A
PRE AMP &
VOLUME(SW)
IC3941
TC94A32BFG-TBB
IC3942 (1/2)
OPA2134UA-TBB
IC3942 (2/2)
OPA2134UA-TBB
CN3904
CKS1761-A
CN3905
CKS1761-A
F CN3431
F CN3433
IVSW1
IVSW2
MVCK
MVDT
MVST2
SW1
SW2
(SW1)
(SW2)
PV
I 2/2
I 1/2

10.11 VOLUME ASSY (2/2)

NOTES

1.RESISTORS
Unit: k-k Ω , M-M Ω or Ω unless otherwise noted.
Rated power: 1/16W unless otherwise noted.
Tolerance: ±5%(J) unless otherwise noted.

2.CAPACITORS
No marked Capacitors are CEAT or CKSRYB.
Unit: p-pF or μF unless otherwise noted.
Rated Voltage: shown as
"Capacity(μF)/Voltage(V)",
or 50V unless otherwise noted.

3.DIODES
No marked Diodes are 1SS352.

※Parts or parts block marked by "STBY" are standby.

2/2 VOLUME ASSY (AWX8737)



2/2


PRE AMP & VOLUME (F)
PRE AMP & VOLUME (C)
GNDA
V+15A
V-15A
GNDD
IVL
IVR
IVC1
IVC2
IC3501 TC94A32BFG-TBB
IC3521 TC94A32BFG-TBB
IC3502(1/2) OPA2134UA-TBB
IC3502 (2/2) OPA2134UA-TBB
IC3522(1/2) OPA2134UA-TBB
IC3522 (2/2) OPA2134UA-TBB
L
R
C1
C2
(L)
(R)
(C1)
(C2)
MVCK
MVDT
MVST1

10.12 FRONT USB and FRONT INPUT ASSYS





The ⚠ mark found on some component parts indicates the importance of the safety factor of the part. Therefore,when replacing,be sure to use parts of identical designation.

NOTES

1.RESISTORS
Unit: k-kΩ, M-MΩ or Ω unless otherwise noted.
Rated power: 1/16W unless otherwise noted.
Tolerance: (J)±5% unless otherwise noted.

2.CAPACITORS
No marked Capacitors are CEAT or CKSRYB.
Unit: p-pF or μF unless otherwise noted.
Rated Voltage: shown as "Capacity(μF)/Voltage(V)", or 50V unless otherwise noted.

3.DIODES
No marked Diodes are 1SS352.

※ Parts or parts block marked by "STBY" are standby.

10.13 DIGI BRIDGE and BUFF ASSYS



NOTES

1.RESISTORS
Unit: k-k Ω , M-M Ω or Ω unless otherwise noted.
Rated power: 1/16W unless otherwise noted.
Tolerance: ±5%(J) unless otherwise noted.

2.CAPACITORS
No marked Capacitors are CEAT or CKSRYB.
Unit: p-pF or μF unless otherwise noted.
Rated Voltage: shown as
"Capacity(μF)/Voltage(V)",
or 50V unless otherwise noted.

3.DIODES
No marked Diodes are 1SS352.

※Parts or parts block marked by "STBY" are standby.



10.14 USB ASSY




MAIN
IC781
IC741
TC7SZ125FU
CN702
HLEM11S-1
1/2 CN7008
IC702
NJM2872BF18
1.8VReg.
IC703
NJM2886DL3-33
3.3VReg.
BOOT MODE
5→3
3→5
V+3R3
V+5D
V+1R8
V3D
GNDD
CLK_OUT
XRST3
WUP3
USB_RX3
USB_TX
XRST
WUP
USB_RX
USB_TX
USB_TX3
SDCLK
SDCKE
Chip Size
RESISTOR
:2125Size RS1/10S~
:1608Size RS1/16S~
:1005Size RS1/16SS~
CAPACITOR
:2125Size CKSQ**~
:1608Size CCSR**~ CKSR**~
:1005Size CCSS**~ CKSS**~
ELECTRIC CAPS
JQ:CEJQ***M**

N 1/2 NEW ITEM ASSY (AWX8741)



NOTES

1.RESISTORS
Unit: k-kΩ, M-MΩ or Ω unless otherwise noted.
Rated power: 1/16W unless otherwise noted.
Tolerance: (J)±5% unless otherwise noted.

2.CAPACITORS
No marked Capacitors are CEAT or CKSRYB.
Unit: p-pF or μF unless otherwise noted.
Rated Voltage: shown as "Capacity(μF)/Voltage(V)", or 50V unless otherwise noted.

3.DIODES
No marked Diodes are 1SS352.

※Parts or parts block marked by "STBY" are standby.

N 1/2


V+3UN
V+5US
V+5US_IN
CN7001
XKP3081
V+5US
GNDU
GNDU
V+3UN
X232C
232C CTS
232C RX
232C TX
POFF
DISP DO
DISP CLK
DISP REQ
DISP RDY
DISP DI
MAIN DI
MAIN DO
MAIN CLK
MAIN REQ
MAIN RDY
MAIN RST
XUART2
V 2/3 CN8015
CN7003
CKS1760
GNDU(HR)
GNDU(HR)
HD_SCL
HD_SDA
HR_RST
XM_OL
XM_POW
XM_LSDT
XM_LINK
XM_RST
XM_IRQ
XM_TX
XM_RX
XM_RATE
XM_FS
XM_MUTE
V 2/3 CN8016
CN7009
CKS1754
XM_DT4
IPSPDIF
GNDIP
NET_RX
NET_TX
NET_RST
GNDU(NET)
IP VIDEO
GNDV
V+5V
V 2/3 CN8035
IPV
N 2/2
CN7008
CKS3376
USBCTL
USBXFLAG
USBPOW
V+5IP
USBXRST
GNDIP
IPSPDIF
GNDIP
USBWP
USBRX(DUM)
USBTX(DMU)
M CN702
N 1/2
XSIRST
NDI
NCLK
NREQ
XNRST
SIRX3
SITX3
TUDO3
232HDRX
X232
232HDTX
IPRX
IPUSB
IPTX
SIRX
SITX
TUDO
IPNRX
IPNTX
IC7003 (1/4) TC74VHC125FTS1
IC7003 (2/4)
IC7003 (3/4)
IC7003 (4/4)
IC7004 TC7SET08FUS1
IC7005 (1/6) TC74VHC04FTS1
IC7005 (2/6)
IC7005 (3/6)
IC7005 (4/6)
IC7005 (5/6)
IC7005 (6/6)
IC7006 (1/4)
IC7006 (2/4)
IC7006 (3/4)
IC7006 (4/4) TC74VHC125FTS
IC7007 (1/4)
IC7007 (2/4)
IC7007 (3/4)
IC7007 (4/4) TC74VHC125FTS1
X232
232CT
POFF
DNDO
DNCK
DNREQ
DNRDY
DNDI
NDO
NRDY
HRRST
XMOL
XMPOW
XMLSDT
XMLINK
XMRST
XMANT
XMTX
XMRX
XMRATE
XMFS
XMMUTE
XMDT4
NETRX
NETTX
NETRST
USBPOW
USBXRST
USBWP
V+5V
V+5IP
GNDV
STBY
GNDCH
GNDU
GNDIP

10.16 NEW ITEM ASSY (2/2)

N 2/2 NEW ITEM ASSY (AWX8741)




FROM TUNER MODULE
TUNER MODULE FM:80mA AM:60mA
(KU ONLY)
CN7005
CKS3376
T CE
T DI
T CLK
T DO
GNDT
TL
V+9T
TR
VSM
FM DET
GNDT
V+9T
V+12T2
V+12T1
V+12T
Q7101 2SA1602A(EF)
Q7103 2SD1664(PQR)
R7103 0
D7101 STBY
R7101 4.7k
R7102 4.7k
R7104 390
R7105 100
R7106 220
R7107 220
R7108 220
C7101 0.1/16
V+5US
R7109 100
IC7101
TC74VHCT08AFTS1
GNDU
C7103 STBY
D7102 UDZS10(B)
C7102 100/16
Q7102 RT1N431M (4.7k)
C7105 STBY
C7104 STBY
GNDT
V+15A
CN7002
iPod_R
GNDA
GNDA
iPod_L
V+15A
SIRIUS_R
GNDSEP
SIRIUS_L
GNDSEP
TUNER_R
GNDSEP
TUNER_L
V+12T
XKP3077
C CN3412
GNDEP
IC7204 BA4560F
R7223 5.1k
R7224 5.1k
R7225 10k
R7226 10k
R7227 10k
R7228 10k
R7229 100
C7209 10/50
R7230 100
C7210 10/50
C7231 STBY
C7232 STBY
R7231 0
R7232 0
R7233 0
R7234 0
R7235 STBY
R7236 STBY
R7237 STBY
R7238 STBY
C7235 STBY
C7236 STBY
C7237 STBY
C7238 STBY
IC7201 NJM2794V
C7205 4.7/50
C7206 4.7/50
C7207 4.7/50
C7208 4.7/50
C7203 100p CH
C7204 100p CH
C7211 10/50
C7212 0.1/25
C7213 0.1/25
C7220 22/25
C7229 0.1/25
R7205 100k
R7206 100k
V+12A
IPV
N 1/2
IC7202 NJM2505AF
C7214 4.7/50
C7215 4.7/50
R7208 100
R7209 100
C7216 STBY
C7217 0.1/16
C7218 STBY
R7210 0
R7211 STBY
V+5V
GNDV
Q7203 2SD1664(PQR)
R7219 STBY
R7220 680
R7221 100
C7227 47/25
C7233 STBY
D7212 UDZS12(B)
C7228 100/16
GNDA
IC7301 STBY
R7307 0
R7308 0
R7309 0
R7310 0
C7305 STBY
C7306 STBY
C7307 STBY
C7308 STBY
C7309 10/50
C7310 10/50
C7311 STBY
C7312 STBY
C7313 STBY
C7303 100p CH
C7304 100p CH
R7313 STBY
C7318 STBY
R7305 100k
R7306 100k
7001 VEF1040

10.17 MAIN DIGITAL ASSY (1/8)



MAIN DIGITAL ASSY
O 1/8 (JJ:AWX8722)
(KU/CA:AWX8721)

R CN995 V 2/3 CN8005

(*) MARKS		SIMUKE1	
MODEL		R187	R188
AWX8721	SC-09TX/KU	-	47k
AWX8722	SC-LX90/OTHER	47k	-



10.18 MAIN DIGITAL ASSY (2/8)



MAIN DIGITAL ASSY
O2/8 (JJ:AWX8722) (KU/CA:AWX8721)



10.19 MAIN DIGITAL ASSY (3/8)



MAIN DIGITAL ASSY
O 3/8 (JJ:AWX8722) (KU/CA:AWX8721)



V3/3 CN8008

10.20 MAIN DIGITAL ASSY (4/8)




O 1/8
O 2/8
O 1/8
Q 1/3 CN402
CN302
AKM7054
SPICLK
MISO
RST1
DSPON
REQ1
RST2
MMODE
RST3
REQ3
DDIRECT
SRC
DSDDIRECT
XTL0
Z4XM
SEL4B
SPDIS1
MOSI
ROWE
DS232
SS2
HREQ2
SPIDS3
BUSY2
DSDPCM
XSRC
XM
SEL4A
XON
GNDD
V+5D
V+5DSP
D300
RB050L-40
V+3DD17
V+3DD18
V+3DD19
V+3DD
V+3DD15
V+3DD16
V+3DD20
V+3DD21
IC342
IC343
IC344
IC345
IC346
IC340(1/4)
IC340(2/4)
IC340(3/4)
IC340(4/4)
IC341
TC74LCX157FTS1
TC74VHC08FTS1
DSPOUT
DSPIN
DOUT
DDSD
DDBD
DDCD
DDFD
HDXD
IEBK
HDBK
HDSDCLK
DDBK
DDXD
DDLK
DDMK
DOBK
DOLK
DOFD
BAMK
CD
SD
BD
WD
E1D
E2D
DSD1L
DSD3L
DSD4L
DSD5L
DSD7L
DSD3
LRCK6
DSDCLK
O 5/8
O 8/8
O 4/8

10.21 MAIN DIGITAL ASSY (5/8)




O3/8
XMFD
XMLK
XMBK
XMMK
V+3DD28
V+3DD
KU/CA : AWX8721 ONLY
IC511
TC74LCX157FTS1
IC505
TC74VHC153FT
EXCEPT AWX8721
R492
SEL5A
SEL5B
HDMI
XM
IELK
HDLK
ZL 33/16
C527
R
CN991
CN306
CKS1764
R
CN993
CN305
GNDD
V+3DD29
V+3DD30
V+3DD31
V+3DD32
V+3DD33
IC506 (1/2)
IC506 (2/2)
TC7WH125FU
IC508(1/4)
IC508(2/4)
IC508(3/4)
IC508(4/4)
IC509 (1/4)
IC509 (2/4)
IC509 (3/4)
IC509 (4/4)
TC74VHC08FTS1
IC510 (1/4)
IC510 (2/4)
IC510 (3/4)
IC510 (4/4)
IC347(2/4)
IC347(1/4)
IC347(3/4)
IC347(4/4)
TC74LCX125FTS1
KU/CA : AWX8721 ONLY
Z2DIN
Z3XM
ZDAC
BAUDIO
DOLK
DOBK
DOFD
XDSDDIRECT
Z2LK
Z2BK
Z2FD
Z2MK
Z3LK
Z3BK
Z3FD
Z3MK
BALCK
BABCK
BAFD
HDSD2
HDSD4
HDSD6
HDSD8
DSD2
DSD4
DSD6
DSD8
DOUT
O4/8
O8/8
O5/8

10.22 MAIN DIGITAL ASSY (6/8)




O 1/8
ATT
XADRST
192K
F96K
F48K
Q971(1/2)
RT3T22M
V+3AD1
V+5ADC1
CONT
V+3AD
IC651
AK5385BVF
AD CONVERTER
VREFL
AVSS
VCOM
LIN+
LIN-
CKS0
DVSS
DVSS
OVF
PDN
DIF
M/S
LRCK
BICK
VREFR
AVSS
TEST
RIN+
RIN-
AVDD
AVSS
BVSS
DFS1
HPFE
DFS0
MCLK
CKS1
SDTO
V+5AD
ADLK
ADBK
ADMK
ADFD
FL,FR
V+3AD2
V+5ADC2
IC751
C,SW
ADCD
AD
GNDAD
XM
GNDA
ADFR
GNDAZ
GNDASP
Z2ADFL
Z2ADFR
GNDD
XMDT4
XMMUTE
XMFS
XMRATE
XMRX
XMTX
XMANT
XMRST
XMLINK
XMLSDT
XMPOW
XMOL
CKS1764
CN972
O 5/8
O 4/8
V 3/3 CN8007
O 6/8

10.23 MAIN DIGITAL ASSY (7/8)




O1/8
XADRST
192K
F96K
F48K
CONT
V+3AD3
V+5ADC3
V+5AD
IC851
AK5385BVF
AD CONVERTER
SL,SR
VREFL
AVSS
VCOM
LIN+
LIN-
CKS0
DVDD
DVSS
OVF
PDN
DIF
M/S
LRCK
BICK
VREFR
AVSS
TEST
RIN+
RIN-
AVDD
AVSS
BVSS
DFS1
HPFE
DFS0
MCLK
CKS1
SDTO
C821
C822
C823
C824
C854
C816
C856
C855
ACH7196 10/50
L852
QTL1013
R851
R852
R853
R854
R857
R858
R855
R856
C851 ACH7272
220/6.3
L851
QTL1013
C815
D801
MC2848-11
D803
MC2846-11
D804
MC2846-11
D802
MC2846-11
ADLK
ADBK
V+3AD4
V+5ADC4
IC951
AK5385BVF
SBL,SBR
C921
C922
C923
C924
C954
C916
C956
C955
L952
QTL1013
R951
R952
R953
R954
R957
R958
R955
R956
C951 ACH7272
220/6.3
L951
QTL1013
C915
D901
MC2848-11
D903
MC2846-11
D904
MC2846-11
D902
MC2846-11
ADBD
AD
GNDAD
ADLK
ADBK
ADMK
ADSD
ADBD
O4/8
O7/8

10.24 MAIN DIGITAL ASSY (8/8)









101

ZCA-BK1 ×2



NOTES

1.RESISTORS
Unit : k-kΩ, M-MΩ or Ω unless otherwise noted.
Rated power: 1/16W unless otherwise noted.
Tolerance : ±5%(J) unless otherwise noted.

2.CAPACITORS
Unit : p-pF or μF unless otherwise noted.
Rated Voltage: shown as "Capacity(μF)/Voltage(V)", or 50V unless otherwise noted.

ZL : CEHAZL

※Parts or parts block marked by "*" or "STBY" are standby.

8/8

10.25 SUB DIGITAL ASSY (1/2)

P 1/2 SUB DIGITAL ASSY (AWX8747)



NOTES

1.RESISTORS
Unit : k-k Ω, M-M Ω or Ω unless otherwise noted.
Rated power: 1/16W unless otherwise noted.
Tolerance : ±5%(J) unless otherwise noted.

2.CAPACITORS
Unit : p-pF or μF unless otherwise noted.
Rated Voltage: shown as "Capacity(μF)/Voltage(V)", or 50V unless otherwise noted.

ZL : CEHAZL

※Parts or parts block marked by "*" or "STBY" are standby.

P 1/2


V+5DR4
V+5DR4
TC74VHCT08AFTS1
IC1904 (1/4)
IC1904 (2/4)
IC1904 (3/4)
IC1904 (4/4)
R1958 22
R1957 22
R1955 22
R1954 22
L1909 QTL1013
C1953 STBY
C1965 0.01 YB
R1829 100k
R1830 100k
CN1802
XKP3081
IPOD3
GNDD(IPOD)
IPOD5
GNDD
HDR5
GNDD(HDR)
HDR3
GNDD
NETSP3
GNDD(NET)
MAIN_SPDIF
GNDD
Z2_SPDIF
GNDD
Z4_SPDIF
V+5D
V+5D
GNDD
GNDD
V+3DR
V-5D
V 3/3 CN8011
V+5D
V+3DR
C1836 ACH7211 47/35
C1829 0.1/16 YB
C1830 0.1/16 YB
C1837 ACH7211 47/35
C1838 0.1/16 YB
GNDD
V+5D
V-5D
IC1906
TC74VHCT08AFTS1
(1/4)
IC1906
(2/4)
IC1906
(3/4)
IC1906
(4/4)
RFRST
RFSTP
RF-5VON
to SUB DIGITAL ASSY(2/2)
RF+5VON
DEMO
RFUNLK
from SUB DIGITAL ASSY(2/2)
P 2/2
C1833 0.1/16 YB
R1826 0
C1966 STBY
C1967 0.01YB
STB
DATA
CLOCK
RFRST
RFON
RFSTP
NC
VSS
VDD
OE
NC
NC
NC
NC
Qs'
Qs
IC1806
TC4094BFN
R1963 47k
R1965 47k
R1964 47k
GNDDS
C1832 0.1/16 YB
R1812 0
R1813 0
R1814 0
R1815 0
A5
B5
C5
A6
STB
DATA
CLOCK
A5
B5
C5
A6
VSS
VDD
OE
B6
C6
A7
B7
Qs'
Qs
IC1805
TC4094BFN
C7
B6
C6
A7
B7
CN1801
XKP3075
C7
RFUNLK
DEXP_ST
DEXP_DATA
DEXP_CLOCK
DEXP_OE
GNDDS
GNDDS
V+3DS
V 2/3 CN8010
V+3DS
R1816 47k
R1817 47k
R1818 47k
R1819 47k
R1820 47k
R1821 47k
R1822 47k
R1823 47k
R1855 220k
R1856 100k
R1857 220k
R1858 470k
R1854 100k
C1831 0.1/16 YB
GNDDS
903
852
853
834
835

10.26 SUB DIGITAL ASSY (2/2)

P 2/2 SUB DIGITAL ASSY (AWX8747)



NOTES

1.RESISTORS
Unit : k-k Ω, M-M Ω or Ω unless otherwise noted.
Rated power: 1/16W unless otherwise noted.
Tolerance : ±5%(J) unless otherwise noted.

2.CAPACITORS
Unit : p-pF or μF unless otherwise noted.
Rated Voltage: shown as "Capacity(μF)/Voltage(V)", or 50V unless otherwise noted.
NP : CEANP (Non Poler)
ZL : CEHAZL

※Parts or parts block marked by "*" or "STBY" are standby.

The ⚠ mark found on some component parts indicates the importance of the safety factor of the part. Therefore, when replacing, be sure to use parts of identical designation.

P 2/2



DEMODULATOR BLOCK



10.27 DSP ASSY (1/3) (Guide page)



	AWX8868
C131	1000p
C132	0.1u
C133	1000p
C134	0.1u
C135	1000p
C136	0.1u
C137	1000p
C138	0.1u
C139	1000p
C140	0.1u
C141	1000p
C142	0.1u
R111	180
R112	220
R113	100
R121	47
R122	22

	AWX8868
C167	0.1u
C168	1000p
C171	1000p
C172	0.1u
C173	1000p
C174	0.1u
C503	0.1u
C504	1000p
R403	82
R404	68
R407	22
R408	100
IC164	AYW7220-A

	AWX8868
C411	470p
C412	0.1u
R411	100
R412	100
L402	QTL1013
IC411	TC7SH32FUS1



NOTE
1. RESISTORS
Unit: k-k Ω , M-M Ω or Ω unless otherwise noted.
Rated Power: 1/16w unless otherwise noted.
Tolerance: (J)5% unless otherwise noted.
2. CAPACITORS
Unit: p-pF or u-uF unless otherwise noted.
Ratings: Capacity(F)/Voltage(V) unless otherwise noted.
3. NM: No Mount

Q 1/3

Q 4/8 CN301

Q 4/8 CN302

Large size SCH diagram

1/2

2/2

1/2



Q1/3 DSP ASSY (AWX8868)

Q2/3, 3/3: SPICLK, MISO, MOSI

Q2/3: SS2, RST2, REQ2, BUSY2, MODE2, MCLK1, CLKON, DS2T, DCCT

Q3/3: SPDS3, RST3, REQ3, ROWE



	AWX8868
C131	1000p
C132	0.1u
C133	1000p
C134	0.1u
C135	1000p
C136	0.1u
C137	1000p
C138	0.1u
C139	1000p
C140	0.1u
C141	1000p
C142	0.1u
R111	180
R112	220
R113	100
R121	47
R122	22

	AWX8868
C167	0.1u
C168	1000p
C171	1000p
C172	0.1u
C173	1000p
C174	0.1u
C503	0.1u
C504	1000p
R403	82
R404	68
R407	22
R408	100
IC164	AYW7220-A

Large size SCH diagram





NOTE
1. RESISTORS
Unit: k-k Ω , M-M Ω or Ω unless otherwise noted.
Rated Power: 1/16w unless otherwise noted.
Toleranee: (J)5% unless otherwise noted.
2. CAPACITORS
Unit: p-pF or u-uF unless otherwise noted.
Ratings: Capacity(F)/Voltage(V) unless otherwise noted.
3. NM: No Mount

Q 1/3


1st DSP
IC101
ADSP-21366KBCZ-1AA
1st DSP Block
REQ1
MCLK1
MOSI
SPICLK
MISO
RST1
SPDS1
CN101
STBY
QTL1013-A
ACH7275-A
100u/16
100u/6.3
3.3V
1.2V
10mA
560mA
AD2
AD3
AD5
AD6
AD7
FLAG1
VDDINT
BOOTCFG1
CLKCFG1
CLKCFG0
AD1
VDDEXT
FLAG0
BOOTCFG0
XTAL
TMS
CLKIN
TCK
TRST
TDI
AVSS
CLKOUT
AVDD
TDO
EMU
SPICLK
MOSI
RESET
MISO
SPIDS
DAI_P14
DAI_P15
DAI_P16
DAI_P17
DAI_P18
DAI_P19
DAI_P20
FLAG2
FLAG3
LCK2
SCK2
LCK1
SCK1
MCK1
DT0I
DT1I
DT2I
DT3I
DT4I
1stRadI

10.28 DSP ASSY (2/3)

Q2/3 DSP ASSY (AWX8868)

	AWX8868
C600	100u
C601	1000p
C602	0.1u
C603	1000p
C604	0.1u
C605	1000p
C606	0.1u
C607	1000p
C621	1000p
C622	0.1u
C623	1000p
C624	0.1u
C625	1000p
C626	0.1u
C627	1000p
C651	1000p
C652	0.1u
C653	0.1u
C654	1000p
C655	NM
C656	NM
R601	100
R602	100
R603	100
R604	47
R605	100
R606	100
R607	47
R608	47
R609	47
R610	100
R611	100
R612	22
R621	100
R622	100
R623	100
R624	47
R625	100
R627	47
R628	47
R629	47
R630	100
R631	100
R632	68
R645	0
R646	0
R651	100
R652	47
R653	100
R654	47
R655	NM
R656	NM
R657	180
R658	47
R659	100
R660	47
R661	NM
R662	NM
R902	NM
L601	QTL1013
IC601	TC74VHC74FTS1
IC602	TC7SH86FUS1
IC603	TC74VHC00FTS1
IC621	TC74VHC74FTS1
IC622	TC7SH86FUS1
IC623	TC74VHC00FTS1
IC651	TC74VHC74FTS1
IC652	TC74VHC157FTS1
IC653	NM

	AWX8868
R202	NM
R203	NM
R206	100
R208	100
R211	NM
R212	NM
R220	NM
R221	22
R222	22
R223	22
R226	10k
R227	10k
R641	NM
R642	NM
R643	NM
R644	NM

	AWX8868
C541	100u
C542	10u
C543	1000p
C544	10u
R541	9.1k
R542	18k
R543	10k
R546	NM
R547	0
L540	QTL1013
L541	4.7u
L542	NM
IC541	BD9107FVM
F540	NM

	AWX8868
C201	470p
C202	0.1u
C203	470p
C204	0.1u
C205	470p
C206	0.1u
C207	470p
C208	0.1u
C209	470p
C210	0.1u
C211	470p
C212	0.1u
C213	470p
C214	0.1u
C215	470p
C216	0.1u
C217	470p
C218	0.1u
C219	470p
C220	0.1u
C221	470p
C222	0.1u
C223	470p
C224	0.1u
R201	180





	AWX8868
R246	NM
R247	47k
R248	NM
R249	100
Q201	RT1N241M

	AWX8868
R237	100
R240	10k

	AWX8868
C271	NM
C272	NM
R271	NM
R272	NM
R273	NM
R274	NM
R275	NM
R276	NM
R277	NM
R278	NM
R279	NM
R280	NM
L271	NM
IC271	NM

	AWX8868
C701	470p
C702	0.1u
C703	470p
C704	0.1u
C711	100u
C751	NM
C752	NM
C753	NM
C754	NM
C757	NM
R701	22
R703	22
R704	22
R705	22
R751	NM
R752	NM
R753	NM
R754	NM
R755	NM
L701	QTL1013
L702	QTL1013
L751	NM
IC701	TC7WH04FU
IC751	NM
Q751	NM
X701	ASS7074-A
X751	NM

NOTE
1. RESISTORS
Unit: k-k Ω , M-M Ω or Ω unless otherwise noted.
Rated Power: 1/16w unless otherwise noted.
Toleranee: (J)5% unless otherwise noted.
2. CAPACITORS
Unit: p-pF or u-uF unless otherwise noted.
Ratings: Capacity(F)/Voltage(V) unless otherwise noted.
3. NM: No Mount

10.29 DSP ASSY (3/3) (Guide page)



	AWX8868
C361	0.1u
C362	NM
C363	0.1u
C364	NM
C365	0.1u
C366	NM
C367	0.1u
C368	1000p
C369	0.1u
C370	NM
C371	1000p
C372	0.1u
C373	1000p
C374	0.1u
C375	1000p
C376	0.1u
C377	1000p
C378	0.1u
C381	NM
C382	NM
C383	100u
R361	47
R362	47
R363	47
R364	47
R365	47
R366	47
R367	47
R370	47
R371	47
R372	47
R374	47
R375	47
R376	47
R377	47
R905	NM
R906	NM
R907	NM
L361	QTL1013
L362	QTL1013
L363	QTL1013
L364	QTL1013
L371	QTL1013
L372	QTL1013
IC361	TC74VHC573FTS1
IC362	TC74VHC573FTS1
IC363	TC7W139FU
IC364	AYW7221-A
IC365	TC7SH32FUS1
IC371	CY7C1049D3310VXI
IC372	CY7C1049D3310VXI

	AWX8868
C301	470p
C302	0.1u
C303	470p
C304	0.1u
C305	470p
C306	0.1u
C307	470p
C308	0.1u
C309	470p
C310	0.1u
C311	470p
C312	0.1u
C313	470p
C314	0.1u
C315	470p
C316	0.1u
C317	470p
C318	0.1u
C327	470p
C328	0.1u
C331	1000p
C332	0.1u
C333	1000p
C334	0.1u
C335	1000p
C336	0.1u
C337	1000p
C338	0.1u
C339	1000p
C340	0.1u
C341	1000p
C342	0.1u
C345	0.01u
C351	100u
C352	100u
R301	47
R302	47
R303	47
R304	47
R305	10
R306	47
R307	10
R311	180
R312	180
R313	100
R314	100
R315	100
R316	100
R321	22
R322	22
R323	22
R324	22
R325	22
R331	4.7k
R332	4.7k
R334	100
R335	4.7k
R336	4.7k
R337	100
R339	100
R342	100
R343	100
R344	100
R345	100
R346	4.7k
R347	NM
R348	NM
R350	0
R903	NM
R904	NM
L301	QTL1013
L302	QTL1013
IC301	ADSP-21366KBCZ-1AA
CN301	NM


3rd DSP Block
STBY
3rdDSP
*CN301
CN301:VKN1600
*IC301
ADSP-21366KBCZ-1AA
3RD DSP
3.3V
1.2V
GNDD
Q1/3, 2/3
Q1/3
Q2/3

Large size SCH diagram





NOTE
1. RESISTORS
Unit: k-k Ω, M-M Ω or Ω unless otherwise noted.
Rated Power: 1/16w unless otherwise noted.
Toleranee: (J)5% unless otherwise noted.
2. CAPACITORS
Unit: p-pF or u-uF unless otherwise noted.
Ratings: Capacity(F)/Voltage(V) unless otherwise noted.
3. NM: No Mount

R339	100
R342	100
R343	100
R344	100
R345	100
R346	4.7K
R347	NM
R348	NM
R350	0
R803	NM
R804	NM
L301	GTL1013
L302	GTL1013
IC301	ADSP-21368KBC-21AA
CN301	NM

Q 3/3 DSP ASSY (AWX8868)

Q 1/3, 2/3 Q 1/3 Q 2/3

SPICLK MISO MOSI SPDS3 RST3 REQ3 ROWE MCLK3



	AWX8868
C361	0.1u
C362	NM
C363	0.1u
C364	NM
C365	0.1u
C366	NM
C367	0.1u
C368	1000p
C369	0.1u
C370	NM
C371	1000p
C372	0.1u
C373	1000p
C374	0.1u
C375	1000p
C376	0.1u
C377	1000p
C378	0.1u
C381	NM
C382	NM
C383	100u
R361	47
R362	47
R363	47
R364	47
R365	47
R366	47
R367	47
R371	47
R372	47
R374	47
R375	47
R376	47
R377	47
R905	NM
R906	NM
R907	NM
L361	QTL1013
L362	QTL1013
L363	QTL1013
L364	QTL1013
L371	QTL1013
L372	QTL1013
IC361	TC74VHC573FTS1
IC362	TC74VHC573FTS1
IC363	TC7W139FU
IC364	AYW7221-A
IC365	TC7SH32FUS1
IC371	CY7C1049D3310VXI
IC372	CY7C1049D3310VXI

	AWX8868
C301	470p
C302	0.1u
C303	470p
C304	0.1u
C305	470p
C306	0.1u
C307	470p
C308	0.1u
C309	470p
C310	0.1u
C311	470p
C312	0.1u
C313	470p
C314	0.1u
C315	470p
C316	0.1u
C317	470p
C318	0.1u
C327	470p
C328	0.1u
C331	1000p
C332	0.1u
C333	1000p
C334	0.1u
C335	1000p
C336	0.1u
C337	1000p
C338	0.1u
C339	1000p
C340	0.1u
C341	1000p
C342	0.1u
C345	0.01u
C351	100u
C352	100u
R301	47
R302	47
R303	47
R304	47
R305	10
R306	47
R307	10
R311	180
R312	180
R313	100
R314	100
R315	100
R316	100
R321	22
R322	22
R323	22
R324	22
R325	22
R331	4.7k
R332	4.7k
R334	100
R335	4.7k
R336	4.7k
R337	100
R339	100
R342	100
R343	100
R344	100
R345	100
R346	4.7k
R347	NM
R348	NM
R350	0
R903	NM
R904	NM

Large size SCH diagram






3rd DSP Block
3RD DSP
ADSP-21366KBCZ-1AA
*IC301
STBY
*CN301
CN301:VKN1600
REQ3
3rdDSP
MCLK3
MOSI
SPICLK
MISO
RST3
SPDS3
LCKO
SCKO
LCK3
SCK3
MCK3
DT4O2
QTL1013-A
*L302
*L301
*C352
ACH7275-A
100u/6.3
100u/16
*C351
10mA
560mA
*R350
0
*R332 4.7k
R333
NM
*R334
100
*R330
*R331
4.7k
*R303
*R304
*R345 100
*R347
*R348
*R346
4.7k
*R344 100
*R343 100
*R342 100
*R339
100
*R337
100
R340
R341
R338
*C345
*C328
0.1u/10
*C327
470p/50
*R322
22
*R321
22
*R313
100
*R312
180
*R311
180
*R335
4.7k
*R336
4.7k
*R315
*C301 470p/50
*C302 0.1u/10
*C303 470p/50
*C304 0.1u/10
*C305 470p/50
*C306 0.1u/10
*C307 470p/50
*C308 0.1u/10
*C309 470p/50
*C310 0.1u/10
*C311 470p/50
*C312 0.1u/10
*C313 470p/50
*C314 0.1u/10
*C315 470p/50
*C316 0.1u/10
*C317 470p/50
*C318 0.1u/10
*C331 1000p/50
*C332 0.1u/10
*C333 1000p/50
*C334 0.1u/10
*C335 1000p/50
*C336 0.1u/10
*C337 1000p/50
*C338 0.1u/10
*C339 1000p/50
*C340 0.1u/10
*C341 1000p/50
*C342 0.1u/10
3.3V
1.2V
V1C
V1C2
V1D3
VDDINT
VDDEXT
GND
AD5 AD6 AD7 FLAG1 VDDINT VDDINT BOOTCFG1 CLKCFG1 CLKCFG0
AD4 VDDEXT VDDINT FLAG0 GND GND BOOTCFG0 GND XTAL
GND VDDEXT TMS
GND CLKIN TCK
TRST TDI
AVSS CLKOUT
AVDD TDO
VDDEXT EMU
SPICLK MOSI
RESET MISO
VDDINT SPIDS
VDDINT DAI_P18 VDDEXT FLAG2 GND GND GND GND GND
DAI_P16 DAI_P17 DAI_P19 DAI_P20 FLAG3 VDDINT VDDINT GND GND

10.30 DAC ASSY (1/4)



S 1/4 DAC ASSY (JJ:AWX8724) (KU/CA:AWX8723)



S 1/4

10.31 DAC ASSY (2/4)



DAC ASSY
S 2/4 (JJ:AWX8724) (KU/CA:AWX8723)



10.32 DAC ASSY (3/4)



DAC ASSY
S 3/4 (JJ:AWX8724) (KU/CA:AWX8723)



10.33 DAC ASSY (4/4)



NOTES

1.RESISTORS
Unit : k-kΩ, M-MΩ or Ω unless otherwise noted.
Rated power: 1/16W unless otherwise noted.
Tolerance : ±5%(J) unless otherwise noted.

2.CAPACITORS
Unit : p-pF or μF unless otherwise noted.
Rated Voltage: shown as "Capacity(μF)/Voltage(V)", or 50V unless otherwise noted.

ZL : CEHAZL

※Parts or parts block marked by "*" or "STBY" are standby.

DAC ASSY
S 4/4 (JJ:AWX8724)
(KU/CA:AWX8723)



10.34 HN MODULE ASSY (1/6)



	USED	VACANT
C	7601-7639	7614
CN	7601,7602	7601,7602
F	7601,7602	
IC	7601,7602	7602
R	7601-7663,7666	7622,7623,7645,7648
TP	7601-7648	
X	7601	


DRAM0_A[12:0]
DRAM0_BA[1:0]
T 2/6
V+3_3V
TP7601
TP7602
TP7603
TP7604
TP7605
TP7606
TP7607
GND
PB_CS2_L
PB_RD_L
PB_WR_L
PB_IORDY
T 2/6
NO USE
CN7602
CKS4829-TBB
HN5
TP7638
Substitutive symbol for Serial Flash IC
IC7602
BA4560RF-TBB
TP7639
TP7643
TP7644
TP7645
TP7646
A OUTPUT
A-INPUT
A+INPUT
V-
B OUTPUT
B-INPUT
B+INPUT
V+
PB_AD[15:0]
PB_A[15:0]
T 2/6
PCI_AD[31:0]
T 3/6,4/6
PCI_CBE0_L
PCI_CBE1_L
PCI_STOP_L
PCI_TRDY_L
PCI_DEVSEL_L
PCI_PAR
PCI_CBE2_L
PCI_FRAME_L
PCI_IRDY_L
PCI_CBE3_L
T 3/6,4/6
TP7633
TP7632
TP7634
TP7635
TP7636
SO0
PCI
SO0
SO0
SO0
T 5/6
USB_PCI_GNT_L
T 4/6
ENET_PCI_GNT_L
T 3/6
USB_PCI_IDSEL
T 4/6
ENET_PCI_IDSEL
T 3/6
USB_PCI_REQ_L
T 4/6
ENET_PCI_REQ_L
T 3/6
SO0_BCLK
T 5/6
TP7637
VO1
VO2
VO2
VO2
T 5/6
T 5/6
T 5/6
T 5/6
NO USE
NO USE
RAB4CQ103J-T
RAB4CQ103J-T
RAB4CQ103J-T
T 1/6

10.35 HN MODULE ASSY (2/6)

T 2/6 HN MODULE ASSY (AWV2535)



T 2/6

	USED	VACANT
C	7701-7717 7722-7726	
F	7701	
IC	7701-7703	
R	7701-7722	7708 7719-7722



10.36 HN MODULE ASSY (3/6)

T 3/6 HN MODULE ASSY (AWV2535)

	USED	VACANT
C	7751-7779	7763
CN	7751-7753	7751
F	7751-7753	
IC	7751,7753,7754	
JA	7752	
Q	7751	
R	7751-7758	
TP	7751-7756,7760	
X	7751	



C7752	R7759	RS1/16SS0R0J-T
C7753	R7760	RS1/16SS0R0J-T
C7760	R7761	RS1/16SS0R0J-T
C7761	R7762	RS1/16SS0R0J-T


V+3_3V
PCI_CBE0_L
PCI_CBE1_L
PCI_PAR
PCI_SERR_L
PCI_PERR_L
PCI_STOP_L
PCI_DEVSEL_L
PCI_TRDY_L
PCI_AD[31:0]
PCI_IRDY_L
PCI_FRAME_L
PCI_CBE2_L
IC7754
RTL8100CL-LF-K
ENET_PCI_IDSEL
PCI_CBE3_L
ENET_PCI_REQ_L
PCI_INTA_L
ENET_PCI_GNT_L
PCI_33M_RTL8100
BRD_RST3_L
GND
T 1/6,4/6
T 1/6
T 5/6

10.37 HN MODULE ASSY (4/6)

T 4/6 HN MODULE ASSY (AWV2535)

	USED	VACANT
C	7801-7824	7804,7825
CN	7801	
F	7801-7806	
IC	7801-7803	7802
L	7801	
R	7801-7830	7802,7804,7805,7813,7817,7827,7828 7830
TP	7801-7808	
X	7801	



T 4/6


CN7801
KM200NA5L
J5291
HN3
USBP1 P
USBP1 N
USBP2 P
USBP2 N
USBP3 P
USBP3 N
USBP4 P
USBP4 N
USBOCI L
CGNDUSB
USB POWER BLOCK
IC7803
R5523N001B-TLB
IC7801
VT6212L-G-K
IC7802
BR93L46RFJ-W-TBB
TESTMODE
ATPGEN
NO USE
PCI_CBE0_L
PCI_CBE1_L
PCI_PAR
PCI_STOP_L
PCI_DEVSEL_L
PCI_TRDY_L
PCI_IRDY_L
PCI_FRAME_L
PCI_CBE2_L
PCI_CBE3_L
USB_PCI_IDSEL
T 1/6,3/6
T 1/6
T 4/6
Use R7831,7832(RS1/16S0R0J-T) instead of F7805,C7805.
GND

10.38 HN MODULE ASSY (5/6)



T 5/6

	USED	VACANT
C	7851-7869,7871,7872,7874-7878 7880-7890	7856-7862,7866,7868,7869, 7876-7878,7880-7887
CN	7851	
F	7851-7858	7851,7856,7858
IC	7852,7853,7855-7857	7853,7856
L	7851-7854	7851
Q	7851-7858	7851,7858
R	7851-7900 7951-7966	7852-7854,7867,7871,7872, 7876-7881,7886-7894,7898 7951-7955,7957-7958 7962,7963,7966
TP	7851-7859,7861-7866	
X	7851	



T 2/6
T 3/6
T 4/6
T 1/6
T 4/6
T 3/6
T 1/6
T 5/6

10.39 HN MODULE ASSY (6/6)

T 6/6 HN MODULE ASSY (AWV2535)



	USED	VACANT
C	7901-7922,7924,7925	7913-7917,7921,7922
CN	7901	
D	7901-7902	
F	7901-7902	7902
IC	7901-7905	7901,7905
L	7901-7902	
R	7901-7923	7913,7914,7916,7918,7920-7923
TP	7901-7924	


V+5V
IC7903
LTC3412EFE-TBB
SVIN
PVIN
PGOOD
SW
ITH
SW
VFB
PGND
RT
PGND
SYNC/MODE
SW
RUN/SS
SW
SGND
PVIN
NO USE
R7901
SS
15K
R7902
SS
4.7M
C7903
22/10
C7904
CH
470P
C7905
CH
100P
C7911
CH
SS
100P/50
R7905
SS
0
R7903
F
SS
309K
R7906
D
SS
200K
R7904
D
SS
82K
C7925
CH
SS
22P/50
L7901
ATH1206- -TRB
1.5
V+3_3V
TP7903
C7912
10/6.3
BCG1050- -T
GND


V+5V
IC7904
LTC3412EFE-TBB
SVIN
PVIN
PGOOD
SW
ITH
SW
VFB
PGND
RT
PGND
SYNC/MODE
SW
RUN/SS
SW
SGND
PVIN
R7923
SS
10K
R7907
SS
5.6K
R7908
SS
4.7M
C7906
22/10
C7907
CH
100P
C7908
CH
220P/50
C7918
CH
SS
100P/50
NO USE
R7911
SS
0
R7909
F
SS
309K
R7912
D
SS
75K
R7910
D
SS
150K
C7924
CH
SS
100P/50
L7902
ATH1207- -TRB
3.3
V+1_2V
TP7905
C7919
10/6.3
BCG1050- -T
GND


V+3_3V
V+1_2V
D7901
RB051L-40-TRB


V+DDR
V+1_2V
D7902
RB051L-40-TRB

10.40 PREOUT ASSY (1/2)

U 1/2 PREOUT ASSY (AWX8738)




(L)
(R)
L2
L3
L4
L5
R5
R4
R3
R2
GNDU
IC3542
3CFG-012-TBB
STB
DATA
GND
CK
CH
C3545
100p
R3545
220
R3546
220
R3544
220
IC9001(1/2)
IC9001(2/2)
IC9002(1/2)
IC9002(2/2)
IC9003(1/2)
IC9003(2/2)
IC9004(1/2)
IC9004(2/2)
IC9005(1/2)
IC9005(2/2)
V+15A
V-15A
STBY
CN3516
KM200NA15L
GNDCH
L5
GNDA
GNDCH
L4
GNDA
GNDCH
L3
GNDA
GNDCH
L2
GNDA
GNDCH
L1
GNDA
CN3517
KM200NA15LR
GNDCH
R1
GNDA
GNDCH
R2
GNDA
GNDCH
R3
GNDA
GNDCH
R4
GNDA
GNDCH
R5
GNDA
GNDCH
BE CN5504, BD CN5602
BE CN5503

10.41 PREOUT ASSY (2/2)

U 2/2 PREOUT ASSY (AWX8738)



NOTES

1.RESISTORS
Unit: k-k Ω , M-M Ω or Ω unless otherwise noted.
Rated power: 1/16W unless otherwise noted.
Tolerance: ±5%(J) unless otherwise noted.

2.CAPACITORS
No marked Capacitors are CEAT or CKSRYB.
Unit: p-pF or μF unless otherwise noted.
Rated Voltage: shown as
"Capacity(μF)/Voltage(V)",
or 50V unless otherwise noted.

3.DIODES
No marked Diodes are 1SS352.

※Parts or parts block marked by "STBY" are standby.


PREOUT
PRE OUT (Rear Panel)
JA3504 AKB7189 STBY
SW1
SW2
FL
FR
C1
C2
SL
SR
SBL
SBR
X1L
X1R
X2L
X2R
GNDCH
GNDCH2
GNDCH3
V-15A
V+15A

10.42 MOTHER 1 ASSY (1/3)

V 1/3 MOTHER1 ASSY (JJ:AWX8771) (KU/CA:AWX8770)



NOTES

1.RESISTORS
Unit: k-k Ω , M-M Ω or Ω unless otherwise noted.
Rated power: 1/16W unless otherwise noted.
Tolerance: ±5%(J) unless otherwise noted.

2.CAPACITORS
No marked Capacitors are CEAT or CKSRYB.
Unit: p-pF or μF unless otherwise noted.
Rated Voltage: shown as
"Capacity(μF)/Voltage(V)",
or 50V unless otherwise noted.

3.DIODES
No marked Diodes are 1SS352.

※Parts or parts block marked by "STBY" are standby.

*SIMUKE

	AWX 8770	AWX 8771
	/KU/CA	/JJ
R8151	100k	100k
R8152	-	100k
R8153	100k	-
R8154	-	100k



10.43 MOTHER 1 ASSY (2/3)




For New Item
u-com
Backup Power
IC8023 NJM2880U1-33
IC8021 NJM2872BF33
IC8022 NJM2880U1-33
Q8046 2SB1189(QR)
Q8047 2SA1602A(EF)
Q8045 RT1N241M
POFF
CN8029 19P-1.25FJ
CN8030 13P-1.25FJ
CN8031 21P-1.25FJ
CN8015 XKP3070
CN8016 KU MODEL ONLY (AWX8790-) CKS1726
CN8035 CKS1720
IC8082 TC74VHC08FTS1
IC8081 TC74VHCT08AFTS1
Q8031 RT1P241M E
Q8033 RT1N141M-11
AD 1/2 CN8501
AD 1/2 CN8502
AD 1/2 CN8503
N 1/2 CN7001
N 1/2 CN7003
N 1/2 CN7009
V 1/3
V 2/3
V 3/3
DISPLAY
MAIN
SPDIF
EVENT
V+3UN
V+5_6US
V+5_6ST
V+3US
V+5US
V+3UM
V+5UM
V+12F
GNDU
GNDHR
GNDUHR
GNDUNT
GNDUNEW
STBY
12VON
DFWRITE
UCOM_WRITE
ACPOWER
232CTS
232RX
232TX
SMRY1
SMRY2
ACRY
ACWP3
WWP3
SCL
SDA
RST
XM
EVTDO3
EVTRDY3
EVTDI3
EVTREQ3
EVTCK3
EVTRST3
GVIP
GNV
NETV
NETCB
NETCR
IPOD3
GIPS
NETTX
NETRX
NETRS
IPV
GVIP
V+5V

10.44 MOTHER 1 ASSY (3/3)




V 3/3 MOTHER1 ASSY
(JJ:AWX8771)
(KU/CA:AWX8770)
MUTE
V 1/3
A-CTRL
V 2/3
CN8021
CKS1718
Z2MUTE
Z3MUTE
ZVDT
ZVCK
MDDT
MDCK
MDST
Z2 MUTE
Z3 MUTE
Z VOL DT
Z VOL CLK
MODE DT
MODE CLK
MODE STB
GNDD
H 1/2 CN3209
I 1/2 CN3903
AIDT
AICK
AIST
GNDU
HPMUTE
RYHP
V 1/3
PREMUTE
GNDD
CN8025
XKP3068
AMIST
A2IST
A3IST
INDT
INCK
Z2LDA
GSEP72
Z2RDA
GSEP73
Z3LDA
GSEP61
Z3RDA
GSEP62
AZ2IST
AZ3IST
INDT
INCLK
GNDD
GNDA
ZONE2 D/A L
ZONE2 D/A R
ZONE3 D/A L
ZONE3 D/A R
A CN3005
CN8022
XKP3071
XRDA
GSEP7
XLDA
GSEP8
E1RDA
GSEP9
E1LDA
GSEP10
SRDA
GSEP11
SLDA
GSEP12
FRDA
FLDA
GSEP13
C2DA
GSEP14
C1DA
GSEP15
SBRDA
GSEP16
EXR DA
GNDSP
EXL DA
SRB DA
SLB DA
SRA DA
FR DA
FL DA
C2 DA
C1 DA
SBR DA
GDAC
H 2/2 CN3208
CN8027
XKP3066
V 1/3
RYHP
HPRY
GNDA(SEP)
HP R
HP L
VMIST
V2IST
V3IST
VZ2IST
VZ3IST
B CN3106
SBLDA
GSEP17
SW2DA
GSEP18
SW1DA
GSEP19
GSEP20
SBLAD
GSEP29
SBRAD
GSEP30
SLAD
GNDZAD
SRAD
GNDZAD
FLAD
GSEP25
FRAD
GSEP26
CAD
GSEP27
SWAD
GSEP28
SBL DA
SW2 DA
SW1 DA
GNDASP
SBL AD
SBR AD
SL AD
SR AD
FL AD
FR AD
C AD
SW AD
H 1/2 CN3206
CN8028
CKS1724
Z2LAD
Z2RAD
ADGNDZAD
C8209
0.1/16
NETL
GNW
NETR
R8298
STBY
R8299
STBY
HRL
GNDAX
GHR
HRR
C8208
0.1/16
Z2VOLIN L
GNDZ2
Z2VOLIN R
NET L
GSEPNW
NET R
HR L
GSEPHR
HR R
B CN3105
NEWITEM
V 2/3
CN8023
XKP3071
CN8019
XKP3064
HP R
GNDA
HP L
GNDA
GNDA
Z2VOUT L
GSEPZ2
Z2VOUT R
GSEPZ2
GSEP3
Z2LVO
GSEP5
Z2RVO
GSEP4
CN8024
CKS1721
Z2VOLOUT L
GSEPZ2
Z2VOLOUT R
GSEPZ2
Z2VOLIN L
GNDZ2
Z2VOLIN R
GNDZ2
NC
NC
NC
H 1/2 CN3207
CN8026
CKS1719
V+15A
GNDA
V-15A
A CN3004
Conector Direction
Rear Panel Side
V 3/3

10.45 ICE INTERFACE ASSY

ICE INTERFACE ASSY (AWX8779)



NOTES

1.RESISTORS
Unit: k-k Ω , M-M Ω or Ω unless otherwise noted.
Rated power: 1/16W unless otherwise noted.
Tolerance: ±5%(J) unless otherwise noted.

2.CAPACITORS
No marked Capacitors are CEAT or CKSRYB.
Unit: p-pF or μF unless otherwise noted.
Rated Voltage: shown as
"Capacity(μF)/Voltage(V)",
or 50V unless otherwise noted.

3.DIODES
No marked Diodes are 1SS352.

※Parts or parts block marked by "STBY" are standby.


TO ICE POWER AMP ASSY
TO ICE POWER SMPS ASSY
CN8301
RKN1065-
CN8302
KM200NA7L
IC8303
BU4094BCFV
IC8304
TC74VHCT08AFTS1
IC8305
BU4094BCFV
IC8306
TC74VHCT08AFTS1
IC8307
TC74VHCT08AFTS1
IC8308
TC74VHCT08AFTS1-TBB
IC8309
TC74VHCT08AFTS1
V+5ICE
V+3U
GNDAMP
GNDSMPS
GNDS
STBY
MUTE1
MUTE2
MUTE3
MUTE4
MUTE5
RY5
RY7
RY9
V+5ICE
DISABLE1_2
DISABLE3_4
DISABLE5_6
DISABLE7_8
DISABLE9_10
F MUTE(MUTE1)
S1 MUTE(MUTE2)
SB MUTE(MUTE3)
S2 MUTE(MUTE4)
C MUTE(MUTE5)
GND(AM2 STBY)
AM1
AMP OL DET
RELAY1_2
RELAY3_4
RELAY5_6
RELAY7_8
RELAY9_10
GNDAMP
MAX TEMP
TEMP OL
DC DET
GNDAMP
NC
LATCH MONITOR
TEMP OUT SEC
POWER MONITOR
AVOID TX1
V+5SMPS
GNDSMPS
VNF1084
KN8301

10.46 COMPOSITE ASSY (1/2)




IC2015
IC2014
TC4094BFN
CSITE_CNT
Q2151
2SC4081 (RS)
Q2152
2SA1576A
V+5CV
V+3CV
V-5CV
V-3CV
GVV
GNDU
GOS1
STBY
IC2019
TC74VHCT32AFT
IC2018
LCDMUM
LCDMUD
LCDMUH
LCDINH
Z2OSRS_2
Z3OSRS_2
Z2OSRS_3
Z3OSRS_3
CN2004
CKS3370
NC
XVMUTE
XZ2MUTE
XZ3MUTE
XZ4MUTE
MMUTE
Z2MUTE
Z3MUTE
Z4MUTE
CN2001
RKN1065
LCDWP
Z2HDOUT
CVHDOUT
Z2HDIN
CVHDIN
Rear
Front
AE 3/8 CN601
X 2/2
X 1/2
CN2405
2001
VEF1040-

10.47 COMPOSITE ASSY (2/2)

X 2/2 COMPOSITE ASSY (AWX8778)



NOTES

1.RESISTORS
Unit: k-k Ω , M-M Ω or Ω unless otherwise noted.
Rated power: 1/16W unless otherwise noted.
Tolerance: ±5%(J) unless otherwise noted.

2.CAPACITORS
No marked Capacitors are CEAT or CKSRYB.
Unit: p-pF or μF unless otherwise noted.
Rated Voltage: shown as
"Capacity(μF)/Voltage(V)",
or 50V unless otherwise noted.

3.DIODES
No marked Diodes are 1SS355.

※Parts or parts block marked by "STBY" are standby.

X 2/2



IC2001-IC2004

INH	VMA VZ2A VZ3A VZ4A	VMB VZ2B VZ3B VZ4B	VMC VZ2C VZ3C VZ4C	OUT
GND	H	L	L	TV
	L	H	L	SAT
	H	H	L	F:S-VIDEO
	L	L	H	VIDEO1
	H	L	H	VIDEO2
	L	H	H	DVR1/VCR1
	H	H	H	DVR2/VCR2
	L	L	L	DVD

IC2005

MINH	VMSA	VMSB	OUT
L	L	L	MAIN Through
	L	H	OTHER1 HDMI
	H	L	HDMI OUT
	H	H	OTHER1 Through
H	*	*	MUTE

IC2006

INH	VO1A	OUT
GND	L	CVBS NETWORK
	H	I-POD

IC2007

MINH	VMSA	VMSB	OUT
L	L	L	ZONE2 Through
	L	H	OTHER2 HDMI
	H	L	Z2 HDMI OUT
	H	H	OTHER2 Through
H	*	*	MUTE

IC2008

INH	VO2A	OUT
GND	L	ZONE2 OSD
	H	I-POD

IC2009

Z3INH	VZ3SA	VZ3SB	OUT
L	L	L	ZONE3 Through
	L	H	ZONE3 OSD
	H	L	I-POD
	H	H	GND
H	*	*	MUTE

IC2010

LCDINH	LCD	OUT
L	L	HDMI LINE
	H	Through LINE
H	*	MUTE

IC2006

SW1	SW2	VRA	VRB	OUT	
				VOUT1	VOUT2
L	L	H	L	MUTE	RECB
		L	H	RECA	MUTE
		H	H	RECA	RECB
		L	L	MUTE	MUTE

10.48 S-VIDEO ASSY

Y S-VIDEO ASSY (AWX8725)



IC2201-IC2203

SVA, SZA, SRA,	SVB, SZB, SRB,	SMINH S2INH SRINH	OUT
L	L	L	IN1
L	H	L	DVR1/VCR1
H	L	L	DVR2/VCR2
H	H	L	Front S
——	——	H	FULL OPEN

IC2204

SVMA	SOINH	OUT
L	L	THROUGH
H	L	HDMI(VC)
——	H	FULL OPEN

IC2209,IC2210

SRM1	SRM2	OUT
L	H	OUT1
H	L	OUT2
H	H	OUT1&OUT2
L	L	MUTE


V+5S
V-5S
Q2201 2SC4081(RS)
Q2202 2SC4081(RS)
Q2310
STBY
SVMA
SYOT
SCOT
SOINH
SVCIN
SVYIN
SREC_Y
SREC_C
SRM2
SRM1
SZ2YIN
SZ2CIN
SOUT SEL TC74HC4053AF
IC2204
RECOUT Y SELECTOR
IC2209
RECOUT C SELECTOR
IC2210
NJM2279M
EL5260IYZ
IC2208
IC2211
JA2202 AKP7049 MONITOR OUT (3/3)
JA2201 AKP7049 DVR1/VCR1 OUT (1/3)
JA2201 AKP7049 DVR2/VCR2 OUT (3/3)
JA2203 AKB7187 MONITOR OUT (1/2)
JA2203 AKB7187 ZONE2 OUT (2/2)
(CHASSIS)
GVV
V-5CV
V+5CV
TC4094BFN
CN2203 XKP3075
CN2501
EXPST
EXPOE
EXPCK
CDT1
CDET1
CDET2
MVMUTE
Z2MUTE
NC
ECSS
EOES
ECLKS
CD1
CD2
CN2202 XKP3083
SIGNAL
AD 1/2 CN8506
Front
Rear
NOTES
1.RESISTORS
Unit: k-k Ω , M-M Ω or Ω unless otherwise noted.
Rated power: 1/16W unless otherwise noted.
Tolerance: ±5%(J) unless otherwise noted.
2.CAPACITORS
No marked Capacitors are CEAT or CKSRYB.
Unit: p-pF or μF unless otherwise noted.
Rated Voltage: shown as "Capacity(μF)/Voltage(V)", or 50V unless otherwise noted.
3.DIODES
No marked Diodes are 1SS355.
※Parts or parts block marked by "STBY" are standby.

10.49 COMPONENT ASSY



Z COMPONENT ASSY (JJ:AWX8727) (KU/CA:AWX8726)



10.50 VIDEO BRIDGE ASSY

AA VIDEO BRIDGE ASSY (AWX8743)



NOTES

1.RESISTORS
Unit: k-k Ω , M-M Ω or Ω unless otherwise noted.
Rated power: 1/16W unless otherwise noted.
Tolerance: ±5%(J) unless otherwise noted.

2.CAPACITORS
No marked Capacitors are CEAT or CKSRYB.
Unit: p-pF or μF unless otherwise noted.
Rated Voltage: shown as
"Capacity(μF)/Voltage(V)",
or 50V unless otherwise noted.

3.DIODES
No marked Diodes are 1SS352.

※Parts or parts block marked by "STBY" are standby.

AA

A

B

C

D

E

F

10.51 IR 232C ASSY (1/2)

AC 1/2 IR 232C ASSY (AWX8746)



EVENT U-com Down Lord Switch (From RS-232C)

NOTES

1.RESISTORS
Unit: k-k Ω , M-M Ω or Ω unless otherwise noted.
Rated power: 1/16W unless otherwise noted.
Tolerance: ±5%(J) unless otherwise noted.

2.CAPACITORS
No marked Capacitors are CEAT or CKSRYB.
Unit: p-pF or μF unless otherwise noted.
Rated Voltage: shown as
"Capacity(μF)/Voltage(V)",
or 50V unless otherwise noted.

3.DIODES
No marked Diodes are 1SS352.

※Parts or parts block marked by "STBY" are standby.




AC 2/2
SR23
23CTS
23TXD
23RXD
23DET
E23RX
E23TX
E23CT
23SW5
V50U
V50E
L6201
QTL1013
C6201
220/16
GNDU
EVENT
AC 2/2
for
JIG Down Lord
CN6281
VKN1413
DBGP2
DBGP1
DBGP0
EVERT
RESET
GNDU
NC
EVENT UCOM
IC6201
PDC158A8
Reference Point
of Crystal
CECIO
SRIN
IRIN
EVERQ
EVERT
KEY1
KEY2
KEY3
HDAD1
HDAD2
HDDI1
HDDI2
FANDET
12DET
MCDET
HPDET
KEYP
HTPLG
LPOWER
LACRY
Zone4 KEY
Zone3 KEY
Zone2 KEY
C6213 STBY
R6222 47K
C6204 0.1
C6205 0.1
C6206 0.1
C6207 0.1
C6208 0.1
C6209 12p
C6210 12p
C6211 0.01
C6212 STBY
C6203 0.1
R6201 100
R6202 100k
R6203 1M
R6204 0
R6205 100
R6206 100k
R6208 47k
R6209 47k
R6210 100
R6211 100
R6212 470k
R6213 STBY
R6214 47k
R6215 100k
R6216 47k
R6217 100
R6218 47k
R6219 100
R6220 100
R6221 100
R6222 47K
R6223 100
R6224 100
R6225 100
R6226 100
R6227 100
R6228 100
R6231 100k
R6232 100k
R6233 100k
X6201
CSTS653
15MHz
CH
D6201
MC2848-11
D6401
MC2848-11
D6402
MC2848-11
D6411
MC2848-11
IC6411
NJM2880U1-33
Vin
Vout
Cont.
GND
NB
V33U
V56U
V56ST
V50U
C6411 0.1/16
C6412 0.1/16
C6413 2.2/10
C6403 1.0/16
5.6V -> 3.3V Block
for DISP u-com
4.7k
SROUT
AC 1/2

10.52 IR 232C ASSY (2/2)



AC 2/2


AC 2/2 IR 232C ASSY (AWX8746)
IC6391 AYW7218 (MBM29LV400TC-70PFTN)
FLASH ROM
DLF
IC6392 TC7SH08FUS1
IC6051 TC74VHC125AFTS1
IC6052 TC74VHCT125AFTS1
232C or SR+
DISPLAY U-com Down Lord (From RS-232C) or SR+ TX/RX UART Switch
CN6409 VKN1412
CN6405 VKN1418
CN6406 VKN1416
CN6407 KM200NA7
CN6408 CKS3374
CN6402 CKS1764
CN6401 XKP3077
AE 2/8 CN251
AH CN5093
AH CN5092
AJ CN6501
BC CN4012
AD 1/2 CN8509
AD 1/2 CN8508
AC 1/2
AC 2/2
SC-09TX
115

10.53 MOTHER 2 ASSY (1/2)




AD 2/2
CN8504
XKP3071
X 1/2 CN2003
TRGON2
TRGON3
TRGON1
GNDU
MMUTE
Z2MUTE
Z3MUTE
Z4MUTE
LMUTE_M
LMUTE_D
VSYNC
M_OS_DT
M_OS_CK
M_OS_CS
M_OS_RST
Z2_OS_DT
Z2_OS_CK
Z2_OS_CS
Z2_OS_RST
Z3_OS_DT
Z3_OS_CK
Z3_OS_CS
Z3_OS_RST
GNDU
LCD V
GNDV
VMMU
VZ2MU
VZ3MU
VZ4MU
LCMU_M
LCMU_D
VSYNC
M_OS_CS
M_OS_RST
Z3_OS_DT
Z3_OS_CK
GNDUV
IC8506
TC74VHCT541AFTS1
Y8X
Y7X
Y6X
Y5X
Y4X
Y3X
Y2X
Y1X
G2X
VCC
GND
A8
A7
A6
A5
A4
A3
A2
A1
G1X
R8581 330
R8582 330
R8583 330
R8584 330
R8585 330
R8586 330
R8587 330
R8588 330
R8557 STBY
R8554 STBY
R8556 STBY
R8553 STBY
R8555 STBY
R8552 STBY
R8551 STBY
R8550 STBY
M_OS_DT
M_OS_CK
Z2_OS_DT
Z2_OS_CK
Z2_OS_CS
Z2_OS_RST
Z3_OS_CS
Z3_OS_RST
R8590 100k
R8589 100k
C8530 0.1/16
R8547 47K STBY
D8512 STBY
LCD
R8595 STBY
R8596 STBY
R8597 STBY
GV12
Front C'site
Front S(Y)
Front S(C)
R8599 STBY
R8598 STBY
L CN5303
GNDV
LCD V
GAV
FV
GAV
FY
GAV
FC
V+5V
GNDV
V-5V
CN8514
KM200NA11
CN8507
XKP3069
Z CN2402
GNW
NWY
GNW
NWB
GNW
NWR
V+5V
V+5V
GAV
GAV
V-5V
V-5V
GAV
CVZONE3
GAV
CVZONE4
V-5CV
GCV
V+5CV
V+5_6ST
V+5_6U
CN8508
XKP3066
AC 2/2 CN6401
V+5.6ST
V+5.6U
V+5.6U
GNDU
GNDU
GNDU
GNDU
V+12F
1WUP
232CTS
232RX
232TX
STBYOFF
V+12F
1W WUP
232CTS
232RX
232TX
STBYOFF
CN8509
CKS1730
AC 2/2 CN6402
N2D_DO
N2D_CK
N2D_RQ
N2D_RD
N2D_DI
DISP_DI
DISP_DO
DISP_CK
DISP_RQ
DISP_RDY
DISP_RST
EVT_DI
EVT_DO
EVT_CK
EVT_RQ
EVT_RDY
EVT_RST
232SW4
232SW5
VSYNC
NEW2DI DO
NEW2DI CK
NEW2DI REQ
NEW2DI RDY
NEW2DI DI
DISP DI
DISP DO
DISP CK
DISP REQ
DISP RDY
DISP RST
EVENT DI
EVENT DO
EVENT CK
EVENT REQ
EVENT RDY
EVENT RST
232SW4
232SW5
VSYNC
CN8510
CKS1730
AC 2/2 CN6403
LCMU_D
M_OS_DT
M_OS_CK
M_OS_CS
M_OS_RST
Z2_OS_DT
Z2_OS_CK
Z2_OS_CS
Z2_OS_RST
Z3_OS_DT
Z3_OS_CK
Z3_OS_CS
Z3_OS_RST
GNDUV
WPCK
WPDT
WPCS
WPRST
BUSY
LMUTE_D
M_OS_DT
M_OS_CK
M_OS_CS
M_OS_RST
Z2_OS_DT
Z2_OS_CK
Z2_OS_CS
Z2_OS_RST
Z3_OS_DT
Z3_OS_CK
Z3_OS_CS
Z3_OS_RST
GNDU
GNDU
WPCK
WPDT
WPCS
WPRST
BUSY
CN8511
CKS1730
AC 2/2 CN6404
GNDUW
V+12V
V+5_6UO
AD 2/2
12VDET
MFWRITE
SRTX
SRRX
SRIN
RMC
SROUT
GCC
GNDU
12VDET
MFWRITE
MFWRITE
V+12F
V+5.6U
V+5.6U
GNDU
GNDU
GNDST
GNDST
GNDLCD
GNDLCD
GNDU
GNDU
SRTX
SRRX
SRIN
RMC
SROUT
NOTES
1.RESISTORS
Unit: k-k Ω , M-M Ω or Ω unless otherwise noted.
Rated power: 1/16W unless otherwise noted.
Tolerance: ±5%(J) unless otherwise noted.
2.CAPACITORS
No marked Capacitors are CEAT or CKSRYB. MBA:CQMBA
Unit: p-pF or μF unless otherwise noted.
Rated Voltage: shown as
"Capacity(μF)/Voltage(V)",
or 50V unless otherwise noted.
3.DIODES
No marked Diodes are 1SS352.
※Parts or parts block marked by "STBY" are standby.

10.54 MOTHER 2 ASSY (2/2)

AD 2/2 MOTHER2 ASSY (AWX8776)







N 2/2 CN7006

NOTES

1.RESISTORS
Unit: k-k Ω , M-M Ω or Ω unless otherwise noted.
Rated power: 1/16W unless otherwise noted.
Tolerance: ±5%(J) unless otherwise noted.

2.CAPACITORS
No marked Capacitors are CEAT or CKSRYB. MBA:CQMBA
Unit: p-pF or μF unless otherwise noted.
Rated Voltage: shown as
"Capacity(μF)/Voltage(V)",
or 50V unless otherwise noted.

3.DIODES
No marked Diodes are 1SS352.

※Parts or parts block marked by "STBY" are standby.


C8573
0.01
R8579
4.7k
D8503
UDZS5R1(B)
12VDET
AD 1/2
8507 ANH-575 (HEAT SINK)
8506 BBZ30P080FNI (SCREW)
BC CN4005
J8512
ADX7580
V+12V
GND
V+12V
IC8503
NJM78M56FA
IN
OUT
V+5_6UO
C8503
0.01
C8518
10/50
C8505
0.01
C8504
100/16
D8501
RB501V-40
D8502
STBY
L8501
100
STBY
Q8502
RT1P241M
(22k)
Q8501 (10k)
RT1N141M-11
R8503
100k
12VON
GCC
MFWRITE
AD 1/2
CN8513
TUC-P05P-B1
BC CN4001
SMPS RY1
SMPS RY2
NC
ACRY
WAKEUP
SM_RY1
SM_RY2
ACRY
WUP
SM_RY1
SM_RY2
ACRY
WUP
AD 1/2
iPOD REG
V+8UN
V+5IPOD
CN4752
KM200NA3R
N 2/2 CN7006
IPOD+8
GNDIPOD
iPOD+5
GNDIPOD
IC4752
NJM78M05FA
OUT
IN
D4752
MTZJ6R2(B)
C4755
100/16
C4756
0.01
C4754
0.01
C4753
4700/16
C4758
0.1
D4751
D5SBA20(B)
C4757
0.1
R4751
4.7
1/4W
MJF
C4751
0.1/50
MBA
R4752
STBY
IC4751
AEK7021
7A/125V
CN4751
B2B-EH
AC iPOD
AC iPOD
TO MAIN TRANS
8508 ANH-717 (HEAT SINK)
8509 BBZ30P080FNI (SCREW)
CQMBA
CAUTION
FOR CONTINUED PROTECTION AGAINST RISK OF FIRE,
REPLACE ONLY WITH SAME TYPE NO. 491007 MFD.
BY LITTELFUSE INC.FOR IC4751.
AD 2/2

10.55 HDMI ASSY (1/8) (Guide page)



AE 1/8 HDMI ASSY (AWQ7038)



Large size SCH diagram

1/2

2/2

1/2



AE 1/8 HDMI ASSY (AWQ7038)




Large size SCH diagram
1/2
2/2
2/2
AE 2/8,5/8
AE 2/8
AE 2/8,7/8
AE 2/8,5/8
AE 2/8
AE 1/8


RSDA4
RSCL4
IC107
TC7NB257FK
C123
0.1u/10
V+5E4
Q107
HN1K02FU
R149 NM
R150 NM
V+3RX
USCL
USDA
R201 0
R202
R206 0
10
R209 33
R210 33
USCL
USDA
R213 68
R215 47
R218 10
R219 5k
R220 1M
470
HDMI Receiver
IC201
R236 4.7k (F)
V+3RX
2:16G-3:16B-5:1C
RXDV

AE 2/8,3/8,5/8

10.56 HDMI ASSY (2/8) (Guide page)



AE 2/8

AE 2/8 HDMI ASSY (AWQ7038)



AC 2/2 CN6409

AE 1/8

AE 5/8

AE 1/8,3/8,4/8,5/8

AE 1/8,3/8,5/8

AE 7/8

AE 1/8

AE 2/8

Large size SCH diagram

1/2

2/2

1/2



AE 2/8 HDMI ASSY (AWQ7038)




Large size SCH diagram
1/2
2/2
2/2
HDMI Transmitter
IC461
HDSPDIF
HDMCK
HDSD3
HDSD2
HDSD1
HDSD0/DL0
HDWS/DR0
HDSCK/DCK
R462 10
R464 10
R466 470
R465 1k
R473 10
R472 10
R471 33
R470 33
TX2INT
TX2RST
USCL
USDA
PWR12
R475 4.7k
R476 4.7k
R477 2.7k
R478 2.7k
Q461 (1/2) UMB1N
Q461 (2/2) UMB1N
Q462 DTC114YUA
V+5HD2
GNDD
VA465 NM
VA467 NM
C481
C482
C483
C484
C485
C486
C487
C488
VCG1066-A
R479 47k
C480 0.1u/10
C498 NM
ATH7022-A
L466
L468
L467
L469
R480 100
R481 100
V+3TX2
JA461 AK7220-A
HDMI OUT2
Hot Plug Detect
DDC/CEC GND
SDA
SCL
NC
Clock-
Clock Shield
Data0+
Data0- Shield
Data1+
Data1- Shield
Data2+
Data2- Shield
NC
5V Power
HDSCK/DCK
HDSCK
BABCK
HDMCK
HDMCLK
BAMCK
XBAOUT
R419 100
R420 100
R453 0
TC74LCX157FT(EL)
IC401
SEL
GND
VCC
C403 0.1u/10
OTL1013-A
V+3R3HD
R418 100
R417 100
BADATA
HDSD0
HDSD0/DL0
BALRCK
HDWS
HDWS/DR0
HDMIA
BAUD
UCHD
RXDV
1:16B:3:16B:5:1C
AE 1/8
AE 7/8
AE 1/8,3/8,5/8
AE 2/8
130
SC-09TX


IC421
HDMI Transmitter
IC252
S-1112B33MC-L6S
IC251
CN251
VKN1412-A
CECIO
ADPWR1
ADPWR2
IOPWR1
IOPWR2
HPD
ST5V
GNDU
AC 2/2 CN6409
JA421
AKP7220-A
HDMI OUT1
Data2+
Data2 Shield
Data2-
Data1+
Data1 Shield
Data1-
Data0+
Data0 Shield
Data0-
Clock+
Clock Shield
Clock-
CEC
SCL
SDA
DDC/CEC GND
+5V
Hot Plug Detect
ATH7022-A
VCG1066-A
UMB1N
DTC114YUA
AE 1/8
AE 5/8
AE 1/8,3/8,4/8,5/8
AE 1/8,3/8,5/8
AE 7/8
EXHD
UCHD
RXDV
BAUD
HDMIA
USDA
USCL
TX1RST
TX1INT
PUSL1
HDSPDIF
HDMCK
HDSD3
HDSD2
HDSD1
HDSD0/DL0
HDWS/DR0
HDSCK/DCK
GNDD
GNDC
V+5ST
V+5R1
V+5R2
V+5R3
V+5R4
V+5R5
V+5R6
V+5HD1
V+3TX1
V+3R3HD

10.57 HDMI ASSY (3/8) (Guide page)




IC607
ADV7340BSTZ
Video Encoder
IC612
ADR512ARTZ
IC613
SM5309AV
Video Filter
CN601
VKN1428-A
CN602
VKN1430-A
CN603
VKN1434-A
AE 1/8,2/8,5/8
AE 4/8
AE 5/8
AE 4/8
X 1/2 CN2001
Y CN2201
Z CN2401
AE 2/8,4/8,5/8
AE 3/8

Large size SCH diagram




AE 4/8
AE 2/8
IC502
88DE2710-K
Video Format Cobverter
F/DE
VS
HS
LLC
SCSCL
SCSDA
SCRST
V+1R25C
V+1S
V+3S
V+3R3SC
TDET2
GND


Large size
SCH diagram
1/2
2/2
2/2


IC607
ADV7340BSTZ
Video Encoder
IC612
ADR512ARTZ
IC613
SM3094V
Video Filter
CN603
VKN1434-A
Z CN2401
Y CN22(
AE 2/8,4/8,5/8


AE 1/8,2/8,5/8
AE 4/8
AE 5/8
AE 4/8
Y CN2201
X 1/2 CN2001
CN602
CN601
DVSW5
DVSW3
DVSW6
DVSW2
DVSW4
V+3S
GNDD

10.58 HDMI ASSY (4/8)



AE 3/8

AE 4/8


AE 3/8,5/8
AE 2/8,3/8
AE 2/8,3/8,5/5
AE 3/8
AE 2/8
AE 4/8
IC717
LC87F5DC8A-TQFP
PDC166A8
WP CPU
IC716
ADV7180BSTZ
Video Decoder
CN701
VKN1410-A
STBY
IC710
S29AL016D70TFI010
AYW7188-A/J
IC711
MM1117XF
IC712
MM1108XFS1
IC713
MM1117XF
IC714
MM1504XN
Q702
2SA1576A(QR)
Q703
2SC4081(QR)
Q704
2SC4081(QR)
Q705
2SA1576A(QR)
Q706
R1N241M
D701
1SS355
D702
RB501V-40
D703
RB501V-40
X702
VSS1216-A
12MHz
X703
CSTLS27.37-A
27.37444MHz
V+3R3WP
V+5A
V+5O
V+3R3VC
V+3OD
V+1R8VC
GNDD
GNDW
WPCVO
MCVO
LCDCV
OLSL3
XNT/PAL
WPRST1
WPCS1
OLSEL1
FONTSEL
OSINT
OSHS
OSCK
OSDV
UCWP
AVIO
UCHD
WALL PAPER & OSD

10.59 HDMI ASSY (5/8)





HDMI CPU & SUB DVC

10.60 HDMI ASSY (6/8) (Guide page)




IC1006
PD5787A
1394 CPU
IC1004
AYW7113
S29AL004D70TFI010
IC1003
K4S641632K-UC75
IC1005
NJU7093AF
IC1008
PD8112A
Flow Control
IC1009
PST9245
IC1007
TC74VHC125FTS1
CN1001
(NONUSE)
RKN1048-A
TC7WH126FU
X1002
22.5792MHz
X1003
24.576MHz
X1001
6.144MHz
Q1001
HT1P24M
V+12I
V+3IU
V+3R3IE
V+5D
V+3LP
V+12I
GNDD
GNDPS
AE 5/8,7/8
AE 7/8
AE 6/8

Large size SCH diagram






IC1001
TC7SH08FU(S1
L1001
ATL7010-A
L1002
QTL1013-A
JA1001
VKN1800-A
JA1002
VKN1800-A
ATH7015-A
V+3R3IE
GNDD
GNDP
XTAL
BIAS1
BIAS0
TPB0N
TPB0P
TPA0N
TPA0P
TPB1N
TPB1P
TPA1N
TPA1P


PD8112A
IC1008
Flow Control
Large size
SCH diagram
1/2
2/2
2/2
AE 7/8
AE 6/8

IC1006
PD5787A
1394 CPU
IC1004
AYW7113
S29AL004D70TF1010
CN1001
(NONUSE)
RKN1048-A
AE 5/8,7/8
X1002
X1003
IC1010
TC7WH126FU
IC1009
PST9245
IC1007
TC74VHC125FTS
Q1002
RT1P241M
D1001
RB501V-40
X1001-A
X1004-A
X1005-A
L1009
L1010
L1011
L1012
V+12I
V+3IU
V+3R3IE
V+5D
V+5D
V+12
GNDD
GNDD
GNDD
GNDD
XWR
XRD
XCS_MEM
XCS_IO
XCS_FL
DSGAIN
MSAD0
MSAFR
MSACK
TRST
TCK
TMS
TDO
XTAL
MMST2
MMST1
MMST0
IMTO
SACHSL
RXTRG
FSSL1
FSSL0
CKSL
SLTYP1
SLTYP0
FLOW
OUTEN
RSTFLW
SADCT
XINIT
IERST
IEINT
OUTEN
SL4FS
VCOE
MRREQ
HPS
WAIT
BUSCLK
IXCE
IXRD
IXWR
IECK
IEDO
IEDI
TRST
RSTMR
WDTMR
MMST2
IA1
IA2
IA3
IA4
IA5
IA6
IA7
IA8
IA9
IA10
IA11
IA12
IA13
IA14
IA15
IA16
IA17
IA18
IDQ0
IDQ1
IDQ2
IDQ3
IDQ4
IDQ5
IDQ6
IDQ7
IDQ8
IDQ9
IDQ10
IDQ11
IDQ12
IDQ13
IDQ14
IDQ15

10.61 HDMI ASSY (7/8)



AE 7/8 HDMI ASSY (AWQ7038)



10.62 HDMI ASSY (8/8)




V+3R3VC
CN11
B5P-VH
V+5
GND
GND
V+6
PWRGD
AX J4602
IC13
TPS54350PWP
BOOT
PH2
PH1
LSG
VBIAS
PGND
AGND
VSENSECOMP
POWERPAD
VIN1
VIN2
UVLO
PWRGD
SYNC
RT
ENA
Q11
RTQ045N03
Q12
RT1N241M
Q13
RT1P241M
Q14
2SC4081(OR)
D12
UDZS3R6(B)
L11
ATH7050-A
L15
ATH7050-A
TDET3
GNDD
V+2R5VC
IC11
NJM2885DL1-25
V+5HD1
IC14
NJM2872BF05
V+5HD2
IC15
NJM2872BF05
KN11
VNF1109
GNDS
V+1R8VC
IC12
NJM2846DL3-18
D11
1SR154-400
V+3R3WP
IC18
S-1112B33MC-L6S
V+1R5WP
IC16
S-1112B15MC-L6A
V+5O
V+5D
V+5A
IC17
NJM2885DL1-05
GNDS2

10.63 DISPLAY, ICE BLUE, PERCH FFC, PERCH DISP and PERCH PS ASSYS





NOTES

1.RESISTORS
Unit: k-k Ω , M-M Ω or Ω unless otherwise noted.
Rated power: 1/16W unless otherwise noted.
Tolerance: ±5%(J) unless otherwise noted.

2.CAPACITORS
No marked Capacitors are CEAT or CKSRYB.
Unit: p-pF or μF unless otherwise noted.
Rated Voltage: shown as
"Capacity(μF)/Voltage(V)",
or 50V unless otherwise noted.

3.DIODES
No marked Diodes are 1SS352.

※Parts or parts block marked by "STBY" are standby.

10.64 5.1 TFT MODULE

Monitor Input

AK 5.1 TFT MODULE (AWV7006)

AF CN5001

CN801
52793-2870-MOLEX
28P

+8V	28
+8V	27
GND	26
GND	25
SD	24
SI	23
CL	22
DI	21
CS	20
FSHIFT	19
SW1	18
LTBOX	17
BLCONT	16
P-ON1	15
P-ON2	14
P-ON3	13
JUST	12
CPHSEL	11
QHSEL	10
GND	9
VIDEO/SYNC	8
GND	7
VR	6
GND	5
VG	4
GND	3
VB	2
GND	1

CLK, DATA, CERB, SW1, LTBOX, JUST, CPHSEL, QHSEL, VIDEO, VR, VG, VB

	VPOS			HPOS			
	3	2	1	4	3	2	1
NTSC	1	0	0	0	1	1	0
PAL	1	1	0	1	0	0	1

NTSC/PAL discriminating signal

NTSC_H

PAL_L

Video Processing Block


NTSC/PAL
PAL ONLY
NTSC ONLY
CN501
30FLZ-RSM1-TB-GB
+17V
-13V
3.3V
5V (LF)
5V (SW)
LTBOX
JUST

10.65 TACT,POWER SW and VOL ENCODER ASSYS



AL TACT ASSY (AWX8730)



NOTES

1.RESISTORS
Unit: k-k Ω , M-M Ω or Ω unless otherwise noted.
Rated power: 1/16W unless otherwise noted.
Tolerance: ±5%(J) unless otherwise noted.

2.CAPACITORS
No marked Capacitors are CEAT or CKSRYB.
Unit: p-pF or μF unless otherwise noted.
Rated Voltage: shown as
"Capacity(μF)/Voltage(V)",
or 50V unless otherwise noted.

3.DIODES
No marked Diodes are 1SS352.

4.TACT SWITCHES
No marked Switchs are VSG1024.

※Parts or parts block marked by "STBY" are standby.

SWITCHES

S5121 : ZONE2		S5134 :	
S5122 : CTRL		S5135 :	
S5123 : SPEAKERS		S5136 :	STATUS
S5124 : STREAM DIRECT		S5137 :	LCD VIEW
S5125 : A PARA		S5138 :	DIMMER
S5126 : V PARA		S5141 :	ZONE4
S5127 : SETUP		S5142 :	ENTER
S5128 : RETURN		S5143 :	BAND
S5131 : ZONE3		S5144 :	T.EDIT
S5132 :		S5145 :	FAV1
S5133 :		S5146 :	FAV2

10.66 ICE REG, ICE 5 and ICE 12 ASSYS



AP AQ AR

AO FUNC ENCODER ASSY (AWX8753)



AP ICE REG ASSY (AWX8751)



FROM ANALOG TRANSFORMER (T1501)

FU11	REK 1146
FU12	2.5A 125V

CAUTION

FOR CONTINUED PROTECTION AGAINST RISK OF FIRE,REPLACE WITH SAME TYPE AND RATINGS OF FUSE.

NOTES

1.RESISTORS
Unit : k-k Ω , M-M Ω or Ω unless otherwise noted.
Rated power : 1/16W unless otherwise noted.
Tolerance : ± 5%(J) unless otherwise noted.

2.CAPACITORS
No marked Capacitors are CEAT or CKSRYB MBA :CQMBA
Unit : p-pF or μ F unless otherwise noted.
Rated Voltage : shown as
"Capacity(μ F)/Voltage(V)",
or 50V unless otherwise noted.

3.DIODES
No marked Diodes are 1SS355.

※ Parts or parts block marked by "NM" are standby.

10.67 DD DSP,DSP DIODE & HN DIODE ASSYS

CAUTION
FOR CONTINUED PROTECTION AGAINST RISK OF FIRE, REPLACE ONLY WITH SAME TYPE NO. 491005 FOR IC4305 MFD. BY LITTELFUSE INC.

CAUTION
FOR CONTINUED PROTECTION AGAINST RISK OF FIRE, REPLACE WITH SAME TYPE AND RATINGS OF FUSE.



	FU4301	FU4351
KU	REK1148 (5A 125V)	REK1146 (2.5A 125V)

AS DD DSP ASSY (AWX8748)



NOTES

1.RESISTORS
Unit: k-kΩ, M-MΩ or Ω unless otherwise noted.
Rated power: 1/16W unless otherwise noted.
Tolerance: ±5%(J) unless otherwise noted.

2.CAPACITORS
No marked Capacitors are CEAT or CKSRYB. MBA:CQMBA
Unit: p-pF or μF unless otherwise noted.
Rated Voltage: shown as
"Capacity(μF)/Voltage(V)",
or 50V unless otherwise noted.

3.DIODES
No marked Diodes are 1SS355.

※Parts or parts block marked by "STBY" are standby.

10.68 DD DISP and FAN-12V ASSYS



AW DD DISP ASSY (AWX8784)





NOTES

1.RESISTORS
Unit: k-kΩ, M-MΩ or Ω unless otherwise noted.
Rated power: 1/16W unless otherwise noted.
Tolerance: ±5%(J) unless otherwise noted.

2.CAPACITORS
No marked Capacitors are CEAT or CKSRYB. MBA:CQMBA
Unit: p-pF or μF unless otherwise noted.
Rated Voltage: shown as
"Capacity(μF)/Voltage(V)",
or 50V unless otherwise noted.

3.DIODES
No marked Diodes are 1SS355.

※Parts or parts block marked by "STBY" are standby.

The ⚠ mark found on some component parts indicates the importance of the safety factor of the part. Therefore,when replacing,be sure to use parts of identical designation.

CAUTION

FOR CONTINUED PROTECTION AGAINST RISK OF FIRE, REPLACE WITH SAME TYPE AND RATINGS OF FUSE.

CAUTION

FOR CONTINUED PROTECTION AGAINST RISK OF FIRE, REPLACE ONLY WITH SAME TYPE NO. 491007 FOR IC4702, IC4703 MFD. BY LITTELFUSE INC.

10.69 DD HDMI and HDMI DIODE ASSYS



CAUTION
FOR CONTINUED PROTECTION AGAINST RISK OF FIRE, REPLACE WITH SAME TYPE AND RATINGS OF FUSE.

CAUTION
FOR CONTINUED PROTECTION AGAINST RISK OF FIRE, REPLACE ONLY WITH SAME TYPE NO. 491007 FOR IC4602 MFD. BY LITTELFUSE INC.

		FU4601
AWK7959	KU	REK1151 (6A 125V)
AWK7959	JJ	REK1151 (6A 125V)

NOTES
1.RESISTORS
Unit: k-kΩ, M-MΩ or Ω unless otherwise noted.
Rated power: 1/16W unless otherwise noted.
Tolerance: ±5%(J) unless otherwise noted.
2.CAPACITORS
No marked Capacitors are CEAT or CKSRYB. MBA:CQMBA
Unit: p-pF or μF unless otherwise noted.
Rated Voltage: shown as "Capacity(μF)/Voltage(V)", or 50V unless otherwise noted.
3.DIODES
No marked Diodes are 1SS355.
※Parts or parts block marked by "STBY" are standby.

AX DD HDMI ASSY (AWX8750)



10.70 2CH DD ASSY

AZ 2CH DD ASSY (AWX8961)



NOTES

1.RESISTORS
Unit: k-k Ω , M-M Ω or Ω unless otherwise noted.
Rated power: 1/16W unless otherwise noted.
Tolerance: ±5%(J) unless otherwise noted.

2.CAPACITORS
No marked Capacitors are CEAT or CKSRYB. MBA:CQMBA
Unit: p-pF or μF unless otherwise noted.
Rated Voltage: shown as
"Capacity(μF)/Voltage(V)",
or 50V unless otherwise noted.

3.DIODES
No marked Diodes are 1SS355.

※Parts or parts block marked by "STBY" are standby.


CN4607
V+5V
V+5V
V+5V
GND
GND
GND
GND
GND
GND
V+6V
V+6V
V+6V
B12B-XH
AX CN4605
C4603 10u/35 CCG1236
C4604 10u/35 CCG1236
C4605 10u/35 CCG1236
C4666 STBY
C4665 STBY
IC4631 RSS066N03
IC4632 RSS065N03
L4632 1.0u STBY 3.5uH
L4631 ATH7055 3.5uH
R4631 10m CCN1148
R4642 0
R4643 0
R4602 10 1/4W
D4632 RB050L-40
C4631 470u ACG7061
C4632 100u/16 ACH7282
C4608 0.1u
C4609
C4606 4.7u/16
D4631 RB160M-40
D4611 RB160M-40
C4633 0.1u/25
R4636 1M
C4636 0.022u
R4633 10
R4632 10
R4640 270 B ACN7159
R4638 270 B ACN7159
R4641 270 B ACN7159
R4639 270 B ACN7159
C4635 1000p
C4634 STBY
R4634 130k D
R4635 20k D
R4607 STBY
R4608 0
R4606 0
C4618 33p
R4617 15k
C4617 1000p
C4607 0.01u
C4638 33p
R4637 33k
C4637 4700p
TG1
SW1
BOOST1
Vin
BG1
EXTVcc
INTVcc
PGND
BG2
BOOST2
SW2
TG2
RUN/SS2
SENSE+1
SENSE-1
Vosence1
PLLFLTR
PLLIN
FCB
Ith1
SGND
3.3Vout
Ith2
Vosence2
SENSE-2
SENSE+2

10.71 A-REG and DA DIODE ASSYS





FU6	REK1145 2A125V
FU7	REK1146 2.5A125V
FU8	REK1146 2.5A125V
FU9	REK1144 1.6A125V
FU10	REK1144 1.6A125V

NOTES

1.RESISTORS
Unit : k-k Ω , M-M Ω or Ω unless otherwise noted.
Rated power : 1/16W unless otherwise noted.
Tolerance : ± 5%(J) unless otherwise noted.

2.CAPACITORS
No marked Capacitors are CEAT or CKSRYB MBA :CQMBA
Unit : p-pF or μ F unless otherwise noted.
Rated Voltage : shown as
"Capacity(μ F)/Voltage(V)",
or 50V unless otherwise noted.

3.DIODES
No marked Diodes are 1SS355.

※ Parts or parts block marked by "NM" are standby.

CAUTION

FOR CONTINUED PROTECTION AGAINST RISK OF FIRE,
REPLACE WITH SAME TYPE AND RATINGS OF FUSE.

CAUTION

FOR CONTINUED PROTECTION AGAINST RISK OF FIRE,
REPLACE ONLY WITH SAME TYPE NO.491005 FOR IC4101
MFD. BY LITTELFUSE INC.

10.72 PRIMARY and ICE INPUT 4CH ASSYS




BC
PRIMARY ASSY
(JJ:AWX8757)
(KU/CA:AWX8756)
NOTES
1.RESISTORS
Unit : k-k Ω, M-M Ω or Ω unless otherwise noted.
Rated power : 1/16W unless otherwise noted.
Tolerance : ± 5%(J) unless otherwise noted.
2.CAPACITORS
No marked Capacitors are CEAT or CKSRYB MBA :CQMBA
Unit : p-pF or µ F unless otherwise noted.
Rated Voltage : shown as
"Capacity(µ F)/Voltage(V)".
or 50V unless otherwise noted.
3.DIODES
No marked Diodes are 1SS355.
※ Parts or parts block marked by "NM" are standby.
CAUTION
FOR CONTINUED PROTECTION AGAINST RISK OF FIRE, REPLACE WITH SAME TYPE AND RATINGS OF FUSE.
FU3 REK1149 4A125V
FU4 REK1145 2A125V
CN24 B2P3S-VH
BG J11
CN22 B2P3-VH
ACAN
ACAL
TO ANALOG TRANSFORMER (T1501)
CN23 B2P4-VH
ACDL
ACDN
TO DIGITAL TRANSFORMER (T1502)
CN4001 TUC-P05X-B1
W.UP
AC RY
GNDU
PRY2
PRY1
AD 2/2 CN8513
CN4012 52044-0945
V+5.6ST
GNDST
GNDST
ST RC
AC RY
FAN ON/OFF
FAN H/L
FAN DET
NC
AC 2/2 CN6408
CN4002 B3B-PH-K-Y
FAN+12
GNDU
FAN-12
AW J4702
CN4007 KM200NA2
FAN+10V
GNDU
AE 5/8 CN805
CN4005 KM200NA2LR
V+12VTri
GNDU
AD 2/2 J8512
CN4004 KM200NA9L
RY 3
RY1,2
RY+12
RY+12
RY1,2
FAN1+12
FAN1-12
FAN2+12
FAN2-12
BF J13,J18
CN4006 KM200NA3 NM
FAN3+12
GNDU
FAN3 DET
TO FAN3
KN4002 VNE1949-A
KN4001 VNF1084
RY21 XSR3010-A
T21 ATT7100-A
IC4001
D4001 S1WB(A)60SD-TRB
IC4002 PQ20RX11
Q4001
RT1N241M
X2 VOLTAGE DET
230V MODEL:STBY
AMP RY CONT
FAN ON/OFF
FAN H/L
LOW SPEED
HIGH SPEED
V+12FAN
V-12FAN
GNDU
FAN DET
LF KU ATT7100-
JJ ATT7042-
WY ATT7040-
BC

10.73 ICE INPUT 6CH ASSY

BE ICE INPUT 6CH ASSY (AWX8945)





NOTES

1.RESISTORS
Unit: k-k Ω , M-M Ω or Ω unless otherwise noted.
Rated power: 1/16W unless otherwise noted.
Tolerance: ±5%(J) unless otherwise noted.

2.CAPACITORS
No marked Capacitors are CEAT or CKSRYB.
Unit: p-pF or μF unless otherwise noted.
Rated Voltage: shown as
"Capacity(μF)/Voltage(V)",
or 50V unless otherwise noted.

3.DIODES
No marked Diodes are 1SS352.

※Parts or parts block marked by "STBY" are standby.

10.74 PFC and INLET ASSYS



FU1

CAUTION

FOR CONTINUED PROTECTION AGAINST RISK OF FIRE, REPLACE WITH SAME TYPE AND RATINGS OF FUSE.

*

	VIDEO COMPLEX ASSY	INLET ASSY		⚠ (FU1)
	AWK7951	AWX8731	KU	REK1151 (6A 125V)
	AWK7952	AWX8731	JJ	REK1151 (6A 125V)

FU2 FOR AWK7951

CAUTION

FOR CONTINUED PROTECTION AGAINST RISK OF FIRE, REPLACE ONLY WITH SAME TYPE NO.SHV14-15A N4 MFD. BY SOC CORPORATION FOR FU2.

**

	VIDEO COMPLEX ASSY	PFC ASSY		⚠ (FU2)	H13	H14	H16	H17	L11
	AWK7951	AWX8735	KU	AEK7077 (15A 400V)	AKR7004	AKR7004	STBY	STBY	ATH7062
	AWK7952	AWX8962	JJ	AEK7077 (15A 400V)	AKR7004	AKR7004	STBY	STBY	ATH7062



NOTES

1.RESISTORS
Unit: k-k Ω , M-M Ω or Ω unless otherwise noted.
Rated power: 1/16W unless otherwise noted.
Tolerance: ±5%(J) unless otherwise noted.

2.CAPACITORS
No marked Capacitors are CEAT or CKSRYB.
Unit: p-pF or μF unless otherwise noted.
Rated Voltage: shown as
"Capacity(μF)/Voltage(V)",
or 50V unless otherwise noted.

3.DIODES
No marked Diodes are 1SS355.

※Parts or parts block marked by "STBY" are standby.

The ⚠ mark found on some component parts indicates the importance of the safety factor of the part. Therefore, when replacing, be sure to use parts of identical designation.

11. PCB CONNECTION DIAGRAM

NOTE FOR PCB DIAGRAMS :

1. Part numbers in PCB diagrams match those in the schematic diagrams.
2. A comparison between the main parts of PCB and schematic diagrams is shown below.

Symbol In PCB Diagrams	Symbol In Schematic Diagrams	Part Name
		Transistor
		Transistor with resistor
		Field effect transistor
		Resistor array
		3-terminal regulator

3. The parts mounted on this PCB include all necessary parts for several destinations.
   For further information for respective destinations, be sure to check with the schematic diagram.
4. View point of PCB diagrams.



A

B

C

D

E

F

11.1 A-AUDIO, AUDIO BRIDGE 1 and AUDIO BRIDGE 2 ASSYS

SIDE A

A A-AUDIO ASSY



D AUDIO BRIDGE 2 ASSY




N8026
3004
3004
KN3001
C3002
C3001
C3015
C3016
JA3003
JA3002
JA3001
(ANP7588-C)
C AUDIO BRIDGE 1 ASSY
N CN7002
CN3412
A-BRIDGE1
AWX8764
PC
A30C5/C7
J3411
BA CN4103
CN3411
(ANP7586-C)
Y
X
0
10
20
30
40
50
60
70
80
90
100
110
120
130
290
300
310
320

SIDE B

C AUDIO BRIDGE 1 ASSY





SIDE B

A A-AUDIO ASSY



D AUDIO BRIDGE 2 ASSY



11.2 V-AUDIO and REC SEL ASSYS

SIDE A




G REC SEL ASSY
CN3110
AA
[[G]]
A30C5/C7
CN3108
CN3108
L CN5304
(ANP7588-C)
CN3851
A CN3007
CN3852
A CN3009
RECSEL ASS'Y
AWX8740
LF
[[G]]
A30C5/C7
Production Code
CN3854
CN3855
CN3854
CN3855
(ANP7587-B)
Y
X
250
240
230
220
210
200
190
180
170
160
150
140
130
120
110
160
170
180
190
200
210
220
300
310
320
330

SIDE B

G REC SEL ASSY





SIDE B

B V-AUDIO ASSY



11.3 AUDIO BRIDGE 3, AUDIO BRIDGE 4 and MULTI CH IN ASSYS

SIDE A

H MULTI CH IN ASSY



E AUDIO BRIDGE 3 ASSY



F AUDIO BRIDGE 4 ASSY



SIDE B

E AUDIO BRIDGE 3 ASSY



H MULTI CH IN



F AUDIO BRIDGE 4 ASSY



SIDE B

JLTI CH IN ASSY



11.4 VOLUME ASSY

SIDE A **SIDE A**

I VOLUME ASSY



SIDE B

VOLUME ASSY



11.5 FRONT USB and HN MODULE ASSYS

SIDE A

T HN MODULE ASSY



SIDE A


J FRONT USB ASSY
(ANP2192-A)
(ANP7589-C)
CN7901
CN7801
CN5291
J4303
AS
60
50
40
30
20
10
Y 0
280
290
300
310
320
X

SIDE B

J FRONT USB ASSY



IC Q

Q7854
Q7851
Q7855
Q7856
IC7701
Q7857
IC7802
IC7801
Q7858
Q7852
IC7751
IC7602

T HN MODULE ASSY



(ANP2192-A)

: ASSY


CN7851
TP7851
TP7852
TP7853
TP7854
TP7855
TP7856
TP7857
TP7858
TP7859
TP7862
TP7863
TP7864
TP7865
TP7866
TP7868
TP7871
TP7872
TP7874
TP7876
TP7877
TP7885
TP7886
TP7887
TP7888
TP7889
TP7890
TP7891
TP7892
TP7893
TP7894
TP7895
TP7896
TP7897
TP7898
TP7899
TP7900
TP7901
TP7902
TP7903
TP7904
TP7905
TP7906
TP7907
TP7908
TP7909
TP7910
TP7911
TP7912
TP7913
TP7914
TP7915
TP7916
TP7917
TP7918
TP7919
TP7920
TP7921
TP7922
TP7923
TP7924
TP7925
TP7926
TP7927
TP7928
TP7929
TP7930
TP7931
TP7932
TP7933
TP7934
TP7935
TP7936
TP7937
TP7938
TP7939
TP7940
TP7941
TP7942
TP7943
TP7944
TP7945
TP7946
TP7947
TP7948
TP7949
TP7950
TP7951
TP7952
TP7953
TP7954
TP7955
TP7956
TP7957
TP7958
TP7959
TP7960
TP7961
TP7962
TP7963
TP7964
TP7965
TP7966
TP7967
TP7968
TP7969
TP7970
TP7971
TP7972
TP7973
TP7974
TP7975
TP7976
TP7977
TP7978
TP7979
TP7980
TP7981
TP7982
TP7983
TP7984
TP7985
TP7986
TP7987
TP7988
TP7989
TP7990
TP7991
TP7992
TP7993
TP7994
TP7995
TP7996
TP7997
TP7998
TP7999
TP8000
TP8001
TP8002
TP8003
TP8004
TP8005
TP8006
TP8007
TP8008
TP8009
TP8010
TP8011
TP8012
TP8013
TP8014
TP8015
TP8016
TP8017
TP8018
TP8019
TP8020
TP8021
TP8022
TP8023
TP8024
TP8025
TP8026
TP8027
TP8028
TP8029
TP8030
TP8031
TP8032
TP8033
TP8034
TP8035
TP8036
TP8037
TP8038
TP8039
TP8040
TP8041
TP8042
TP8043
TP8044
TP8045
TP8046
TP8047
TP8048
TP8049
TP8050
TP8051
TP8052
TP8053
TP8054
TP8055
TP8056
TP8057
TP8058
TP8059
TP8060
TP8061
TP8062
TP8063
TP8064
TP8065
TP8066
TP8067
TP8068
TP8069
TP8070
TP8071
TP8072
TP8073
TP8074
TP8075
TP8076
TP8077
TP8078
TP8079
TP8080
TP8081
TP8082
TP8083
TP8084
TP8085
TP8086
TP8087
TP8088
TP8089
TP8090
TP8091
TP8092
TP8093
TP8094
TP8095
TP8096
TP8097
TP8098
TP8099
TP8100
TP8101
TP8102
TP8103
TP8104
TP8105
TP8106
TP8107
TP8108
TP8109
TP8110
TP8111
TP8112
TP8113
TP8114
TP8115
TP8116
TP8117
TP8118
TP8119
TP8120
TP8121
TP8122
TP8123
TP8124
TP8125
TP8126
TP8127
TP8128
TP8129
TP8130
TP8131
TP8132
TP8133
TP8134
TP8135
TP8136
TP8137
TP8138
TP8139
TP8140
TP8141
TP8142
TP8143
TP8144
TP8145
TP8146
TP8147
TP8148
TP8149
TP8150
TP8151
TP8152
TP8153
TP8154
TP8155
TP8156
TP8157
TP8158
TP8159
TP8160
TP8161
TP8162
TP8163
TP8164
TP8165
TP8166
TP8167
TP8168
TP8169
TP8170
TP8171
TP8172
TP8173
TP8174
TP8175
TP8176
TP8177
TP8178
TP8179
TP8180
TP8181
TP8182
TP8183
TP8184
TP8185
TP8186
TP8187
TP8188
TP8189
TP8190
TP8191
TP8192
TP8193
TP8194
TP8195
TP8196
TP8197
TP8198
TP8199
TP8200
TP8201
TP8202
TP8203
TP8204
TP8205
TP8206
TP8207
TP8208
TP8209
TP8210
TP8211
TP8212
TP8213
TP8214
TP8215
TP8216
TP8217
TP8218
TP8219
TP8220
TP8221
TP8222
TP8223
TP8224
TP8225
TP8226
TP8227
TP8228
TP8229
TP8230
TP8231
TP8232
TP8233
TP8234
TP8235
TP8236
TP8237
TP8238
TP8239
TP8240
TP8241
TP8242
TP8243
TP8244
TP8245
TP8246
TP8247
TP8248
TP8249
TP8250
TP8251
TP8252
TP8253
TP8254
TP8255
TP8256
TP8257
TP8258
TP8259
TP8260
TP8261
TP8262
TP8263
TP8264
TP8265
TP8266
TP8267
TP8268
TP8269
TP8270
TP8271
TP8272
TP8273
TP8274
TP8275
TP8276
TP8277
TP8278
TP8279
TP8280
TP8281
TP8282
TP8283
TP8284
TP8285
TP8286
TP8287
TP8288
TP8289
TP8290
TP8291
TP8292
TP8293
TP8294
TP8295
TP8296
TP8297
TP8298
TP8299
TP8300
TP8301
TP8302
TP8303
TP8304
TP8305
TP8306
TP8307
TP8308
TP8309
TP8310
TP8311
TP8312
TP8313
TP8314
TP8315
TP8316
TP8317
TP8318
TP8319
TP8320
TP8321
TP8322
TP8323
TP8324
TP8325
TP8326
TP8327
TP8328
TP8329
TP8330
TP8331
TP8332
TP8333
TP8334
TP8335
TP8336
TP8337
TP8338
TP8339
TP8340
TP8341
TP8342
TP8343
TP8344
TP8345
TP8346
TP8347
TP8348
TP8349
TP8350
TP8351
TP8352
TP8353
TP8354
TP8355
TP8356
TP8357
TP8358
TP8359
TP8360
TP8361
TP8362
TP8363
TP8364
TP8365
TP8366
TP8367
TP8368
TP8369
TP8370
TP8371
TP8372
TP8373
TP8374
TP8375
TP8376
TP8377
TP8378
TP8379
TP8380
TP8381
TP8382
TP8383
TP8384
TP8385
TP8386
TP8387
TP8388
TP8389
TP8390
TP8391
TP8392
TP8393
TP8394
TP8395
TP8396
TP8397
TP8398
TP8399
TP8400
TP8401
TP8402
TP8403
TP8404
TP8405
TP8406
TP8407
TP8408
TP8409
TP8410
TP8411
TP8412
TP8413
TP8414
TP8415
TP8416
TP8417
TP8418
TP8419
TP8420
TP8421
TP8422
TP8423
TP8424
TP8425
TP8426
TP8427
TP8428
TP8429
TP8430
TP8431
TP8432
TP8433
TP8434
TP8435
TP8436
TP8437
TP8438
TP8439
TP8440
TP8441
TP8442
TP8443
TP8444
TP8445
TP8446
TP8447
TP8448
TP8449
TP8450
TP8451
TP8452
TP8453
TP8454
TP8455
TP8456
TP8457
TP8458
TP8459
TP8460
TP8461
TP8462
TP8463
TP8464
TP8465
TP8466
TP8467
TP8468
TP8469
TP8470
TP8471
TP8472
TP8473
TP8474
TP8475
TP8476
TP8477
TP8478
TP8479
TP8480
TP8481
TP8482
TP8483
TP8484
TP8485
TP8486
TP8487
TP8488
TP8489
TP8490
TP8491
TP8492
TP8493
TP8494
TP8495
TP8496
TP8497
TP8498
TP8499
TP8500
TP8501
TP8502
TP8503
TP8504
TP8505
TP8506
TP8507
TP8508
TP8509
TP8510
TP8511
TP8512
TP8513
TP8514
TP8515
TP8516
TP8517
TP8518
TP8519
TP8520
TP8521
TP8522
TP8523
TP8524
TP8525
TP8526
TP8527
TP8528
TP8529
TP8530
TP8531
TP8532
TP8533
TP8534
TP8535
TP8536
TP8537
TP8538
TP8539
TP8540
TP8541
TP8542
TP8543
TP8544
TP8545
TP8546
TP8547
TP8548
TP8549
TP8550
TP8551
TP8552
TP8553
TP8554
TP8555
TP8556
TP8557
TP8558
TP8559
TP8560
TP8561
TP8562
TP8563
TP8564
TP8565
TP8566
TP8567
TP8568
TP8569
TP8570
TP8571
TP8572
TP8573
TP8574
TP8575
TP8576
TP8577
TP8578
TP8579
TP8580
TP8581
TP8582
TP8583
TP8584
TP8585
TP8586
TP8587
TP8588
TP8589
TP8590
TP8591
TP8592
TP8593
TP8594
TP8595
TP8596
TP8597
TP8598
TP8599
TP8600
TP8601
TP8602
TP8603
TP8604
TP8605
TP8606
TP8607
TP8608
TP8609
TP8610
TP8611
TP8612
TP8613
TP8614
TP8615
TP8616
TP8617
TP8618
TP8619
TP8620
TP8621
TP8622
TP8623
TP8624
TP8625
TP8626
TP8627
TP8628
TP8629
TP8630
TP8631
TP8632
TP8633
TP8634
TP8635
TP8636
TP8637
TP8638
TP8639
TP8640
TP8641
TP8642
TP8643
TP8644
TP8645
TP8646
TP8647
TP8648
TP8649
TP8650
TP8651
TP8652
TP8653
TP8654
TP8655
TP8656
TP8657
TP8658
TP8659
TP8660
TP8661
TP8662
TP8663
TP8664
TP8665
TP8666
TP8667
TP8668
TP8669
TP8670
TP8671
TP8672
TP8673
TP8674
TP8675
TP8676
TP8677
TP8678
TP8679
TP8680
TP8681
TP8682
TP8683
TP8684
TP8685
TP8686
TP8687
TP8688
TP8689
TP8690
TP8691
TP8692
TP8693
TP8694
TP8695
TP8696
TP8697
TP8698
TP8699
TP8700
TP8701
TP8702
TP8703
TP8704
TP8705
TP8706
TP8707
TP8708
TP8709
TP8710
TP8711
TP8712
TP8713
TP8714
TP8715
TP8716
TP8717
TP8718
TP8719
TP8720
TP8721
TP8722
TP8723
TP8724
TP8725
TP8726
TP8727
TP8728
TP8729
TP8730
TP8731
TP8732
TP8733
TP8734
TP8735
TP8736
TP8737
TP8738
TP8739
TP8740
TP8741
TP8742
TP8743
TP8744
TP8745
TP8746
TP8747
TP8748
TP8749
TP8750
TP8751
TP8752
TP8753
TP8754
TP8755
TP8756
TP8757
TP8758
TP8759
TP8760
TP8761
TP8762
TP8763
TP8764
TP8765
TP8766
TP8767
TP8768
TP8769
TP8770
TP8771
TP8772
TP8773
TP8774
TP8775
TP8776
TP8777
TP8778
TP8779
TP8780
TP8781
TP8782
TP8783
TP8784
TP8785
TP8786
TP8787
TP8788
TP8789
TP8790
TP8791
TP8792
TP8793
TP8794
TP8795
TP8796
TP8797
TP8798
TP8799
TP8800
TP8801
TP8802
TP8803
TP8804
TP8805
TP8806
TP8807
TP8808
TP8809
TP8810
TP8811
TP8812
TP8813
TP8814
TP8815
TP8816
TP8817
TP8818
TP8819
TP8820
TP8821
TP8822
TP8823
TP8824
TP8825
TP8826
TP8827
TP8828
TP8829
TP8830
TP8831
TP8832
TP8833
TP8834
TP8835
TP8836
TP8837
TP8838
TP8839
TP8840
TP8841
TP8842
TP8843
TP8844
TP8845
TP8846
TP8847
TP8848
TP8849
TP8850
TP8851
TP8852
TP8853
TP8854
TP8855
TP8856
TP8857
TP8858
TP8859
TP8860
TP8861
TP8862
TP8863
TP8864
TP8865
TP8866
TP8867
TP8868
TP8869
TP8870
TP8871
TP8872
TP8873
TP8874
TP8875
TP8876
TP8877
TP8878
TP8879
TP8880
TP8881
TP8882
TP8883
TP8884
TP8885
TP8886
TP8887
TP8888
TP8889
TP8890
TP8891
TP8892
TP8893
TP8894
TP8895
TP8896
TP8897
TP8898
TP8899
TP8900
TP8901
TP8902
TP8903
TP8904
TP8905
TP8906
TP8907
TP8908
TP8909
TP8910
TP8911
TP8912
TP8913
TP8914
TP8915
TP8916
TP8917
TP8918
TP8919
TP8920
TP8921
TP8922
TP8923
TP8924
TP8925
TP8926
TP8927
TP8928
TP8929
TP8930
TP8931
TP8932
TP8933
TP8934
TP8935
TP8936
TP8937
TP8938
TP8939
TP8940
TP8941
TP8942
TP8943
TP8944
TP8945
TP8946
TP8947
TP8948
TP8949
TP8950
TP8951
TP8952
TP8953
TP8954
TP8955
TP8956
TP8957
TP8958
TP8959
TP8960
TP8961
TP8962
TP8963
TP8964
TP8965
TP8966
TP8967
TP8968
TP8969
TP8970
TP8971
TP8972
TP8973
TP8974
TP8975
TP8976
TP8977
TP8978
TP8979
TP8980
TP8981
TP8982
TP8983
TP8984
TP8985
TP8986
TP8987
TP8988
TP8989
TP8990
TP8991
TP8992
TP8993
TP8994
TP8995
TP8996
TP8997
TP8998
TP8999
TP9000
TP9001
TP9002
TP9003
TP9004
TP9005
TP9006
TP9007
TP9008
TP9009
TP9010
TP9011
TP9012
TP9013
TP9014
TP9015
TP9016
TP9017
TP9018
TP9019
TP9020
TP9021
TP9022
TP9023
TP9024
TP9025
TP9026
TP9027
TP9028
TP9029
TP9030
TP9031
TP9032
TP9033
TP9034
TP9035
TP9036
TP9037
TP9038
TP9039
TP9040
TP9041
TP9042
TP9043
TP9044
TP9045
TP9046
TP9047
TP9048
TP9049
TP9050
TP9051
TP9052
TP9053
TP9054
TP9055
TP9056
TP9057
TP9058
TP9059
TP9060
TP9061
TP9062
TP9063
TP9064
TP9065
TP9066
TP9067
TP9068
TP9069
TP9070
TP9071
TP9072
TP9073
TP9074
TP9075
TP9076
TP9077
TP9078
TP9079
TP9080
TP9081
TP9082
TP9083
TP9084
TP9085
TP9086
TP9087
TP9088
TP9089
TP9090
TP9091
TP9092
TP9093
TP9094
TP9095
TP9096
TP9097
TP9098
TP9099
TP9100
TP9101
TP9102
TP9103
TP9104
TP9105
TP9106
TP9107
TP9108
TP9109
TP9110
TP9111
TP9112
TP9113
TP9114
TP9115
TP9116
TP9117
TP9118
TP9119
TP9120
TP9121
TP9122
TP9123
TP9124
TP9125
TP9126
TP9127
TP9128
TP9129
TP9130
TP9131
TP9132
TP9133
TP9134
TP9135
TP9136
TP9137
TP9138
TP9139
TP9140
TP9141
TP9142
TP9143
TP9144
TP9145
TP9146
TP9147
TP9148
TP9149
TP9150
TP9151
TP9152
TP9153
TP9154
TP9155
TP9156
TP9157
TP9158
TP9159
TP9160
TP9161
TP9162
TP9163
TP9164
TP9165
TP9166
TP9167
TP9168
TP9169
TP9170
TP9171
TP9172
TP9173
TP9174
TP9175
TP9176
TP9177
TP9178
TP9179
TP9180
TP9181
TP9182
TP9183
TP9184
TP9185
TP9186
TP9187
TP9188
TP9189
TP9190
TP9191
TP9192
TP9193
TP9194
TP9195
TP9196
TP9197
TP9198
TP9199
TP9200
TP9201
TP9202
TP9203
TP9204
TP9205
TP9206
TP9207
TP9208
TP9209
TP9210
TP9211
TP9212
TP9213
TP9214
TP9215
TP9216
TP9217
TP9218
TP9219
TP9220
TP9221
TP9222
TP9223
TP9224
TP9225
TP9226
TP9227
TP9228
TP9229
TP9230
TP9231
TP9232
TP9233
TP9234
TP9235
TP9236
TP9237
TP9238
TP9239
TP9240
TP9241
TP9242
TP9243
TP9244
TP9245
TP9246
TP9247
TP9248
TP9249
TP9250
TP9251
TP9252
TP9253
TP9254
TP9255
TP9256
TP9257
TP9258
TP9259
TP9260
TP9261
TP9262
TP9263
TP9264
TP9265
TP9266
TP9267
TP9268
TP9269
TP9270
TP9271
TP9272
TP9273
TP9274
TP9275
TP9276
TP9277
TP9278
TP9279
TP9280
TP9281
TP9282
TP9283
TP9284
TP9285
TP9286
TP9287
TP9288
TP9289
TP9290
TP9291
TP9292
TP9293
TP9294
TP9295
TP9296
TP9297
TP9298
TP9299
TP9300
TP9301
TP9302
TP9303
TP9304
TP9305
TP9306
TP9307
TP9308
TP9309
TP9310
TP9311
TP9312
TP9313
TP9314
TP9315
TP9316
TP9317
TP9318
TP9319
TP9320
TP9321
TP9322
TP9323
TP9324
TP9325
TP9326
TP9327
TP9328
TP9329
TP9330
TP9331
TP9332
TP9333
TP9334
TP9335
TP9336
TP9337
TP9338
TP9339
TP9340
TP9341
TP9342
TP9343
TP9344
TP9345
TP9346
TP9347
TP9348
TP9349
TP9350
TP9351
TP9352
TP9353
TP9354
TP9355
TP9356
TP9357
TP9358
TP9359
TP9360
TP9361
TP9362
TP9363
TP9364
TP9365
TP9366
TP9367
TP9368
TP9369
TP9370
TP9371
TP9372
TP9373
TP9374
TP9375
TP9376
TP9377
TP9378
TP9379
TP9380
TP9381
TP9382
TP9383
TP9384
TP9385
TP9386
TP9387
TP9388
TP9389
TP9390
TP9391
TP9392
TP9393
TP9394
TP9395
TP9396
TP9397
TP9398
TP9399
TP9400
TP9401
TP9402
TP9403
TP9404
TP9405
TP9406
TP9407
TP9408
TP9409
TP9410
TP9411
TP9412
TP9413
TP9414
TP9415
TP9416
TP9417
TP9418
TP9419
TP9420
TP9421
TP9422
TP9423
TP9424
TP9425
TP9426
TP9427
TP9428
TP9429
TP9430
TP9431
TP9432
TP9433
TP9434
TP9435
TP9436
TP9437
TP9438
TP9439
TP9440
TP9441
TP9442
TP9443
TP9444
TP9445
TP9446
TP9447
TP9448
TP9449
TP9450
TP9451
TP9452
TP9453
TP9454
TP9455
TP9456
TP9457
TP9458
TP9459
TP9460
TP9461
TP9462
TP9463
TP9464
TP9465
TP9466
TP9467
TP9468
TP9469
TP9470
TP9471
TP9472
TP9473
TP9474
TP9475
TP9476
TP9477
TP9478
TP9479
TP9480
TP9481
TP9482
TP9483
TP9484
TP9485
TP9486
TP9487
TP9488
TP9489
TP9490
TP9491
TP9492
TP9493
TP9494
TP9495
TP9496
TP9497
TP9498
TP9499
TP9500
TP9501
TP9502
TP9503
TP9504
TP9505
TP9506
TP9507
TP9508
TP9509
TP9510
TP9511
TP9512
TP9513
TP9514
TP9515
TP9516
TP9517
TP9518
TP9519
TP9520
TP9521
TP9522
TP9523
TP9524
TP9525
TP9526
TP9527
TP9528
TP9529
TP9530
TP9531
TP9532
TP9533
TP9534
TP9535
TP9536
TP9537
TP9538
TP9539
TP9540
TP9541
TP9542
TP9543
TP9544
TP9545
TP9546
TP9547
TP9548
TP9549
TP9550
TP9551
TP9552
TP9553
TP9554
TP9555
TP9556
TP9557
TP9558
TP9559
TP9560
TP9561
TP9562
TP9563
TP9564
TP9565
TP9566
TP9567
TP9568
TP9569
TP9570
TP9571
TP9572
TP9573
TP9574
TP9575
TP9576
TP9577
TP9578
TP9579
TP9580
TP9581
TP9582
TP9583
TP9584
TP9585
TP9586
TP9587
TP9588
TP9589
TP9590
TP9591
TP9592
TP9593
TP9594
TP9595
TP9596
TP9597
TP9598
TP9599
TP9600
TP9601
TP9602
TP9603
TP9604
TP9605
TP9606
TP9607
TP9608
TP9609
TP9610
TP9611
TP9612
TP9613
TP9614
TP9615
TP9616
TP9617
TP9618
TP9619
TP9620
TP9621
TP9622
TP9623
TP9624
TP9625
TP9626
TP9627
TP9628
TP9629
TP9630
TP9631
TP9632
TP9633
TP9634
TP9635
TP9636
TP9637
TP9638
TP9639
TP9640
TP9641
TP9642
TP9643
TP9644
TP9645
TP9646
TP9647
TP9648
TP9649
TP9650
TP9651
TP9652
TP9653
TP9654
TP9655
TP9656
TP9657
TP9658
TP9659
TP9660
TP9661
TP9662
TP9663
TP9664
TP9665
TP9666
TP9667
TP9668
TP9669
TP9670
TP9671
TP9672
TP9673
TP9674
TP9675
TP9676
TP9677
TP9678
TP9679
TP9680
TP9681
TP9682
TP9683
TP9684
TP9685
TP9686
TP9687
TP9688
TP9689
TP9690
TP9691
TP9692
TP9693
TP9694
TP9695
TP9696
TP9697
TP9698
TP9699
TP9700
TP9701
TP9702
TP9703
TP9704
TP9705
TP9706
TP9707
TP9708
TP9709
TP9710
TP9711
TP9712
TP9713
TP9714
TP9715
TP9716
TP9717
TP9718
TP9719
TP9720
TP9721
TP9722
TP9723
TP9724
TP9725
TP9726
TP9727
TP9728
TP9729
TP9730
TP9731
TP9732
TP9733
TP9734
TP9735
TP9736
TP9737
TP9738
TP9739
TP9740
TP9741
TP9742
TP9743
TP9744
TP9745
TP9746
TP9747
TP9748
TP9749
TP9750
TP9751
TP9752
TP9753
TP9754
TP9755
TP9756
TP9757
TP9758
TP9759
TP9760
TP9761
TP9762
TP9763
TP9764
TP9765
TP9766
TP9767
TP9768
TP9769
TP9770
TP9771
TP9772
TP9773
TP9774
TP9775
TP9776
TP9777
TP9778
TP9779
TP9780
TP9781
TP9782
TP9783
TP9784
TP9785
TP9786
TP9787
TP9788
TP9789
TP9790
TP9791
TP9792
TP9793
TP9794
TP9795
TP9796
TP9797
TP9798
TP9799
TP9800
TP9801
TP9802
TP9803
TP9804
TP9805
TP9806
TP9807
TP9808
TP9809
TP9810
TP9811
TP9812
TP9813
TP9814
TP9815
TP9816
TP9817
TP9818
TP9819
TP9820
TP9821
TP9822
TP9823
TP9824
TP9825
TP9826
TP9827
TP9828
TP9829
TP9830
TP9831
TP9832
TP9833
TP9834
TP9835
TP9836
TP9837
TP9838
TP9839
TP9840
TP9841
TP9842
TP9843
TP9844
TP9845
TP9846
TP9847
TP9848
TP9849
TP9850
TP9851
TP9852
TP9853
TP9854
TP9855
TP9856
TP9857
TP9858
TP9859
TP9860
TP9861
TP9862
TP9863
TP9864
TP9865
TP9866
TP9867
TP9868
TP9869
TP9870
TP9871
TP9872
TP9873
TP9874
TP9875
TP9876
TP9877
TP9878
TP9879
TP9880
TP9881
TP9882
TP9883
TP9884
TP9885
TP9886
TP9887
TP9888
TP9889
TP9890
TP9891
TP9892
TP9893
TP9894
TP9895
TP9896
TP9897
TP9898
TP9899
TP9900
TP9901
TP9902
TP9903
TP9904
TP9905
TP9906
TP9907
TP9908
TP9909
TP9910
TP9911
TP9912
TP9913
TP9914
TP9915
TP9916
TP9917
TP9918
TP9919
TP9920
TP9921
TP9922
TP9923
TP9924
TP9925
TP9926
TP9927
TP9928
TP9929
TP9930
TP9931
TP9932
TP9933
TP9934
TP9935
TP9936
TP9937
TP9938
TP9939
TP9940
TP9941
TP9942
TP9943
TP9944
TP9945
TP9946
TP9947
TP9948
TP9949
TP9950
TP9951
TP9952
TP9953
TP9954
TP9955
TP9956
TP9957
TP9958
TP9959
TP9960
TP9961
TP9962
TP9963
TP9964
TP9965
TP9966
TP9967
TP9968
TP9969
TP9970
TP9971
TP9972
TP9973
TP9974
TP9975
TP9976
TP9977
TP9978
TP9979
TP9980
TP9981
TP9982
TP9983
TP9984
TP9985
TP9986
TP9987
TP9988
TP9989
TP9990
TP9991
TP9992
TP9993
TP9994
TP9995
TP9996
TP9997
TP9998
TP9999
TP10000

11.6 FRONT INPUT and FRONT BUFF ASSYS

SIDE A

K FRONT INPUT ASSY



SIDE A


AD CN8514
L FRONT BUFF ASSY
CN5303
FRONT BUFF ASSY
AWX8775
CN5304
B CN3108
CN5302
(ANP7591-D)
PC

SIDE B

L FRONT BUFF ASSY



K FRONT INPUT ASSY





11.7 USB and NEW ITEM ASSYS

SIDE A

M USB ASSY




CN8035
CN8016
CN8015
CN3412
CN7009
CN7003
CN7001
CN7007
CN7006
CN4752
CN7002
CN7008
NEW ITEM ASSY
PC
LF
NEWITEM
AWX8741
AWX8742
CONTACT SIDE
OPEN SIDE
(ANP7589-C)

SIDE B

A

B

C

N NEW ITEM ASSY

D

E

F



110

SIDE B

M USB ASSY



11.8 MAIN DIGITAL ASSY

SIDE A

O MAIN DIGITAL ASSY



SIDE A


Q CN401
R CN997
R CN991
R CN993
R CN995
CN301
CN308
CN306
CN305
CN104
CN307
K J5201
CN302
Q CN402
CN103
CN102
CN101
(ANP7585-C)
CN8005
V CN8004
V CN8003
160 170 180 190 200 210 220 230 240 250 260 270 280 290 300 310 320

SIDE B

O MAIN DIGITAL ASSY



SIDE B


CN304
CN303
J973
J105
CN103
CN971
CN972
CN201
(ANP7585-C)
140
130
120
110
100
90
80
70
60
50
40
30
20
10
0
Y
170
160
150
140
130
120
110
100
90
80
70
60
50
40
30
20
10
0
X

11.9 SUB DIGITAL ASSY

SIDE A **SIDE A**

P SUB DIGITAL ASSY



SIDE B

SIDE B

P SUB DIGITAL ASSY



11.10 DSP and DIGI BRIDGE ASSYS

SIDE A

Q DSP ASSY





(ANP7611-B)



(ANP7591-D)

SIDE B

R DIGI BRIDGE ASSY





SIDE B

A

Q DSP ASSY



(ANP7611-B)

IC Q

IC603 IC601 IC602

IC622 IC623 IC621

IC401

Q201

IC161

IC361

IC162 IC362

IC372

IC364 IC164

IC172

B C D E F

11.11 DAC ASSY

SIDE A

S DAC ASSY




V CN8001
CN1102
CN1051
CN1002
CN1001
CN1081
(ANP7585-C)
R CN998
R CN992
R CN994
R CN996
DAC ASSY
AWX8723
AWX8724
AWX
150 160 170 180 190 200 210 220 230 240 250 260 270 280 290 300 310 320

SIDE B

S DAC ASSY



SIDE B


CN1102
CN1103
CN1101
CN1082
J1052
(ANP7585-C)
250
240
230
220
210
200
190
180
170
160
150
140
130
120
110
Y
170 160 150 140 130 120 110 100 90 80 70 60 50 40 30 20 10 0
X

11.12 PREOUT, ICE INPUT 4CH and ICE INPUT 6CH ASSYS

SIDE A

BE ICE INPUT 6CH ASSY



U PREOUT ASSY



U BE





BD ICE INPUT 4CH ASSY







SIDE B

BE ICE INPUT 6CH ASSY





BD ICE INPUT 4CH ASSY





U BD BE

SIDE B

SSY



U PREOUT ASSY



U BE

11.13 MOTHER 1 ASSY



SIDE A
V MOTHER 1 ASSY
I CN3903
CN8020
CN8024
H CN3207
CN8023
H CN3206
CN8022
H CN3208
CN8021
H CN3209
CN8026
A CN3004
CN8025
A CN3005
U CN3515
CN8019
U CN3513
CN8018
CN8009
W CN8304
CN8035
N CN7009
CN8011
P CN1802
CN8016
N CN7003
CN8012
AE CN804
CN8015
N CN7001
CN8029
AD CN8501
CN8030
AD CN8502
CN8031
AD CN8503
CN8027
B CN3106
CN8028
B CN3105
FF
EE
DD
CC
BB
AA
MULTI IN
VOLUME
PREOUT
NEW ITEM
ICT
FC
A-AUDIO
V-AUDIO
MOTH2
(ANP7591-D)
SC-09TX
223

SIDE B

A

B

C

D

E

F

V MOTHER 1 ASSY

CN8009

CN8025 CN8022 CN8024 CN8019 CN8035 CN8011
CN8026 CN8021 CN8023 CN8020 CN8018 CN8016 CN8012
CN8015



280 270 260 250 240 230 220 210 200 190 180 170 160 150 140 130 120

SC-09TX


SIDE B
MOTHER1 ASSY
CN8009
CN8011
CN8012
CN8014
CN8003
CN8004
CN8001
CN8005
CN8010
CN8002
CN8034
CN8006
CN8007
CN8008
CN8033
CN8036
CN8027
CN8004
CN8005
CN8010
CN8001
CN8002
CN8006
CN8007
CN8008
CN8011
CN8033
CN8034
CN8036
LF
AWX
(ANP7591-D)
SC-09TX
X
Y

11.14 S-VIDEO, ICE INTERFACE and VIDEO BRIDGE ASSYS

SIDE A

Y S-VIDEO ASSY



AA VIDEO BRIDGE ASSY



AD CN8506

W ICE INTERFACE ASSY



SIDE B

AA VIDEO BRIDGE ASSY



W ICE INTERFACE ASSY



SIDE B

Y S-VIDEO ASSY



11.15 COMPOSITE and COMPONENT ASSYS

SIDE A

X COMPOSITE ASSY



Z COMPONENT ASSY



SIDE B

Z COMPONENT ASSY



X COMPOSITE ASSY



11.16 IR 232C ASSY

SIDE A **SIDE A**



SIDE B

AC IR 232C ASSY



11.17 MOTHER 2 ASSY

SIDE A

AD MOTHER 2 ASSY



SIDE A


V CN8030
V CN8029
CN8502
CN8501
COMPOSITE
CN8504
X CN2003
KK
S-VIDEO
CN8506
Y CN2202
CN4752
N CN7006
TO MAIN TRANS
(DIGITAL)
CN8507
Z CN2402
CN4751
CN8514
L CN5303
J8512
BC CN4005
ICT
FC
CAUTION
iPOD REG
REPLACE WITH SAME TYPE NO.491007.
MFD.BY LITTELFUSE INC. FOR IC4751.
PC
NN
IR&232C
CN8513
BC CN4001
CN8508
(ANP7592-C)
AC CN6401

SIDE B

AD MOTHER 2 ASSY



SIDE B



11.18 HDMI ASSY

SIDE A

AE HDMI ASSY



(ANP7625-B)


FAN(FOR HDMI)
CN801
BC CN4007
CN805
AX J4602
CN11
CN804
V CN8012
CN304
CN303
CN1202
CN1201
HDMI ASSY
AWQ7038
MAX2mm
CONTACT SIDE
CN804
[[G]]
A30C5/C7
LF
UPPER SIDE
部品・パターン禁止領域

SIDE B

AE HDMI ASSY

IC Q

IC11 Q54
IC604 IC601
IC605 IC602 Q55 Q58
IC606 IC603
IC251
IC1201
IC1202 IC12
IC803 Q803 Q801
IC504 Q802
IC617 Q53 Q303
IC1206 Q12
Q302
Q301
IC17
IC609 IC610
IC309 IC304
IC310 IC307
IC311 IC308
IC1207 IC501 Q1202
IC18
IC1213 Q57 Q14
IC612
IC614 IC615
IC1210 IC616
IC607
IC613
IC611
IC704
IC1204
IC804
IC710 Q706
IC1205
IC709
IC801
IC707
Q902
IC203 IC901 Q201
IC205 IC208
IC202 IC713 Q601
IC712
IC1006
IC714 Q602
IC711 IC204
IC206 IC207 Q603
IC1009 Q107 Q903
IC107
IC102 IC105 Q104 Q154
IC157 Q105 Q155
IC155 IC152 Q106 Q156
Q462 Q901
IC101 IC156
IC153 IC151
IC106 IC103 Q461
IC1004
Q904





(ANP7625-B)

11.19 DISPLAY,ICEBLUE,PERCH FFC,PERCH DISP and PERCH PS ASSYS

SIDE A

AF DISPLAY ASSY



AG ICE BLUE ASSY



AF AG

AJ PERCH PS ASSY



AK CN801



AI PERCH DISP ASSY



AH PERCH FFC ASSY



SIDE B

AJ PERCH PS ASSY



AI PERCH DISP ASSY





AH PERCH FFC ASSY



SIDE B

AF DISPLAY ASSY



AG ICE BLUE ASSY



11.20 TACT,POWER SW,VOL ENCODER and FUNC ENCODER ASSYS

SIDE A





AL **AM**

SIDE A



(ANP7586-C)

AN VOLUME ENCODER ASSY



(ANP7590-B)

CN5081

AF CN5006

AO FUNCTION ENCODER ASSY



(ANP7590-B)

SIDE B

AL TACT ASSY



AN VOLUME ENCODER ASSY



CN5081

(ANP7590-B)

AO FUNCTION ENCODER ASSY



(ANP7590-B)

SIDE B



AM POWER SW ASSY



11.21 ICE REG, ICE 5 and ICE 12 ASSYS

SIDE A **SIDE A**

AP ICE REG ASSY



(ANP7590-B)

AQ ICE 5 ASSY



(ANP7590-B)

AR ICE 12 ASSY



(ANP7590-B)

SIDE B

SIDE B

AP ICE REG ASSY



(ANP7590-B)

AR ICE 12 ASSY



(ANP7590-B)

AQ ICE 5 ASSY



(ANP7590-B)

11.22 DD DSP, DSP DIODE and HN DIODE ASSYS

SIDE A

SIDE A

AT DSP DIODE ASSY



AU HN DIODE ASSY



AS DD DSP ASSY



AS **AT** **AU**

SIDE B

SIDE B

AU HN DIODE ASSY



AT DSP DIODE ASSY



AS DD DSP ASSY



11.23 FAN-12V and DD DISP ASSYS

SIDE A

SIDE A

AV FAN-12V ASSY



AW DD DISP ASSY



SIDE B

SIDE B

AV FAN-12V ASSY



AW DD DISP ASSY



5 6 7 8

11.24 DD HDMI, HDMI DIODE and 2CH DD ASSYS

SIDE A

AX DD HDMI ASSY



AZ 2CH DD ASSY



TO MAIN TRANS(DIGITAL) AE CN11

140

AY HDMI DIODE ASSY



SIDE B

AZ 2CH DD ASSY



AY HDMI DIODE ASSY



140

SIDE B

AX DD HDMI ASSY



11.25 A-REG and DA DIODE ASSYS

SIDE A



BB DA DIODE ASSY



(ANP7590-B)

JP4121

J TRANS (ANALOG)

C J3411

CN4105

CN4103



(ANP7590-B)

JP4102

X CN2005

SIDE B

BB DA DIODE ASSY



(ANP7590-B)

BA A-REG ASSY

IC Q

IC4101

Q4132

Q4131

Q4151



BA **BB**

SIDE B


CN4103
CN4105
CN4121
CN4104
CN4102
CN4101
ANALOG REG
A+ROUGHLOCK
A-ROUGHLOCK
A-RL GATE
AD REG
ATTENTION
EN CAS DE REMPLACEMENT
DES FUSIBLES IC4101
N'UTILISER QUE LA
REFERENCE 491005
DE CHEZ LITTELFUSE INC.
IC4101
D4111
C4126
C4141
C4142
C4123
C4118
C4115
C4117
C4116
(ANP7590-B)

11.26 PRIMARY, PFC and INLET ASSYS



ANALOG)

SIDE A





BG INLET ASSY





BF PFC ASSY



BC PRIMARY ASSY



(ANP7590-B)



(ANP7586-C)

IC Q

Q4032
Q4038
Q4044
Q4033
Q4031
Q4043
Q4041
Q4042
Q4039
Q4040
IC4002
Q4024
Q4021
Q4022
Q4001
Q4012 Q4013
Q4011
Q4023
Q4035
Q4036
Q4037

12. PCB PARTS LIST

NOTES: ● *Parts marked by "NSP" are generally unavailable because they are not in our Master Spare Parts List.*

● *The ⚠ mark found on some component parts indicates the importance of the safety factor of the part. Therefore, when replacing, be sure to use parts of identical designation.*

● *When ordering resistors, first convert resistance values into code form as shown in the following examples.*

Ex.1 When there are 2 effective digits (any digit apart from 0), such as 560 ohm and 47k ohm (tolerance is shown by J=5%, and K=10%).

560 Ω → 56 x 10^1 → 561 ····· RD1/4PU 5 6 1 J
47k Ω → 47 x 10^3 → 473 ····· RD1/4PU 4 7 3 J
0.5 Ω → R50 ····· RN2H R 5 0 K
1 Ω → 1R0 ····· RS1P 1 R 0 K

Ex.2 When there are 3 effective digits (such as in high precision metal film resistors).

5.62k Ω → 562 x 10^1 → 5621 ····· RN1/4PC 5 6 2 1 F

● *Meaning of the figures and others in the parentheses in the parts list.*

Example) IC 301 is on the point (face A, 91 of x-axis, and 111 of y-axis) of the corresponding PC board.

IC 301 (A, 91, 111) IC NJM2068V

LIST OF ASSEMBLIES

Mark	No.	Description	Part No.
	1	MAIN DIGITAL ASSY	AWK7949
	2	MAIN DIGITAL ASSY	AWX8721
	2	DAC ASSY	AWX8723
	1	VIDEO COMPLEX ASSY	AWK7951
	2	S-VIDEO ASSY	AWX8725
	2	COMPONENT ASSY	AWX8726
	2	TACT ASSY	AWX8730
	2	INLET ASSY	AWX8731
	2	VIDEO BRIDGE ASSY	AWX8743
	2	AUDIO BRIDGE 1 ASSY	AWX8764
	2	PFC ASSY	AWX8735
	1	VOLUME & PREOUT ASSY	AWK7956
	2	VOLUME ASSY	AWX8737
	2	PREOUT ASSY	AWX8738
	2	MULTI CH IN ASSY	AWX8739
	2	REC SEL ASSY	AWX8740
	2	POWER SW ASSY	AWX8755
	2	AUDIO BRIDGE 3 ASSY	AWX8767
	1	AUDIO INPUT ASSY	AWK7958
	2	V-AUDIO ASSY	AWX8744
	2	A-AUDIO ASSY	AWX8745
	2	IR 232C ASSY	AWX8746
	2	SUB DIGITAL ASSY	AWX8747
	1	COMPLEX 1 ASSY	AWK7959
	2	NEW ITEM ASSY	AWX8741
	2	DD DSP ASSY	AWX8748
	2	DD HDMI ASSY	AWX8750
	2	AUDIO BRIDGE 4 ASSY	AWX8766
	2	FRONT INPUT ASSY	AWX8774
	2	FRONT USB ASSY	AWX8781
	2	DD DISP ASSY	AWX8784
	2	ICE INPUT 4CH ASSY	AWX8946
	2	DSP DIODE ASSY	AWX8956
	2	HDMI DIODE ASSY	AWX8957
	2	HN DIODE ASSY	AWX8958
	2	FAN-12V ASSY	AWX8959
	1	COMPLEX 2 ASSY	AWK7960
	2	ICE REG ASSY	AWX8751
	2	FUNC ENCODER ASSY	AWX8753
	2	VOL ENCODER ASSY	AWX8754
	2	PRIMARY ASSY	AWX8756
	2	A-REG ASSY	AWX8761
	2	AUDIO BRIDGE 2 ASSY	AWX8765
	2	DA DIODE ASSY	AWX8965
	2	ICE 5 ASSY	AWX8968
	2	ICE 12 ASSY	AWX8969
	1	MOTHER 1 ASSY	AWK7965
	2	DIGI BRIDGE ASSY	AWX8752
	2	MOTHER 1 ASSY	AWX8770
	2	FRONT BUFF ASSY	AWX8775
	2	ICE INPUT 6CH ASSY	AWX8945
	1	MOTHER 2 ASSY	AWK7969
	2	MOTHER 2 ASSY	AWX8776
	2	DISPLAY ASSY	AWX8777
	2	COMPOSITE ASSY	AWX8778
	2	ICE INTERFACE ASSY	AWX8779
	2	ICEBLUE ASSY	AWX8780
	2	PERCH FFC ASSY	AWX8782
	2	PERCH DISP ASSY	AWX8783
	2	PERCH PS ASSY	AWX8785
	1	HDMI ASSY	AWQ7038
	1	HN MODULE ASSY	AWV2535
	1	USB ASSY	AWX8867
	1	DSP ASSY	AWX8868
	1	2CH DD ASSY	AWX8961
⚠	1	ICEPOWER AMP ASSY	AWH7010
⚠	1	ICEPOWER SMPS ASSY	AWR7048
	1	5.1 TFT MODULE	AWV7006
	1	FM/AM TUNER UNIT	AXX7250

Mark	No.	Description	Part No.

A A-AUDIO ASSY

MISCELLANEOUS

IC	3001 (A,270,208)	IC	NJM2068MD
IC	3051 (A,257,175)	ANALOG SWITCH IC	TC9273CFG-004
IC	3052 (A,197,202)	ANALOG SWITCH IC	TC9273CFG-004
IC	3053 (A,222,201)	ANALOG SWITCH IC	TC9273CFG-004
IC	3851 (A,194,175)	OP-AMP IC	UPC4570G2-A
JA	3001 (A,313,154)	JACK	VKB1133
JA	3002 (A,313,182)	JACK	VKB1133
JA	3003 (A,313,210)	JACK	VKB1133
KN	3001 (A,308,235)	SCREW PLATE	VNE1948
CN	3004 (A,288,236)	CONNECTOR	CKS1753
CN	3005 (A,250,232)	17P SOCKET	XKP3079
CN	3006 (A,167,228)	19P SOCKET	XKP3080
CN	3007 (A,259,145)	CONNECTOR	CKS1753
CN	3009 (A,209,145)	PLUG	CKS1764
CN	3010 (A,163,179)	PLUG	CKS1764
CN	3011 (A,290,141)	2P CONNECTOR	B02B-XASK-1

RESISTORS

R	3003 (B,292,164)		RS1/16S105J
R	3004 (B,292,158)		RS1/16S105J
R	3005 (B,292,176)		RS1/16S105J
R	3006 (B,292,169)		RS1/16S105J
R	3007 (B,292,187)		RS1/16S105J
R	3008 (B,292,182)		RS1/16S105J
R	3009 (B,292,198)		RS1/16S105J
R	3010 (B,292,193)		RS1/16S105J
R	3011 (B,285,213)		RS1/16S104J
R	3012 (B,285,206)		RS1/16S104J
R	3013 (B,290,153)		RS1/16S222J
R	3014 (B,290,147)		RS1/16S222J
R	3015 (B,290,164)		RS1/16S331J
R	3016 (B,290,158)		RS1/16S331J
R	3017 (B,289,177)		RS1/16S331J
R	3018 (B,289,169)		RS1/16S331J
R	3019 (B,290,187)		RS1/16S331J
R	3020 (B,290,182)		RS1/16S331J
R	3021 (B,290,198)		RS1/16S331J
R	3022 (B,290,193)		RS1/16S331J
R	3023 (B,282,212)		RS1/16S561J
R	3024 (B,282,207)		RS1/16S561J
R	3025 (B,275,211)		RS1/16S104J
R	3026 (B,275,205)		RS1/16S104J
R	3027 (A,270,214)		RS1/16S561J
R	3028 (A,269,203)		RS1/16S561J
R	3029 (A,272,216)		RS1/16S394J
R	3030 (A,273,200)		RS1/16S394J
R	3031 (A,270,216)		RS1/16S303J
R	3032 (A,271,200)		RS1/16S303J
R	3033 (A,262,215)		RS1/16S471J
R	3034 (A,267,200)		RS1/16S471J
R	3035 (B,254,210)		RS1/16S224J
R	3036 (B,254,204)		RS1/16S224J
R	3051 (A,249,164)		RS1/16S221J
R	3052 (A,247,164)		RS1/16S221J
R	3053 (A,248,184)		RS1/16S221J
R	3054 (A,184,201)		RS1/16S221J
R	3055 (A,185,194)		RS1/16S221J
R	3056 (A,187,212)		RS1/16S221J
R	3057 (A,211,204)		RS1/16S221J
R	3058 (A,211,193)		RS1/16S221J
R	3059 (A,211,211)		RS1/16S221J
R	3851 (A,199,183)		RS1/16S221J
R	3852 (A,198,166)		RS1/16S221J
R	3853 (A,197,180)		RS1/16S104J
R	3854 (A,196,169)		RS1/16S104J
R	3855 (B,179,172)		RS1/16S474J
R	3856 (B,179,177)		RS1/16S474J
R	3857 (A,192,182)		RS1/16S0R0J
R	3858 (A,191,168)		RS1/16S0R0J
R	3859 (B,216,180)		RS1/16S104J
R	3860 (B,218,175)		RS1/16S104J
R	3887 (A,194,181)		RS1/16S0R0J
R	3888 (A,193,168)		RS1/16S0R0J

CAPACITORS

C	3001 (A,293,213)		CEAT221M25
C	3002 (A,293,224)		CEAT221M25
C	3003 (B,304,149)		CCSRCH221J50
C	3004 (B,304,145)		CCSRCH221J50
C	3005 (B,304,163)		CCSRCH221J50
C	3006 (B,304,159)		CCSRCH221J50
C	3007 (B,304,177)		CCSRCH221J50
C	3008 (B,304,173)		CCSRCH221J50
C	3009 (B,304,191)		CCSRCH221J50
C	3010 (B,304,187)		CCSRCH221J50
C	3011 (B,304,205)		CCSRCH221J50
C	3012 (B,304,201)		CCSRCH221J50
C	3013 (B,304,219)		CCSRCH221J50
C	3014 (B,304,215)		CCSRCH221J50
C	3015 (A,278,215)		CEAT100M50
C	3016 (A,278,204)		CEAT100M50
C	3017 (B,273,211)		CCSRCH331J50
C	3018 (B,273,205)		CCSRCH331J50
C	3019 (A,264,212)	ELECT. CAPACITOR	CEAT470M25
C	3020 (A,264,202)	ELECT. CAPACITOR	CEAT470M25
C	3021 (A,273,214)		CCSRCH561J50
C	3022 (A,272,203)		CCSRCH561J50
C	3023 (A,273,216)		CKSRYB822K50
C	3024 (A,274,200)		CKSRYB822K50
C	3025 (A,269,216)		CKSRYB122K50
C	3026 (A,270,200)		CKSRYB122K50
C	3027 (A,267,216)		CKSRYB122K50
C	3028 (A,268,200)		CKSRYB122K50
C	3029 (A,257,210)		CEAT100M50
C	3030 (A,257,204)		CEAT100M50
C	3031 (A,274,211)		CKSRYB103K50
C	3032 (A,274,206)		CKSRYB103K50
C	3051 (A,268,172)		CKSRYB103K50
C	3052 (A,268,177)		CKSRYB103K50
C	3053 (A,207,199)		CKSRYB103K50
C	3054 (A,207,207)		CKSRYB103K50
C	3055 (A,233,198)		CKSRYB103K50
C	3056 (A,232,205)		CKSRYB103K50
C	3057 (A,246,166)		CCSRCH101J50
C	3058 (A,211,201)		CCSRCH101J50

Mark	No.	Description	Part No.
C	3059 (A,186,201)		CCSRCH101J50
C	3851 (A,205,181)		CEAT4R7M50
C	3852 (A,206,168)		CEAT4R7M50
C	3855 (A,190,177)		CKSRYB103K50
C	3856 (A,190,172)		CKSRYB103K50
C	3857 (A,186,181)	ELECT. CAPACITOR	CEAT470M25
C	3858 (A,185,168)	ELECT. CAPACITOR	CEAT470M25

B V-AUDIO ASSY

MISCELLANEOUS

IC	3151 (A,231,59)	ANALOG SWITCH IC	TC9273CFG-004
IC	3152 (A,290,59)	ANALOG SWITCH IC	TC9273CFG-004
IC	3153 (A,262,59)	ANALOG SWITCH IC	TC9273CFG-004
JA	3101 (A,178,116)	6P PIN JACK	AKB7193
JA	3102 (A,178,81)	PIN JACK(4P)	AKB7186
JA	3103 (A,178,53)	PIN JACK(4P)	AKB7186
JA	3104 (A,178,25)	PIN JACK(4P)	AKB7186
CN	3105 (A,198,14)	PLUG	CKS1758
CN	3106 (A,224,17)	13P SOCKET	XKP3077
CN	3108 (A,319,73)	PLUG(15P)	KM200NA15
CN	3109 (A,256,104)	PLUG	CKS1761
CN	3110 (A,306,104)	PLUG	CKS1759

RESISTORS

R	3103 (B,198,95)		RS1/16S105J
R	3104 (B,198,99)		RS1/16S105J
R	3107 (B,198,77)		RS1/16S105J
R	3108 (B,198,82)		RS1/16S105J
R	3109 (B,198,68)		RS1/16S105J
R	3110 (B,198,73)		RS1/16S105J
R	3111 (B,198,56)		RS1/16S105J
R	3112 (B,198,64)		RS1/16S105J
R	3113 (B,198,45)		RS1/16S105J
R	3114 (B,198,51)		RS1/16S105J
R	3115 (B,198,34)		RS1/16S105J
R	3116 (B,198,40)		RS1/16S105J
R	3117 (B,197,25)		RS1/16S105J
R	3118 (B,197,29)		RS1/16S105J
R	3119 (B,202,103)		RS1/16S222J
R	3120 (A,201,109)		RS1/16S222J
R	3121 (B,200,95)		RS1/16S331J
R	3122 (B,201,99)		RS1/16S331J
R	3123 (B,200,86)		RS1/16S222J
R	3124 (B,200,91)		RS1/16S222J
R	3125 (B,200,77)		RS1/16S331J
R	3126 (B,200,82)		RS1/16S331J
R	3127 (B,200,68)		RS1/16S331J
R	3128 (B,200,73)		RS1/16S331J
R	3129 (B,200,56)		RS1/16S331J
R	3130 (B,200,64)		RS1/16S331J
R	3131 (B,200,45)		RS1/16S331J
R	3132 (B,200,51)		RS1/16S331J
R	3133 (B,200,34)		RS1/16S331J
R	3134 (B,200,40)		RS1/16S331J
R	3135 (B,200,25)		RS1/16S331J
R	3136 (B,200,29)		RS1/16S331J
R	3151 (A,244,67)		RS1/16S221J
R	3152 (A,244,65)		RS1/16S221J
R	3153 (A,243,50)		RS1/16S221J
R	3154 (A,305,62)		RS1/16S221J
R	3155 (A,303,62)		RS1/16S221J
R	3156 (A,300,51)		RS1/16S221J
R	3157 (A,273,68)		RS1/16S221J
R	3158 (A,273,66)		RS1/16S221J
R	3159 (A,273,51)		RS1/16S221J

CAPACITORS

C	3101 (B,187,129)		CCSRCH221J50
C	3102 (B,187,133)		CCSRCH221J50
C	3103 (B,187,114)		CCSRCH221J50
C	3104 (B,187,118)		CCSRCH221J50
C	3105 (B,187,100)		CCSRCH221J50
C	3106 (B,187,104)		CCSRCH221J50
C	3107 (B,187,86)		CCSRCH221J50
C	3108 (B,187,90)		CCSRCH221J50
C	3109 (B,187,72)		CCSRCH221J50
C	3110 (B,187,76)		CCSRCH221J50
C	3111 (B,187,58)		CCSRCH221J50
C	3112 (B,187,62)		CCSRCH221J50
C	3113 (B,187,44)		CCSRCH221J50
C	3114 (B,187,48)		CCSRCH221J50
C	3115 (B,187,30)		CCSRCH221J50
C	3116 (B,187,34)		CCSRCH221J50
C	3117 (B,187,16)		CCSRCH221J50
C	3118 (B,187,20)		CCSRCH221J50
C	3141 (B,186,109)		CKSRYB103K50
C	3143 (B,186,81)		CKSRYB103K50
C	3145 (B,186,53)		CKSRYB103K50
C	3147 (B,186,25)		CKSRYB103K50
C	3151 (A,220,61)		CKSRYB103K50
C	3152 (A,220,55)		CKSRYB103K50
C	3153 (A,250,61)		CKSRYB103K50
C	3154 (A,250,56)		CKSRYB103K50
C	3155 (A,278,61)		CKSRYB103K50
C	3156 (A,278,56)		CKSRYB103K50
C	3157 (A,244,64)		CCSRCH101J50
C	3158 (A,301,62)		CCSRCH101J50
C	3159 (A,273,65)		CCSRCH101J50

C AUDIO BRIDGE 1 ASSY

MISCELLANEOUS

J	3411 (A,48,40)	5P HOUSHING ASSY	ADX7626
CN	3411 (A,45,18)	19P PLUG	XKP3069
CN	3412 (A,38,111)	13P PLUG	XKP3066

D AUDIO BRIDGE 2 ASSY

MISCELLANEOUS

CN	3421,3422	CONNECTOR	CKS1730

Mark	No.	Description	Part No.

E AUDIO BRIDGE 3 ASSY

MISCELLANEOUS

CN	3441 (A,282,43)	CONNECTOR	CKS1727
CN	3442 (A,234,20)	CONNECTOR	CKS1727
CN	3443 (A,312,43)	CONNECTOR	CKS1727
CN	3444 (A,264,20)	CONNECTOR	CKS1727

F AUDIO BRIDGE 4 ASSY

MISCELLANEOUS

CN	3431 (A,201,192)	CONNECTOR	CKS1727
CN	3432 (A,198,221)	CONNECTOR	CKS1727
CN	3433 (A,171,221)	CONNECTOR	CKS1727
CN	3434 (A,171,192)	CONNECTOR	CKS1727

G REC SEL ASSY

MISCELLANEOUS

IC	3861 (A,189,138)	OP-AMP IC	BA4560RF
IC	3871 (A,193,185)	OP-AMP IC	BA4560RF
IC	3881 (A,190,161)	E-SW IC	TC9162CFG
CN	3851 (A,175,216)	CONNECTOR	CKS1719
CN	3852 (A,175,166)	CONNECTOR	CKS1730
CN	3854 (A,208,192)	CONNECTOR	CKS1727
CN	3855 (A,208,142)	PLUG	CKS1725

RESISTORS

R	3861 (A,181,141)		RS1/16S221J
R	3862 (A,197,140)		RS1/16S221J
R	3863 (A,183,141)		RS1/16S474J
R	3864 (A,196,140)		RS1/16S474J
R	3867 (A,184,135)		RS1/16S0R0J
R	3868 (A,194,134)		RS1/16S0R0J
R	3869 (A,182,143)		RS1/16S474J
R	3870 (A,197,142)		RS1/16S474J
R	3871 (B,199,182)		RS1/16S221J
R	3872 (B,187,183)		RS1/16S221J
R	3873 (B,196,186)		RS1/16S474J
R	3874 (B,190,187)		RS1/16S474J
R	3875 (B,197,175)		RS1/16S474J
R	3876 (B,189,175)		RS1/16S474J
R	3877 (A,199,181)		RS1/16S0R0J
R	3878 (A,187,182)		RS1/16S0R0J
R	3879 (B,201,186)		RS1/16S474J
R	3880 (B,185,187)		RS1/16S474J
R	3881 (A,199,154)		RS1/16S221J
R	3882 (A,199,153)		RS1/16S221J
R	3883 (A,180,154)		RS1/16S221J
R	3893 (A,200,183)		RS1/16S0R0J
R	3894 (A,187,184)		RS1/16S0R0J
R	3899 (A,183,138)		RS1/16S0R0J
R	3900 (A,196,137)		RS1/16S0R0J

CAPACITORS

C	3861 (A,180,143)		CKSRYB105K16
C	3862 (A,199,141)		CKSRYB105K16
C	3865 (A,187,134)		CKSRYB103K50
C	3866 (A,193,142)		CKSRYB103K50
C	3867 (A,183,130)	ELECT. CAPACITOR	CEAT220M25
C	3868 (A,195,130)	ELECT. CAPACITOR	CEAT220M25
C	3871 (B,201,182)		CKSRYB105K16
C	3872 (B,185,183)		CKSRYB105K16
C	3875 (A,191,181)		CKSRYB103K50
C	3876 (A,196,188)		CKSRYB103K50
C	3877 (A,199,177)		CEAT100M50
C	3878 (A,188,177)		CEAT100M50
C	3881 (A,193,173)		CKSRYB103K50
C	3882 (A,187,173)		CKSRYB103K50
C	3885 (A,182,154)		CCSRCH101J50

H MULTI CH IN ASSY

MISCELLANEOUS

IC	3211 (A,46,179)	OP-AMP IC	UPC4570G2-A
IC	3221 (A,46,197)	OP-AMP IC	UPC4570G2-A
IC	3231 (A,46,215)	OP-AMP IC	UPC4570G2-A
IC	3251 (A,72,205)	E-SW IC	TC9163CFG
IC	3261 (A,118,205)	E-SW IC	TC9162CFG
IC	3263 (B,136,216)	IC	NJM2068MD
IC	3264 (B,136,195)	IC	NJM2068MD
IC	3265 (B,122,220)	IC	NJM2068MD
IC	3266 (B,115,194)	IC	NJM2068MD
IC	3267 (A,133,169)	ANALOG SW ARRAY	TC9274CFG-022
IC	3303 (A,64,147)	ELECTRIC VOL IC(2CH)	BD3812F
⚠ IC	3321 (A,82,154)	IC	NJM78L05UA
⚠ IC	3322 (A,82,144)	IC	NJM79L05UA
IC	3323 (A,64,161)	ELECTRIC VOL IC(2CH)	BD3812F
Q	3301 (A,37,145)	TRANSISTOR	IMX25
Q	3302 (A,65,154)	DIGITAL TRANSISTOR	DTC124EUA
Q	3303 (A,91,157)	TRANSISTOR	UMD2N
Q	3321 (A,37,158)	TRANSISTOR	IMX25
Q	3322 (A,65,168)	DIGITAL TRANSISTOR	DTC124EUA
Q	3323 (A,97,157)	TRANSISTOR	UMD2N
D	3303 (A,98,150)	DIODE	RB521S-30
D	3321 (A,78,155)	DIODE	RB521S-30
D	3322 (A,78,143)	DIODE	RB521S-30
JA	3201 (A,14,196)	PIN JACK(4P)	AKB7188
JA	3202 (A,14,224)	PIN JACK(4P)	AKB7188
JA	3301 (A,14,154)	PIN JACK(4P)	AKB7188
CN	3204 (A,164,155)	PLUG	CKS1764
CN	3206 (A,59,232)	23P SOCKET	XKP3083
CN	3207 (A,52,235)	CONNECTOR	CKS1755
CN	3208 (A,95,232)	23P SOCKET	XKP3083
CN	3209 (A,141,235)	CONNECTOR	CKS1752
CN	3210 (A,100,144)	PLUG	CKS1761
CN	3211 (A,129,144)	PLUG	CKS1761

RESISTORS

R	3201 (B,31,192)		RS1/16S105J
R	3202 (B,31,186)		RS1/16S105J
R	3211 (B,31,206)		RS1/16S104J
R	3212 (B,31,200)		RS1/16S104J
R	3213 (B,33,206)		RS1/16S331J
R	3214 (B,33,200)		RS1/16S331J
R	3215 (B,42,182)		RS1/16S104J
R	3216 (B,42,176)		RS1/16S104J

Mark	No.	Description	Part No.
R	3217 (B,57,182)		RS1/16S474J
R	3218 (B,57,176)		RS1/16S474J
R	3219 (B,49,182)		RS1/16S101J
R	3220 (B,50,176)		RS1/16S101J
R	3221 (B,31,220)		RS1/16S104J
R	3222 (B,31,214)		RS1/16S104J
R	3223 (B,33,220)		RS1/16S331J
R	3224 (B,33,214)		RS1/16S331J
R	3225 (B,42,200)		RS1/16S104J
R	3226 (B,42,194)		RS1/16S104J
R	3227 (B,57,200)		RS1/16S474J
R	3228 (B,57,194)		RS1/16S474J
R	3229 (B,49,200)		RS1/16S101J
R	3230 (B,50,194)		RS1/16S101J
R	3231 (B,31,231)		RS1/16S104J
R	3232 (B,31,228)		RS1/16S104J
R	3233 (B,33,230)		RS1/16S331J
R	3234 (B,33,226)		RS1/16S331J
R	3235 (B,42,218)		RS1/16S104J
R	3236 (B,42,212)		RS1/16S104J
R	3237 (B,57,218)		RS1/16S474J
R	3238 (B,57,212)		RS1/16S474J
R	3239 (B,49,218)		RS1/16S101J
R	3240 (B,50,212)		RS1/16S101J
R	3251 (A,80,216)		RS1/16S221J
R	3252 (A,81,216)		RS1/16S221J
R	3253 (A,80,193)		RS1/16S221J
R	3261 (A,129,219)		RS1/16S221J
R	3262 (A,130,219)		RS1/16S221J
R	3263 (A,128,191)		RS1/16S221J
R	3265 (A,132,214)		RS1/16S101J
R	3266 (A,133,200)		RS1/16S101J
R	3267 (A,132,216)		RS1/16S153J
R	3268 (A,132,196)		RS1/16S153J
R	3269 (A,137,212)		RS1/16S0R0J
R	3270 (A,136,200)		RS1/16S0R0J
R	3271 (A,138,218)		RS1/16S912J
R	3272 (A,138,196)		RS1/16S912J
R	3273 (A,133,218)		RS1/16S912J
R	3274 (A,137,191)		RS1/16S912J
R	3275 (B,141,214)		RS1/16S101J
R	3276 (B,141,193)		RS1/16S101J
R	3277 (B,143,210)		RS1/16S104J
R	3278 (B,143,201)		RS1/16S104J
R	3279 (A,119,217)		RS1/16S103J
R	3280 (A,116,197)		RS1/16S103J
R	3281 (A,117,219)		RS1/16S222J
R	3282 (A,118,190)		RS1/16S222J
R	3283 (A,119,219)		RS1/16S123J
R	3284 (A,118,193)		RS1/16S123J
R	3285 (A,123,215)		RS1/16S103J
R	3286 (A,113,192)		RS1/16S103J
R	3287 (A,120,219)		RS1/16S103J
R	3288 (A,117,193)		RS1/16S103J
R	3289 (A,127,219)		RS1/16S103J
R	3290 (A,116,190)		RS1/16S103J
R	3291 (B,127,222)		RS1/16S101J
R	3292 (B,119,190)		RS1/16S101J
R	3293 (B,141,218)		RS1/16S104J
R	3294 (B,141,196)		RS1/16S104J
R	3295 (A,134,183)		RS1/16S221J
R	3296 (A,131,184)		RS1/16S221J
R	3297 (A,128,184)		RS1/16S221J
R	3299 (B,141,210)		RS1/16S474J
R	3300 (A,133,198)		RS1/16S474J
R	3301 (B,41,148)		RS1/16S474J
R	3302 (B,41,142)		RS1/16S474J
R	3303 (B,39,148)		RS1/16S681J
R	3304 (B,39,142)		RS1/16S681J
R	3305 (A,37,150)		RS1/16S103J
R	3306 (A,38,141)		RS1/16S103J
R	3307 (B,35,148)		RS1/16S221J
R	3308 (B,35,142)		RS1/16S221J
R	3311 (A,91,155)		RS1/16S331J
R	3312 (A,67,154)		RS1/16S103J
R	3313 (A,57,153)		RS1/16S102J
R	3314 (A,59,153)		RS1/16S102J
R	3315 (A,91,153)		RS1/16S102J
R	3321 (B,41,161)		RS1/16S474J
R	3322 (B,41,154)		RS1/16S474J
R	3323 (B,39,161)		RS1/16S681J
R	3324 (B,39,154)		RS1/16S681J
R	3325 (A,37,162)		RS1/16S103J
R	3326 (A,38,153)		RS1/16S103J
R	3327 (B,35,161)		RS1/16S221J
R	3328 (B,35,154)		RS1/16S221J
R	3331 (A,97,155)		RS1/16S331J
R	3332 (A,67,168)		RS1/16S103J
R	3333 (A,57,167)		RS1/16S102J
R	3334 (A,59,167)		RS1/16S102J
R	3335 (A,97,153)		RS1/16S102J
R	3341 (B,46,182)		RS1/16S0R0J
R	3342 (B,46,176)		RS1/16S0R0J
R	3345 (A,48,187)		RS1/16S0R0J
R	3346 (A,45,171)		RS1/16S0R0J
R	3347 (B,46,200)		RS1/16S0R0J
R	3348 (B,46,194)		RS1/16S0R0J
R	3351 (A,48,205)		RS1/16S0R0J
R	3352 (A,45,189)		RS1/16S0R0J
R	3353 (B,46,218)		RS1/16S0R0J
R	3354 (B,46,212)		RS1/16S0R0J
R	3357 (A,48,223)		RS1/16S0R0J
R	3358 (A,45,207)		RS1/16S0R0J

CAPACITORS

C	3201 (B,24,191)		CCSRCH221J50
C	3202 (B,24,187)		CCSRCH221J50
C	3211 (B,24,205)		CCSRCH221J50
C	3212 (B,24,201)		CCSRCH221J50
C	3213 (A,39,185)	ELECT. CAPACITOR	ACH7196
C	3214 (A,39,174)	ELECT. CAPACITOR	ACH7196
C	3215 (B,44,182)		CCSRCH101J50
C	3216 (B,44,176)		CCSRCH101J50
C	3217 (A,44,185)		CKSRYB103K50
C	3218 (A,48,174)		CKSRYB103K50
C	3219 (A,53,182)	ELECT. CAPACITOR	ACH7197
C	3220 (A,53,176)	ELECT. CAPACITOR	ACH7197
C	3221 (B,24,219)		CCSRCH221J50

Mark	No.	Description	Part No.
C	3222 (B,24,215)		CCSRCH221J50
C	3223 (A,39,203)	ELECT. CAPACITOR	ACH7196
C	3224 (A,39,191)	ELECT. CAPACITOR	ACH7196
C	3225 (B,44,200)		CCSRCH101J50
C	3226 (B,44,194)		CCSRCH101J50
C	3227 (A,44,203)		CKSRYB103K50
C	3228 (A,48,192)		CKSRYB103K50
C	3229 (A,53,200)	ELECT. CAPACITOR	ACH7197
C	3230 (A,53,194)	ELECT. CAPACITOR	ACH7197
C	3231 (B,24,233)		CCSRCH221J50
C	3232 (B,24,229)		CCSRCH221J50
C	3233 (A,39,221)	ELECT. CAPACITOR	ACH7196
C	3234 (A,39,209)	ELECT. CAPACITOR	ACH7196
C	3235 (B,44,218)		CCSRCH101J50
C	3236 (B,44,212)		CCSRCH101J50
C	3237 (A,44,221)		CKSRYB103K50
C	3238 (A,48,210)		CKSRYB103K50
C	3239 (A,53,218)	ELECT. CAPACITOR	ACH7197
C	3240 (A,53,212)	ELECT. CAPACITOR	ACH7197
C	3241 (B,19,191)		CKSRYB103K50
C	3243 (B,19,219)		CKSRYB103K50
C	3251 (A,63,214)		CKSRYB103K50
C	3252 (A,65,195)		CKSRYB103K50
C	3253 (A,80,196)		CCSRCH101J50
C	3261 (A,107,207)		CKSRYB103K50
C	3262 (A,107,202)		CKSRYB103K50
C	3265 (B,131,221)		CKSRYB103K50
C	3266 (B,131,197)		CKSRYB103K50
C	3267 (A,134,218)		CCSRCH220J50
C	3268 (A,137,193)		CCSRCH220J50
C	3269 (B,131,217)		CKSRYB103K50
C	3270 (B,131,193)		CKSRYB103K50
C	3271 (A,148,209)	ELECT. CAPACITOR	ACH7198
C	3272 (A,148,199)	ELECT. CAPACITOR	ACH7198
C	3273 (A,123,217)		CCSRCH220J50
C	3274 (A,113,193)		CCSRCH220J50
C	3275 (B,117,223)		CKSRYB103K50
C	3276 (B,110,197)		CKSRYB103K50
C	3277 (A,125,219)		CCSRCH220J50
C	3278 (A,116,191)		CCSRCH220J50
C	3279 (B,117,219)		CKSRYB103K50
C	3280 (B,110,193)		CKSRYB103K50
C	3281 (A,148,216)	ELECT. CAPACITOR	ACH7198
C	3282 (A,148,192)	ELECT. CAPACITOR	ACH7198
C	3283 (A,132,155)		CKSRYB103K50
C	3284 (A,135,155)		CKSRYB103K50
C	3285 (A,127,193)		CCSRCH101J50
C	3286 (A,137,182)		CCSRCH101J50
C	3305 (A,69,151)		CKSRYB103K50
C	3306 (A,69,148)		CKSRYB103K50
C	3307 (A,46,149)		CEAT100M50
C	3308 (A,46,143)		CEAT100M50
C	3311 (B,23,149)		CCSRCH221J50
C	3312 (B,23,145)		CCSRCH221J50
C	3313 (A,57,150)		CCSRCH101J50
C	3314 (A,59,150)		CCSRCH101J50
C	3315 (A,94,155)		CKSRYB103K50
C	3320 (A,92,148)	ELECT. CAPACITOR	CEAT102M6R3
C	3321 (A,80,149)		CKSRYB103K50
C	3322 (A,80,148)		CKSRYB103K50
C	3323 (A,74,155)		CEAT1R0M50
C	3324 (A,74,146)		CEAT1R0M50
C	3325 (A,69,165)		CKSRYB103K50
C	3326 (A,69,162)		CKSRYB103K50
C	3327 (A,46,161)		CEAT100M50
C	3328 (A,46,155)		CEAT100M50
C	3331 (B,23,163)		CCSRCH221J50
C	3332 (B,23,159)		CCSRCH221J50
C	3333 (A,57,164)		CCSRCH101J50
C	3334 (A,59,164)		CCSRCH101J50
C	3335 (A,99,155)		CKSRYB103K50

VOLUME ASSY

MISCELLANEOUS

IC	3501 (A,275,180)	E-VR IC	TC94A32BFG
IC	3502 (A,244,180)	IC	OPA2134UA
IC	3521 (A,275,164)	E-VR IC	TC94A32BFG
IC	3522 (A,244,164)	IC	OPA2134UA
IC	3901 (A,275,197)	E-VR IC	TC94A32BFG
IC	3902 (A,244,197)	IC	OPA2134UA
IC	3921 (A,275,147)	E-VR IC	TC94A32BFG
IC	3922 (A,244,147)	IC	OPA2134UA
IC	3941 (A,275,213)	E-VR IC	TC94A32BFG
IC	3942 (A,244,213)	IC	OPA2134UA
IC	3961 (A,275,131)	E-VR IC	TC94A32BFG
IC	3962 (A,244,131)	IC	OPA2134UA
CN	3901 (A,305,176)	PLUG	CKS1761
CN	3902 (A,305,147)	PLUG	CKS1761
CN	3903 (A,218,138)	7P SOCKET	XKP3074
CN	3904 (A,282,103)	PLUG	CKS1761
CN	3905 (A,252,103)	PLUG	CKS1761
	3901 (A,306,134)	PCB BINDER	VEF1040
	3902 (A,306,111)	PCB BINDER	VEF1040
	3903 (A,308,214)	PCB BINDER	VEF1040

RESISTORS

R	3501 (A,249,173)		RS1/16S221J
R	3502 (A,249,187)		RS1/16S221J
R	3503 (B,249,177)		RS1/16S104J
R	3504 (B,249,183)		RS1/16S104J
R	3505 (B,244,177)		RS1/16S474J
R	3506 (B,244,183)		RS1/16S474J
R	3507 (B,235,175)		RS1/16S101J
R	3508 (B,235,185)		RS1/16S101J
R	3511 (A,286,174)		RS1/16S221J
R	3512 (A,288,185)		RS1/16S221J
R	3513 (A,288,183)		RS1/16S221J
R	3521 (A,249,157)		RS1/16S221J
R	3522 (A,249,171)		RS1/16S221J
R	3523 (B,249,161)		RS1/16S104J
R	3524 (B,249,167)		RS1/16S104J
R	3525 (B,244,161)		RS1/16S474J
R	3526 (B,244,167)		RS1/16S474J
R	3527 (B,235,159)		RS1/16S101J
R	3528 (B,235,168)		RS1/16S101J
R	3531 (A,286,158)		RS1/16S221J
R	3532 (A,288,168)		RS1/16S221J

Mark	No.	Description	Part No.
R	3533 (A,288,166)		RS1/16S221J
R	3901 (A,249,190)		RS1/16S221J
R	3902 (A,249,204)		RS1/16S221J
R	3903 (B,249,194)		RS1/16S104J
R	3904 (B,249,200)		RS1/16S104J
R	3905 (B,244,194)		RS1/16S474J
R	3906 (B,244,200)		RS1/16S474J
R	3907 (B,235,192)		RS1/16S101J
R	3908 (B,235,201)		RS1/16S101J
R	3911 (A,286,191)		RS1/16S221J
R	3912 (A,288,201)		RS1/16S221J
R	3913 (A,288,199)		RS1/16S221J
R	3921 (A,249,140)		RS1/16S221J
R	3922 (A,249,154)		RS1/16S221J
R	3923 (B,249,144)		RS1/16S104J
R	3924 (B,249,150)		RS1/16S104J
R	3925 (B,244,144)		RS1/16S474J
R	3926 (B,244,150)		RS1/16S474J
R	3927 (B,235,142)		RS1/16S101J
R	3928 (B,235,152)		RS1/16S101J
R	3931 (A,286,141)		RS1/16S221J
R	3932 (A,288,152)		RS1/16S221J
R	3933 (A,288,150)		RS1/16S221J
R	3941 (A,249,206)		RS1/16S221J
R	3942 (A,249,220)		RS1/16S221J
R	3943 (B,249,210)		RS1/16S104J
R	3944 (B,249,216)		RS1/16S104J
R	3945 (B,244,210)		RS1/16S474J
R	3946 (B,244,216)		RS1/16S474J
R	3947 (B,235,208)		RS1/16S101J
R	3948 (B,235,218)		RS1/16S101J
R	3951 (A,286,207)		RS1/16S221J
R	3952 (A,288,218)		RS1/16S221J
R	3953 (A,288,216)		RS1/16S221J
R	3961 (A,249,124)		RS1/16S221J
R	3962 (A,249,138)		RS1/16S221J
R	3963 (B,249,128)		RS1/16S104J
R	3964 (B,249,134)		RS1/16S104J
R	3965 (B,244,128)		RS1/16S474J
R	3966 (B,244,134)		RS1/16S474J
R	3967 (B,235,127)		RS1/16S101J
R	3968 (B,235,135)		RS1/16S101J
R	3971 (A,286,125)		RS1/16S221J
R	3972 (A,288,135)		RS1/16S221J
R	3973 (A,288,133)		RS1/16S221J

CAPACITORS

Mark	No.	Description	Part No.
C	3503 (A,252,176)	ELECT. CAPACITOR	ACH7199
C	3504 (A,252,184)	ELECT. CAPACITOR	ACH7199
C	3505 (A,261,176)	ELECT. CAPACITOR	ACH7198
C	3506 (A,261,184)	ELECT. CAPACITOR	ACH7198
C	3507 (B,247,177)		CCSRCH101J50
C	3508 (B,247,183)		CCSRCH101J50
C	3509 (A,243,176)		CCSRCH330J50
C	3510 (A,244,185)		CCSRCH330J50
C	3511 (B,283,187)		CCSRCH101J50
C	3513 (B,240,183)		CKSRYB103K50
C	3514 (B,242,177)		CKSRYB103K50
C	3517 (B,267,175)		CKSRYB103K50
C	3518 (B,267,185)		CKSRYB103K50
C	3523 (A,252,159)	ELECT. CAPACITOR	ACH7199
C	3524 (A,252,168)	ELECT. CAPACITOR	ACH7199
C	3525 (A,261,159)	ELECT. CAPACITOR	ACH7198
C	3526 (A,261,168)	ELECT. CAPACITOR	ACH7198
C	3527 (B,247,161)		CCSRCH101J50
C	3528 (B,247,167)		CCSRCH101J50
C	3529 (A,243,159)		CCSRCH330J50
C	3530 (A,244,168)		CCSRCH330J50
C	3531 (B,283,170)		CCSRCH101J50
C	3533 (B,240,167)		CKSRYB103K50
C	3534 (B,242,161)		CKSRYB103K50
C	3537 (B,267,159)		CKSRYB103K50
C	3538 (B,267,169)		CKSRYB103K50
C	3903 (A,252,192)	ELECT. CAPACITOR	ACH7199
C	3904 (A,252,201)	ELECT. CAPACITOR	ACH7199
C	3905 (A,261,192)	ELECT. CAPACITOR	ACH7198
C	3906 (A,261,201)	ELECT. CAPACITOR	ACH7198
C	3907 (B,247,194)		CCSRCH101J50
C	3908 (B,247,200)		CCSRCH101J50
C	3909 (A,243,192)		CCSRCH330J50
C	3910 (A,244,201)		CCSRCH330J50
C	3911 (B,283,203)		CCSRCH101J50
C	3913 (B,240,200)		CKSRYB103K50
C	3914 (B,242,194)		CKSRYB103K50
C	3917 (B,267,192)		CKSRYB103K50
C	3918 (B,267,202)		CKSRYB103K50
C	3923 (A,252,143)	ELECT. CAPACITOR	ACH7199
C	3924 (A,252,151)	ELECT. CAPACITOR	ACH7199
C	3925 (A,261,143)	ELECT. CAPACITOR	ACH7198
C	3926 (A,261,151)	ELECT. CAPACITOR	ACH7198
C	3927 (B,247,144)		CCSRCH101J50
C	3928 (B,247,150)		CCSRCH101J50
C	3929 (A,243,143)		CCSRCH330J50
C	3930 (A,244,152)		CCSRCH330J50
C	3931 (B,283,153)		CCSRCH101J50
C	3933 (B,240,150)		CKSRYB103K50
C	3934 (B,242,144)		CKSRYB103K50
C	3937 (B,267,142)		CKSRYB103K50
C	3938 (B,267,152)		CKSRYB103K50
C	3943 (A,252,209)	ELECT. CAPACITOR	ACH7199
C	3944 (A,252,217)	ELECT. CAPACITOR	ACH7199
C	3945 (A,261,209)	ELECT. CAPACITOR	ACH7198
C	3946 (A,261,217)	ELECT. CAPACITOR	ACH7198
C	3947 (B,247,210)		CCSRCH101J50
C	3948 (B,247,216)		CCSRCH101J50
C	3949 (A,243,209)		CCSRCH330J50
C	3950 (A,244,218)		CCSRCH330J50
C	3951 (B,283,219)		CCSRCH101J50
C	3953 (B,240,216)		CKSRYB103K50
C	3954 (B,242,210)		CKSRYB103K50
C	3957 (B,267,208)		CKSRYB103K50
C	3958 (B,267,218)		CKSRYB103K50
C	3963 (A,252,126)	ELECT. CAPACITOR	ACH7199
C	3964 (A,252,135)	ELECT. CAPACITOR	ACH7199
C	3965 (A,261,126)	ELECT. CAPACITOR	ACH7198
C	3966 (A,261,135)	ELECT. CAPACITOR	ACH7198
C	3967 (B,247,128)		CCSRCH101J50
C	3968 (B,247,134)		CCSRCH101J50

Mark	No.	Description	Part No.
C	3969 (A,243,126)		CCSRCH330J50
C	3970 (A,244,135)		CCSRCH330J50
C	3971 (B,283,137)		CCSRCH101J50
C	3973 (B,240,134)		CKSRYB103K50
C	3974 (B,242,128)		CKSRYB103K50
C	3977 (B,268,127)		CKSRYB103K50
C	3978 (B,267,136)		CKSRYB103K50

J FRONT USB ASSY

MISCELLANEOUS

L	5292 (A,309,35)	CHIP FERRITE BEADS	VTL1169
JA	5291 (A,290,30)	USB CONNECTOR	VKB1226
KN	5203 (A,315,38)	WRAPPING TERMINAL	VNF1084
CN	5291 (A,309,14)	PLUG(5P)	KM200NA5LR

RESISTORS

R	5291 (A,309,32)	RS1/16S0R0J
R	5292 (A,309,27)	RS1/16S0R0J
R	5294 (B,309,23)	RS1/16S0R0J
R	5295 (A,307,17)	RS1/16S0R0J
R	5296 (A,319,27)	RS1/16S0R0J
R	5297 (B,306,18)	RS1/16S0R0J
R	5298	RS1/16S0R0J
R	5299	RS1/16S0R0J
R	9293	RS1/16S0R0J
R	9294	RS1/16S0R0J
R	9297	RS1/16S0R0J

CAPACITORS

C	5292 (B,318,27)	CKSRYB104K50
C	5293 (A,305,30)	CCSRCH101J50

K FRONT INPUT ASSY

MISCELLANEOUS

IC	5221 (A,306,179)	IC	NJM2068MD
D	5221 (B,300,185)	DIODE	DAN217
D	5222 (B,307,160)	DIODE	UDZS5R1(B)
D	5223 (B,310,160)	DIODE	UDZS5R1(B)
D	5224 (A,307,200)	DIODE	UDZS5R1(B)
L	5201 (A,303,83)	INDUCTOR	CTF1387
L	5202 (A,303,77)	INDUCTOR	CTF1387
L	5203 (B,312,56)	CHIP SOLID INDUCTOR	QTL1013
J	5201	3P HOUSING ASSY	ADX7617
JA	5201 (A,291,54)	OPT. LINK IN	AKS7005
JA	5202 (A,291,70)	PIN JACK(4P)	XKX3003
JA	5203 (A,289,193)	JACK	RKN1004
KN	5201 (A,307,75)	WRAPPING TERMINAL	VNF1084
KN	5202 (A,307,226)	WRAPPING TERMINAL	VNF1084
CN	5201 (A,316,97)	11P PLUG	XKP3065
CN	5202 (A,316,178)	11P PLUG	XKP3065
	5204	PHONE JACK	AKN7029

RESISTORS

R	5203 (A,305,83)	RS1/16S104J
R	5204 (A,305,78)	RS1/16S104J
R	5205 (A,307,86)	RS1/16S221J
R	5206 (A,309,78)	RS1/16S221J
R	5207 (B,311,52)	RS1/16S101J
R	5208 (B,305,118)	RS1/16S750J
R	5209 (B,303,109)	RS1/16S750J
R	5210 (B,301,103)	RS1/16S750J
R	5221 (A,303,200)	RS1/16S102J
R	5223 (B,295,186)	RS1/16S104J
R	5224 (B,304,186)	RS1/16S101J
R	5225 (B,303,182)	RS1/16S104J
R	5226 (B,307,182)	RS1/16S472J
R	5227 (A,309,184)	RS1/16S333J
R	5228 (B,309,182)	RS1/16S101J
R	5229 (B,304,179)	RS1/16S472J
R	5230 (B,309,176)	RS1/16S333J
R	5231 (B,309,172)	RS1/16S101J
R	5232 (B,309,164)	RS1/16S104J
R	5233 (A,303,198)	RS1/16S682J
R	5234 (A,309,197)	RS1/16S102J
R	5241 (A,309,202)	RS1/16S102J
R	5251 (B,307,103)	RS1/16S0R0J
R	5252 (A,308,81)	RS1/16S0R0J
R	5253 (B,320,157)	RS1/16S0R0J
R	5257 (B,306,211)	RS1/16S0R0J
R	5258 (B,306,209)	RS1/16S0R0J
R	5259 (B,306,207)	RS1/16S0R0J

CAPACITORS

C	5201 (A,307,83)	CCSRCH221J50
C	5202 (A,307,78)	CCSRCH221J50
C	5203 (B,305,55)	CKSRYB104K50
C	5204 (B,305,116)	CKSRYB104K50
C	5222 (B,295,189)	CCSRCH471J50
C	5223 (A,304,188)	CEAT100M50
C	5224 (B,305,182)	CCSRCH101J50
C	5225 (A,309,186)	CCSRCH330J50
C	5226 (B,307,176)	CCSRCH330J50
C	5227 (A,309,177)	CKSRYB103K50
C	5228 (A,309,180)	CKSRYB103K50
C	5229 (A,317,148)	CEAT100M50
C	5230 (A,317,156)	CEAT100M50
C	5231 (A,305,170)	CEAT100M50
C	5233 (A,304,194)	CEAT100M50
C	5241 (A,316,199)	CKSRYB392K50
C	5242 (A,319,199)	CKSRYB392K50
C	5251 (B,303,79)	CKSRYB104K50
C	5252 (B,303,77)	CKSRYB102K50
C	5253 (B,303,75)	CCSRCH101J50
C	5254 (B,303,93)	CKSRYB104K50
C	5255 (B,303,90)	CKSRYB102K50
C	5256 (B,303,88)	CCSRCH101J50
C	5257 (B,306,205)	CKSRYB103K50
C	5258 (B,306,203)	CKSRYB102K50
C	5259 (B,306,200)	CCSRCH101J50
C	5264 (B,311,155)	CKSRYB104K50
C	5268 (B,308,109)	CKSRYB103K50
C	5270 (B,306,66)	CKSRYB103K50
C	9254	CKSRYB102K50
C	9255	CKSRYB103K50

Mark	No.	Description	Part No.
C	9256		CCSRCH101J50

L FRONT BUFF ASSY

MISCELLANEOUS

IC	5301 (A,157,222)	OP-AMP IC	BA4560RF
Q	5321 (B,184,227)	TRANSISTOR	2SC4154
Q	5322 (B,195,227)	TRANSISTOR	2SC4154
Q	5323 (B,206,227)	TRANSISTOR	2SC4154
Q	5391 (B,224,221)	TRANSISTOR	RT1N140M
D	5391 (B,226,226)	DIODE	1SS352
D	5392 (B,224,226)	DIODE	1SS352
RY	5391 (A,231,223)	RELAY	VSR1017
CN	5301 (A,151,202)	11P SOCKET	XKP3076
CN	5302 (A,232,202)	11P SOCKET	XKP3076
CN	5303 (A,313,216)	L-PLUG(11P)	KM200NA11L
CN	5304 (A,289,205)	L-PLUG(15P)	KM200NA15L
CN	5305 (A,139,239)	7P CONNECTOR	52044-0745

RESISTORS

R	5301 (B,160,218)		RS1/16S104J
R	5302 (B,154,218)		RS1/16S104J
R	5303 (B,160,220)		RS1/16S221J
R	5304 (B,154,220)		RS1/16S221J
R	5305 (B,160,224)		RS1/16S104J
R	5306 (B,154,222)		RS1/16S104J
R	5307 (B,164,225)		RS1/16S101J
R	5308 (B,150,225)		RS1/16S101J
R	5327 (B,184,222)		RS1/16S332J
R	5328 (B,195,222)		RS1/16S332J
R	5329 (B,206,222)		RS1/16S332J
R	5333 (B,183,231)		RS1/16S114J
R	5334 (B,194,231)		RS1/16S114J
R	5335 (B,205,231)		RS1/16S114J
R	5336 (B,186,222)		RS1/16S184J
R	5337 (B,197,222)		RS1/16S184J
R	5338 (B,208,222)		RS1/16S184J
R	5339 (B,186,231)		RS1/16S0R0J
R	5340 (B,197,231)		RS1/16S0R0J
R	5341 (B,208,231)		RS1/16S0R0J
R	5351		RS1/16S0R0J
R	5352		RS1/16S0R0J
R	5353		RS1/16S0R0J
R	5354		RS1/16S0R0J
R	5355		RS1/16S0R0J
R	5356		RS1/16S0R0J
R	5357		RS1/16S0R0J
R	5358		RS1/16S0R0J
R	5359		RS1/16S0R0J
R	5360		RS1/16S0R0J
R	5361		RS1/16S0R0J
R	5362		RS1/16S0R0J
R	5363		RS1/16S0R0J
R	5364		RS1/16S0R0J
R	5365		RS1/16S0R0J
R	5366		RS1/16S0R0J
R	5367		RS1/16S0R0J
R	5368		RS1/16S0R0J
R	5369		RS1/16S0R0J
R	5370		RS1/16S0R0J
R	5371		RS1/16S0R0J
R	5372		RS1/16S0R0J
R	5373		RS1/16S0R0J
R	5374		RS1/16S0R0J
R	5375		RS1/16S0R0J
R	5376		RS1/16S0R0J
R	5377		RS1/16S0R0J
R	5378		RS1/16S0R0J
R	5379		RS1/16S0R0J
R	5380		RS1/16S0R0J
R	5381		RS1/16S0R0J
R	5382		RS1/16S0R0J
R	5383		RS1/16S0R0J
R	5384		RS1/16S0R0J
R	5385		RS1/16S0R0J
R	5386		RS1/16S0R0J
R	5387		RS1/16S0R0J
R	5388		RS1/16S0R0J
R	5389		RS1/16S0R0J
R	5390		RS1/16S0R0J
R	5393 (B,226,221)		RS1/10S0R0J

CAPACITORS

C	5301 (A,165,217)		CEAL100M16
C	5302 (A,149,217)		CEAL100M16
C	5303 (B,160,222)		CCSRCH101J50
C	5304 (B,154,224)		CCSRCH101J50
C	5305 (A,167,227)	ELECTR. CAPACITOR	CEAL470M25
C	5306 (A,147,227)	ELECTR. CAPACITOR	CEAL470M25
C	5307 (A,159,226)		CKSRYB103K50
C	5308 (A,155,226)		CKSRYB103K50
C	5309 (A,162,231)		CEAL330M25
C	5310 (A,155,231)		CEAL330M25
C	5321 (A,187,214)	ELECTR. CAPACITOR	CEAL470M25
C	5322 (A,198,214)	ELECTR. CAPACITOR	CEAL470M25
C	5323 (A,209,214)	ELECTR. CAPACITOR	CEAL470M25
C	5327 (B,188,231)		CKSRYB103K50
C	5328 (B,184,218)		CKSRYB103K50
C	5329 (B,199,231)		CKSRYB103K50
C	5330 (B,195,218)		CKSRYB103K50
C	5331 (B,210,231)		CKSRYB103K50
C	5332 (B,206,218)		CKSRYB103K50

M USB ASSY

MISCELLANEOUS

	IC	701 (A,35,38)	USB MEDIA CONTROL IC	TCC8600-00X-EA-UG
⚠	IC	702 (A,63,28)	IC	NJM2872BF18
⚠	IC	703 (A,84,25)	IC	NJM2886DL3-33
	IC	741 (A,64,16)	IC	TC7SZ125FU
	IC	761 (A,67,47)	SD-RAM(64M)	HY57V641620FTP-6
	IC	762 (A,90,42)	FLASH ROM	AYW7236
	IC	781 (A,41,15)	IC	341S2154
	IC	951 (A,59,17)	L-MOS AND GATE	TC7SET08FUS1
	L	701 (A,41,54)	INDUCTOR	LCTC100K1608
	L	702 (A,46,53)	CHIP SOLID INDUCTOR	QTL1013
	L	703 (A,23,54)	CHIP SOLID INDUCTOR	QTL1013

Mark	No.		Description	Part No.
L	704	(A,21,29)	CHIP SOLID INDUCTOR	QTL1013
L	733	(A,36,54)	COIL	VTH1043
L	741	(A,63,19)	CHIP SOLID INDUCTOR	QTL1013
L	761	(A,74,38)	CHIP SOLID INDUCTOR	QTL1013
L	762	(A,90,57)	CHIP SOLID INDUCTOR	QTL1013
L	763	(A,47,16)	CHIP SOLID INDUCTOR	QTL1013
L	952	(A,57,14)	CHIP SOLID INDUCTOR	QTL1013
KN	791	(A,30,13)	WRAPPING TERMINAL	VNF1084
X	702	(A,49,46)	CRYSTAL OSCILLATOR	CSS1614
X	703	(A,41,24)	RESONATOR	CSS1319
CN	701	(A,39,60)	CONNECTOR	B4B-PH-K-Y
CN	702	(A,87,16)	CONNECTOR	HLEM11S-1

RESISTORS

R	700	(A,43,57)		RS1/16S0R0J
R	702	(A,48,39)		RS1/16SS101J
R	703	(A,50,40)		RS1/16SS101J
R	704	(A,42,46)		RS1/16SS472J
R	705	(A,25,37)		RS1/16SS472J
R	707	(A,36,49)		RS1/16SS473J
R	708	(A,40,53)		RS1/16SS101J
R	709	(A,41,47)		RS1/16SS103J
R	710	(A,50,39)		RS1/16SS101J
R	711	(A,48,37)		RS1/16SS101J
R	712	(A,29,48)		RS1/16SS101J
R	713	(A,30,49)		RS1/16SS101J
R	714	(A,31,48)		RS1/16SS101J
R	717	(A,22,30)		RS1/16SS101J
R	718	(A,23,30)		RS1/16SS101J
R	719	(A,26,47)		RS1/16SS101J
R	720	(A,27,49)		RS1/16SS101J
R	724	(A,31,51)		RS1/16SS472J
R	725	(A,33,53)		RS1/16SS472J
R	726	(A,34,54)		RS1/16SS472J
R	727	(A,25,41)		RS1/16SS220J
R	728	(A,32,49)		RS1/16SS101J
R	729	(A,51,37)		RS1/16SS101J
R	732	(A,30,60)		RS1/16S0R0J
R	734	(A,30,61)		RS1/16S0R0J
R	735	(A,38,52)		RS1/16SS153J
R	736	(A,34,51)		RS1/16SS153J
R	737	(A,37,51)		RS1/16SS390J
R	738	(A,35,51)		RS1/16SS390J
R	739	(A,86,20)		RS1/16SS221J
R	740	(A,33,50)		RS1/16SS101J
R	741	(A,66,19)		RS1/16SS560J
R	742	(A,77,23)		RS1/16SS101J
R	743	(A,75,23)		RS1/16SS101J
R	744	(A,73,23)		RS1/16SS101J
R	747	(A,45,41)		RS1/16S225J
R	748	(A,46,45)		RS1/16SS470J
R	752	(A,41,19)		RS1/16SS103J
R	753	(A,35,21)		RS1/16SS104J
R	754	(A,34,21)		RS1/16SS104J
R	755	(A,33,21)		RS1/16SS104J
R	756	(A,36,15)		RS1/16SS103J
R	758	(A,36,14)		RS1/16S1003F
R	763	(A,88,58)		RS1/16SS473J
R	764	(A,36,18)		RS1/16SS103J

Mark	No.		Description	Part No.
R	951	(A,40,57)		RS1/16SS101J
R	952	(A,38,55)		RS1/16SS473J
R	953	(A,25,28)		RS1/16SS101J
R	954	(A,25,29)		RS1/16SS473J
R	955	(A,56,22)		RS1/16SS101J
R	956	(A,26,49)		RS1/16SS473J
R	958	(A,60,20)		RS1/16SS101J

CAPACITORS

C	701	(A,29,28)		CKSSYB104K10
C	702	(A,30,28)		CKSSYB471K50
C	703	(A,32,28)		CKSSYB104K10
C	704	(A,33,28)		CKSSYB471K50
C	705	(A,36,27)		CKSSYB104K10
C	706	(A,37,27)		CKSSYB471K50
C	707	(A,40,27)		CKSSYB104K10
C	708	(A,39,27)		CKSSYB471K50
C	709	(A,43,47)		CKSSYB104K10
C	710	(A,43,48)		CKSSYB471K50
C	711	(A,42,50)		CKSSYB104K10
C	712	(A,44,50)		CKSSYB471K50
C	713	(A,38,49)		CCSRCH331J50
C	714	(A,42,52)		CKSQYB225K10
C	715	(A,41,49)		CKSRYB122K50
C	716	(A,47,36)		CKSSYB104K10
C	717	(A,47,32)		CKSSYB104K10
C	718	(A,47,33)		CKSSYB471K50
C	719	(A,25,45)		CKSSYB471K50
C	720	(A,26,45)		CKSSYB104K10
C	721	(A,24,47)		CEJQ101M6R3
C	723	(A,23,33)		CKSSYB471K50
C	724	(A,24,34)		CKSSYB104K10
C	726	(A,21,41)		CKSSYB104K10
C	727	(A,26,39)		CKSSYB471K50
C	728	(A,24,39)		CKSSYB104K10
C	729	(A,25,35)		CKSSYB471K50
C	730	(A,65,27)		CKSSYB103K16
C	734	(A,48,36)		CKSSYB471K50
C	735	(A,23,44)		CKSSYB103K16
C	736	(A,26,30)		CKSSYB471K50
C	739	(A,46,50)		CCSRCH100D50
C	740	(A,46,47)		CCSRCH471J50
C	741	(A,92,19)		CEJQ101M16
C	742	(A,92,24)		CKSRYB104K16
C	743	(A,93,27)		CKSQYB225K10
C	744	(A,97,26)		CEJQ470M10
C	745	(A,65,31)		CKSQYB105K16
C	746	(A,67,28)		CKSQYB475K6R3
C	747	(A,34,48)		CKSSYB104K10
C	748	(A,33,48)		CKSSYB471K50
C	749	(A,44,21)		CCSRCH120J50
C	750	(A,41,21)		CCSRCH120J50
C	751	(A,45,17)		CKSSYB105K6R3
C	752	(A,62,16)		CKSSYB104K10
C	761	(A,76,39)		CKSSYB104K10
C	762	(A,77,39)		CKSSYB471K50
C	763	(A,71,39)		CKSSYB471K50
C	764	(A,67,40)		CKSSYB471K50
C	766	(A,57,40)		CKSSYB471K50

Mark	No.	Description	Part No.
C	767	(A,90,55)	CKSSYB104K10
C	768	(A,90,54)	CKSSYB471K50
C	769	(A,43,55)	CKSRYB104K16
C	793	(A,62,18)	CKSSYB471K50
C	795	(A,42,58)	CKSSYB104K10
C	798	(A,35,16)	CKSRYB102K50
C	799	(A,33,16)	CKSRYB104K16
C	952	(A,57,17)	CKSRYB104K16

N NEW ITEM ASSY

MISCELLANEOUS

	IC	7001	(A,250,189) CPU	PEG293B8
	IC	7002	(A,234,207) FLASH ROM IC	SST25V512ACS
	IC	7003	(A,234,164) IC	TC74VHC125FTS1
	IC	7004	(A,260,209) L-MOS AND GATE	TC7SET08FUS1
	IC	7005	(A,244,164) IC	TC74VHC04FTS1
	IC	7006	(A,253,164) IC	TC74VHC125FTS1
	IC	7007	(A,230,183) IC	TC74VHC125FTS1
	IC	7101	(A,229,199) IC	TC74VHCT08AFTS1
	IC	7201	(A,198,169) IC	NJM2794V
	IC	7202	(A,172,162) IC	NJM2505AF
	IC	7204	(A,276,231) IC	BA4560F
	Q	7101	(A,230,215) TRANSISTOR(SC-70)	2SA1602A
	Q	7102	(A,229,222) DIGITAL TR(SC-70)	RT1N431M
⚠	Q	7103	(A,221,210) TRANSISTOR	2SD1664
	Q	7201	(A,176,165) CHIP TRANSISTOR	RN1901
	Q	7202	(A,152,181) CHIP TRANSISTOR	RSR015P03
⚠	Q	7203	(A,280,212) TRANSISTOR	2SD1664
	D	7102	(A,219,218) DIODE	UDZS10(B)
	D	7201	(A,154,175) DIODE	UDZS6R2(B)
	D	7202	(A,154,176) DIODE	UDZS6R2(B)
	D	7203	(A,154,173) DIODE	UDZS6R2(B)
	D	7204	(A,154,178) DIODE	UDZS6R2(B)
	D	7210	(A,160,170) DIODE	UDZS6R2(B)
	D	7211	(A,160,168) DIODE	UDZS6R2(B)
	D	7212	(A,274,208) DIODE	UDZS12(B)
	D	7301	(A,154,152) DIODE	UDZS6R2(B)
	D	7302	(A,154,155) DIODE	UDZS6R2(B)
	D	7303	(A,154,150) DIODE	UDZS6R2(B)
	D	7304	(A,154,156) DIODE	UDZS6R2(B)
	D	7308	(A,149,150) DIODE	DAN217U
	L	7001	(B,257,150) CHIP SOLID INDUCTOR	QTL1013
	JA	7001	(A,129,153) SOCKET	BKP1127
	JA	7002	(A,129,171) 20P SOCKET	AKP7226
	X	7001	(A,249,173) RESONATOR	CSS1716
	CN	7001	(A,255,148) 21P SOCKET	XKP3081
	CN	7002	(A,276,167) 13P SOCKET	XKP3077
	CN	7003	(A,168,144) PLUG	CKS1760
	CN	7004	(A,268,197) 10P CONNECTOR	VKN1414
	CN	7005	(A,216,202) CONNECTOR	CKS3376
	CN	7006	(A,177,179) PLUG(3P)	KM200NA3R
	CN	7007	(A,158,161) CONNECTOR	B4B-PH-K-Y
	CN	7008	(A,214,184) CONNECTOR	CKS3376
	CN	7009	(A,150,144) CONNECTOR	CKS1754
		7001	(A,284,200) PCB BINDER	VEF1040

RESISTORS

	R	7001	(A,238,174)	RS1/16S101J
	R	7002	(A,240,174)	RS1/16S101J
	R	7003	(A,241,174)	RS1/16S101J
	R	7004	(A,245,170)	RS1/16S512J
	R	7005	(A,245,174)	RS1/16S101J
	R	7006	(B,255,176)	RS1/16S473J
	R	7007	(A,255,174)	RS1/16S101J
	R	7008	(A,257,174)	RS1/16S101J
	R	7009	(A,260,174)	RAB4C101J
	R	7010	(A,263,174)	RS1/16S101J
	R	7011	(A,263,183)	RAB4C101J
	R	7012	(B,260,185)	RS1/16S222J
	R	7013	(A,263,187)	RAB4C101J
	R	7014	(A,260,206)	RS1/16S101J
	R	7015	(A,263,190)	RS1/16S104J
	R	7017	(A,263,193)	RS1/16S104J
	R	7018	(A,250,204)	RAB4C101J
	R	7019	(B,253,202)	RS1/16S104J
	R	7020	(A,246,204)	RAB4C101J
	R	7021	(B,244,199)	RS1/16S473J
	R	7024	(A,243,202)	RS1/16S101J
	R	7025	(A,242,202)	RS1/16S101J
	R	7026	(A,235,198)	RAB4C101J
	R	7027	(B,238,198)	RS1/16S104J
	R	7028	(A,236,192)	RAB4C101J
	R	7029	(A,235,188)	RS1/16S101J
	R	7030	(A,235,186)	RS1/16S101J
	R	7031	(A,237,182)	RS1/16S221J
	R	7032	(A,237,181)	RS1/16S221J
	R	7033	(A,238,179)	RS1/16S221J
	R	7034	(A,238,178)	RS1/16S104J
	R	7041	(A,233,158)	RS1/16S101J
	R	7042	(A,231,158)	RS1/16S104J
	R	7043	(A,235,158)	RS1/16S101J
	R	7044	(A,236,156)	RS1/16S104J
	R	7045	(A,238,170)	RS1/16S101J
	R	7046	(A,236,170)	RS1/16S104J
	R	7047	(A,234,170)	RS1/16S104J
	R	7048	(A,235,170)	RS1/16S104J
	R	7049	(A,231,170)	RS1/16S104J
	R	7050	(A,258,210)	RS1/16S221J
	R	7051	(A,240,162)	RS1/16S221J
	R	7052	(A,241,158)	RS1/16S104J
	R	7053	(A,245,158)	RS1/16S221J
	R	7054	(A,247,159)	RS1/16S104J
	R	7055	(A,243,158)	RS1/16S101J
	R	7056	(A,242,170)	RS1/16S101J
	R	7058	(A,251,157)	RS1/16S104J
	R	7059	(A,255,170)	RS1/16S104J
	R	7060	(A,250,170)	RS1/16S104J
	R	7061	(A,252,170)	RS1/16S104J
	R	7062	(A,229,176)	RS1/16S101J
	R	7063	(A,232,176)	RS1/16S104J
	R	7064	(A,230,190)	RS1/16S104J
	R	7065	(A,227,190)	RS1/16S104J
	R	7066	(A,229,190)	RS1/16S104J
	R	7071	(B,245,152)	RS1/16S224J
	R	7072	(B,243,152)	RS1/16S104J
	R	7073	(B,240,152)	RS1/16S104J
	R	7074	(B,254,152)	RS1/16S104J

Mark	No.	Description	Part No.
R	7075 (B,237,152)		RS1/16S474J
R	7076 (B,234,152)		RS1/16S104J
R	7077 (B,230,152)		RS1/16S104J
R	7079 (B,220,149)		RS1/16S104J
R	7080 (B,224,150)		RS1/16S104J
R	7081 (A,172,149)		RS1/16S104J
R	7082 (A,169,149)		RS1/16S104J
R	7083 (B,155,150)		RS1/16S104J
R	7085 (A,257,164)		RS1/16S104J
R	7086 (B,232,205)		RS1/16S224J
R	7101 (A,229,218)		RS1/16S472J
R	7102 (A,229,219)		RS1/16S472J
R	7103 (A,226,212)		RS1/16S0R0J
R	7104 (A,224,212)		RS1/16S391J
R	7105 (A,220,215)		RS1/16S101J
R	7106 (B,221,201)		RS1/16S221J
R	7107 (B,221,195)		RS1/16S221J
R	7108 (B,221,197)		RS1/16S221J
R	7109 (A,226,194)		RS1/16S101J
R	7201 (B,153,171)		RS1/16S473J
R	7202 (B,153,177)		RS1/16S473J
R	7203 (B,182,167)		RS1/16S331J
R	7204 (B,182,172)		RS1/16S331J
R	7205 (B,268,223)		RS1/16S104J
R	7206 (B,283,223)		RS1/16S104J
R	7207 (B,153,168)		RS1/16S750J
R	7208 (B,161,168)		RS1/16S101J
R	7209 (A,162,162)		RS1/16S101J
R	7210 (B,163,153)		RS1/16S0R0J
R	7212 (A,179,162)		RS1/16S514J
R	7213 (A,179,164)		RS1/16S393J
R	7214 (A,176,170)		RS1/16S0R0J
R	7215 (A,172,178)		RS1/16S103J
R	7216 (A,174,170)		RS1/16S101J
R	7217 (B,139,165)		RS1/16S0R0J
R	7218 (B,139,171)		RS1/16S0R0J
R	7220 (B,279,213)		RS1/16S681J
R	7221 (A,278,209)		RS1/16S101J
R	7223 (A,270,234)		RS1/16S512J
R	7224 (A,283,233)		RS1/16S512J
R	7225 (A,268,231)		RS1/16S103J
R	7226 (A,285,230)		RS1/16S103J
R	7227 (A,269,231)		RS1/16S103J
R	7228 (A,282,231)		RS1/16S103J
R	7229 (A,270,229)		RS1/16S101J
R	7230 (A,283,229)		RS1/16S101J
R	7231 (B,268,229)		RS1/16S0R0J
R	7232 (B,282,229)		RS1/16S0R0J
R	7233 (A,266,233)		RS1/16S0R0J
R	7234 (A,285,234)		RS1/16S0R0J
R	7239 (A,145,181)		RS1/16S0R0J
R	7240 (B,137,165)		RS1/16S0R0J
R	7301 (A,158,151)		RS1/16S104J
R	7302 (A,158,156)		RS1/16S104J
R	7303 (A,160,149)		RS1/16S331J
R	7304 (A,160,156)		RS1/16S331J
R	7305 (B,261,222)		RS1/16S104J
R	7306 (B,261,228)		RS1/16S104J
R	7307 (A,236,223)		RS1/16S0R0J
R	7308 (A,236,228)		RS1/16S0R0J
R	7309 (B,244,218)		RS1/16S0R0J
R	7310 (B,244,232)		RS1/16S0R0J
R	7312 (A,146,158)		RS1/16S0R0J
R	7314 (A,146,152)		RS1/16S0R0J
R	7315 (A,146,156)		RS1/16S0R0J

CAPACITORS

C	7001 (B,241,174)		CKSRYB103K50
C	7002 (A,253,172)		CKSRYB104K16
C	7003 (A,252,200)		CKSRYB104K16
C	7004 (A,238,185)		CKSRYB104K16
C	7005 (A,263,151)		CEAT101M10
C	7006 (A,238,207)		CKSRYB104K16
C	7007 (A,230,165)		CKSRYB104K16
C	7008 (A,260,212)		CKSRYB104K16
C	7009 (A,240,165)		CKSRYB104K16
C	7010 (A,249,164)		CKSRYB104K16
C	7011 (A,226,184)		CKSRYB104K16
C	7012 (B,147,149)		CKSRYB104K16
C	7101 (A,225,199)		CKSRYB104K16
C	7102 (A,223,218)		CEAT101M16
C	7203 (B,184,167)		CCSRCH101J50
C	7204 (B,184,172)		CCSRCH101J50
C	7205 (A,185,162)		CEAT4R7M50
C	7206 (A,185,176)		CEAT4R7M50
C	7207 (A,191,166)		CEAT4R7M50
C	7208 (A,191,172)		CEAT4R7M50
C	7209 (A,271,225)		CEAT100M50
C	7210 (A,282,225)		CEAT100M50
C	7211 (A,204,169)		CEAT100M50
C	7212 (A,197,176)	ELECT. CAPACITOR	CEAT220M25
C	7213 (A,198,173)		CKSRYB104K25
C	7214 (A,168,168)		CEAT4R7M50
C	7215 (A,168,162)		CEAT4R7M50
C	7217 (A,173,159)		CKSRYB104K16
C	7219 (B,139,177)		CKSRYB103K25
C	7221 (A,167,175)		CEAT101M16
C	7222 (B,172,176)		CKSRYB103K25
C	7223 (A,161,178)		CEAT101M16
C	7225 (A,229,192)		CKSRYB104K16
C	7227 (A,281,205)	ELECT. CAPACITOR	CEAT470M25
C	7228 (A,275,213)		CEAT101M16
C	7229 (A,277,227)		CKSRYB104K25
C	7230 (A,275,221)	ELECT. CAPACITOR	CEAT220M25
C	7303 (A,163,150)		CCSRCH101J50
C	7304 (A,162,153)		CCSRCH101J50
C	7309 (A,258,218)		CEAT100M50
C	7310 (A,258,232)		CEAT100M50
C	7315 (A,149,148)		CKSRYB103K25

O MAIN DIGITAL ASSY

MISCELLANEOUS

IC	101 (A,277,44)	CPU	PEG291A8
IC	102 (A,299,48)	FLASH ROM	AYW7217
IC	103 (A,245,45)	PORT EXPANDER IC	BU4094BCFV
IC	104 (A,233,45)	PORT EXPANDER IC	BU4094BCFV
IC	105 (A,205,39)	PORT EXPANDER IC	BU4094BCFV

Mark	No.		Description	Part No.
	IC	106	(A,243,26) PORT EXPANDER IC	BU4094BCFV
	IC	107	(A,233,26) PORT EXPANDER IC	BU4094BCFV
	IC	108	(A,254,19) IC	TC74VHC125FTS1
A	IC	109	(A,267,72) IC	TC74VHC125FTS1
	IC	110	(A,220,45) IC	TC74VHC04FTS1
	IC	111	(A,286,19) IC	TC74VHC125FTS1
	IC	112	(A,296,19) IC	TC74VHC02FTS1
	IC	113	(A,307,19) IC	TC74VHC125FTS1
	IC	114	(A,275,19) IC	TC74VHC08FTS1
	IC	115	(A,265,19) IC	TC74VHC08FTS1
	IC	116	(A,315,19) IC	TC74VHC00FTS1
	IC	117	(A,184,17) REGULATOR IC	NJM2880U1-33
	IC	118	(A,186,24) REGULATOR IC	NJM2872BF33
B	IC	119	(A,306,32) IC	TC74VHC125FTS1
	IC	120	(A,219,24) PORT EXPANDER IC	BU4094BCFV
	IC	201	(A,33,88) IC	TC7WU04FU
	IC	202	(A,33,79) IC	TC7WU04FU
	IC	203	(A,33,65) IC	TC7WU04FU
	IC	204	(A,33,57) IC	TC7WU04FU
	IC	205	(A,43,72) LOGIC IC	SN74HC151PW
	IC	206	(A,44,62) LOGIC IC	SN74HC151PW
	IC	207	(A,44,52) LOGIC IC	SN74HC151PW
	IC	208	(A,189,60) DA I/F TRANSCEIVER	AK4115VQ
	IC	209	(A,193,23) REGURATOR IC	AHK432IGY-0.5
C	IC	210	(A,31,22) REGULATOR IC	NJM2880U1-33
	IC	211	(B,169,79) IC	NJM2885DL1-33
	IC	212	(A,46,80) LOAD SWITCHING	AAT4618IGV-0.5-1
	IC	213	(A,41,27) IC	TC7WH125FU
	IC	214	(A,175,43) IC	TC74VHC125FTS1
	IC	301	(A,55,110) XM/DT IC	BU9450KV
	IC	302	(A,36,115) LOAD SWITCHING	AAT4618IGV-0.5-1
	IC	303	(A,75,109) REGULATOR IC	NJM2872BF33
	IC	331	(A,178,83) IC	TC74LCX125FTS1
	IC	332	(A,189,84) IC	TC74LCX157FTS1
	IC	333	(A,201,86) IC	TC74VHC126FTS1
D	IC	334	(A,164,107) LOGIC IC	TC74VHC153FT
	IC	335	(A,173,107) LOGIC IC	TC74VHC153FT
	IC	336	(A,184,107) LOGIC IC	TC74VHC153FT
	IC	337	(A,195,107) LOGIC IC	TC74VHC153FT
	IC	338	(A,233,89) IC	TC74VHC08FTS1
	IC	339	(A,233,76) IC	TC74LCX157FTS1
	IC	340	(A,233,62) IC	TC74VHC08FTS1
	IC	341	(A,209,109) IC	TC74LCX157FTS1
	IC	342	(A,308,101) IC	TC74LCX157FTS1
	IC	343	(A,308,86) IC	TC74LCX157FTS1
E	IC	344	(A,294,86) IC	TC74LCX157FTS1
	IC	345	(A,281,71) IC	TC74LCX157FTS1
	IC	346	(A,294,68) IC	TC74LCX157FTS1
	IC	347	(A,295,101) IC	TC74LCX125FTS1
	IC	501	(A,42,43) IC	TC7SZ125FU
	IC	502	(A,245,79) DA I/F TRANSCEIVER	AK4114VQ
	IC	506	(A,250,106) IC	TC7WH125FU
	IC	507	(A,276,86) IC	TC74LCX157FTS1
	IC	508	(A,272,101) IC	TC74VHC08FTS1
	IC	509	(A,283,100) IC	TC74VHC08FTS1
	IC	510	(A,262,105) IC	TC74VHC08FTS1
F	IC	511	(A,241,107) IC	TC74LCX157FTS1
	IC	512	(A,184,96) IC	TC7SH08FUS1
	IC	581	(A,59,30) OP-AMP IC	BA4560RF
	IC	582	(A,59,59) AD CONVERTER IC	AK5358AET
	IC	601	(A,79,36) IC	NJM2068MD
	IC	602	(A,79,44) IC	NJM2068MD
	IC	603	(A,79,24) OP-AMP IC	UPC4570G2-A
	IC	651	(A,79,75) AD CONVERTER IC	AK5385BVF
	IC	701	(A,103,36) IC	NJM2068MD
	IC	702	(A,103,44) IC	NJM2068MD
	IC	703	(A,103,24) OP-AMP IC	UPC4570G2-A
	IC	751	(A,103,75) AD CONVERTER IC	AK5385BVF
	IC	801	(A,127,36) IC	NJM2068MD
	IC	802	(A,127,44) IC	NJM2068MD
	IC	803	(A,127,24) OP-AMP IC	UPC4570G2-A
	IC	851	(A,127,75) AD CONVERTER IC	AK5385BVF
	IC	901	(A,151,36) IC	NJM2068MD
	IC	902	(A,151,44) IC	NJM2068MD
	IC	903	(A,151,24) OP-AMP IC	UPC4570G2-A
	IC	951	(A,151,75) AD CONVERTER IC	AK5385BVF
	IC	971	(A,62,87) IC	NJM2391DL1-33
	Q	601	(A,79,29) TRANSISTOR	IMX25
	Q	701	(A,103,29) TRANSISTOR	IMX25
	Q	801	(A,127,29) TRANSISTOR	IMX25
	Q	901	(A,151,29) TRANSISTOR	IMX25
	Q	971	(A,139,14) TRANSISTOR	RT3T22M
	D	101	(A,295,28) CHIP DIODE	RB501V-40
	D	102	(A,180,22) CHIP DIODE	RB501V-40
	D	300	(B,320,74) CHIP DIODE	RB050L-40
	D	301	(A,28,115) DIODE	UDZS5R6(B)
	D	302	(A,30,115) DIODE	UDZS5R6(B)
	D	581	(B,62,57) DIODE	DAN217
	D	582	(B,56,57) DIODE	DAN217
	D	601	(B,82,76) DIODE	MC2848-11
	D	602	(B,75,76) DIODE	MC2848-11
	D	603	(B,82,72) DIODE	MC2846-11
	D	604	(B,75,72) DIODE	MC2846-11
	D	701	(B,106,76) DIODE	MC2848-11
	D	702	(B,99,76) DIODE	MC2848-11
	D	703	(B,106,72) DIODE	MC2846-11
	D	704	(B,99,72) DIODE	MC2846-11
	D	801	(B,130,76) DIODE	MC2848-11
	D	802	(B,123,76) DIODE	MC2848-11
	D	803	(B,130,72) DIODE	MC2846-11
	D	804	(B,123,72) DIODE	MC2846-11
	D	901	(B,154,76) DIODE	MC2848-11
	D	902	(B,147,76) DIODE	MC2848-11
	D	903	(B,154,72) DIODE	MC2846-11
	D	904	(B,147,72) DIODE	MC2846-11
	L	101	(A,188,29) CHIP SOLID INDUCTOR	QTL1013
	L	102	(A,178,23) CHIP SOLID INDUCTOR	QTL1013
	L	201	(A,30,90) CHIP SOLID INDUCTOR	QTL1013
	L	202	(A,30,82) CHIP SOLID INDUCTOR	QTL1013
	L	203	(A,30,68) CHIP SOLID INDUCTOR	QTL1013
	L	204	(A,30,59) CHIP SOLID INDUCTOR	QTL1013
	L	205	(A,46,76) CHIP SOLID INDUCTOR	QTL1013
	L	206	(A,46,66) CHIP SOLID INDUCTOR	QTL1013
	L	207	(A,46,56) CHIP SOLID INDUCTOR	QTL1013
	L	208	(A,27,23) CHIP SOLID INDUCTOR	QTL1013
	L	209	(B,177,63) CHIP SOLID INDUCTOR	QTL1013
	L	210	(A,174,58) CHIP SOLID INDUCTOR	QTL1013
	L	211	(A,193,39) CHIP SOLID INDUCTOR	QTL1013
	L	212	(B,315,98) CHIP SOLID INDUCTOR	QTL1013

Mark	No.	Description	Part No.
L	213	(A,45,30) CHIP SOLID INDUCTOR	QTL1013
L	214	(A,169,41) CHIP SOLID INDUCTOR	QTL1013
L	301	(A,67,103) CHIP SOLID INDUCTOR	QTL1013
L	302	(A,33,119) CHIP SOLID INDUCTOR	ATL7002
L	331	(A,173,85) CHIP SOLID INDUCTOR	QTL1013
L	332	(A,185,89) CHIP SOLID INDUCTOR	QTL1013
L	333	(A,198,92) CHIP SOLID INDUCTOR	QTL1013
L	334	(A,160,111) CHIP SOLID INDUCTOR	QTL1013
L	335	(A,170,112) CHIP SOLID INDUCTOR	QTL1013
L	336	(A,181,112) CHIP SOLID INDUCTOR	QTL1013
L	337	(A,191,112) CHIP SOLID INDUCTOR	QTL1013
L	338	(A,229,91) CHIP SOLID INDUCTOR	QTL1013
L	339	(A,229,79) CHIP SOLID INDUCTOR	QTL1013
L	340	(A,229,65) CHIP SOLID INDUCTOR	QTL1013
L	341	(A,204,112) CHIP SOLID INDUCTOR	QTL1013
L	342	(A,303,103) CHIP SOLID INDUCTOR	QTL1013
L	343	(A,303,88) CHIP SOLID INDUCTOR	QTL1013
L	344	(A,289,88) CHIP SOLID INDUCTOR	QTL1013
L	345	(A,276,74) CHIP SOLID INDUCTOR	QTL1013
L	346	(A,289,70) CHIP SOLID INDUCTOR	QTL1013
L	347	(A,290,103) CHIP SOLID INDUCTOR	QTL1013
L	501	(A,38,42) CHIP SOLID INDUCTOR	QTL1013
L	502	(A,43,39) COIL	PTL1003
L	503	(A,32,39) COIL	PTL1017
L	504	(A,240,70) CHIP SOLID INDUCTOR	QTL1013
L	505	(A,246,69) CHIP SOLID INDUCTOR	QTL1013
L	508	(A,236,112) CHIP SOLID INDUCTOR	QTL1013
L	509	(A,246,109) CHIP SOLID INDUCTOR	QTL1013
L	510	(A,271,90) CHIP SOLID INDUCTOR	QTL1013
L	511	(A,267,103) CHIP SOLID INDUCTOR	QTL1013
L	512	(A,278,103) CHIP SOLID INDUCTOR	QTL1013
L	513	(A,256,109) CHIP SOLID INDUCTOR	QTL1013
L	514	(A,180,95) CHIP SOLID INDUCTOR	QTL1013
L	581	(A,54,56) CHIP SOLID INDUCTOR	QTL1013
L	582	(A,64,56) CHIP SOLID INDUCTOR	QTL1013
L	651	(A,89,83) CHIP SOLID INDUCTOR	QTL1013
L	652	(A,68,83) CHIP SOLID INDUCTOR	QTL1013
L	751	(A,113,83) CHIP SOLID INDUCTOR	QTL1013
L	752	(A,92,83) CHIP SOLID INDUCTOR	QTL1013
L	851	(A,137,83) CHIP SOLID INDUCTOR	QTL1013
L	852	(A,116,83) CHIP SOLID INDUCTOR	QTL1013
L	951	(A,161,83) CHIP SOLID INDUCTOR	QTL1013
L	952	(A,140,83) CHIP SOLID INDUCTOR	QTL1013
L	971	(A,57,81) CHIP SOLID INDUCTOR	ATL7002
F	501	(B,26,43) CHIP MAGNET CORE	DTF1068
F	502	(B,23,43) INDUCTOR	CTF1661
J	105	(A,39,88) 3P HOUSING ASSY	ADX7559
J	973	(A,65,69) 2P HOUSING ASSY	ADX7591
JA	201	(A,13,94) JACK	AKB7148
JA	202	(A,13,66) JACK	AKB7148
JA	203	(A,13,29) OPT. LINK OUT	AKS7006
JA	204	(A,13,15) OPT. LINK OUT	AKS7006
JA	300	(A,13,115) 4P SOCKET	AKP7201
JA	501	(A,13,45) 1P PIN JACK	AKB7191
X	101	(A,264,44) CERAMIC RESONATOR	ASS7087
X	201	(A,179,36) CRYSTAL OSCILLATOR	ASS7072
X	301	(A,66,108) CRYSTAL RESONATOR	ASS7065
CN	101	(A,230,10) PLUG	CKS1759
CN	102	(A,197,10) PLUG	CKS1764
CN	103	(A,153,10) CONNECTOR	CKS1752
CN	104	(A,323,120) CONNECTOR	CKS1755
CN	201	(A,30,10) PLUG	CKS1761
CN	301	(A,215,57) 26P PLUG	AKM7054
CN	302	(A,316,38) 26P PLUG	AKM7054
CN	303	(A,114,114) PLUG	CKS3542
CN	304	(A,149,114) PLUG	CKS3539
CN	305	(A,303,120) PLUG	CKS1764
CN	306	(A,269,120) PLUG	CKS1764
CN	307	(A,319,103) L-PLUG(3P)	KM200NA3L
CN	308	(A,234,120) PLUG	CKS1750
CN	971	(A,85,10) PLUG	CKS1764
CN	972	(A,56,10) PLUG	CKS1764
JP	101	(A,43,95) JUMPER WIRE 130(1.6)	ADB7035

RESISTORS

R	91		RS1/16S0R0J
R	92		RS1/16S0R0J
R	93		RS1/16S0R0J
R	102	(B,274,48)	RS1/16S472J
R	103	(A,261,54)	RAB4C101J
R	104	(B,264,49)	RS1/16S473J
R	105	(A,261,50)	RAB4C101J
R	106	(B,266,49)	RS1/16S104J
R	107	(B,272,48)	RS1/16S101J
R	109	(A,265,48)	RS1/16S101J
R	110	(B,274,45)	RS1/16S101J
R	111	(B,279,45)	RS1/16S473J
R	112	(B,266,40)	RS1/16S101J
R	113	(B,276,40)	RS1/16S473J
R	114	(B,269,40)	RS1/16S101J
R	115	(B,274,40)	RS1/16S224J
R	116	(A,262,28)	RS1/16S104J
R	117	(A,260,43)	RAB4C101J
R	118	(B,260,42)	RS1/16S104J
R	119	(B,258,42)	RS1/16S473J
R	120	(A,262,35)	RAB4C101J
R	121	(B,255,15)	RS1/16S224J
R	123	(B,274,37)	RS1/16S182J
R	125	(A,265,32)	RS1/16S101J
R	126	(A,263,28)	RS1/16S101J
R	127	(A,267,28)	RAB4C101J
R	128	(B,279,40)	RS1/16S473J
R	129	(A,272,28)	RS1/16S473J
R	131	(A,277,27)	RAB4C101J
R	132	(B,288,38)	RS1/16S473J
R	133	(A,282,27)	RAB4C101J
R	134	(A,287,29)	RS1/16S101J
R	135	(A,289,29)	RS1/16S101J
R	136	(B,286,42)	RS1/16S101J
R	137	(B,293,47)	RS1/16S473J
R	138	(B,290,47)	RS1/16S101J
R	139	(B,287,47)	RS1/16S101J
R	140	(B,285,47)	RS1/16S101J
R	141	(B,293,42)	RS1/16S101J
R	142	(A,277,60)	RAB4C101J
R	143	(B,278,56)	RS1/16S473J
R	144	(A,271,60)	RAB4C101J
R	145	(B,276,56)	RS1/16S473J

Mark	No.	Description	Part No.
R	146	(A,267,60)	RAB4C101J
R	147	(B,273,56)	RS1/16S473J
R	148	(B,281,56)	RS1/16S101J
R	149	(B,284,52)	RS1/16S473J
R	150	(B,271,56)	RS1/16S224J
R	151	(A,250,24)	RS1/16S224J
R	152	(B,283,42)	RS1/16S473J
R	154	(B,297,48)	RS1/16S473J
R	155	(A,243,38)	RAB4C473J
R	156	(A,245,52)	RAB4C473J
R	157	(A,232,38)	RAB4C473J
R	158	(A,233,52)	RAB4C473J
R	159	(A,211,37)	RAB4C473J
R	160	(A,211,42)	RAB4C473J
R	161	(A,227,20)	RS1/16S474J
R	162	(A,243,34)	RAB4C473J
R	163	(A,233,20)	RAB4C473J
R	164	(A,231,34)	RAB4C473J
R	165	(A,252,13)	RS1/16S224J
R	166	(A,256,25)	RS1/16S224J
R	167	(A,253,25)	RS1/16S474J
R	168	(A,253,13)	RS1/16S104J
R	169	(A,256,13)	RS1/16S104J
R	170	(A,255,25)	RS1/16S104J
R	171	(A,220,52)	RS1/16S104J
R	172	(A,272,67)	RS1/16S224J
R	173	(A,267,67)	RS1/16S104J
R	174	(A,293,13)	RS1/16S104J
R	175	(A,295,13)	RS1/16S104J
R	176	(A,297,13)	RS1/16S104J
R	177	(A,300,13)	RS1/16S104J
R	178	(A,263,24)	RS1/16S104J
R	179	(A,265,13)	RS1/16S104J
R	180	(B,273,17)	RS1/16S104J
R	181	(B,276,17)	RS1/16S104J
R	182	(B,278,15)	RS1/16S104J
R	183	(A,275,13)	RS1/16S104J
R	184	(A,263,13)	RS1/16S104J
R	185	(B,260,15)	RS1/16S104J
R	186	(B,287,52)	RS1/16S101J
R	188	(B,281,48)	RS1/16S473J
R	189	(B,269,56)	RS1/16S101J
R	191	(A,273,13)	RS1/16S104J
R	192	(A,261,14)	RS1/16S104J
R	194	(A,212,24)	RS1/16S0R0J
R	195	(A,308,38)	RS1/16S104J
R	196	(A,297,27)	RS1/16S104J
R	197	(A,222,17)	RS1/16S473J
R	198	(A,218,32)	RAB4C473J
R	199	(A,207,31)	RAB4C473J
R	200	(A,220,17)	RS1/16S473J
R	201	(B,29,102)	RS1/16S750J
R	202	(B,24,86)	RS1/16S750J
R	203	(B,24,72)	RS1/16S750J
R	204	(B,25,58)	RS1/16S750J
R	205	(B,29,88)	RS1/16S473J
R	206	(B,27,82)	RS1/16S473J
R	207	(B,29,66)	RS1/16S473J
R	208	(B,28,54)	RS1/16S473J
R	209	(B,31,88)	RS1/16S222J
R	210	(B,31,79)	RS1/16S222J
R	211	(B,31,66)	RS1/16S222J
R	212	(B,31,56)	RS1/16S222J
R	213	(A,35,84)	RS1/16S471J
R	214	(A,35,75)	RS1/16S471J
R	215	(A,35,61)	RS1/16S471J
R	216	(A,36,54)	RS1/16S471J
R	217	(A,35,90)	RS1/16S101J
R	218	(A,36,81)	RS1/16S101J
R	219	(A,36,68)	RS1/16S101J
R	220	(A,36,58)	RS1/16S101J
R	221	(B,46,70)	RS1/16S220J
R	222	(B,44,70)	RS1/16S220J
R	223	(A,39,68)	RS1/16S101J
R	224	(B,44,60)	RS1/16S220J
R	225	(B,44,66)	RS1/16S220J
R	226	(A,37,61)	RS1/16S101J
R	227	(B,44,50)	RS1/16S220J
R	228	(B,44,56)	RS1/16S220J
R	229	(B,35,52)	RS1/16S101J
R	230	(A,37,27)	RS1/16S101J
R	231	(A,46,28)	RS1/16S220J
R	232	(A,46,26)	RS1/16S101J
R	233	(A,37,26)	RS1/16S220J
R	234	(A,44,84)	RS1/16S104J
R	235		RS1/16S0R0J
R	240	(A,64,116)	RS1/16S104J
R	241	(A,64,114)	RS1/16S104J
R	242	(B,315,106)	RS1/16S104J
R	243	(B,181,55)	RS1/16S104J
R	244	(A,182,51)	RS1/16S104J
R	245	(B,187,54)	RS1/16S104J
R	246	(A,180,67)	RS1/16S104J
R	247	(A,180,65)	RS1/16S104J
R	248	(A,180,64)	RS1/16S104J
R	250	(A,197,82)	RS1/16S104J
R	251	(A,194,68)	RS1/16S220J
R	252	(B,194,69)	RS1/16S220J
R	253	(A,194,71)	RS1/16S221J
R	254	(B,191,69)	RS1/16S220J
R	255	(B,188,69)	RS1/16S101J
R	256	(A,189,69)	RS1/16S101J
R	257	(A,184,70)	RS1/16S470J
R	258	(A,183,70)	RS1/16S470J
R	259	(A,181,70)	RS1/16S470J
R	260	(B,182,62)	RS1/16S470J
R	261	(B,182,60)	RS1/16S470J
R	262	(A,181,54)	RS1/16S101J
R	263	(A,184,51)	RS1/16S470J
R	264	(B,188,54)	RS1/16S101J
R	265	(B,194,54)	RS1/16S101J
R	266	(A,187,49)	RAB4C221J
R	268	(A,199,58)	RS1/16S1002F
R	269	(B,194,59)	RS1/16S220J
R	270	(B,202,61)	RS1/16S220J
R	271	(B,196,63)	RS1/16S220J
R	272	(B,194,65)	RS1/16S220J
R	273	(B,197,67)	RS1/16S220J

Mark	No.		Description	Part No.
R	274	(A,202,50)		RS1/16S0R0J
R	275	(B,48,21)		RS1/16S104J
R	276	(B,45,21)		RS1/16S104J
R	277	(B,43,21)		RS1/16S104J
R	278	(B,40,21)		RS1/16S104J
R	279	(B,50,21)		RS1/16S104J
R	280	(A,193,28)		RN1/16SE6801D
R	281	(A,196,27)		RN1/16SE3901D
R	282	(A,196,24)		RN1/16SE2200D
R	283	(A,196,36)	CARBON FILM RESISTOR	RD1/4MUF221J
R	284	(A,175,37)		RS1/16S151J
R	285	(A,182,44)		RS1/16S220J
R	286	(A,176,48)		RS1/16S101J
R	287	(A,176,47)		RS1/16S101J
R	288	(A,180,44)		RS1/16S104J
R	289	(A,173,37)		RS1/16S151J
R	290	(A,176,50)		RS1/16S104J
R	292	(A,54,117)		RS1/16S104J
R	293	(A,49,117)		RS1/16S0R0J
R	295	(A,64,117)		RS1/16S101J
R	297	(B,65,113)		RS1/16S101J
R	298	(B,53,113)		RS1/16S104J
R	300	(A,41,119)		RS1/16S104J
R	303	(B,36,112)		RS1/16S101J
R	304	(B,36,116)		RS1/16S101J
R	305	(B,38,112)		RS1/16S102J
R	306	(B,38,116)		RS1/16S102J
R	307	(A,63,104)		RS1/16S681J
R	308	(A,62,106)		RS1/16S0R0J
R	309	(A,62,109)		RS1/16S105J
R	310	(A,56,117)		RAB4C470J
R	311	(A,52,117)		RS1/16S104J
R	312	(A,51,117)		RS1/16S104J
R	313	(A,47,111)		RAB4C101J
R	314	(B,52,117)		RS1/16S104J
R	315	(B,48,116)		RS1/16S104J
R	317	(B,50,113)		RS1/16S104J
R	319	(A,47,114)		RS1/16S104J
R	320	(A,47,107)		RS1/16S101J
R	321	(A,48,106)		RS1/16S101J
R	322	(A,49,104)		RS1/16S101J
R	323	(B,182,80)		RS1/16S0R0J
R	324	(B,182,85)		RS1/16S470J
R	325	(A,41,114)		RS1/16S101J
R	326	(A,41,116)		RS1/16S101J
R	328	(A,176,77)		RS1/16S104J
R	329	(A,180,90)		RS1/16S104J
R	330	(A,176,90)		RS1/16S104J
R	331	(A,180,92)		RS1/16S470J
R	332	(A,175,90)		RS1/16S101J
R	333	(A,177,77)		RS1/16S470J
R	334	(A,180,89)		RS1/16S101J
R	335	(A,178,90)		RS1/16S101J
R	336	(A,185,78)		RS1/16S101J
R	337	(A,187,78)		RS1/16S101J
R	338	(A,188,78)		RS1/16S470J
R	339	(A,190,78)		RS1/16S470J
R	340	(A,191,78)		RS1/16S101J
R	341	(A,193,78)		RS1/16S101J
R	342	(A,191,90)		RS1/16S470J
R	343	(A,188,91)		RS1/16S470J
R	344	(A,198,80)		RS1/16S101J
R	345	(A,200,80)		RS1/16S470J
R	346	(A,201,80)		RS1/16S101J
R	347	(A,203,80)		RS1/16S151J
R	348	(A,202,93)		RS1/16S470J
R	349	(A,201,93)		RS1/16S470J
R	350	(A,163,101)		RS1/16S0R0J
R	351	(A,162,101)		RS1/16S0R0J
R	352	(A,166,101)		RS1/16S470J
R	353	(A,164,113)		RS1/16S0R0J
R	354	(A,163,113)		RS1/16S0R0J
R	355	(A,166,113)		RS1/16S470J
R	356	(A,171,101)		RS1/16S0R0J
R	357	(A,171,102)		RS1/16S0R0J
R	358	(A,175,101)		RS1/16S470J
R	359	(A,174,114)		RS1/16S0R0J
R	360	(A,172,114)		RS1/16S0R0J
R	361	(A,175,114)		RS1/16S470J
R	362	(A,185,101)		RS1/16S470J
R	363	(A,181,100)		RS1/16S101J
R	364	(A,181,102)		RS1/16S101J
R	365	(A,187,101)		RS1/16S470J
R	366	(A,184,113)		RS1/16S0R0J
R	367	(A,186,113)		RS1/16S470J
R	368	(A,194,101)		RS1/16S0R0J
R	369	(A,193,101)		RS1/16S0R0J
R	370	(A,196,101)		RS1/16S470J
R	371	(A,196,114)		RS1/16S101J
R	372	(A,195,114)		RS1/16S101J
R	373	(A,193,114)		RS1/16S101J
R	374	(A,198,114)		RS1/16S470J
R	375	(A,234,81)		RS1/16S470J
R	376	(A,234,83)		RS1/16S470J
R	377	(A,234,95)		RS1/16S470J
R	378	(A,232,94)		RS1/16S470J
R	379	(A,231,71)		RS1/16S470J
R	380	(B,226,77)		RS1/16S470J
R	381	(A,235,68)		RS1/16S470J
R	382	(A,231,82)		RS1/16S470J
R	383	(A,229,58)		RS1/16S470J
R	384	(A,232,68)		RS1/16S181J
R	385	(A,229,55)		RS1/16S101J
R	386	(A,238,60)		RS1/16S470J
R	387	(A,237,65)		RS1/16S470J
R	388	(A,233,68)		RS1/16S470J
R	389	(A,209,103)		RS1/16S470J
R	390	(A,205,105)		RS1/16S181J
R	391	(A,210,99)		RS1/16S101J
R	392	(A,209,116)		RS1/16S470J
R	393	(A,208,99)		RS1/16S101J
R	394	(A,210,116)		RS1/16S470J
R	395	(B,306,97)		RS1/16S0R0J
R	396	(A,308,96)		RS1/16S101J
R	397	(B,308,97)		RS1/16S0R0J
R	398	(A,311,96)		RS1/16S101J
R	399	(B,310,103)		RS1/16S0R0J
R	400	(A,311,108)		RS1/16S101J
R	401	(B,307,103)		RS1/16S0R0J

Mark	No.		Description	Part No.
R	402	(A,308,108)		RS1/16S101J
R	403	(A,305,80)		RS1/16S221J
R	404	(A,306,80)		RS1/16S101J
R	405	(A,308,80)		RS1/16S101J
R	406	(A,309,80)		RS1/16S470J
R	407	(A,311,80)		RS1/16S101J
R	408	(A,309,92)		RS1/16S0R0J
R	409	(A,312,92)		RS1/16S470J
R	410	(A,306,92)		RS1/16S0R0J
R	411	(A,308,92)		RS1/16S101J
R	412	(B,288,80)		RS1/16S0R0J
R	413	(A,292,80)		RS1/16S470J
R	414	(A,294,80)		RS1/16S221J
R	415	(A,295,80)		RS1/16S101J
R	416	(A,297,80)		RS1/16S470J
R	417	(B,295,88)		RS1/16S0R0J
R	418	(A,295,92)		RS1/16S101J
R	419	(B,293,88)		RS1/16S0R0J
R	420	(A,293,92)		RS1/16S101J
R	421	(A,278,65)		RS1/16S0R0J
R	422	(B,277,70)		RS1/16S0R0J
R	423	(A,280,65)		RS1/16S151J
R	424	(A,281,65)		RS1/16S0R0J
R	425	(B,284,68)		RS1/16S0R0J
R	426	(A,285,69)		RS1/16S151J
R	427	(A,283,78)		RS1/16S0R0J
R	428	(B,283,75)		RS1/16S0R0J
R	429	(A,284,78)		RS1/16S151J
R	430	(A,280,78)		RS1/16S0R0J
R	431	(B,279,70)		RS1/16S0R0J
R	432	(A,281,78)		RS1/16S151J
R	433	(B,292,72)		RS1/16S0R0J
R	434	(B,290,65)		RS1/16S0R0J
R	435	(A,293,62)		RS1/16S151J
R	436	(A,296,63)		RS1/16S101J
R	437	(A,298,64)		RS1/16S151J
R	438	(B,294,72)		RS1/16S0R0J
R	439	(A,298,74)		RS1/16S151J
R	440	(A,292,75)		RS1/16S101J
R	441	(A,294,74)		RS1/16S101J
R	442	(A,296,74)		RS1/16S220J
R	443	(B,291,97)		RS1/16S0R0J
R	444	(B,294,97)		RS1/16S0R0J
R	445	(B,290,102)		RS1/16S0R0J
R	446	(B,292,102)		RS1/16S0R0J
R	447	(A,296,95)		RS1/16S151J
R	448	(A,293,95)		RS1/16S151J
R	449	(A,297,108)		RS1/16S151J
R	450	(A,295,108)		RS1/16S151J
R	451	(A,112,108)		RS1/16S104J
R	452	(A,110,108)		RS1/16S104J
R	453	(A,108,108)		RS1/16S104J
R	454	(A,105,108)	RESISTOR ARRAY	RAB4C104J
R	455	(A,102,108)		RS1/16S104J
R	456	(A,98,108)		RS1/16S104J
R	457	(A,96,108)		RS1/16S104J
R	458	(A,94,108)		RS1/16S104J
R	459	(A,91,108)	RESISTOR ARRAY	RAB4C104J
R	460	(A,87,108)		RS1/16S104J
R	461	(A,83,108)		RS1/16S104J
R	462	(A,141,108)		RS1/16S104J
R	463	(A,138,108)	RESISTOR ARRAY	RAB4C104J
R	464	(A,133,108)	RESISTOR ARRAY	RAB4C104J
R	465	(A,129,108)		RS1/16S104J
R	466	(A,127,108)		RS1/16S104J
R	478	(A,206,103)		RS1/16S101J
R	480	(B,234,108)		RS1/16S0R0J
R	481	(A,236,103)		RS1/16S101J
R	490	(B,241,110)		RS1/16S0R0J
R	497	(A,211,103)		RS1/16S101J
R	501	(A,45,43)		RS1/16S470J
R	502	(B,42,43)		RS1/16S220J
R	503	(B,40,34)		RS1/16S750J
R	506	(B,240,83)		RS1/16S220J
R	507	(B,237,84)		RS1/16S220J
R	508	(B,240,79)		RS1/16S220J
R	509	(B,237,80)		RS1/16S220J
R	510	(A,245,71)		RS1/16S101J
R	511	(A,251,70)		RS1/16S101J
R	512	(A,251,72)		RS1/16S470J
R	513	(B,250,79)		RS1/16S470J
R	514	(B,250,83)		RS1/16S470J
R	515	(A,253,78)		RS1/16S221J
R	516	(A,253,82)		RAB4C221J
R	517	(A,253,85)		RS1/16S101J
R	518	(A,246,87)		RS1/16S1802F
R	519	(A,242,87)		RS1/16S220J
R	520	(A,240,87)		RS1/16S220J
R	524	(A,169,45)		RS1/16S101J
R	525	(A,172,48)		RS1/16S101J
R	535	(A,245,99)		RS1/16S101J
R	536	(A,241,95)		RS1/16S101J
R	537	(A,241,97)		RS1/16S101J
R	538	(A,237,100)		RS1/16S220J
R	539	(A,244,101)		RS1/16S470J
R	540	(A,239,113)		RS1/16S0R0J
R	541	(B,243,106)		RS1/16S470J
R	542	(B,241,106)		RS1/16S0R0J
R	543	(A,243,113)		RS1/16S470J
R	544	(A,248,101)		RS1/16S101J
R	545	(A,246,111)		RS1/16S101J
R	546	(A,249,111)		RS1/16S470J
R	547	(A,251,101)		RS1/16S470J
R	548	(A,275,80)		RS1/16S220J
R	549	(A,272,80)		RS1/16S220J
R	550	(A,274,80)		RS1/16S151J
R	551	(A,277,80)		RS1/16S220J
R	552	(A,278,80)		RS1/16S101J
R	553	(A,278,93)		RS1/16S470J
R	554	(A,274,93)		RS1/16S470J
R	555	(B,267,102)		RS1/16S0R0J
R	556	(A,273,96)		RS1/16S101J
R	557	(B,273,100)		RS1/16S0R0J
R	558	(A,269,107)		RS1/16S470J
R	559	(A,269,96)		RS1/16S220J
R	560	(A,276,96)		RS1/16S220J
R	561	(A,274,108)		RS1/16S220J
R	562	(A,272,108)		RS1/16S220J

Mark	No.	Description	Part No.
R	563	(B,282,96)	RS1/16S0R0J
R	564	(A,283,95)	RS1/16S101J
R	565	(B,284,102)	RS1/16S0R0J
R	566	(B,280,100)	RS1/16S470J
R	567	(A,283,94)	RS1/16S470J
R	568	(A,284,106)	RS1/16S470J
R	569	(A,259,100)	RS1/16S101J
R	570	(A,262,99)	RS1/16S101J
R	571	(B,262,104)	RS1/16S0R0J
R	572	(A,258,110)	RS1/16S0R0J
R	573	(A,259,98)	RS1/16S220J
R	574	(A,264,99)	RS1/16S220J
R	575	(A,265,110)	RS1/16S220J
R	576	(A,262,110)	RS1/16S220J
R	579	(A,250,87)	RS1/16S0R0J
R	580	(B,186,99)	RS1/16S101J
R	581	(B,62,27)	RS1/16S104J
R	582	(B,56,27)	RS1/16S104J
R	583	(B,62,31)	RS1/16S152J
R	584	(B,56,31)	RS1/16S152J
R	585	(B,62,33)	RS1/16S122J
R	586	(B,56,33)	RS1/16S122J
R	590	(B,61,50)	RS1/16S0R0J
R	591	(B,61,63)	RS1/16S101J
R	592	(B,55,64)	RS1/16S101J
R	593	(A,60,65)	RS1/16S470J
R	594	(A,59,65)	RS1/16S101J
R	595	(A,57,65)	RS1/16S101J
R	596	(A,252,76)	RS1/16S470J
R	600	(A,183,98)	RS1/16S470J
R	601	(B,84,28)	RS1/16S6801F
R	602	(B,74,28)	RS1/16S6801F
R	603	(B,82,28)	RS1/16S221J
R	604	(B,76,28)	RS1/16S221J
R	605	(B,82,31)	RS1/16S182J
R	606	(B,76,31)	RS1/16S182J
R	607	(A,82,29)	RS1/16S223J
R	608	(A,76,29)	RS1/16S223J
R	609	(B,81,24)	RS1/16S474J
R	610	(B,77,24)	RS1/16S474J
R	611	(B,86,34)	RS1/16S2701F
R	612	(B,72,34)	RS1/16S2701F
R	613	(A,86,36)	RS1/16S3901F
R	614	(A,72,36)	RS1/16S3901F
R	615	(A,85,39)	RS1/16S8200F
R	616	(A,72,39)	RS1/16S8200F
R	617	(A,86,41)	RS1/16S3901F
R	618	(A,72,41)	RS1/16S3901F
R	619	(A,86,45)	RS1/16S3901F
R	620	(A,72,45)	RS1/16S3901F
R	621	(A,81,66)	RS1/16S220J
R	622	(A,76,66)	RS1/16S220J
R	623	(A,83,66)	RS1/16S220J
R	624	(A,74,66)	RS1/16S220J
R	625	(B,86,58)	RS1/16S682J
R	626	(B,72,58)	RS1/16S682J
R	627	(B,88,58)	RS1/16S682J
R	628	(B,70,58)	RS1/16S682J
R	629	(B,80,65)	RS1/16S1002F
R	630	(B,77,65)	RS1/16S1002F
R	631	(B,84,65)	RS1/16S1002F
R	632	(B,73,65)	RS1/16S1002F
R	651	(B,69,76)	RS1/16S101J
R	652	(B,87,76)	RS1/16S101J
R	653	(A,80,82)	RS1/16S101J
R	654	(A,82,82)	RS1/16S221J
R	655	(A,76,82)	RS1/16S470J
R	656	(B,75,83)	RS1/16S101J
R	657	(A,77,82)	RS1/16S470J
R	658	(B,71,76)	RS1/16S101J
R	659	(B,80,48)	RS1/16S0R0J
R	660		RS1/16S0R0J
R	701	(B,108,28)	RS1/16S6801F
R	702	(B,98,28)	RS1/16S6801F
R	703	(B,106,28)	RS1/16S221J
R	704	(B,100,28)	RS1/16S221J
R	705	(B,106,31)	RS1/16S182J
R	706	(B,100,31)	RS1/16S182J
R	707	(A,106,29)	RS1/16S223J
R	708	(A,100,29)	RS1/16S223J
R	709	(B,105,24)	RS1/16S474J
R	710	(B,101,24)	RS1/16S474J
R	711	(B,110,34)	RS1/16S2701F
R	712	(B,96,34)	RS1/16S2701F
R	713	(A,110,36)	RS1/16S3901F
R	714	(A,96,36)	RS1/16S3901F
R	715	(A,109,39)	RS1/16S8200F
R	716	(A,96,39)	RS1/16S8200F
R	717	(A,110,41)	RS1/16S3901F
R	718	(A,96,41)	RS1/16S3901F
R	719	(A,110,45)	RS1/16S3901F
R	720	(A,96,45)	RS1/16S3901F
R	721	(A,105,66)	RS1/16S220J
R	722	(A,100,66)	RS1/16S220J
R	723	(A,107,66)	RS1/16S220J
R	724	(A,98,66)	RS1/16S220J
R	725	(B,110,58)	RS1/16S682J
R	726	(B,96,58)	RS1/16S682J
R	727	(B,112,58)	RS1/16S682J
R	728	(B,94,58)	RS1/16S682J
R	729	(B,104,65)	RS1/16S1002F
R	730	(B,101,65)	RS1/16S1002F
R	731	(B,108,65)	RS1/16S1002F
R	732	(B,97,65)	RS1/16S1002F
R	751	(B,93,76)	RS1/16S101J
R	752	(B,111,76)	RS1/16S101J
R	753	(A,104,82)	RS1/16S101J
R	754	(A,106,82)	RS1/16S221J
R	755	(A,100,82)	RS1/16S470J
R	756	(B,99,83)	RS1/16S101J
R	757	(A,101,82)	RS1/16S470J
R	758	(B,95,76)	RS1/16S101J
R	759	(B,104,48)	RS1/16S0R0J
R	760		RS1/16S0R0J
R	801	(B,132,28)	RS1/16S6801F
R	802	(B,122,28)	RS1/16S6801F
R	803	(B,130,28)	RS1/16S221J
R	804	(B,124,28)	RS1/16S221J

Mark	No.		Description	Part No.
R	805	(B,130,31)		RS1/16S182J
R	806	(B,124,31)		RS1/16S182J
R	807	(A,130,29)		RS1/16S223J
R	808	(A,124,29)		RS1/16S223J
R	809	(B,129,24)		RS1/16S474J
R	810	(B,125,24)		RS1/16S474J
R	811	(B,134,34)		RS1/16S2701F
R	812	(B,120,34)		RS1/16S2701F
R	813	(A,134,36)		RS1/16S3901F
R	814	(A,120,36)		RS1/16S3901F
R	815	(A,133,39)		RS1/16S8200F
R	816	(A,120,39)		RS1/16S8200F
R	817	(A,134,41)		RS1/16S3901F
R	818	(A,120,41)		RS1/16S3901F
R	819	(A,134,45)		RS1/16S3901F
R	820	(A,120,45)		RS1/16S3901F
R	821	(A,129,66)		RS1/16S220J
R	822	(A,124,66)		RS1/16S220J
R	823	(A,131,66)		RS1/16S220J
R	824	(A,122,66)		RS1/16S220J
R	825	(B,134,58)		RS1/16S682J
R	826	(B,120,58)		RS1/16S682J
R	827	(B,136,58)		RS1/16S682J
R	828	(B,118,58)		RS1/16S682J
R	829	(B,128,65)		RS1/16S1002F
R	830	(B,125,65)		RS1/16S1002F
R	831	(B,132,65)		RS1/16S1002F
R	832	(B,121,65)		RS1/16S1002F
R	851	(B,117,76)		RS1/16S101J
R	852	(B,135,76)		RS1/16S101J
R	853	(A,128,82)		RS1/16S101J
R	854	(A,130,82)		RS1/16S221J
R	855	(A,124,82)		RS1/16S470J
R	856	(B,123,83)		RS1/16S101J
R	857	(A,125,82)		RS1/16S470J
R	858	(B,119,76)		RS1/16S101J
R	859	(B,128,48)		RS1/16S0R0J
R	860			RS1/16S0R0J
R	901	(B,156,28)		RS1/16S6801F
R	902	(B,146,28)		RS1/16S6801F
R	903	(B,154,28)		RS1/16S221J
R	904	(B,148,28)		RS1/16S221J
R	905	(B,154,31)		RS1/16S182J
R	906	(B,148,31)		RS1/16S182J
R	907	(A,154,29)		RS1/16S223J
R	908	(A,148,29)		RS1/16S223J
R	909	(B,153,24)		RS1/16S474J
R	910	(B,149,24)		RS1/16S474J
R	911	(B,158,34)		RS1/16S2701F
R	912	(B,144,34)		RS1/16S2701F
R	913	(A,158,36)		RS1/16S3901F
R	914	(A,144,36)		RS1/16S3901F
R	915	(A,157,39)		RS1/16S8200F
R	916	(A,144,39)		RS1/16S8200F
R	917	(A,158,41)		RS1/16S3901F
R	918	(A,144,41)		RS1/16S3901F
R	919	(A,158,45)		RS1/16S3901F
R	920	(A,144,45)		RS1/16S3901F
R	921	(A,153,66)		RS1/16S220J
R	922	(A,148,66)		RS1/16S220J
R	923	(A,155,66)		RS1/16S220J
R	924	(A,146,66)		RS1/16S220J
R	925	(B,158,58)		RS1/16S682J
R	926	(B,144,58)		RS1/16S682J
R	927	(B,160,58)		RS1/16S682J
R	928	(B,142,58)		RS1/16S682J
R	929	(B,152,65)		RS1/16S1002F
R	930	(B,149,65)		RS1/16S1002F
R	931	(B,156,65)		RS1/16S1002F
R	932	(B,145,65)		RS1/16S1002F
R	951	(B,141,76)		RS1/16S101J
R	952	(B,159,76)		RS1/16S101J
R	953	(A,152,82)		RS1/16S101J
R	954	(A,154,82)		RS1/16S221J
R	955	(A,148,82)		RS1/16S470J
R	956	(B,147,83)		RS1/16S101J
R	957	(A,149,82)		RS1/16S470J
R	958	(B,143,76)		RS1/16S101J
R	959	(B,152,48)		RS1/16S0R0J
R	960			RS1/16S0R0J
R	961	(B,102,108)		RS1/16S0R0J
R	962	(B,105,108)		RS1/16S0R0J
R	963	(B,107,108)		RS1/16S0R0J
R	964	(B,118,109)		RS1/16S0R0J
R	965	(B,121,109)		RS1/16S0R0J
R	966	(A,126,108)		RS1/16S0R0J
R	967	(A,121,108)		RS1/16S0R0J
R	968	(A,119,108)		RS1/16S0R0J
R	969	(A,118,108)		RS1/16S0R0J
R	970	(A,116,108)		RS1/16S0R0J
R	971	(A,143,15)		RS1/16S104J

CAPACITORS

C	101	(B,39,100)		CKSRYB104K16
C	102	(A,265,54)		CKSRYB104K16
C	103	(A,266,54)		CKSRYB102K50
C	105	(A,265,40)		CKSRYB104K16
C	106	(A,265,41)		CKSRYB102K50
C	107	(A,265,35)		CKSRYB104K16
C	108	(A,266,35)		CKSRYB102K50
C	109	(A,290,45)		CKSRYB104K16
C	110	(A,289,45)		CKSRYB102K50
C	112	(A,298,60)		CKSRYB102K50
C	113	(A,300,60)		CKSRYB104K16
C	114	(A,241,46)		CKSRYB104K16
C	115	(A,229,46)		CKSRYB104K16
C	116	(A,201,40)		CKSRYB104K16
C	117	(A,239,28)		CKSRYB104K16
C	118	(A,229,27)		CKSRYB104K16
C	119	(A,41,102)	ELECT. CAPACITOR	ACH7273
C	120	(A,178,15)		CKSRYB104K16
C	121	(A,178,18)		CKSQYB225K10
C	122	(A,173,17)	ELECT. CAPACITOR	ACH7210
C	123	(A,173,29)	ELECT. CAPACITOR	ACH7210
C	124	(A,186,21)		CKSRYB104K16
C	125	(A,184,27)		CKSQYB225K10
C	128	(A,260,59)		CEHAZL330M16
C	129	(A,250,19)		CKSRYB104K16

Mark	No.	Description	Part No.
C	130	(A,267,68)	CKSRYB104K16
C	131	(A,216,46)	CKSRYB104K16
C	132	(A,292,20)	CKSRYB104K16
C	133	(A,282,20)	CKSRYB104K16
C	134	(A,271,19)	CKSRYB104K16
C	135	(A,302,33)	CKSRYB104K16
C	136	(A,261,20)	CKSRYB104K16
C	137	(A,311,20)	CKSRYB104K16
C	139	(A,188,19)	CKSRYB104K16
C	140	(A,188,27)	CKSRYB104K16
C	141	(A,303,20)	CKSRYB104K16
C	142	(A,215,23)	CKSRYB104K16
C	143	(A,32,96) ELECT. CAPACITOR	ACH7211
C	144	(B,32,93)	CKSRYB104K16
C	201	(B,23,102)	CKSRYB103K50
C	202	(B,26,86)	CKSRYB103K50
C	203	(B,26,72)	CKSRYB103K50
C	204	(B,27,58)	CKSRYB103K50
C	205	(B,33,88)	CCSRCH470J50
C	206	(B,33,79)	CCSRCH470J50
C	207	(B,33,66)	CCSRCH470J50
C	208	(B,33,56)	CCSRCH470J50
C	209	(B,35,88)	CCSRCH220J50
C	210	(B,35,79)	CCSRCH220J50
C	211	(B,35,66)	CCSRCH220J50
C	212	(B,35,56)	CCSRCH220J50
C	213	(A,30,87)	CKSRYB104K16
C	214	(A,30,78)	CKSRYB104K16
C	215	(A,30,64)	CKSRYB104K16
C	216	(A,30,56)	CKSRYB104K16
C	217	(A,35,87)	CKSRYB103K50
C	218	(A,36,78)	CKSRYB103K50
C	219	(A,36,65)	CKSRYB103K50
C	220	(A,37,57)	CKSRYB103K50
C	221	(A,29,73) ELECT. CAPACITOR	CEHAZL101M10
C	222	(A,30,50) ELECT. CAPACITOR	CEHAZL101M10
C	223	(A,30,30) ELECT. CAPACITOR	CEHAZL101M10
C	224	(B,25,27)	CKSRYB104K16
C	225	(B,25,14)	CKSRYB104K16
C	227	(A,43,76)	CKSRYB103K50
C	228	(A,46,83)	CKSQYB105K16
C	230	(A,43,66)	CKSRYB103K50
C	231	(B,43,82)	CKSRYB224K16
C	233	(A,43,56)	CKSRYB103K50
C	234	(A,33,26)	CKSRYB104K16
C	235	(A,31,18)	CKSRYB104K16
C	236	(A,29,26)	CKSQYB225K10
C	237	(A,40,82) ELECT. CAPACITOR	CEHAZL101M10
C	239	(A,41,29)	CKSRYB103K50
C	252	(A,174,63) OS CAPACITOR	ACH7204
C	253	(A,191,70)	CKSRYB471K50
C	254	(A,191,71)	CKSRYB104K16
C	255	(A,186,71)	CKSRYB104K16
C	256	(A,186,69)	CKSRYB471K50
C	257	(A,171,53) OS CAPACITOR	ACH7203
C	258	(A,180,61)	CKSRYB104K16
C	259	(A,181,61)	CKSRYB471K50
C	260	(A,181,57)	CKSRYB471K50
C	261	(A,180,57)	CKSRYB104K16
C	262	(A,190,51)	CKSRYB471K50
C	263	(A,190,50)	CKSRYB104K16
C	266	(A,198,54) ELECT. CAPACITOR	ACH7266
C	267	(B,196,59)	CKSRYB103K50
C	268	(A,198,46) OS CAPACITOR	ACH7204
C	269	(A,198,58)	CKSRYB104K16
C	270	(A,197,58)	CKSRYB471K50
C	271	(A,198,62)	CKSRYB104K16
C	272	(A,197,62)	CKSRYB471K50
C	273	(A,197,65)	CKSRYB471K50
C	274	(A,199,65)	CKSRYB104K16
C	275	(B,35,21)	CKSRYB104K16
C	276	(B,29,22)	CKSRYB104K16
C	277	(A,186,34) OS CAPACITOR	ACH7204
C	278	(A,180,33)	CKSRYB104K16
C	279	(A,193,26)	CKSRYB105K10
C	280	(A,173,71)	CEHAZL101M25
C	281	(B,169,70)	CKSRYB224K16
C	282	(B,166,70)	CKSQYB225K10
C	283	(B,32,21)	CKSRYB104K16
C	284	(A,171,39)	CKSRYB471K50
C	285	(A,171,38)	CKSRYB104K16
C	301	(A,29,110)	CEAT101M16
C	302	(A,33,115)	CKSRYB224K16
C	303	(A,26,110)	CKSRYB102K50
C	304	(B,34,112)	CKSRYB104K16
C	305	(B,34,116)	CKSRYB104K16
C	306	(B,40,115)	CKSRYB104K16
C	307	(A,63,106)	CCSRCH120J50
C	308	(A,63,110)	CCSRCH120J50
C	310	(A,55,99) ELECT. CAPACITOR	CEHAZL101M10
C	311	(B,56,116)	CKSRYB104K16
C	312	(B,56,114)	CKSRYB471K50
C	313	(A,36,119)	CKSQYB105K16
C	314	(A,78,114)	CKSRYB104K16
C	315	(A,75,115)	CKSQYB225K10
C	316	(A,76,112)	CKSRYB104K16
C	317	(A,234,115)	CKSRYB102K50
C	318	(B,315,74)	CKSRYB103K50
C	331	(A,155,108) ELECT. CAPACITOR	ACH7267
C	332	(A,172,82)	CKSRYB104K16
C	333	(A,174,82)	CKSRYB471K50
C	334	(A,184,83)	CKSRYB104K16
C	335	(A,185,83)	CKSRYB471K50
C	336	(A,197,86)	CKSRYB471K50
C	337	(A,195,86)	CKSRYB104K16
C	338	(A,159,107)	CKSRYB104K16
C	339	(A,160,107)	CKSRYB471K50
C	340	(A,168,108)	CKSRYB104K16
C	341	(A,169,108)	CKSRYB471K50
C	342	(A,179,108)	CKSRYB104K16
C	343	(A,180,108)	CKSRYB471K50
C	344	(A,190,107)	CKSRYB104K16
C	345	(A,191,107)	CKSRYB471K50
C	346	(A,228,89)	CKSRYB104K16
C	347	(A,229,89)	CKSRYB471K50
C	348	(A,227,76)	CKSRYB104K16
C	349	(A,229,76)	CKSRYB471K50
C	350	(A,228,62)	CKSRYB104K16
C	351	(A,229,62)	CKSRYB471K50

Mark	No.	Description	Part No.
C	352	(A,204,109)	CKSRYB104K16
C	353	(A,205,109)	CKSRYB471K50
C	355	(A,303,101)	CKSRYB104K16
C	356	(A,304,101)	CKSRYB471K50
C	357	(A,303,86)	CKSRYB104K16
C	358	(A,304,86)	CKSRYB471K50
C	359	(A,288,86)	CKSRYB104K16
C	360	(A,290,86)	CKSRYB471K50
C	361	(A,275,71)	CKSRYB104K16
C	362	(A,277,71)	CKSRYB471K50
C	363	(A,289,68)	CKSRYB104K16
C	364	(A,290,68)	CKSRYB471K50
C	365	(A,290,101)	CKSRYB104K16
C	366	(A,291,101)	CKSRYB471K50
C	367	(A,85,108)	CKSRYB104K16
C	368	(A,100,108)	CKSRYB472K50
C	369	(A,114,108)	CKSRYB471K50
C	370	(A,130,108)	CKSRYB104K16
C	371	(A,143,108)	CKSRYB472K50
C	372	(A,146,108)	CKSRYB471K50
C	373	(A,308,67)	CKSRYB224K16
C	374	(A,308,70)	CKSRYB471K50
C	501	(A,33,45) ELECT. CAPACITOR	CEHAZL101M10
C	502	(A,42,45)	CKSRYB102K50
C	503	(A,42,46)	CKSRYB104K16
C	504	(B,44,43)	CKSRYB104K16
C	507	(B,19,43)	CKSRYB104K16
C	508	(B,17,43)	CKSRYB471K50
C	511	(A,241,65)	CEHAZL330M16
C	512	(A,241,71)	CKSRYB104K16
C	513	(A,241,73)	CKSRYB102K50
C	514	(A,250,65)	CEHAZL330M16
C	515	(A,247,71)	CKSRYB104K16
C	516	(A,247,72)	CKSRYB471K50
C	518	(A,244,87)	CKSRYB474K10
C	519	(A,246,92)	CEHAZL330M16
C	520	(A,248,87)	CKSRYB104K16
C	521	(A,247,87)	CKSRYB471K50
C	522	(A,264,86) ELECT. CAPACITOR	ACH7267
C	527	(A,220,110)	CEHAZL330M16
C	530	(A,235,108)	CKSRYB104K16
C	531	(A,237,108)	CKSRYB471K50
C	532	(A,245,106)	CKSRYB104K16
C	533	(A,247,106)	CKSRYB471K50
C	534	(A,270,86)	CKSRYB104K16
C	535	(A,272,86)	CKSRYB471K50
C	536	(A,267,101)	CKSRYB104K16
C	537	(A,268,101)	CKSRYB471K50
C	538	(A,278,100)	CKSRYB104K16
C	539	(A,279,100)	CKSRYB471K50
C	540	(A,256,105)	CKSRYB104K16
C	541	(A,258,105)	CKSRYB471K50
C	542	(A,179,97)	CKSRYB104K16
C	543	(A,181,97)	CKSRYB471K50
C	581	(A,62,24)	CEAT100M50
C	582	(A,56,24)	CEAT100M50
C	583	(A,59,26)	CKSRYB473K25
C	584	(A,59,34)	CKSRYB473K25
C	585	(A,62,39)	CEAT100M50
C	586	(A,56,39)	CEAT100M50
C	591	(A,56,44)	CEAT101M16
C	592	(A,59,51)	CKSRYB104K16
C	593	(B,58,50)	CKSQYB225K10
C	594	(A,62,44)	CEAT101M16
C	595	(A,63,53)	CKSRYB471K50
C	596	(A,63,52)	CKSRYB104K16
C	601	(A,87,31) ELECT. CAPACITOR	ACH7198
C	602	(A,71,31) ELECT. CAPACITOR	ACH7198
C	603	(A,84,36)	CCSRCH101J50
C	604	(A,73,36)	CCSRCH101J50
C	605	(A,81,40)	CKSRYB103K50
C	606	(A,79,49)	CKSRYB103K50
C	607	(A,77,32)	CKSRYB103K50
C	608	(A,77,40)	CKSRYB103K50
C	611	(A,82,54) ELECT. CAPACITOR	ACH7196
C	612	(A,76,54) ELECT. CAPACITOR	ACH7196
C	613	(A,88,54) ELECT. CAPACITOR	ACH7196
C	614	(A,70,54) ELECT. CAPACITOR	ACH7196
C	615	(A,86,72)	CKSRYB103K50
C	616	(A,71,72)	CKSRYB103K50
C	617	(A,82,58) ELECT. CAPACITOR	CEHAZL101M10
C	618	(A,76,58) ELECT. CAPACITOR	CEHAZL101M10
C	619	(B,82,65)	CKSRYB104K16
C	620	(B,75,65)	CKSRYB104K16
C	621	(A,70,65) ELECT. CAPACITOR	CEHAZL221M10
C	622	(A,87,65) ELECT. CAPACITOR	CEHAZL221M10
C	623	(A,81,69)	CKSRYB104K16
C	624	(A,77,69)	CKSRYB104K16
C	625	(A,87,24) ELECT. CAPACITOR	ACH7211
C	626	(A,71,22) ELECT. CAPACITOR	ACH7211
C	627	(A,81,20)	CKSRYB103K50
C	628	(A,77,20)	CKSRYB103K50
C	651	(A,86,81) ELECT. CAPACITOR	ACH7272
C	652	(A,87,75)	CKSRYB104K16
C	653	(A,85,75)	CKSRYB471K50
C	654	(A,84,71)	CKSRYB224K16
C	655	(A,72,81) ELECT. CAPACITOR	ACH7196
C	656	(A,73,75)	CKSRYB104K16
C	657	(B,89,76)	CKSRYB102K50
C	701	(A,111,31) ELECT. CAPACITOR	ACH7198
C	702	(A,95,31) ELECT. CAPACITOR	ACH7198
C	703	(A,108,36)	CCSRCH101J50
C	704	(A,97,36)	CCSRCH101J50
C	705	(A,105,40)	CKSRYB103K50
C	706	(A,103,49)	CKSRYB103K50
C	707	(A,101,32)	CKSRYB103K50
C	708	(A,101,40)	CKSRYB103K50
C	711	(A,106,54) ELECT. CAPACITOR	ACH7196
C	712	(A,100,54) ELECT. CAPACITOR	ACH7196
C	713	(A,112,54) ELECT. CAPACITOR	ACH7196
C	714	(A,94,54) ELECT. CAPACITOR	ACH7196
C	715	(A,110,72)	CKSRYB103K50
C	716	(A,95,72)	CKSRYB103K50
C	717	(A,106,58) ELECT. CAPACITOR	CEHAZL101M10
C	718	(A,100,58) ELECT. CAPACITOR	CEHAZL101M10
C	719	(B,106,65)	CKSRYB104K16
C	720	(B,99,65)	CKSRYB104K16
C	721	(A,94,65) ELECT. CAPACITOR	CEHAZL221M10

Mark	No.	Description	Part No.
C	722	(A,111,65) ELECT. CAPACITOR	CEHAZL221M10
C	723	(A,105,69)	CKSRYB104K16
C	724	(A,101,69)	CKSRYB104K16
C	725	(A,111,24) ELECT. CAPACITOR	ACH7211
C	726	(A,95,22) ELECT. CAPACITOR	ACH7211
C	727	(A,105,20)	CKSRYB103K50
C	728	(A,101,20)	CKSRYB103K50
C	751	(A,110,81) ELECT. CAPACITOR	ACH7272
C	752	(A,111,75)	CKSRYB104K16
C	753	(A,109,75)	CKSRYB471K50
C	754	(A,108,71)	CKSRYB224K16
C	755	(A,96,81) ELECT. CAPACITOR	ACH7196
C	756	(A,97,75)	CKSRYB104K16
C	757	(B,113,76)	CKSRYB102K50
C	801	(A,135,31) ELECT. CAPACITOR	ACH7198
C	802	(A,119,31) ELECT. CAPACITOR	ACH7198
C	803	(A,132,36)	CCSRCH101J50
C	804	(A,121,36)	CCSRCH101J50
C	805	(A,129,40)	CKSRYB103K50
C	806	(A,127,49)	CKSRYB103K50
C	807	(A,125,32)	CKSRYB103K50
C	808	(A,125,40)	CKSRYB103K50
C	811	(A,130,54) ELECT. CAPACITOR	ACH7196
C	812	(A,124,54) ELECT. CAPACITOR	ACH7196
C	813	(A,136,54) ELECT. CAPACITOR	ACH7196
C	814	(A,118,54) ELECT. CAPACITOR	ACH7196
C	815	(A,134,72)	CKSRYB103K50
C	816	(A,119,72)	CKSRYB103K50
C	817	(A,130,58) ELECT. CAPACITOR	CEHAZL101M10
C	818	(A,124,58) ELECT. CAPACITOR	CEHAZL101M10
C	819	(B,130,65)	CKSRYB104K16
C	820	(B,123,65)	CKSRYB104K16
C	821	(A,118,65) ELECT. CAPACITOR	CEHAZL221M10
C	822	(A,135,65) ELECT. CAPACITOR	CEHAZL221M10
C	823	(A,129,69)	CKSRYB104K16
C	824	(A,125,69)	CKSRYB104K16
C	825	(A,135,24) ELECT. CAPACITOR	ACH7211
C	826	(A,119,22) ELECT. CAPACITOR	ACH7211
C	827	(A,129,20)	CKSRYB103K50
C	828	(A,125,20)	CKSRYB103K50
C	851	(A,134,81) ELECT. CAPACITOR	ACH7272
C	852	(A,135,75)	CKSRYB104K16
C	853	(A,133,75)	CKSRYB471K50
C	854	(A,132,71)	CKSRYB224K16
C	855	(A,120,81) ELECT. CAPACITOR	ACH7196
C	856	(A,121,75)	CKSRYB104K16
C	857	(B,137,76)	CKSRYB102K50
C	901	(A,159,31) ELECT. CAPACITOR	ACH7198
C	902	(A,143,31) ELECT. CAPACITOR	ACH7198
C	903	(A,156,36)	CCSRCH101J50
C	904	(A,145,36)	CCSRCH101J50
C	905	(A,153,40)	CKSRYB103K50
C	906	(A,151,49)	CKSRYB103K50
C	907	(A,149,32)	CKSRYB103K50
C	908	(A,149,40)	CKSRYB103K50
C	911	(A,154,54) ELECT. CAPACITOR	ACH7196
C	912	(A,148,54) ELECT. CAPACITOR	ACH7196
C	913	(A,160,54) ELECT. CAPACITOR	ACH7196
C	914	(A,142,54) ELECT. CAPACITOR	ACH7196
C	915	(A,158,72)	CKSRYB103K50
C	916	(A,143,72)	CKSRYB103K50
C	917	(A,154,58) ELECT. CAPACITOR	CEHAZL101M10
C	918	(A,148,58) ELECT. CAPACITOR	CEHAZL101M10
C	919	(B,154,65)	CKSRYB104K16
C	920	(B,147,65)	CKSRYB104K16
C	921	(A,142,65) ELECT. CAPACITOR	CEHAZL221M10
C	922	(A,159,65) ELECT. CAPACITOR	CEHAZL221M10
C	923	(A,153,69)	CKSRYB104K16
C	924	(A,149,69)	CKSRYB104K16
C	925	(A,159,24) ELECT. CAPACITOR	ACH7211
C	926	(A,143,22) ELECT. CAPACITOR	ACH7211
C	927	(A,153,20)	CKSRYB103K50
C	928	(A,149,20)	CKSRYB103K50
C	951	(A,158,81) ELECT. CAPACITOR	ACH7272
C	952	(A,159,75)	CKSRYB104K16
C	953	(A,157,75)	CKSRYB471K50
C	954	(A,156,71)	CKSRYB224K16
C	955	(A,144,81) ELECT. CAPACITOR	ACH7196
C	956	(A,145,75)	CKSRYB104K16
C	957	(B,161,76)	CKSRYB102K50
C	970	(A,58,75) ELECT. CAPACITOR	ACH7273
C	972	(A,57,83)	CKSRYB104K16
C	973	(A,64,79) ELECT. CAPACITOR	CEHAZL100M50
C	975	(A,157,91)	CKSRYB471K50
C	976	(B,111,14)	CKSRYB473K25
C	977	(A,155,91)	CKSRYB104K16
C	978	(A,106,16)	CKSRYB473K25
C	979	(B,80,92)	CKSRYB471K50
C	980	(B,82,92)	CKSRYB104K16
C	981	(B,66,72)	CKSRYB104K16
C	983	(A,69,91)	CKSRYB471K50
C	984	(A,68,91)	CKSRYB104K16
C	985	(A,115,92)	CKSRYB471K50
C	986	(A,114,92)	CKSRYB104K16

P SUB DIGITAL ASSY

MISCELLANEOUS

IC	1801	(A,91,166) LOGIC IC	TC74ACT151F
IC	1802	(A,73,166) LOGIC IC	TC74ACT151F
IC	1803	(A,55,166) LOGIC IC	TC74ACT151F
IC	1805	(A,116,146) LOGIC IC	TC4094BFN
IC	1806	(A,131,146) LOGIC IC	TC4094BFN
IC	1901	(A,120,180) RF DEMODULATOR IC	PM4007B
IC	1902	(A,93,196) OP-AMP IC	BA4560RF
IC	1903	(A,46,211) VIDEO AMP IC	TK15420M
IC	1904	(A,74,145) IC	TC74VHCT08AFTS1
IC	1905	(A,146,174) SRAM(256K)	CY62256NLL-55ZXI
IC	1906	(A,85,145) IC	TC74VHCT08AFTS1
Q	1902	(B,42,220) TRANSISTOR	2SC4154
Q	1903	(A,49,225) TRANSISTOR	2SC4154
Q	1904	(B,66,198) TRANSISTOR(SC-70)	2SA1602A
Q	1905	(B,58,205) TRANSISTOR(SC-70)	2SA1602A
Q	1906	(A,34,224) TRANSISTOR	2SC4154
Q	1907	(A,32,216) TRANSISTOR	2SC4154
Q	1908	(B,60,182) TRANSISTOR	RT1N141M-11
Q	1909	(A,38,184) TRANSISTOR	2SD1781K
Q	1910	(A,47,185) TRANSISTOR	2SB1132

Mark	No.	Description	Part No.
Q	1911 (B,64,182)	DIGITAL TR(SC-70)	RT1P441M
D	1902 (A,138,206)	VARI-CAP DIODE	KV1862K-G
L	1801 (B,27,211)	CHIP SOLID INDUCTOR	QTL1013
L	1802 (B,27,198)	CHIP SOLID INDUCTOR	QTL1013
L	1803 (B,27,184)	CHIP SOLID INDUCTOR	QTL1013
L	1804 (B,27,169)	CHIP SOLID INDUCTOR	QTL1013
L	1805 (B,27,159)	CHIP SOLID INDUCTOR	QTL1013
L	1806 (B,23,149)	CHIP SOLID INDUCTOR	QTL1013
L	1808 (A,82,171)	CHIP SOLID INDUCTOR	QTL1013
L	1809 (A,64,171)	CHIP SOLID INDUCTOR	QTL1013
L	1810 (A,46,171)	CHIP SOLID INDUCTOR	QTL1013
L	1904 (B,51,190)	CHIP SOLID INDUCTOR	QTL1013
L	1905 (B,37,193)	CHIP SOLID INDUCTOR	QTL1013
L	1906 (B,110,167)	CHIP SOLID INDUCTOR	QTL1013
L	1907 (B,145,163)	CHIP SOLID INDUCTOR	QTL1013
L	1908 (A,48,221)	CHIP COIL	LCTAW680J2520
L	1909 (A,70,151)	CHIP SOLID INDUCTOR	QTL1013
F	1901 (A,71,199)	BAND PASS FILTER	ATF7027
JA	1801 (A,21,206)	OPT. LINK IN	AKS7005
JA	1802 (A,21,193)	OPT. LINK IN	AKS7005
JA	1803 (A,21,179)	OPT. LINK IN	AKS7005
JA	1804 (A,21,165)	OPT. LINK IN	AKS7005
JA	1805 (A,21,151)	OPT. LINK IN	AKS7005
JA	1806 (A,21,138)	OPT. LINK IN	AKS7005
JA	1901 (A,12,225)	JACK	VKB1160
X	1901 (A,126,199)	CRYSTAL FOR VCXO	ASS7009
CN	1801 (A,156,139)	9P SOCKET	XKP3075
CN	1802 (A,55,139)	21P SOCKET	XKP3081
	1901 (A,156,222)	PCB BINDER	VEF1040

RESISTORS

R	1801 (B,23,205)		RS1/16S101J
R	1802 (B,23,191)		RS1/16S101J
R	1803 (B,23,177)		RS1/16S101J
R	1804 (B,23,163)		RS1/16S101J
R	1805 (B,24,152)		RS1/16S101J
R	1806 (B,25,141)		RS1/16S101J
R	1809 (A,93,160)		RS1/16S101J
R	1810 (A,75,160)		RS1/16S101J
R	1811 (A,57,160)		RS1/16S101J
R	1812 (A,121,152)		RS1/16S0R0J
R	1813 (A,120,152)		RS1/16S0R0J
R	1814 (A,118,152)		RS1/16S0R0J
R	1815 (A,121,141)		RS1/16S0R0J
R	1816 (A,117,152)		RS1/16S473J
R	1817 (A,115,152)		RS1/16S473J
R	1818 (A,108,149)		RS1/16S473J
R	1819 (A,110,149)		RS1/16S473J
R	1820 (A,108,144)		RS1/16S473J
R	1821 (A,107,144)		RS1/16S473J
R	1822 (A,117,140)		RS1/16S473J
R	1823 (A,118,140)		RS1/16S473J
R	1826 (A,136,141)		RS1/16S0R0J
R	1829 (A,65,146)		RS1/16S104J
R	1830 (B,71,144)		RS1/16S104J
R	1831 (A,89,160)		RS1/16S220J
R	1832 (A,87,160)		RS1/16S220J
R	1833 (A,86,160)		RS1/16S220J
R	1834 (A,87,173)		RS1/16S220J
R	1835 (A,89,173)		RS1/16S220J
R	1836 (A,91,173)		RS1/16S220J
R	1837 (A,92,173)		RS1/16S220J
R	1838 (A,71,160)		RS1/16S220J

Q DSP ASSY

SEMICONDUCTORS

IC	101,301	ADSP-21366KBCZ-1AA
IC	161,162,361,362	TC74VHC573FTS1
IC	163,363	TC7W139FU
IC	164	AYW7220
IC	165,365,411	TC7SH32FUS1
IC	171,371,372	CY7C1049D3310VXI
IC	201	DSPC56371AF180
IC	364	AYW7221
IC	401	TC74VHC08FTS1
IC	511,521	PQ1LAX95MSPQ
IC	531,541	BD9107FVM
IC	601,621,651	TC74VHC74FTS1
IC	602,622	TC7SH86FUS1
IC	603,623	TC74VHC00FTS1
IC	652	TC74VHC157FTS1
IC	701	TC7WH04FU
Q	201	RT1N241M

MISCELLANEOUS

L	101,102	CHIP SOLID INDUCTOR	QTL1013
L	161-164	CHIP SOLID INDUCTOR	QTL1013
L	171	CHIP SOLID INDUCTOR	QTL1013
L	201-203	CHIP SOLID INDUCTOR	QTL1013
L	301,302	CHIP SOLID INDUCTOR	QTL1013
L	361-364	CHIP SOLID INDUCTOR	QTL1013
L	371,372	CHIP SOLID INDUCTOR	QTL1013
L	401,402	CHIP SOLID INDUCTOR	QTL1013
L	530,540	CHIP BEADS	ATL7010
L	531,541	POWER INDUCTOR	ATH7047
L	601,701	CHIP SOLID INDUCTOR	QTL1013
L	702	CHIP SOLID INDUCTOR	QTL1013
X	701	CRYSTAL OSCILLATOR	ASS7074
CN	401,402	26P SOCKET	AKP7198

RESISTORS

R	101-104,161-163		RAB4CQ470J
R	114,204,236,314		RAB4CQ101J
R	123,221,323		RAB4CQ220J
R	131,149,331,346		RAB4CQ472J
R	152,350		RS1/16S0R0J
R	219		RAB4CQ103J
R	301-304,361-363		RAB4CQ470J
R	511		RS1/16SS2002F
R	512,522		RS1/16SS1202F
R	521		RS1/16SS1000F
R	531,541		RS1/16SS9101F
R	532,542		RS1/16SS1802F
R	533,543		RS1/16SS1002F
R	537,547		RS1/10S0R0J
Other Resistors			RS1/16SS###J

CAPACITORS

Mark	No.	Description	Part No.
C	101,103,105,107		CKSSYB471K50
C	102,104,106,108		CKSSYB104K10
C	109,111,113,115		CKSSYB471K50
C	110,112,114,116		CKSSYB104K10
C	117,127,201,203		CKSSYB471K50
C	118,128,132,134		CKSSYB104K10
C	131,133,135,137		CKSSYB102K50
C	136,138,140,142		CKSSYB104K10
C	139,141,168,171		CKSSYB102K50
C	145,228,345		CKSSYB103K25
C	151,183,231,232		CEVW101M16
C	152,352,501,711		ACH7275
C	161,163,165,167		CKSSYB104K10
C	169,172,174,202		CKSSYB104K10
C	173,331,333,335		CKSSYB102K50
C	204,206,208,210		CKSSYB104K10
C	205,207,209,211		CKSSYB471K50
C	212,214,216,218		CKSSYB104K10
C	213,215,217,219		CKSSYB471K50
C	220,222,224,302		CKSSYB104K10
C	221,223,301,303		CKSSYB471K50
C	304,306,308,310		CKSSYB104K10
C	305,307,309,311		CKSSYB471K50
C	312,314,316,318		CKSSYB104K10
C	313,315,317,327		CKSSYB471K50
C	328,332,334,336		CKSSYB104K10
C	337,339,341,368		CKSSYB102K50
C	338,340,342,361		CKSSYB104K10
C	351,383,531,541		CEVW101M16
C	363,365,367,369		CKSSYB104K10
C	371,373,375,377		CKSSYB102K50
C	372,374,376,378		CKSSYB104K10
C	401,411,701,703		CKSSYB471K50
C	402,412,602,604		CKSSYB104K10
C	502		ACH7276
C	503		CKSQYB104K16
C	504		CKSRYB102K50
C	511		CKSQYB105K16
C	512,521,522		CKSRYB105K10
C	532,534,542,544		DCH1201
C	533,543,601,603		CKSSYB102K50
C	600		CEVW101M16
C	605,607,621,623		CKSSYB102K50
C	606,622,624,626		CKSSYB104K10
C	625,627,651,654		CKSSYB102K50
C	652,653,702,704		CKSSYB104K10
R	1839 (A,69,160)		RS1/16S220J
R	1840 (A,68,160)		RS1/16S220J
R	1841 (A,69,173)		RS1/16S220J
R	1842 (A,71,173)		RS1/16S220J
R	1843 (A,73,173)		RS1/16S220J
R	1844 (A,74,173)		RS1/16S220J
R	1845 (A,53,160)		RS1/16S220J
R	1846 (A,51,160)		RS1/16S220J
R	1847 (A,50,160)		RS1/16S220J
R	1848 (A,51,173)		RS1/16S220J
R	1849 (A,53,173)		RS1/16S220J
R	1850 (A,55,173)		RS1/16S220J
R	1851 (A,56,173)		RS1/16S220J
R	1854 (A,153,143)		RS1/16S104J
R	1855 (B,152,148)		RS1/16S224J
R	1856 (B,149,148)		RS1/16S104J
R	1857 (B,149,146)		RS1/16S224J
R	1858 (A,149,143)		RS1/16S474J
R	1859 (A,91,160)		RS1/16S220J
R	1860 (A,73,160)		RS1/16S220J
R	1861 (A,55,160)		RS1/16S220J
R	1903 (B,37,222)		RS1/16S561J
R	1904 (B,31,222)		RS1/16S270J
R	1905 (B,33,222)		RS1/16S270J
R	1906 (B,35,222)		RS1/16S270J
R	1907 (B,39,222)		RS1/16S220J
R	1908 (B,44,222)		RS1/16S102J
R	1909 (B,46,220)		RS1/16S102J
R	1910 (A,48,216)		RS1/16S472J
R	1911 (A,42,216)		RS1/16S102J
R	1912 (A,47,219)		RS1/16S151J
R	1913 (A,45,221)		RS1/16S222J
R	1914 (A,51,224)		RS1/16S102J
R	1915 (A,65,192)		RS1/16S102J
R	1916 (B,73,197)		RS1/16S0R0J
R	1917 (B,68,198)		RS1/16S102J
R	1918 (B,63,200)		RS1/16S102J
R	1919 (B,54,203)		RS1/16S103J
R	1920 (B,51,202)		RS1/16S102J
R	1921 (A,46,207)		RS1/16S472J
R	1922 (B,41,205)		RS1/16S102J
R	1923 (B,54,206)		RS1/16S102J
R	1924 (B,60,205)		RS1/16S332J
R	1925 (B,65,206)		RS1/16S102J
R	1926 (A,29,224)		RS1/16S182J
R	1927 (A,32,221)		RS1/16S103J
R	1928 (A,32,220)		RS1/16S103J
R	1929 (A,35,216)		RS1/16S472J
R	1930 (A,116,192)		RS1/16S221J
R	1931 (A,103,200)		RS1/16S683J
R	1932 (A,100,199)		RS1/16S103J
R	1933 (A,105,201)		RS1/16S273J
R	1934 (A,100,202)		RS1/16S103J
R	1935 (B,102,203)		RS1/16S121J
R	1936 (A,93,201)		RS1/16S473J
R	1937 (A,134,207)		RS1/16S473J
R	1938 (B,139,193)		RS1/16S473J
R	1939 (B,139,201)		RS1/16S394J
R	1940 (B,138,204)		RS1/16S473J
R	1941 (B,125,195)		RS1/16S471J
R	1942 (A,102,188)		RS1/16S103J
R	1943 (A,102,185)		RS1/16S103J
R	1944 (B,94,193)		RS1/16S472J
R	1945 (B,98,193)		RS1/16S392J
R	1946 (B,92,191)		RS1/16S223J
R	1947 (A,91,191)		RS1/16S104J
R	1948 (A,88,193)		RS1/16S822J
R	1949 (B,108,160)		RS1/16S101J
R	1950 (B,113,159)		RS1/16S101J
R	1952 (B,17,224)		RS1/16S0R0J

Mark	No.	Description	Part No.
R	1953	(B,28,219)	RS1/16S0R0J
R	1954	(A,68,146)	RS1/16S220J
R	1955	(A,68,143)	RS1/16S220J
R	1957	(A,68,148)	RS1/16S220J
R	1958	(A,68,145)	RS1/16S220J
R	1959	(A,51,185)	RS1/16S473J
R	1960	(B,58,182)	RS1/16S182J
R	1961	(A,41,184)	RS1/16S473J
R	1962	(A,44,182)	RS1/16S153J
R	1963	(B,131,149)	RS1/16S473J
R	1964	(B,121,151)	RS1/16S473J
R	1965	(B,116,152)	RS1/16S473J
R	1966		RS1/16S0R0J
R	1967		RS1/16S0R0J

CAPACITORS

C	1801	(A,30,193) ELECT. CAPACITOR	CEHAZL101M10
C	1802	(B,23,211)	CKSRYB104K16
C	1804	(B,23,198)	CKSRYB104K16
C	1806	(A,30,167) ELECT. CAPACITOR	CEHAZL101M10
C	1807	(B,23,184)	CKSRYB104K16
C	1809	(B,23,169)	CKSRYB104K16
C	1811	(A,30,153) ELECT. CAPACITOR	CEHAZL101M10
C	1812	(B,23,159)	CKSRYB104K16
C	1814	(B,23,145)	CKSRYB104K16
C	1816	(A,46,151) ELECT. CAPACITOR	CEHAZL101M10
C	1817	(A,84,169)	CKSRYB103K50
C	1818	(A,83,169)	CKSRYB105K16
C	1819	(A,66,169)	CKSRYB103K50
C	1820	(A,65,169)	CKSRYB105K16
C	1821	(A,48,169)	CKSRYB103K50
C	1822	(A,47,169)	CKSRYB105K16
C	1829	(B,34,142)	CKSRYB104K16
C	1830	(B,27,143)	CKSRYB104K16
C	1831	(B,147,142)	CKSRYB104K16
C	1832	(A,123,144)	CKSRYB104K16
C	1833	(A,138,144)	CKSRYB104K16
C	1836	(A,39,148) ELECT. CAPACITOR	ACH7211
C	1837	(A,33,145) ELECT. CAPACITOR	ACH7211
C	1838	(B,31,142)	CKSRYB104K16
C	1908	(B,30,225)	CKSRYB223K50
C	1909	(B,36,219)	CKSRYB104K16
C	1910	(B,43,225)	CKSRYB104K16
C	1911	(A,50,208)	CKSRYB104K16
C	1912	(A,51,193) ELECT. CAPACITOR	CEHAZL101M10
C	1913	(A,42,213)	CKSRYB104K16
C	1914	(A,43,193) ELECT. CAPACITOR	CEHAZL101M10
C	1915	(A,50,218)	CCSRCH750J50
C	1916	(A,44,226)	CKSRYB104K16
C	1917	(A,51,227)	CKSRYB104K16
C	1918	(A,65,205)	CCSRCH561J50
C	1919	(B,58,201)	CKSRYB104K16
C	1920	(B,51,206)	CKSRYB103K50
C	1921	(B,63,203)	CKSRYB104K16
C	1922	(A,31,224)	CKSRYB102K50
C	1923	(A,98,202)	CKSRYB104K16
C	1924	(A,93,203)	CKSRYB104K16
C	1925	(A,105,205) ELECT. CAPACITOR	CEANP4R7M50
C	1926	(A,137,206)	CKSRYB103K50
C	1927	(B,133,205)	CKSRYB103K50
C	1928	(B,123,195)	CCSRCH220J50
C	1929	(B,139,199)	CKSRYB104K16
C	1930	(A,139,196) ELECT. CAPACITOR	CEHAZL101M10
C	1931	(A,104,185)	CKSRYB104K16
C	1932	(B,98,191)	CKSRYB105K6R3
C	1933	(A,91,190)	CKSRYB105K6R3
C	1934	(A,89,198)	CKSRYB104K16
C	1935	(A,97,194)	CKSRYB104K16
C	1936	(A,105,165) ELECT. CAPACITOR	CEHAZL101M10
C	1937	(A,110,170)	CKSRYB471K50
C	1938	(A,110,168)	CKSRYB104K16
C	1939	(A,128,170)	CKSRYB471K50
C	1940	(A,128,168)	CKSRYB104K16
C	1941	(A,134,174)	CKSRYB471K50
C	1942	(A,135,174)	CKSRYB104K16
C	1943	(A,129,191)	CKSRYB471K50
C	1944	(A,129,192)	CKSRYB104K16
C	1945	(A,110,191)	CKSRYB471K50
C	1946	(A,110,192)	CKSRYB104K16
C	1947	(A,107,185)	CKSRYB471K50
C	1948	(A,105,185)	CKSRYB104K16
C	1949	(A,105,182)	CKSRYB471K50
C	1950	(A,104,182)	CKSRYB104K16
C	1951	(A,107,174)	CKSRYB471K50
C	1952	(A,105,174)	CKSRYB104K16
C	1953	(A,73,151)	CKSRYB105K16
C	1956	(A,141,162) ELECT. CAPACITOR	CEHAZL101M10
C	1957	(A,147,165)	CKSRYB471K50
C	1958	(A,147,164)	CKSRYB104K16
C	1965	(A,73,149)	CKSRYB104K16
C	1967	(A,84,151)	CKSRYB103K50

R DIGI BRIDGE ASSY

MISCELLANEOUS

CN	991	(A,312,97) CONNECTOR	CKS1730
CN	992	(A,288,73) CONNECTOR	CKS1730
CN	993	(A,312,62) CONNECTOR	CKS1730
CN	994	(A,288,38) CONNECTOR	CKS1730
CN	995	(A,312,32) CONNECTOR	CKS1721
CN	996	(A,288,19) CONNECTOR	CKS1721
CN	997	(A,312,114) CONNECTOR	CKS1716
CN	998	(A,288,108) CONNECTOR	CKS1716

S DAC ASSY

MISCELLANEOUS

IC	1001	(A,287,143) IC	TC74LCX541FTS1
IC	1002	(A,267,144) IC	TC74LCX541FTS1
IC	1003	(A,107,138) IC	TC74LCX125FTS1
IC	1004	(A,85,138) CLOCK BUFFER IC	CDCVF2310PW
IC	1051	(A,160,132) IC	NJM2391DL1-33
IC	1052	(A,197,132) IC	NJM2391DL1-33
IC	1053	(A,130,137) REGURATOR IC	AHK432IGY-0.5
IC	1057	(A,23,171) IC	NJM2391DL1-33
IC	1081	(A,318,165) PORT EXPANDER IC	BU4094BCFV
IC	1082	(A,306,165) PORT EXPANDER IC	BU4094BCFV

Mark	No.	Description	Part No.
IC	1101 (A,50,161)	SRC IC	SRC4192IDB
IC	1121 (A,50,178)	D/A CONVERTER IC	WM8741GEDS
IC	1151 (A,50,200)	IC	LT1358CS8
IC	1201 (A,86,161)	SRC IC	SRC4192IDB
IC	1221 (A,86,178)	D/A CONVERTER IC	WM8741GEDS
IC	1251 (A,86,200)	IC	LT1358CS8
IC	1301 (A,122,161)	SRC IC	SRC4192IDB
IC	1321 (A,122,178)	D/A CONVERTER IC	WM8741GEDS
IC	1351 (A,122,200)	IC	LT1358CS8
IC	1401 (A,194,161)	SRC IC	SRC4192IDB
IC	1421 (A,194,178)	D/A CONVERTER IC	WM8741GEDS
IC	1451 (A,194,200)	IC	LT1358CS8
IC	1501 (A,158,161)	SRC IC	SRC4192IDB
IC	1521 (A,158,178)	D/A CONVERTER IC	WM8741GEDS
IC	1551 (A,158,200)	IC	LT1358CS8
IC	1601 (A,230,161)	SRC IC	SRC4192IDB
IC	1621 (A,230,178)	D/A CONVERTER IC	WM8741GEDS
IC	1651 (A,230,200)	IC	LT1358CS8
IC	1801 (A,293,189)	AUDIO DAC	AK4387ET
IC	1802 (A,293,206)	OP-AMP IC	BA4560RF
IC	1851 (A,314,189)	AUDIO DAC	AK4387ET
IC	1852 (A,314,206)	OP-AMP IC	BA4560RF
L	1001 (A,284,137)	CHIP SOLID INDUCTOR	QTL1013
L	1002 (A,264,139)	CHIP SOLID INDUCTOR	QTL1013
L	1003 (A,101,141)	CHIP SOLID INDUCTOR	QTL1013
L	1004 (A,92,141)	CHIP SOLID INDUCTOR	QTL1013
L	1051 (A,167,136)	CHIP SOLID INDUCTOR	ATL7002
L	1052 (A,118,133)	CHIP SOLID INDUCTOR	QTL1013
L	1054 (B,21,161)	CHIP SOLID INDUCTOR	ATL7002
L	1055 (A,204,136)	CHIP SOLID INDUCTOR	ATL7002
L	1081 (B,307,153)	CHIP SOLID INDUCTOR	QTL1013
L	1101 (A,38,152)	CHIP SOLID INDUCTOR	QTL1013
L	1102 (A,63,152)	CHIP SOLID INDUCTOR	QTL1013
L	1121 (A,66,167)	CHIP SOLID INDUCTOR	QTL1013
L	1201 (A,74,152)	CHIP SOLID INDUCTOR	QTL1013
L	1202 (A,99,152)	CHIP SOLID INDUCTOR	QTL1013
L	1221 (A,102,167)	CHIP SOLID INDUCTOR	QTL1013
L	1301 (A,110,152)	CHIP SOLID INDUCTOR	QTL1013
L	1302 (A,135,152)	CHIP SOLID INDUCTOR	QTL1013
L	1321 (A,138,167)	CHIP SOLID INDUCTOR	QTL1013
L	1401 (A,182,152)	CHIP SOLID INDUCTOR	QTL1013
L	1402 (A,207,152)	CHIP SOLID INDUCTOR	QTL1013
L	1421 (A,210,167)	CHIP SOLID INDUCTOR	QTL1013
L	1501 (A,146,152)	CHIP SOLID INDUCTOR	QTL1013
L	1502 (A,171,152)	CHIP SOLID INDUCTOR	QTL1013
L	1521 (A,174,167)	CHIP SOLID INDUCTOR	QTL1013
L	1601 (A,218,152)	CHIP SOLID INDUCTOR	QTL1013
L	1602 (A,243,152)	CHIP SOLID INDUCTOR	QTL1013
L	1621 (A,246,167)	CHIP SOLID INDUCTOR	QTL1013
L	1801 (A,288,196)	CHIP SOLID INDUCTOR	QTL1013
L	1851 (A,309,196)	CHIP SOLID INDUCTOR	QTL1013
J	1052 (A,24,146)	2P HOUSING ASSY	ADX7584
KN	1051 (A,13,135)	SCREW PLATE	VNE1948
KN	1052 (A,13,184)	SCREW PLATE	VNE1948
KN	1053 (A,314,145)	WRAPPING TERMINAL	VNF1084
KN	1081 (A,13,220)	SCREW PLATE	VNE1948
X	1001 (A,114,138)	CRYSTAL OSCILLATOR	ASS7072
CN	1001 (A,280,126)	PLUG	CKS1764
CN	1002 (A,245,126)	PLUG	CKS1764
CN	1051 (A,228,126)	PLUG	CKS1750
CN	1081 (A,310,126)	CONNECTOR	CKS1755
CN	1101 (A,108,236)	PLUG	CKS1750
CN	1102 (A,170,236)	PLUG	CKS1764
CN	1103 (A,138,236)	PLUG	CKS1764
	1051 (A,39,135)	PCB BINDER	VEF1040
	1050 (A,174,135)	PCB BINDER	VEF1040

RESISTORS

R	1001 (A,112,134)		RS1/16S470J
R	1003 (A,78,134)		RS1/16S0R0J
R	1004 (A,104,133)		RS1/16S101J
R	1005 (A,104,132)		RS1/16S101J
R	1006 (A,109,133)		RS1/16S101J
R	1008 (A,89,132)		RS1/16S470J
R	1009 (A,293,140)		RS1/16S101J
R	1010 (A,293,141)		RS1/16S101J
R	1011 (A,293,143)		RS1/16S101J
R	1012 (A,295,144)		RS1/16S101J
R	1013 (A,295,146)		RS1/16S101J
R	1014 (A,295,147)		RS1/16S101J
R	1015 (A,279,141)		RAB4C101J
R	1017 (A,291,148)		RS1/16S104J
R	1018 (A,290,148)		RS1/16S104J
R	1019 (A,288,148)		RS1/16S104J
R	1020 (A,287,148)		RS1/16S104J
R	1021 (A,285,148)		RS1/16S104J
R	1022 (A,284,148)		RS1/16S104J
R	1024 (A,273,140)		RS1/16S101J
R	1025 (A,280,144)		RS1/16S101J
R	1026 (A,280,146)		RS1/16S101J
R	1028 (A,259,141)		RAB4C101J
R	1029 (A,259,144)		RS1/16S101J
R	1030 (A,259,146)		RS1/16S101J
R	1032 (A,270,149)		RS1/16S104J
R	1033 (A,269,149)		RS1/16S104J
R	1034 (A,267,149)		RS1/16S104J
R	1035 (A,266,149)		RS1/16S104J
R	1036 (A,264,149)		RS1/16S104J
R	1037 (A,263,149)		RS1/16S104J
R	1039 (A,282,134)	RESISTOR ARRAY	RAB4C104J
R	1046 (B,108,131)		RS1/16S104J
R	1051 (A,121,132)	CARBON FILM RESISTOR	RD1/4MUF221J
R	1052 (A,127,137)		RN1/16SE6801D
R	1053 (A,127,140)		RN1/16SE3901D
R	1054 (A,130,141)		RN1/16SE2200D
R	1061 (A,88,146)		RS1/16S680J
R	1062 (A,87,146)		RS1/16S470J
R	1063 (A,85,146)		RS1/16S470J
R	1064 (A,84,146)		RS1/16S470J
R	1065 (A,82,146)		RS1/16S470J
R	1067 (A,87,132)		RS1/16S820J
R	1081 (A,318,172)	RESISTOR ARRAY	RAB4C104J
R	1082 (A,318,159)	RESISTOR ARRAY	RAB4C104J
R	1083 (A,306,172)	RESISTOR ARRAY	RAB4C104J
R	1085 (A,307,158)		RS1/16S104J
R	1089 (A,323,134)		RS1/16S104J
R	1090 (A,218,173)		RS1/16S104J
R	1091 (A,320,134)		RS1/16S104J

Mark	No.	Description	Part No.
R	1092 (B,298,182)		RS1/16S104J
R	1093 (A,318,134)		RS1/16S104J
R	1094 (A,314,134)	RESISTOR ARRAY	RAB4C104J
R	1096 (A,310,158)		RS1/16S104J
R	1101 (B,46,166)		RS1/16S221J
R	1102 (A,43,167)		RS1/16S101J
R	1103 (A,43,165)		RS1/16S101J
R	1104 (A,43,163)		RS1/16S221J
R	1105 (A,43,162)		RS1/16S101J
R	1106 (B,43,159)		RS1/16S221J
R	1107 (A,43,156)		RS1/16S221J
R	1108 (A,49,154)		RS1/16S0R0J
R	1111 (A,57,162)		RS1/16S470J
R	1112 (A,57,163)		RS1/16S470J
R	1113 (A,57,165)		RS1/16S470J
R	1114 (A,57,166)		RS1/16S221J
R	1115 (B,55,166)		RS1/16S221J
R	1118		RS1/16S0R0J
R	1119		RS1/16S0R0J
R	1121 (A,57,173)		RS1/16S101J
R	1122 (A,46,189)		RS1/16S0R0J
R	1123 (A,58,175)		RS1/16S101J
R	1124 (A,53,171)		RS1/16S470J
R	1125 (A,43,178)		RS1/16S101J
R	1126 (A,43,177)		RS1/16S101J
R	1127 (A,43,175)		RS1/16S221J
R	1128 (A,43,174)		RS1/16S221J
R	1129 (A,43,172)		RS1/16S221J
R	1135 (A,42,181)		RS1/16S0R0J
R	1136 (A,60,184)		RS1/16S0R0J
R	1138		RS1/10S0R0J
R	1139		RS1/16S0R0J
R	1151 (B,45,184)		RS1/16S2001F
R	1152 (B,55,184)		RS1/16S2001F
R	1153 (B,42,184)		RS1/16S2001F
R	1154 (B,58,184)		RS1/16S2001F
R	1155 (B,40,194)		RS1/16S2401F
R	1156 (B,61,194)		RS1/16S2401F
R	1157 (B,47,197)		RS1/16S2401F
R	1158 (B,53,197)		RS1/16S2401F
R	1159 (B,45,197)		RS1/16S1801F
R	1160 (B,55,197)		RS1/16S1801F
R	1161 (A,45,195)		RS1/16S1801F
R	1162 (A,55,195)		RS1/16S1801F
R	1163 (A,47,205)		RS1/16S104J
R	1164 (A,54,205)		RS1/16S104J
R	1165 (A,44,207)	CHIP RESISTOR	RS1/16S2000F
R	1166 (A,57,207)	CHIP RESISTOR	RS1/16S2000F
R	1167 (B,45,211)		RS1/16S0R0J
R	1168 (B,55,211)		RS1/16S0R0J
R	1171 (B,43,216)		RS1/16S0R0J
R	1172 (B,57,216)		RS1/16S0R0J
R	1173 (B,45,188)	CHIP RESISTOR	RS1/16S2400F
R	1174 (B,55,188)	CHIP RESISTOR	RS1/16S2400F
R	1175 (B,40,187)	CHIP RESISTOR	RS1/16S2400F
R	1176 (B,61,187)	CHIP RESISTOR	RS1/16S2400F
R	1201 (B,82,166)		RS1/16S221J
R	1202 (A,79,167)		RS1/16S101J
R	1203 (A,79,165)		RS1/16S101J
R	1204 (A,79,163)		RS1/16S221J
R	1205 (A,79,162)		RS1/16S101J
R	1206 (B,79,159)		RS1/16S221J
R	1207 (A,79,156)		RS1/16S221J
R	1208 (A,85,154)		RS1/16S0R0J
R	1211 (A,93,162)		RS1/16S470J
R	1212 (A,93,163)		RS1/16S470J
R	1213 (A,93,165)		RS1/16S470J
R	1214 (A,93,166)		RS1/16S221J
R	1215 (B,91,166)		RS1/16S221J
R	1218		RS1/16S0R0J
R	1219		RS1/16S0R0J
R	1221 (A,93,173)		RS1/16S101J
R	1222 (A,82,189)		RS1/16S0R0J
R	1223 (A,94,175)		RS1/16S101J
R	1224 (A,89,171)		RS1/16S470J
R	1225 (A,79,178)		RS1/16S101J
R	1226 (A,79,177)		RS1/16S101J
R	1228 (A,79,174)		RS1/16S221J
R	1229 (A,79,172)		RS1/16S221J
R	1231 (A,79,175)		RS1/16S101J
R	1235 (A,78,181)		RS1/16S0R0J
R	1236 (A,96,184)		RS1/16S0R0J
R	1238		RS1/10S0R0J
R	1239		RS1/16S0R0J
R	1251 (B,81,184)		RS1/16S2001F
R	1252 (B,91,184)		RS1/16S2001F
R	1253 (B,78,184)		RS1/16S2001F
R	1254 (B,94,184)		RS1/16S2001F
R	1255 (B,76,194)		RS1/16S2401F
R	1256 (B,97,194)		RS1/16S2401F
R	1257 (B,83,197)		RS1/16S2401F
R	1258 (B,89,197)		RS1/16S2401F
R	1259 (B,81,197)		RS1/16S1801F
R	1260 (B,91,197)		RS1/16S1801F
R	1261 (A,81,195)		RS1/16S1801F
R	1262 (A,91,195)		RS1/16S1801F
R	1263 (A,83,205)		RS1/16S104J
R	1264 (A,90,205)		RS1/16S104J
R	1265 (A,80,207)	CHIP RESISTOR	RS1/16S2000F
R	1266 (A,93,207)	CHIP RESISTOR	RS1/16S2000F
R	1267 (B,81,211)		RS1/16S0R0J
R	1268 (B,91,211)		RS1/16S0R0J
R	1271 (B,79,216)		RS1/16S0R0J
R	1272 (B,93,216)		RS1/16S0R0J
R	1273 (B,81,188)	CHIP RESISTOR	RS1/16S2400F
R	1274 (B,91,188)	CHIP RESISTOR	RS1/16S2400F
R	1275 (B,76,187)	CHIP RESISTOR	RS1/16S2400F
R	1276 (B,97,187)	CHIP RESISTOR	RS1/16S2400F
R	1301 (B,118,166)		RS1/16S221J
R	1302 (A,115,167)		RS1/16S101J
R	1303 (A,115,165)		RS1/16S101J
R	1304 (A,115,163)		RS1/16S221J
R	1305 (A,115,162)		RS1/16S101J
R	1306 (B,115,159)		RS1/16S221J
R	1307 (A,115,156)		RS1/16S221J
R	1308 (A,121,154)		RS1/16S0R0J
R	1311 (A,129,162)		RS1/16S470J
R	1312 (A,129,163)		RS1/16S470J
R	1313 (A,129,165)		RS1/16S470J

Mark	No.	Description	Part No.
R	1314 (A,129,166)		RS1/16S221J
R	1315 (B,127,166)		RS1/16S221J
R	1318		RS1/16S0R0J
R	1319		RS1/16S0R0J
R	1321 (A,129,173)		RS1/16S101J
R	1322 (A,118,189)		RS1/16S0R0J
R	1323 (A,130,175)		RS1/16S101J
R	1324 (A,125,171)		RS1/16S470J
R	1325 (A,115,178)		RS1/16S101J
R	1326 (A,115,177)		RS1/16S101J
R	1328 (A,115,174)		RS1/16S221J
R	1329 (A,115,172)		RS1/16S221J
R	1331 (A,115,175)		RS1/16S101J
R	1335 (A,114,181)		RS1/16S0R0J
R	1336 (A,132,184)		RS1/16S0R0J
R	1338		RS1/10S0R0J
R	1339		RS1/16S0R0J
R	1351 (B,117,184)		RS1/16S2001F
R	1352 (B,127,184)		RS1/16S2001F
R	1353 (B,114,184)		RS1/16S2001F
R	1354 (B,130,184)		RS1/16S2001F
R	1355 (B,112,194)		RS1/16S2401F
R	1356 (B,133,194)		RS1/16S2401F
R	1357 (B,119,197)		RS1/16S2401F
R	1358 (B,125,197)		RS1/16S2401F
R	1359 (B,117,197)		RS1/16S1801F
R	1360 (B,127,197)		RS1/16S1801F
R	1361 (A,117,195)		RS1/16S1801F
R	1362 (A,127,195)		RS1/16S1801F
R	1363 (A,119,205)		RS1/16S104J
R	1364 (A,126,205)		RS1/16S104J
R	1365 (A,116,207)	CHIP RESISTOR	RS1/16S2000F
R	1366 (A,129,207)	CHIP RESISTOR	RS1/16S2000F
R	1367 (B,117,211)		RS1/16S0R0J
R	1368 (B,127,211)		RS1/16S0R0J
R	1371 (B,115,216)		RS1/16S0R0J
R	1372 (B,129,216)		RS1/16S0R0J
R	1373 (B,117,188)	CHIP RESISTOR	RS1/16S2400F
R	1374 (B,127,188)	CHIP RESISTOR	RS1/16S2400F
R	1375 (B,112,187)	CHIP RESISTOR	RS1/16S2400F
R	1376 (B,133,187)	CHIP RESISTOR	RS1/16S2400F
R	1401 (B,190,166)		RS1/16S221J
R	1402 (A,187,167)		RS1/16S101J
R	1403 (A,187,165)		RS1/16S101J
R	1404 (A,187,163)		RS1/16S221J
R	1405 (A,187,162)		RS1/16S101J
R	1406 (B,187,159)		RS1/16S221J
R	1407 (A,187,156)		RS1/16S221J
R	1408 (A,193,154)		RS1/16S0R0J
R	1411 (A,201,162)		RS1/16S470J
R	1412 (A,201,163)		RS1/16S470J
R	1413 (A,201,165)		RS1/16S470J
R	1414 (A,201,166)		RS1/16S221J
R	1415 (B,199,166)		RS1/16S221J
R	1418		RS1/16S0R0J
R	1419		RS1/16S0R0J
R	1421 (A,201,173)		RS1/16S101J
R	1422 (A,190,189)		RS1/16S0R0J
R	1423 (A,202,175)		RS1/16S101J

Mark	No.	Description	Part No.
R	1424 (A,197,171)		RS1/16S470J
R	1425 (A,187,178)		RS1/16S101J
R	1426 (A,187,177)		RS1/16S101J
R	1428 (A,187,174)		RS1/16S221J
R	1429 (A,187,172)		RS1/16S221J
R	1431 (A,187,175)		RS1/16S101J
R	1435 (A,186,181)		RS1/16S0R0J
R	1436 (A,204,184)		RS1/16S0R0J
R	1438		RS1/10S0R0J
R	1439		RS1/16S0R0J
R	1451 (B,189,184)		RS1/16S2001F
R	1452 (B,199,184)		RS1/16S2001F
R	1453 (B,186,184)		RS1/16S2001F
R	1454 (B,202,184)		RS1/16S2001F
R	1455 (B,184,194)		RS1/16S2401F
R	1456 (B,205,194)		RS1/16S2401F
R	1457 (B,191,197)		RS1/16S2401F
R	1458 (B,197,197)		RS1/16S2401F
R	1459 (B,189,197)		RS1/16S1801F
R	1460 (B,199,197)		RS1/16S1801F
R	1461 (A,189,195)		RS1/16S1801F
R	1462 (A,199,195)		RS1/16S1801F
R	1463 (A,191,205)		RS1/16S104J
R	1464 (A,198,205)		RS1/16S104J
R	1465 (A,188,207)	CHIP RESISTOR	RS1/16S2000F
R	1466 (A,201,207)	CHIP RESISTOR	RS1/16S2000F
R	1467 (B,189,211)		RS1/16S0R0J
R	1468 (B,199,211)		RS1/16S0R0J
R	1471 (B,187,216)		RS1/16S0R0J
R	1472 (B,201,216)		RS1/16S0R0J
R	1473 (B,189,188)	CHIP RESISTOR	RS1/16S2400F
R	1474 (B,199,188)	CHIP RESISTOR	RS1/16S2400F
R	1475 (B,184,187)	CHIP RESISTOR	RS1/16S2400F
R	1476 (B,205,187)	CHIP RESISTOR	RS1/16S2400F
R	1501 (B,154,166)		RS1/16S221J
R	1502 (A,151,167)		RS1/16S101J
R	1503 (A,151,165)		RS1/16S101J
R	1504 (A,151,163)		RS1/16S221J
R	1505 (A,151,162)		RS1/16S101J
R	1506 (B,151,159)		RS1/16S221J
R	1507 (A,151,156)		RS1/16S221J
R	1508 (A,157,154)		RS1/16S0R0J
R	1511 (A,165,162)		RS1/16S470J
R	1512 (A,165,163)		RS1/16S470J
R	1513 (A,165,165)		RS1/16S470J
R	1514 (A,165,166)		RS1/16S221J
R	1515 (B,163,166)		RS1/16S221J
R	1518		RS1/16S0R0J
R	1519		RS1/16S0R0J
R	1521 (A,165,173)		RS1/16S101J
R	1522 (A,154,189)		RS1/16S0R0J
R	1523 (A,166,175)		RS1/16S101J
R	1524 (A,161,171)		RS1/16S470J
R	1525 (A,151,178)		RS1/16S101J
R	1526 (A,151,177)		RS1/16S101J
R	1528 (A,151,174)		RS1/16S221J
R	1529 (A,151,172)		RS1/16S221J
R	1531 (A,151,175)		RS1/16S101J
R	1535 (A,150,181)		RS1/16S0R0J

Mark	No.	Description	Part No.
R	1536 (A,168,184)		RS1/16S0R0J
R	1538		RS1/10S0R0J
R	1539		RS1/16S0R0J
R	1551 (B,153,184)		RS1/16S2001F
R	1552 (B,163,184)		RS1/16S2001F
R	1553 (B,150,184)		RS1/16S2001F
R	1554 (B,166,184)		RS1/16S2001F
R	1555 (B,148,194)		RS1/16S2401F
R	1556 (B,169,194)		RS1/16S2401F
R	1557 (B,155,197)		RS1/16S2401F
R	1558 (B,161,197)		RS1/16S2401F
R	1559 (B,153,197)		RS1/16S1801F
R	1560 (B,163,197)		RS1/16S1801F
R	1561 (A,153,195)		RS1/16S1801F
R	1562 (A,163,195)		RS1/16S1801F
R	1563 (A,155,205)		RS1/16S104J
R	1564 (A,162,205)		RS1/16S104J
R	1565 (A,152,207)	CHIP RESISTOR	RS1/16S2000F
R	1566 (A,165,207)	CHIP RESISTOR	RS1/16S2000F
R	1567 (B,153,211)		RS1/16S0R0J
R	1568 (B,163,211)		RS1/16S0R0J
R	1571 (B,151,216)		RS1/16S0R0J
R	1572 (B,165,216)		RS1/16S0R0J
R	1573 (B,153,188)	CHIP RESISTOR	RS1/16S2400F
R	1574 (B,163,188)	CHIP RESISTOR	RS1/16S2400F
R	1575 (B,148,187)	CHIP RESISTOR	RS1/16S2400F
R	1576 (B,169,187)	CHIP RESISTOR	RS1/16S2400F
R	1601 (B,226,166)		RS1/16S221J
R	1602 (A,223,167)		RS1/16S221J
R	1603 (A,223,165)		RS1/16S101J
R	1604 (A,223,163)		RS1/16S221J
R	1605 (A,223,162)		RS1/16S101J
R	1606 (B,223,159)		RS1/16S221J
R	1607 (A,223,156)		RS1/16S221J
R	1608 (A,229,154)		RS1/16S0R0J
R	1611 (A,237,162)		RS1/16S470J
R	1612 (A,237,163)		RS1/16S470J
R	1613 (A,237,165)		RS1/16S470J
R	1614 (A,237,166)		RS1/16S221J
R	1615 (B,235,166)		RS1/16S221J
R	1618		RS1/16S0R0J
R	1619		RS1/16S0R0J
R	1621 (A,237,173)		RS1/16S101J
R	1622 (A,226,189)		RS1/16S0R0J
R	1623 (A,238,175)		RS1/16S101J
R	1624 (A,233,171)		RS1/16S470J
R	1626 (A,223,177)		RS1/16S101J
R	1628 (A,223,174)		RS1/16S221J
R	1629 (A,223,172)		RS1/16S221J
R	1631 (A,223,175)		RS1/16S101J
R	1635 (A,222,181)		RS1/16S0R0J
R	1636 (A,240,184)		RS1/16S0R0J
R	1638		RS1/10S0R0J
R	1639		RS1/16S0R0J
R	1651 (B,225,184)		RS1/16S2001F
R	1652 (B,235,184)		RS1/16S2001F
R	1653 (B,222,184)		RS1/16S2001F
R	1654 (B,238,184)		RS1/16S2001F
R	1655 (B,220,194)		RS1/16S2401F

Mark	No.	Description	Part No.
R	1656 (B,241,194)		RS1/16S2401F
R	1657 (B,227,197)		RS1/16S2401F
R	1658 (B,233,197)		RS1/16S2401F
R	1659 (B,225,197)		RS1/16S1801F
R	1660 (B,235,197)		RS1/16S1801F
R	1661 (A,225,195)		RS1/16S1801F
R	1662 (A,235,195)		RS1/16S1801F
R	1663 (A,227,205)		RS1/16S104J
R	1664 (A,234,205)		RS1/16S104J
R	1665 (A,224,207)	CHIP RESISTOR	RS1/16S2000F
R	1666 (A,237,207)	CHIP RESISTOR	RS1/16S2000F
R	1667 (B,225,211)		RS1/16S0R0J
R	1668 (B,235,211)		RS1/16S0R0J
R	1671 (B,223,216)		RS1/16S0R0J
R	1672 (B,237,216)		RS1/16S0R0J
R	1673 (B,225,188)	CHIP RESISTOR	RS1/16S2400F
R	1674 (B,235,188)	CHIP RESISTOR	RS1/16S2400F
R	1675 (B,220,187)	CHIP RESISTOR	RS1/16S2400F
R	1676 (B,241,187)	CHIP RESISTOR	RS1/16S2400F
R	1718		RS1/16S0R0J
R	1719		RS1/16S0R0J
R	1738		RS1/10S0R0J
R	1739		RS1/16S0R0J
R	1779		RS1/16S0R0J
R	1780		RS1/16S0R0J
R	1801 (A,288,182)		RS1/16S101J
R	1802 (A,290,182)		RS1/16S101J
R	1803 (A,291,182)		RS1/16S101J
R	1804 (A,293,182)		RS1/16S101J
R	1805 (A,297,182)		RAB4C221J
R	1806 (B,297,195)		RS1/16S0R0J
R	1809 (A,289,196)		RS1/16S4R7J
R	1810		RS1/16S0R0J
R	1811 (B,286,204)		RS1/16S223J
R	1812 (B,300,204)		RS1/16S223J
R	1813 (A,285,205)		RS1/16S302J
R	1814 (A,300,205)		RS1/16S302J
R	1815 (A,286,205)		RS1/16S392J
R	1816 (A,299,205)		RS1/16S392J
R	1817 (B,289,208)		RS1/16S332J
R	1818 (B,296,208)		RS1/16S332J
R	1819 (A,286,208)		RS1/16S332J
R	1820 (A,299,208)		RS1/16S332J
R	1821 (A,288,211)		RS1/16S101J
R	1822 (A,297,211)		RS1/16S101J
R	1823 (B,290,219)		RS1/16S104J
R	1824 (B,296,219)		RS1/16S104J
R	1827		RS1/16S0R0J
R	1828		RS1/16S0R0J
R	1851 (A,309,183)		RS1/16S101J
R	1852 (A,311,183)		RS1/16S101J
R	1853 (A,312,183)		RS1/16S101J
R	1854 (A,314,183)		RS1/16S101J
R	1855 (A,318,183)		RAB4C221J
R	1856 (B,318,195)		RS1/16S0R0J
R	1859 (A,310,196)		RS1/16S4R7J
R	1860		RS1/16S0R0J
R	1861 (B,307,204)		RS1/16S223J
R	1862 (B,321,204)		RS1/16S223J

Mark	No.	Description	Part No.
R	1863	(A,306,205)	RS1/16S302J
R	1864	(A,321,205)	RS1/16S302J
R	1865	(A,307,205)	RS1/16S392J
R	1866	(A,320,205)	RS1/16S392J
R	1867	(B,310,208)	RS1/16S332J
R	1868	(B,317,208)	RS1/16S332J
R	1869	(A,307,208)	RS1/16S332J
R	1870	(A,320,208)	RS1/16S332J
R	1871	(A,309,211)	RS1/16S101J
R	1872	(A,318,211)	RS1/16S101J
R	1873	(B,311,219)	RS1/16S104J
R	1874	(B,317,219)	RS1/16S104J
R	1877		RS1/16S0R0J
R	1878		RS1/16S0R0J
R	1891	(A,304,134) RESISTOR ARRAY	RAB4C104J
R	1892	(A,298,135) RESISTOR ARRAY	RAB4C104J
R	1901	(A,28,140)	RS1/16S0R0J
R	1902	(A,28,138)	RS1/16S0R0J
R	1903	(A,28,136)	RS1/16S0R0J
R	1904	(A,28,134)	RS1/16S0R0J
R	1905	(A,28,132)	RS1/16S0R0J
R	1906	(B,29,140)	RS1/16S0R0J
R	1907	(B,29,138)	RS1/16S0R0J
R	1908	(B,29,136)	RS1/16S0R0J
R	1909	(B,29,134)	RS1/16S0R0J
R	1910	(B,29,132)	RS1/16S0R0J
R	1911	(A,43,140)	RS1/16S0R0J
R	1912	(A,43,132)	RS1/16S0R0J
R	1913	(A,43,130)	RS1/16S0R0J
R	1914	(B,42,140)	RS1/16S0R0J
R	1915	(B,45,130)	RS1/16S0R0J
R	1916	(B,45,127)	RS1/16S0R0J
R	1917	(A,142,136)	RS1/16S0R0J
R	1918	(A,142,132)	RS1/16S0R0J
R	1919	(B,142,136)	RS1/16S0R0J
R	1920	(B,142,132)	RS1/16S0R0J
R	1921	(A,142,139)	RS1/16S0R0J
R	1922	(B,142,139)	RS1/16S0R0J
R	1931	(A,19,212)	RS1/16S0R0J
R	1932	(A,21,212)	RS1/16S0R0J
R	1933	(A,22,212)	RS1/16S0R0J
R	1934	(A,24,212)	RS1/16S0R0J
R	1935	(B,19,211)	RS1/16S0R0J
R	1936	(B,21,211)	RS1/16S0R0J
R	1937	(B,23,211)	RS1/16S0R0J
R	1938	(B,26,211)	RS1/16S0R0J
R	1941	(A,29,224)	RS1/16S0R0J
R	1942	(A,29,222)	RS1/16S0R0J
R	1943	(A,29,221)	RS1/16S0R0J
R	1944	(A,29,219)	RS1/16S0R0J
R	1951	(A,42,236)	RS1/16S0R0J
R	1952	(A,42,234)	RS1/16S0R0J
R	1953	(A,42,232)	RS1/16S0R0J
R	1954	(A,42,230)	RS1/16S0R0J
R	1955	(B,43,234)	RS1/16S0R0J
R	1956	(B,43,232)	RS1/16S0R0J
R	1957	(B,43,229)	RS1/16S0R0J
R	1958	(B,43,227)	RS1/16S0R0J
R	1963	(A,32,148)	RS1/16S0R0J
R	1964	(A,32,146)	RS1/16S0R0J
R	1965	(A,31,142)	RS1/16S0R0J
R	1967	(B,21,142)	RS1/16S0R0J
R	1969	(B,32,153)	RS1/16S0R0J
R	1970	(B,32,148)	RS1/16S0R0J
R	1971	(A,20,142)	RS1/16S0R0J
R	1972	(A,21,142)	RS1/16S0R0J
R	1973	(A,23,142)	RS1/16S0R0J
R	1974	(A,24,142)	RS1/16S0R0J
R	1975	(A,26,142)	RS1/16S0R0J
R	1984	(A,105,229)	RS1/16S0R0J

CAPACITORS

C	1001	(A,97,139) OS CAPACITOR	ACH7204
C	1003	(A,287,138)	CKSRYB103K50
C	1004	(A,267,138)	CKSRYB104K16
C	1005	(A,267,139)	CKSRYB471K50
C	1006	(A,101,138)	CKSRYB104K16
C	1007	(A,103,138)	CKSRYB471K50
C	1008	(A,92,139)	CKSRYB104K16
C	1009	(A,91,139)	CKSRYB471K50
C	1010	(A,237,134) ELECT. CAPACITOR	CEHAZL221M10
C	1011	(A,90,143)	CCSRCH101J50
C	1012	(A,92,143)	CKSRYB102K50
C	1013	(A,79,145)	CKSRYB102K50
C	1014	(A,80,145)	CCSRCH101J50
C	1015	(A,83,133)	CKSRYB102K50
C	1016	(A,81,133)	CCSRCH101J50
C	1017	(A,90,136)	CCSRCH101J50
C	1018	(A,92,136)	CKSRYB102K50
C	1019	(B,84,142)	CKSRYB104K16
C	1020	(B,87,142)	CKSRYB104K16
C	1021	(B,83,134)	CKSRYB104K16
C	1022	(B,88,134)	CKSRYB104K16
C	1050	(A,225,134) ELECT. CAPACITOR	ACH7268
C	1051	(B,231,134)	CKSRYB224K16
C	1052	(B,20,149)	CKSRYB224K16
C	1053	(A,165,136)	CKSRYB104K16
C	1055	(A,151,137) ELECT. CAPACITOR	CEHAZL101M10
C	1056	(A,202,136)	CKSRYB104K16
C	1058	(A,188,137) ELECT. CAPACITOR	CEHAZL101M10
C	1059	(A,126,137)	CKSRYB105K6R3
C	1060	(A,121,136) OS CAPACITOR	ACH7204
C	1061	(A,115,135)	CKSRYB104K16
C	1069	(A,19,159) ELECT. CAPACITOR	ACH7268
C	1070	(A,19,167)	CKSRYB104K16
C	1072	(A,26,156) ELECT. CAPACITOR	CEHAZL101M10
C	1077	(B,106,230)	CKSRYB473K25
C	1078	(B,101,230)	CKSRYB473K25
C	1079	(A,19,152) ELECT. CAPACITOR	ACH7268
C	1081	(A,323,163)	CKSRYB104K16
C	1082	(A,311,163)	CKSRYB104K16
C	1101	(A,37,160) OS CAPACITOR	ACH7204
C	1102	(A,42,160)	CKSRYB104K16
C	1103	(A,43,160)	CKSRYB471K50
C	1104	(A,63,160) OS CAPACITOR	ACH7204
C	1105	(A,59,160)	CKSRYB104K16
C	1106	(A,57,160)	CKSRYB471K50
C	1121	(A,63,173) OS CAPACITOR	ACH7204
C	1122	(A,59,178)	CKSRYB104K16

Mark	No.	Description	Part No.
C	1123 (A,57,178)		CKSRYB103K50
C	1124 (A,49,187)	OS CAPACITOR	ACH7203
C	1125 (A,46,184)		CKSRYB104K16
C	1126 (A,57,181)		CKSRYB104K16
C	1127 (A,44,181)		CKSRYB104K16
C	1151 (A,37,178)	ELECT. CAPACITOR	ACH7268
C	1152 (A,63,178)	ELECT. CAPACITOR	ACH7268
C	1153 (A,44,184)		CKSRYB105K6R3
C	1154 (A,57,184)		CKSRYB105K6R3
C	1155 (A,37,191)	PORYPROPYLENE FILM C	VCE1041
C	1156 (A,58,191)	PORYPROPYLENE FILM C	VCE1041
C	1157 (A,37,197)	PORYPROPYRENE FILM C	VCE1040
C	1158 (A,58,197)	PORYPROPYRENE FILM C	VCE1040
C	1159 (A,37,203)	PORYPROPYRENE FILM C	VCE1040
C	1160 (A,63,203)	PORYPROPYRENE FILM C	VCE1040
C	1161 (A,39,208)	ELECT. CAPACITOR	ACH7198
C	1162 (A,62,208)	ELECT. CAPACITOR	ACH7198
C	1163 (A,47,207)		CKSRYB682K50
C	1164 (A,54,207)		CKSRYB682K50
C	1165 (A,62,215)	ELECT. CAPACITOR	ACH7211
C	1166 (A,39,218)	ELECT. CAPACITOR	ACH7211
C	1167 (A,52,204)		CKSRYB103K50
C	1168 (A,48,204)		CKSRYB103K50
C	1201 (A,73,160)	OS CAPACITOR	ACH7204
C	1202 (A,78,160)		CKSRYB104K16
C	1203 (A,79,160)		CKSRYB471K50
C	1204 (A,99,160)	OS CAPACITOR	ACH7204
C	1205 (A,95,160)		CKSRYB104K16
C	1206 (A,93,160)		CKSRYB471K50
C	1221 (A,99,173)	OS CAPACITOR	ACH7204
C	1222 (A,95,178)		CKSRYB104K16
C	1223 (A,93,178)		CKSRYB103K50
C	1224 (A,85,187)	OS CAPACITOR	ACH7203
C	1225 (A,82,184)		CKSRYB104K16
C	1226 (A,93,181)		CKSRYB104K16
C	1227 (A,80,181)		CKSRYB104K16
C	1251 (A,73,178)	ELECT. CAPACITOR	ACH7268
C	1252 (A,99,178)	ELECT. CAPACITOR	ACH7268
C	1253 (A,80,184)		CKSRYB105K6R3
C	1254 (A,93,184)		CKSRYB105K6R3
C	1255 (A,73,191)	PORYPROPYLENE FILM C	VCE1041
C	1256 (A,94,191)	PORYPROPYLENE FILM C	VCE1041
C	1257 (A,73,197)	PORYPROPYRENE FILM C	VCE1040
C	1258 (A,94,197)	PORYPROPYRENE FILM C	VCE1040
C	1259 (A,73,203)	PORYPROPYRENE FILM C	VCE1040
C	1260 (A,99,203)	PORYPROPYRENE FILM C	VCE1040
C	1261 (A,75,208)	ELECT. CAPACITOR	ACH7198
C	1262 (A,98,208)	ELECT. CAPACITOR	ACH7198
C	1263 (A,83,207)		CKSRYB682K50
C	1264 (A,90,207)		CKSRYB682K50
C	1265 (A,98,215)	ELECT. CAPACITOR	ACH7211
C	1266 (A,75,218)	ELECT. CAPACITOR	ACH7211
C	1267 (A,88,204)		CKSRYB103K50
C	1268 (A,84,204)		CKSRYB103K50
C	1301 (A,109,160)	OS CAPACITOR	ACH7204
C	1302 (A,114,160)		CKSRYB104K16
C	1303 (A,115,160)		CKSRYB471K50
C	1304 (A,135,160)	OS CAPACITOR	ACH7204
C	1305 (A,131,160)		CKSRYB104K16
C	1306 (A,129,160)		CKSRYB471K50
C	1321 (A,135,173)	OS CAPACITOR	ACH7204
C	1322 (A,131,178)		CKSRYB104K16
C	1323 (A,129,178)		CKSRYB103K50
C	1324 (A,121,187)	OS CAPACITOR	ACH7203
C	1325 (A,118,184)		CKSRYB104K16
C	1326 (A,129,181)		CKSRYB104K16
C	1327 (A,116,181)		CKSRYB104K16
C	1351 (A,109,178)	ELECT. CAPACITOR	ACH7268
C	1352 (A,135,178)	ELECT. CAPACITOR	ACH7268
C	1353 (A,116,184)		CKSRYB105K6R3
C	1354 (A,129,184)		CKSRYB105K6R3
C	1355 (A,109,191)	PORYPROPYLENE FILM C	VCE1041
C	1356 (A,130,191)	PORYPROPYLENE FILM C	VCE1041
C	1357 (A,109,197)	PORYPROPYRENE FILM C	VCE1040
C	1358 (A,130,197)	PORYPROPYRENE FILM C	VCE1040
C	1359 (A,109,203)	PORYPROPYRENE FILM C	VCE1040
C	1360 (A,135,203)	PORYPROPYRENE FILM C	VCE1040
C	1361 (A,111,208)	ELECT. CAPACITOR	ACH7198
C	1362 (A,134,208)	ELECT. CAPACITOR	ACH7198
C	1363 (A,119,207)		CKSRYB682K50
C	1364 (A,126,207)		CKSRYB682K50
C	1365 (A,134,215)	ELECT. CAPACITOR	ACH7211
C	1366 (A,111,218)	ELECT. CAPACITOR	ACH7211
C	1367 (A,124,204)		CKSRYB103K50
C	1368 (A,120,204)		CKSRYB103K50
C	1401 (A,181,160)	OS CAPACITOR	ACH7204
C	1402 (A,186,160)		CKSRYB471K50
C	1403 (A,187,160)		CKSRYB104K16
C	1404 (A,207,160)	OS CAPACITOR	ACH7204
C	1405 (A,203,160)		CKSRYB104K16
C	1406 (A,201,160)		CKSRYB471K50
C	1421 (A,207,173)	OS CAPACITOR	ACH7204
C	1422 (A,203,178)		CKSRYB104K16
C	1423 (A,201,178)		CKSRYB103K50
C	1424 (A,193,187)	OS CAPACITOR	ACH7203
C	1425 (A,190,184)		CKSRYB104K16
C	1426 (A,201,181)		CKSRYB104K16
C	1427 (A,188,181)		CKSRYB104K16
C	1451 (A,181,178)	ELECT. CAPACITOR	ACH7268
C	1452 (A,207,178)	ELECT. CAPACITOR	ACH7268
C	1453 (A,188,184)		CKSRYB105K6R3
C	1454 (A,201,184)		CKSRYB105K6R3
C	1455 (A,181,191)	PORYPROPYLENE FILM C	VCE1041
C	1456 (A,202,191)	PORYPROPYLENE FILM C	VCE1041
C	1457 (A,181,197)	PORYPROPYRENE FILM C	VCE1040
C	1458 (A,202,197)	PORYPROPYRENE FILM C	VCE1040
C	1459 (A,181,203)	PORYPROPYRENE FILM C	VCE1040
C	1460 (A,207,203)	PORYPROPYRENE FILM C	VCE1040
C	1461 (A,183,208)	ELECT. CAPACITOR	ACH7198
C	1462 (A,206,208)	ELECT. CAPACITOR	ACH7198
C	1463 (A,191,207)		CKSRYB682K50
C	1464 (A,198,207)		CKSRYB682K50
C	1465 (A,206,215)	ELECT. CAPACITOR	ACH7211
C	1466 (A,183,218)	ELECT. CAPACITOR	ACH7211
C	1467 (A,196,204)		CKSRYB103K50
C	1468 (A,192,204)		CKSRYB103K50
C	1501 (A,145,160)	OS CAPACITOR	ACH7204
C	1502 (A,150,160)		CKSRYB104K16

Mark	No.	Description	Part No.
C	1503 (A,151,160)		CKSRYB471K50
C	1504 (A,171,160)	OS CAPACITOR	ACH7204
C	1505 (A,167,160)		CKSRYB104K16
C	1506 (A,165,160)		CKSRYB471K50
C	1521 (A,171,173)	OS CAPACITOR	ACH7204
C	1522 (A,167,178)		CKSRYB104K16
C	1523 (A,165,178)		CKSRYB103K50
C	1524 (A,157,187)	OS CAPACITOR	ACH7203
C	1525 (A,154,184)		CKSRYB104K16
C	1526 (A,165,181)		CKSRYB104K16
C	1527 (A,152,181)		CKSRYB104K16
C	1551 (A,145,178)	ELECT. CAPACITOR	ACH7268
C	1552 (A,171,178)	ELECT. CAPACITOR	ACH7268
C	1553 (A,152,184)		CKSRYB105K6R3
C	1554 (A,165,184)		CKSRYB105K6R3
C	1555 (A,145,191)	PORYPROPYLENE FILM C	VCE1041
C	1556 (A,166,191)	PORYPROPYLENE FILM C	VCE1041
C	1557 (A,145,197)	PORYPROPYRENE FILM C	VCE1040
C	1558 (A,166,197)	PORYPROPYRENE FILM C	VCE1040
C	1559 (A,145,203)	PORYPROPYRENE FILM C	VCE1040
C	1560 (A,171,203)	PORYPROPYRENE FILM C	VCE1040
C	1561 (A,147,208)	ELECT. CAPACITOR	ACH7198
C	1562 (A,170,208)	ELECT. CAPACITOR	ACH7198
C	1563 (A,155,207)		CKSRYB682K50
C	1564 (A,162,207)		CKSRYB682K50
C	1565 (A,170,215)	ELECT. CAPACITOR	ACH7211
C	1566 (A,147,218)	ELECT. CAPACITOR	ACH7211
C	1567 (A,160,204)		CKSRYB103K50
C	1568 (A,156,204)		CKSRYB103K50
C	1601 (A,217,160)	OS CAPACITOR	ACH7204
C	1602 (A,222,160)		CKSRYB104K16
C	1603 (A,223,160)		CKSRYB471K50
C	1604 (A,243,160)	OS CAPACITOR	ACH7204
C	1605 (A,239,160)		CKSRYB104K16
C	1606 (A,237,160)		CKSRYB471K50
C	1621 (A,243,173)	OS CAPACITOR	ACH7204
C	1622 (A,239,178)		CKSRYB104K16
C	1623 (A,237,178)		CKSRYB103K50
C	1624 (A,229,187)	OS CAPACITOR	ACH7203
C	1625 (A,226,184)		CKSRYB104K16
C	1626 (A,237,181)		CKSRYB104K16
C	1627 (A,224,181)		CKSRYB104K16
C	1651 (A,217,178)	ELECT. CAPACITOR	ACH7268
C	1652 (A,243,178)	ELECT. CAPACITOR	ACH7268
C	1653 (A,224,184)		CKSRYB105K6R3
C	1654 (A,237,184)		CKSRYB105K6R3
C	1655 (A,217,191)	PORYPROPYLENE FILM C	VCE1041
C	1656 (A,238,191)	PORYPROPYLENE FILM C	VCE1041
C	1657 (A,217,197)	PORYPROPYRENE FILM C	VCE1040
C	1658 (A,238,197)	PORYPROPYRENE FILM C	VCE1040
C	1659 (A,217,203)	PORYPROPYRENE FILM C	VCE1040
C	1660 (A,243,203)	PORYPROPYRENE FILM C	VCE1040
C	1661 (A,219,208)	ELECT. CAPACITOR	ACH7198
C	1662 (A,242,208)	ELECT. CAPACITOR	ACH7198
C	1663 (A,227,207)		CKSRYB682K50
C	1664 (A,234,207)		CKSRYB682K50
C	1665 (A,242,215)	ELECT. CAPACITOR	ACH7211
C	1666 (A,219,218)	ELECT. CAPACITOR	ACH7211
C	1667 (A,232,204)		CKSRYB103K50
C	1668 (A,228,204)		CKSRYB103K50

Mark	No.	Description	Part No.
C	1801 (A,285,191)		CEAT470M16
C	1802 (A,289,189)		CKSRYB104K16
C	1803 (A,300,191)		CEAT100M50
C	1804 (A,292,196)		CKSRYB104K16
C	1805 (A,292,195)		CKSRYB471K50
C	1810 (A,297,189)		CKSRYB104K16
C	1811 (A,288,200)	ELECT. CAPACITOR	CEAT220M50
C	1812 (A,298,200)	ELECT. CAPACITOR	CEAT220M50
C	1813 (B,289,204)		CCSRCH471J50
C	1814 (B,296,204)		CCSRCH471J50
C	1815 (A,285,208)		CCSRCH391J50
C	1816 (A,300,208)		CCSRCH391J50
C	1817 (A,287,214)		CEAT4R7M50
C	1818 (A,298,214)		CEAT4R7M50
C	1819 (A,294,211)		CKSRYB103K50
C	1820 (A,291,211)		CKSRYB103K50
C	1851 (A,306,191)		CEAT470M16
C	1852 (A,310,189)		CKSRYB104K16
C	1853 (A,321,191)		CEAT100M50
C	1854 (A,313,196)		CKSRYB104K16
C	1855 (A,313,195)		CKSRYB471K50
C	1860 (A,318,189)		CKSRYB104K16
C	1861 (A,309,200)	ELECT. CAPACITOR	CEAT220M50
C	1862 (A,319,200)	ELECT. CAPACITOR	CEAT220M50
C	1863 (B,310,204)		CCSRCH471J50
C	1864 (B,317,204)		CCSRCH471J50
C	1865 (A,306,208)		CCSRCH391J50
C	1866 (A,321,208)		CCSRCH391J50
C	1867 (A,308,214)		CEAT4R7M50
C	1868 (A,319,214)		CEAT4R7M50
C	1869 (A,315,211)		CKSRYB103K50
C	1870 (A,312,211)		CKSRYB103K50

THN MODULE ASSY

SEMICONDUCTORS

NSP	IC 7703	AYW7222

MISCELLANEOUS

NSP	7601 ID LABEL ASSY	AXW7017

Block Name: 8620 BLOCK(U)

SEMICONDUCTORS

	IC 7601	EM8620L-LFC

MISCELLANEOUS

F	7601,7602 CHIP FERRITE BEAD	ATX1066
X	7601 CRYSTAL(27MHZ)	ASS1218

RESISTORS

R	7646,7647	RS1/16SS1400F
R	7649-7651	RAB4CQ330J
R	7652-7654	RAB4CQ103J
	Other Resistors	RS1/16SS###J

CAPACITORS

C	7601-7609	DCH1201

Mark	No.	Description	Part No.
C	7610,7611		CCSSCH7R0D50
C	7612,7613,7615-7639		CKSSYB104K10

Block Name: 8620 DDR BLOCK(U)

SEMICONDUCTORS

IC	7701,7702		HY5DU561622ETPJC

MISCELLANEOUS

F	7701	CHIP SOLID INDUCTOR	ATL7002

RESISTORS

R	7709,7710		RS1/16SS1001F
R	7711-7718		RAB4CQ560J
Other Resistors			RS1/16SS###J

CAPACITORS

C	7701-7717		CKSSYB104K10
C	7722-7726		DCH1201

Block Name: ETHERNET BLOCK(U)

SEMICONDUCTORS

IC	7751		TC74LCX125FTS1
IC	7753		BR93L46RFJ-W
IC	7754		RTL8100CL-LF
Q	7751		2SB1197K

MISCELLANEOUS

F	7751-7753	CHIP SOLID INDUCTOR	ATL7002
JA	7752	RJ45C ONNECTOR TRNS	AKP1307
X	7751	CRYSTAL(25MHZ)	ASS1219
	7752,7753	SCREW TERMINAL	VNE1949

RESISTORS

R	7753		RS1/16SS5601F
R	7754,7755,7757,7758		RS1/16SS49R9F
Other Resistors			RS1/16SS###J

CAPACITORS

C	7751		BCG1059
C	7754,7755		CCSSCH7R0D50
C	7756,7757		CKSSYB103K25
C	7758,7759,7762		CKSSYB104K10
C	7764-7779		CKSSYB104K10

Block Name: HNM USB BLOCK(U)

SEMICONDUCTORS

IC	7801		VT6212L-G
IC	7803		R5523N001B

MISCELLANEOUS

L	7801	CHOKE COIL	ATH1160
F	7802-7804	CHIP SOLID INDUCTOR	ATL7002
F	7806	CHIP SOLID INDUCTOR	ATL7002
X	7801	CRYSTAL(24MHZ)	ASS1221
CN	7801	PLUG(5P)	KM200NA5LR

RESISTORS

R	7803		RS1/16SS5111F
R	7806		RS1/16SS1021F
R	7827		RS1/10S0R0J
R	7831,7832		RS1/16S0R0J
Other Resistors			RS1/16SS###J

CAPACITORS

C	7801-7803		DCH1201
C	7806,7807		CCSSCH200J50
C	7808		CEHVKW221M10
C	7809-7823		CKSSYB104K10
C	7824		CEHVKW100M16

Block Name: HNM IO BLOCK(U)

SEMICONDUCTORS

IC	7852,7855		TC74LCX04FTS1
IC	7853		NJM2746V
IC	7856		WM8728SEDS
IC	7857		TC74LCX125FTS1
Q	7852-7854,7858		2SA1586

MISCELLANEOUS

F	7851-7858	CHIP FERRITE BEAD	ATX1066
X	7851	CRYSTAL(33MHZ)	ASS1216
CN	7851	FFC CONNECTOR 20P RA	AKM1383

RESISTORS

R	7851		RS1/16SS37R4F
R	7859,7861,7875		RS1/16SS75R0F
R	7876,7886		RS1/16SS1501F
R	7877,7887		RS1/16SS6801F
R	7879,7888		RS1/16SS3301F
R	7880,7893		RS1/16SS5101F
R	7895-7897		RS1/16SS75R0F
Other Resistors			RS1/16SS###J

CAPACITORS

C	7851,7853,7855-7858		CKSSYB104K10
C	7852,7859,7860,7881		DCH1201
C	7861-7863,7865		CKSSYB104K10
C	7868,7871,7872,7874		CCSSCH220J50
C	7875		CKSSYB103K25
C	7876,7877		CCSSCH220J50
C	7880,7884		CCSRCH102J50
C	7882,7886		CCSRCH821J50
C	7883,7885,7887		DCH1201

Block Name: HNM POWER BLOCK(U)

SEMICONDUCTORS

IC	7901		LM2664M6X
IC	7902		NJM2846DL3-25
IC	7903,7904		LTC3412EFE
D	7901,7902		RB051L-40

MISCELLANEOUS

L	7901	INDUCTOR	ATH1206
L	7902	INDUCTOR	ATH1207
F	7901	CHIP BEEDS FILTER	ATX1059
F	7902	CHIP SOLID INDUCTOR	ATL7002
CN	7901	CONNECTOR	AKM1290

Mark	No.	Description	Part No.
RESISTORS			
R	7903,7909		RS1/16SS3093F
R	7904		RS1/16SS6202D
R	7906		RS1/16SS2003D
R	7910		RS1/16SS1503D
R	7912		RS1/16SS7502D
R	7917,7919		RS1/10S0R0J
	Other Resistors		RS1/16SS###J
CAPACITORS			
C	7901		CKSRYB334K10
C	7902		CKSQYF475Z10
C	7903,7906		BCG1059
C	7904		CCSRCH471J50
C	7905,7907		CCSRCH102J50
C	7908		CCSRCH222J50
C	7909		CEHVKW101M6R3
C	7910,7914,7917,7920		CKSSYB104K10
C	7911,7918,7924		CCSSCH101J50
C	7912,7919		BCG1050
C	7913,7915,7916,7926		DCH1201
C	7923		CKSSYB104K10
C	7925		CCSSCH220J50

U PREOUT ASSY

MISCELLANEOUS

IC	3541 (A,131,55)	E-SW IC	TC9163CFG
IC	3542 (A,100,55)	ANALOG SWITCH IC	TC9273CFG-012
IC	3581 (A,99,26)	DUAL OP-AMP	NJM4565M
IC	3601 (A,54,90)	OP-AMP IC	UPC4570G2-A
IC	3631 (A,54,78)	OP-AMP IC	UPC4570G2-A
IC	3661 (A,54,66)	OP-AMP IC	UPC4570G2-A
IC	3691 (A,54,54)	OP-AMP IC	UPC4570G2-A
IC	3721 (A,54,42)	OP-AMP IC	UPC4570G2-A
IC	3781 (A,54,102)	OP-AMP IC	UPC4570G2-A
Q	3581 (A,107,26)	TRANSISTOR	IMX25
Q	3582 (A,110,28)	TRANSISTOR	UMD2N
Q	3583 (A,112,38)	TRANSISTOR	2SK208
Q	3584 (A,112,24)	TRANSISTOR	2SK208
Q	3601 (A,34,85)	TRANSISTOR	IMX25
Q	3602 (A,34,93)	TRANSISTOR	IMX25
Q	3631 (A,34,72)	TRANSISTOR	IMX25
Q	3632 (A,34,78)	TRANSISTOR	IMX25
Q	3661 (A,34,59)	TRANSISTOR	IMX25
Q	3662 (A,34,66)	TRANSISTOR	IMX25
Q	3691 (A,34,47)	TRANSISTOR	IMX25
Q	3692 (A,34,54)	TRANSISTOR	IMX25
Q	3721 (A,34,32)	TRANSISTOR	IMX25
Q	3722 (A,34,39)	TRANSISTOR	IMX25
Q	3781 (A,34,98)	TRANSISTOR	IMX25
Q	3782 (A,34,105)	TRANSISTOR	IMX25
D	3501 (A,112,36)	DIODE	1SS352
D	3502 (A,112,31)	DIODE	1SS352
JA	3501 (A,14,96)	PIN JACK(4P)	AKB7186
JA	3502 (A,14,68)	PIN JACK(4P)	AKB7186
JA	3503 (A,14,40)	PIN JACK(4P)	AKB7186

Mark	No.	Description	Part No.
CN	3511 (A,164,80)	PLUG	CKS1761
CN	3512 (A,164,53)	PLUG	CKS1761
CN	3513 (A,138,19)	11P SOCKET	XKP3076
CN	3515 (A,67,19)	9P SOCKET	XKP3075
CN	3516 (A,110,100)	L-PLUG(15P)	KM200NA15L
CN	3517 (A,150,100)	L-PLUG(15P)	KM200NA15LR
RESISTORS			
R	3541 (A,121,62)		RS1/16S221J
R	3542 (A,124,41)		RS1/16S221J
R	3543 (A,126,41)		RS1/16S221J
R	3544 (B,87,59)		RS1/16S221J
R	3545 (A,89,41)		RS1/16S221J
R	3546 (A,91,41)		RS1/16S221J
R	3580 (A,113,28)		RS1/16S473J
R	3581 (A,112,34)		RS1/16S105J
R	3582 (A,112,33)		RS1/16S105J
R	3583 (A,108,32)		RS1/16S102J
R	3584 (A,105,22)		RS1/16S102J
R	3585 (B,106,31)		RS1/16S103J
R	3586 (A,108,21)		RS1/16S103J
R	3587 (A,102,34)		RS1/16S221J
R	3588 (A,100,18)		RS1/16S221J
R	3589 (A,102,31)		RS1/16S224J
R	3590 (A,100,20)		RS1/16S224J
R	3591 (A,99,34)		RS1/16S562J
R	3592 (A,97,18)		RS1/16S562J
R	3593 (A,99,31)		RS1/16S223J
R	3594 (A,97,21)		RS1/16S223J
⚠ R	3595 (A,79,34)	CARBON FILM RESISTOR	RD1/4MUF330J
⚠ R	3596 (A,79,18)	CARBON FILM RESISTOR	RD1/4MUF330J
R	3597 (B,89,29)		RS1/16S104J
R	3598 (B,89,23)		RS1/16S104J
R	3601 (B,68,86)		RS1/16S474J
R	3602 (B,68,93)		RS1/16S474J
R	3603 (B,66,86)		RS1/16S221J
R	3604 (B,66,93)		RS1/16S221J
R	3605 (B,58,87)		RS1/16S104J
R	3606 (B,58,92)		RS1/16S104J
R	3611 (B,40,85)		RS1/16S474J
R	3612 (B,40,93)		RS1/16S474J
R	3613 (B,38,85)		RS1/16S271J
R	3614 (B,38,93)		RS1/16S271J
R	3615 (A,39,86)		RS1/16S103J
R	3616 (A,29,92)		RS1/16S103J
R	3617 (B,36,85)		RS1/16S121J
R	3618 (B,36,93)		RS1/16S121J
R	3619 (A,29,85)		RS1/16S103J
R	3620 (A,39,93)		RS1/16S103J
R	3621 (B,33,85)		RS1/16S101J
R	3622 (B,33,93)		RS1/16S101J
R	3631 (B,68,75)		RS1/16S474J
R	3632 (B,68,80)		RS1/16S474J
R	3633 (B,66,75)		RS1/16S221J
R	3634 (B,66,80)		RS1/16S221J
R	3635 (B,58,75)		RS1/16S104J
R	3636 (B,58,80)		RS1/16S104J
R	3641 (B,40,72)		RS1/16S474J
R	3642 (B,40,78)		RS1/16S474J

Mark	No.	Description	Part No.
R	3643 (B,38,72)		RS1/16S271J
R	3644 (B,38,78)		RS1/16S271J
R	3645 (A,39,72)		RS1/16S103J
R	3646 (A,29,78)		RS1/16S103J
R	3647 (B,36,72)		RS1/16S121J
R	3648 (B,36,78)		RS1/16S121J
R	3649 (A,29,71)		RS1/16S103J
R	3650 (A,39,79)		RS1/16S103J
R	3651 (B,33,72)		RS1/16S101J
R	3652 (B,33,78)		RS1/16S101J
R	3661 (B,68,63)		RS1/16S474J
R	3662 (B,68,68)		RS1/16S474J
R	3663 (B,66,63)		RS1/16S221J
R	3664 (B,66,68)		RS1/16S221J
R	3665 (B,58,63)		RS1/16S104J
R	3666 (B,58,68)		RS1/16S104J
R	3671 (B,40,59)		RS1/16S474J
R	3672 (B,40,66)		RS1/16S474J
R	3673 (B,38,59)		RS1/16S271J
R	3674 (B,38,66)		RS1/16S271J
R	3675 (A,39,60)		RS1/16S103J
R	3676 (A,39,66)		RS1/16S103J
R	3677 (B,36,59)		RS1/16S121J
R	3678 (B,36,66)		RS1/16S121J
R	3679 (A,29,59)		RS1/16S103J
R	3680 (A,29,65)		RS1/16S103J
R	3681 (B,33,59)		RS1/16S101J
R	3682 (B,33,66)		RS1/16S101J
R	3691 (B,68,51)		RS1/16S474J
R	3692 (B,68,56)		RS1/16S474J
R	3693 (B,66,51)		RS1/16S221J
R	3694 (B,66,56)		RS1/16S221J
R	3695 (B,58,51)		RS1/16S104J
R	3696 (B,58,56)		RS1/16S104J
R	3701 (B,40,47)		RS1/16S474J
R	3702 (B,40,54)		RS1/16S474J
R	3703 (B,38,47)		RS1/16S271J
R	3704 (B,38,54)		RS1/16S271J
R	3705 (A,39,48)		RS1/16S103J
R	3706 (A,39,54)		RS1/16S103J
R	3707 (B,36,47)		RS1/16S121J
R	3708 (B,36,54)		RS1/16S121J
R	3709 (A,29,47)		RS1/16S103J
R	3710 (A,29,53)		RS1/16S103J
R	3711 (B,33,47)		RS1/16S101J
R	3712 (B,33,54)		RS1/16S101J
R	3721 (B,68,39)		RS1/16S474J
R	3722 (B,68,44)		RS1/16S474J
R	3723 (B,66,39)		RS1/16S221J
R	3724 (B,66,44)		RS1/16S221J
R	3725 (B,58,39)		RS1/16S104J
R	3726 (B,58,44)		RS1/16S104J
R	3731 (B,40,32)		RS1/16S474J
R	3732 (B,40,39)		RS1/16S474J
R	3733 (B,38,32)		RS1/16S271J
R	3734 (B,38,39)		RS1/16S271J
R	3735 (A,39,33)		RS1/16S103J
R	3736 (A,39,40)		RS1/16S103J
R	3737 (B,36,32)		RS1/16S121J
R	3738 (B,36,39)		RS1/16S121J
R	3739 (A,29,32)		RS1/16S103J
R	3740 (A,29,39)		RS1/16S103J
R	3741 (B,33,32)		RS1/16S101J
R	3742 (B,33,39)		RS1/16S101J
R	3761 (B,40,20)		RS1/16S0R0J
R	3762 (B,40,27)		RS1/16S0R0J
R	3773 (B,31,20)		RS1/16S0R0J
R	3774 (B,31,27)		RS1/16S0R0J
R	3781 (B,68,99)		RS1/16S474J
R	3782 (B,68,104)		RS1/16S474J
R	3783 (B,66,99)		RS1/16S221J
R	3784 (B,66,104)		RS1/16S221J
R	3785 (B,58,99)		RS1/16S104J
R	3786 (B,58,104)		RS1/16S104J
R	3791 (B,40,98)		RS1/16S474J
R	3792 (B,40,105)		RS1/16S474J
R	3793 (B,38,98)		RS1/16S271J
R	3794 (B,38,105)		RS1/16S271J
R	3795 (A,29,98)		RS1/16S103J
R	3796 (A,29,105)		RS1/16S103J
R	3797 (B,36,98)		RS1/16S121J
R	3798 (B,36,105)		RS1/16S121J
R	3799 (A,39,99)		RS1/16S103J
R	3800 (A,39,106)		RS1/16S103J
R	3801 (B,33,98)		RS1/16S101J
R	3802 (B,33,105)		RS1/16S101J
R	3805 (B,55,86)		RS1/16S0R0J
R	3806 (B,55,92)		RS1/16S0R0J
R	3807 (B,53,86)		RS1/16S0R0J
R	3808 (B,52,92)		RS1/16S0R0J
R	3809 (B,55,74)		RS1/16S0R0J
R	3810 (B,55,80)		RS1/16S0R0J
R	3811 (B,53,74)		RS1/16S0R0J
R	3812 (B,52,80)		RS1/16S0R0J
R	3813 (B,55,62)		RS1/16S0R0J
R	3814 (B,55,68)		RS1/16S0R0J
R	3815 (B,53,62)		RS1/16S0R0J
R	3816 (B,52,68)		RS1/16S0R0J
R	3817 (B,55,50)		RS1/16S0R0J
R	3818 (B,55,56)		RS1/16S0R0J
R	3819 (B,53,50)		RS1/16S0R0J
R	3820 (B,52,56)		RS1/16S0R0J
R	3821 (B,55,38)		RS1/16S0R0J
R	3822 (B,55,44)		RS1/16S0R0J
R	3823 (B,53,38)		RS1/16S0R0J
R	3824 (B,52,44)		RS1/16S0R0J
R	3829 (B,55,98)		RS1/16S0R0J
R	3830 (B,55,104)		RS1/16S0R0J
R	3831 (B,53,98)		RS1/16S0R0J
R	3832 (B,52,104)		RS1/16S0R0J
R	9001 (A,77,95)		RS1/16S0R0J
R	9002 (A,91,95)		RS1/16S0R0J
R	9013 (A,93,95)		RS1/16S0R0J
R	9014 (A,107,95)		RS1/16S0R0J
R	9025 (A,109,95)		RS1/16S0R0J
R	9026 (A,123,95)		RS1/16S0R0J
R	9037 (A,125,95)		RS1/16S0R0J
R	9038 (A,139,95)		RS1/16S0R0J
R	9049 (A,141,95)		RS1/16S0R0J

Mark	No.	Description	Part No.
R	9050 (A,155,95)		RS1/16S0R0J

CAPACITORS

C	3541 (B,124,57)		CCSRCH101J50
C	3545 (B,87,53)		CCSRCH101J50
C	3563 (B,143,53)		CKSRYB103K50
C	3564 (B,142,60)		CKSRYB103K50
C	3565 (B,108,52)		CKSRYB103K50
C	3566 (B,108,58)		CKSRYB103K50
C	3583 (A,105,32)		CKSRYB103K50
C	3584 (A,108,23)		CKSRYB103K50
C	3585 (A,106,32)		CKSRYB105K16
C	3586 (A,104,20)		CKSRYB105K16
C	3587 (A,102,33)		CCSRCH221J50
C	3588 (A,100,21)		CCSRCH221J50
C	3589 (A,92,33)		CEAT470M16
C	3590 (A,92,19)		CEAT470M16
C	3593 (B,101,29)		CKSRYB103K50
C	3594 (B,101,24)		CKSRYB103K50
C	3595 (A,85,34)		CEAT471M16
C	3596 (A,85,18)		CEAT471M16
C	3601 (A,61,87)	ELECT. CAPACITOR	ACH7199
C	3602 (A,61,93)	ELECT. CAPACITOR	ACH7199
C	3603 (B,51,86)		CCSRCH101J50
C	3604 (B,50,92)		CCSRCH101J50
C	3605 (A,51,88)		CKSRYB103K50
C	3606 (A,51,92)		CKSRYB103K50
C	3607 (A,45,85)	ELECT. CAPACITOR	ACH7197
C	3608 (A,45,92)	ELECT. CAPACITOR	ACH7197
C	3609 (A,37,86)		CKSRYB103K50
C	3610 (A,31,92)		CKSRYB103K50
C	3611 (A,31,85)		CKSRYB103K50
C	3612 (A,37,93)		CKSRYB103K50
C	3613 (B,23,88)		CCSRCH221J50
C	3614 (B,23,92)		CCSRCH221J50
C	3631 (A,61,75)	ELECT. CAPACITOR	ACH7199
C	3632 (A,61,81)	ELECT. CAPACITOR	ACH7199
C	3633 (B,51,74)		CCSRCH101J50
C	3634 (B,50,80)		CCSRCH101J50
C	3635 (A,51,76)		CKSRYB103K50
C	3636 (A,51,80)		CKSRYB103K50
C	3637 (A,45,72)	ELECT. CAPACITOR	ACH7197
C	3638 (A,45,79)	ELECT. CAPACITOR	ACH7197
C	3639 (A,37,72)		CKSRYB103K50
C	3640 (A,31,78)		CKSRYB103K50
C	3641 (A,31,71)		CKSRYB103K50
C	3642 (A,37,79)		CKSRYB103K50
C	3643 (B,23,73)		CCSRCH221J50
C	3644 (B,23,77)		CCSRCH221J50
C	3661 (A,61,63)	ELECT. CAPACITOR	ACH7199
C	3662 (A,61,69)	ELECT. CAPACITOR	ACH7199
C	3663 (B,51,62)		CCSRCH101J50
C	3664 (B,50,68)		CCSRCH101J50
C	3665 (A,51,64)		CKSRYB103K50
C	3666 (A,51,68)		CKSRYB103K50
C	3667 (A,45,59)	ELECT. CAPACITOR	ACH7197
C	3668 (A,45,66)	ELECT. CAPACITOR	ACH7197
C	3669 (A,37,60)		CKSRYB103K50
C	3670 (A,37,66)		CKSRYB103K50
C	3671 (A,31,59)		CKSRYB103K50
C	3672 (A,31,65)		CKSRYB103K50
C	3673 (B,23,59)		CCSRCH221J50
C	3674 (B,23,63)		CCSRCH221J50
C	3691 (A,61,51)	ELECT. CAPACITOR	ACH7199
C	3692 (A,61,57)	ELECT. CAPACITOR	ACH7199
C	3693 (B,51,50)		CCSRCH101J50
C	3694 (B,50,56)		CCSRCH101J50
C	3695 (A,51,52)		CKSRYB103K50
C	3696 (A,51,56)		CKSRYB103K50
C	3697 (A,45,46)	ELECT. CAPACITOR	ACH7197
C	3698 (A,45,53)	ELECT. CAPACITOR	ACH7197
C	3699 (A,37,48)		CKSRYB103K50
C	3700 (A,37,54)		CKSRYB103K50
C	3701 (A,31,47)		CKSRYB103K50
C	3702 (A,31,53)		CKSRYB103K50
C	3703 (B,23,45)		CCSRCH221J50
C	3704 (B,23,49)		CCSRCH221J50
C	3721 (A,61,39)	ELECT. CAPACITOR	ACH7199
C	3722 (A,61,45)	ELECT. CAPACITOR	ACH7199
C	3723 (B,51,38)		CCSRCH101J50
C	3724 (B,50,44)		CCSRCH101J50
C	3725 (A,51,40)		CKSRYB103K50
C	3726 (A,51,44)		CKSRYB103K50
C	3727 (A,45,33)	ELECT. CAPACITOR	ACH7197
C	3728 (A,45,39)	ELECT. CAPACITOR	ACH7197
C	3729 (A,37,33)		CKSRYB103K50
C	3730 (A,37,40)		CKSRYB103K50
C	3731 (A,31,32)		CKSRYB103K50
C	3732 (A,31,39)		CKSRYB103K50
C	3733 (B,23,31)		CCSRCH221J50
C	3734 (B,23,35)		CCSRCH221J50
C	3781 (A,61,99)	ELECT. CAPACITOR	ACH7199
C	3782 (A,61,105)	ELECT. CAPACITOR	ACH7199
C	3783 (B,51,98)		CCSRCH101J50
C	3784 (B,50,104)		CCSRCH101J50
C	3785 (A,51,100)		CKSRYB103K50
C	3786 (A,51,104)		CKSRYB103K50
C	3787 (A,45,98)	ELECT. CAPACITOR	ACH7197
C	3788 (A,45,104)	ELECT. CAPACITOR	ACH7197
C	3789 (A,31,98)		CKSRYB103K50
C	3790 (A,31,105)		CKSRYB103K50
C	3791 (A,37,99)		CKSRYB103K50
C	3792 (A,37,106)		CKSRYB103K50
C	3793 (B,23,102)		CCSRCH221J50
C	3794 (B,23,106)		CCSRCH221J50
C	3811 (B,19,93)		CKSRYB103K50
C	3812 (B,21,93)		CKSRYB105K16
C	3813 (B,19,64)		CKSRYB103K50
C	3814 (B,21,64)		CKSRYB105K16
C	3815 (B,19,36)		CKSRYB103K50
C	3816 (B,21,36)		CKSRYB105K16

V MOTHER 1 ASSY

MISCELLANEOUS

IC	8001 (A,82,193)	CPU	PEG290B8
IC	8002 (A,111,198)	EEPROM	BR24L16FV-W

Mark	No.	Description	Part No.
IC	8003 (A,63,192)	RESET IC	BU4828F
IC	8004 (A,89,165)	IC	TC74VHC00FTS1
IC	8021 (A,122,142)	REGULATOR IC	NJM2872BF33
IC	8022 (A,244,144)	REGULATOR IC	NJM2880U1-33
IC	8023 (A,239,133)	REGULATOR IC	NJM2880U1-33
IC	8041 (A,55,201)	IC	TC74VHC08FTS1
IC	8042 (A,55,185)	IC	TC74VHC08FTS1
IC	8052 (A,93,118)	IC	TC74VHCT125AFTS1
IC	8072 (A,60,165)	IC	TC74VHCT125AFTS1
IC	8081 (A,83,173)	IC	TC74VHCT08AFTS1
IC	8082 (A,73,158)	IC	TC74VHC08FTS1
IC	8091 (A,79,117)	IC	TC74VHCT125AFTS1
IC	8092 (A,105,119)	IC	TC74VHCT125AFTS1
IC	8121 (A,67,116)	PORT EXPANDER IC	BU4094BCFV
Q	8031 (A,263,125)	DIGITAL TR(SC-70)	RT1P241M
Q	8033 (A,264,122)	TRANSISTOR	RT1N141M-11
Q	8041 (A,110,174)	DIGITAL TR(SC-70)	RT1N431M
Q	8042 (A,99,166)	TRANSISTOR(SC-70)	2SA1602A
Q	8043 (A,99,160)	TRANSISTOR(SC-70)	2SA1602A
Q	8044 (A,50,182)	DIGITAL TR(SC-70)	RT1P241M
Q	8045 (A,256,125)	TRANSISTOR	RT1N241M
Q	8046 (A,260,132)	TRANSISTOR	2SB1189
Q	8047 (A,256,131)	TRANSISTOR(SC-70)	2SA1602A
Q	8048 (A,64,231)	DIGITAL TR(SC-70)	RT1P241M
Q	8049 (A,62,224)	TRANSISTOR	2SC4081
Q	8050 (A,89,217)	DIGITAL TR(SC-70)	RT1P241M
Q	8051 (A,91,224)	TRANSISTOR	2SC4081
D	8021 (B,245,142)	DIODE	MC2848-11
D	8041 (B,112,179)	DIODE	1SS352
D	8042 (A,258,142)	DIODE	MC2848-11
D	8043 (A,263,142)	DIODE	MC2848-11
D	8044 (A,257,137)	DIODE	MC2848-11
D	8045 (A,255,135)	DIODE	MC2848-11
D	8048 (A,60,228)	DIODE	1SS352
D	8049 (A,88,221)	DIODE	1SS352
KN	8001 (A,191,53)	WRAPPING TERMINAL	VNF1084
X	8001 (A,68,193)	CERAMIC RESONATOR	ASS7087
CN	8001 (A,13,151)	CONNECTOR	CKS1730
CN	8002 (A,13,119)	CONNECTOR	CKS1730
CN	8003 (A,40,210)	PLUG	CKS1725
CN	8004 (A,40,177)	CONNECTOR	CKS1730
CN	8005 (A,40,133)	CONNECTOR	CKS1718
CN	8006 (A,40,66)	CONNECTOR	CKS1730
CN	8007 (A,40,36)	CONNECTOR	CKS1730
CN	8008 (A,40,11)	CONNECTOR	CKS1727
CN	8009 (A,44,238)	19P CONNECTOR	19P-1.25FJ
CN	8010 (A,66,137)	9P PLUG	XKP3064
CN	8011 (A,66,37)	21P PLUG	XKP3070
CN	8012 (A,81,138)	18P CONNECTOR	VKN1504
CN	8014 (A,123,28)	20P CONNECTOR	VKN1610
CN	8015 (A,146,119)	21P PLUG	XKP3070
CN	8016 (A,146,32)	CONNECTOR	CKS1726
CN	8018 (A,170,117)	11P PLUG	XKP3065
CN	8019 (A,170,47)	9P PLUG	XKP3064
CN	8020 (A,199,110)	7P PLUG	XKP3063
CN	8021 (A,219,120)	CONNECTOR	CKS1718
CN	8022 (A,220,74)	23P PLUG	XKP3071
CN	8023 (A,220,38)	23P PLUG	XKP3071
CN	8024 (A,219,31)	CONNECTOR	CKS1721
CN	8025 (A,239,77)	17P PLUG	XKP3068
CN	8026 (A,239,19)	CONNECTOR	CKS1719
CN	8027 (A,272,55)	13P PLUG	XKP3066
CN	8028 (A,272,14)	PLUG	CKS1724
CN	8029 (A,277,150)	19P CONNECTOR	19P-1.25FJ
CN	8030 (A,277,119)	13P CONNECTOR	13P-1.25FJ
CN	8031 (A,277,90)	21P CONNECTOR	21P-1.25FJ
CN	8032 (A,115,211)	10P CONNECTOR	VKN1414
CN	8034 (A,13,89)	CONNECTOR	CKS1716
CN	8035 (A,146,15)	CONNECTOR	CKS1720
	8001 (A,100,231)	PCB BINDER	VEF1040

RESISTORS

R	8001 (A,62,195)		RS1/16S104J
R	8002 (A,65,205)		RS1/16S512J
R	8004 (A,55,175)		RS1/16S101J
R	8005 (B,68,189)		RS1/16S104J
R	8006 (B,79,196)		RS1/16S104J
R	8007 (A,100,188)		RAB4C101J
R	8008 (B,70,189)		RS1/16S104J
R	8009 (A,63,184)		RS1/16S0R0J
R	8010 (A,57,175)		RS1/16S101J
R	8011 (A,64,184)		RS1/16S101J
R	8012 (A,100,202)		RS1/16S471J
R	8013 (A,100,200)		RS1/16S471J
R	8016 (A,67,196)		RS1/16S101J
R	8017 (A,99,163)		RS1/16S152J
R	8018 (A,101,162)		RS1/16S152J
R	8020 (A,50,186)		RS1/16S0R0J
R	8021 (A,57,208)		RS1/16S104J
R	8022 (A,55,207)		RS1/16S104J
R	8023 (A,53,195)		RS1/16S104J
R	8024 (A,55,195)		RS1/16S104J
R	8025 (B,54,182)		RS1/16S104J
R	8026 (B,52,182)		RS1/16S104J
R	8027 (A,55,191)		RS1/16S104J
R	8028 (A,57,191)		RS1/16S104J
R	8029 (B,83,196)		RS1/16S104J
R	8030 (B,81,192)		RS1/16S101J
R	8031 (A,265,130)		RS1/16S104J
R	8032 (B,105,151)		RS1/16S104J
R	8033 (B,88,189)		RS1/16S104J
R	8034 (B,82,167)		RS1/16S104J
R	8035 (B,266,127)		RS1/16S0R0J
R	8037 (A,93,210)		RAB4C101J
R	8038 (A,79,216)		RAB4C101J
R	8039 (B,88,226)		RS1/16S0R0J
R	8040 (A,125,140)		RS1/16S0R0J
R	8041 (A,99,156)		RS1/16S224J
R	8042 (A,97,154)		RS1/16S563J
R	8043 (A,99,154)		RS1/16S0R0J
R	8044 (A,110,166)		RS1/16S104J
R	8045 (A,115,198)		RS1/16S104J
R	8046 (B,110,179)		RS1/16S471J
R	8047 (A,108,166)		RS1/16S104J
R	8048 (A,50,179)		RS1/16S224J
R	8049 (A,49,174)		RS1/16S563J
R	8050 (A,50,176)		RS1/16S0R0J
R	8051 (A,70,217)		RAB4C101J

Mark	No.	Description	Part No.
R	8052	(A,64,212)	RAB4C101J
R	8053	(A,72,214)	RS1/16S101J
R	8056	(A,64,203)	RS1/16S101J
R	8057	(A,64,202)	RS1/16S101J
R	8058	(A,76,167)	RS1/16S101J
R	8059	(A,86,132)	RS1/16S104J
R	8060	(A,76,132)	RS1/16S104J
R	8061	(A,86,144)	RS1/16S104J
R	8062	(A,79,144)	RS1/16S104J
R	8063	(A,21,224)	RS1/16S104J
R	8064	(A,32,221)	RS1/16S104J
R	8067	(A,64,163)	RS1/16S104J
R	8068	(A,32,220)	RS1/16S104J
R	8069	(A,25,210)	RS1/16S104J
R	8071	(A,61,177)	RAB4C101J
R	8072	(A,64,173)	RAB4C101J
R	8075	(B,70,180)	RS1/16S104J
R	8076	(B,69,175)	RS1/16S222J
R	8079	(A,69,229)	RS1/16S0R0J
R	8080	(A,153,97)	RS1/16S104J
R	8081	(A,78,180)	RAB4C101J
R	8082	(A,83,180)	RAB4C101J
R	8084	(A,66,227)	RS1/16S473J
R	8085	(B,85,194)	RS1/16S104J
R	8086	(B,90,189)	RS1/16S104J
R	8087	(A,153,100)	RS1/16S104J
R	8088	(A,65,223)	RS1/16S104J
R	8089	(B,269,104)	RS1/16S104J
R	8090	(A,271,88)	RS1/16S104J
R	8091	(A,71,169)	RS1/16S101J
R	8092	(A,107,112)	RS1/16S104J
R	8093	(A,103,112)	RS1/16S104J
R	8095	(A,271,133)	RS1/16S474J
R	8097	(A,153,114)	RS1/16S104J
R	8098	(A,153,112)	RS1/16S104J
R	8102	(A,102,195)	RAB4C101J
R	8103	(A,102,198)	RS1/16S101J
R	8104	(A,102,192)	RS1/16S101J
R	8106	(A,64,227)	RS1/16S104J
R	8107	(A,86,218)	RS1/16S104J
R	8111	(A,90,177)	RS1/16S104J
R	8112	(B,71,218)	RS1/16S104J
R	8113	(A,72,172)	RS1/16S104J
R	8117	(A,177,11)	RS1/16S0R0J
R	8118	(B,179,11)	RS1/16S0R0J
R	8119	(A,91,214)	RS1/16S473J
R	8120	(A,92,217)	RS1/16S104J
R	8121	(B,123,97)	RS1/16S473J
R	8122	(B,125,97)	RS1/16S473J
R	8123	(B,127,97)	RS1/16S473J
R	8124	(B,129,97)	RS1/16S473J
R	8125	(B,123,101)	RS1/16S473J
R	8126	(B,125,101)	RS1/16S473J
R	8127	(B,127,101)	RS1/16S473J
R	8128	(B,35,136)	RS1/16S474J
R	8129	(B,33,136)	RS1/16S224J
R	8130	(B,33,142)	RS1/16S104J
R	8131	(B,35,142)	RS1/16S224J
R	8132	(A,58,134)	RS1/16S473J

Mark	No.	Description	Part No.
R	8141	(A,104,174)	RS1/16S152J
R	8142	(A,107,174)	RS1/16S152J
R	8143	(A,106,174)	RS1/16S473J
R	8144	(A,69,154)	RS1/16S104J
R	8145	(A,271,109)	RS1/16S104J
R	8146	(A,271,113)	RS1/16S104J
R	8147	(A,73,164)	RS1/16S224J
R	8148	(A,96,184)	RS1/16S101J
R	8151	(A,74,217)	RS1/16S104J
R	8153	(A,76,217)	RS1/16S104J
R	8155	(B,89,210)	RS1/16S104J
R	8156	(B,84,206)	RS1/16S104J
R	8157	(B,80,206)	RS1/16S104J
R	8158	(B,88,215)	RS1/16S104J
R	8159	(A,74,179)	RS1/16S104J
R	8165	(B,78,215)	RS1/16S104J
R	8201	(B,29,195)	RS1/16S0R0J
R	8202	(B,29,193)	RS1/16S0R0J
R	8203	(B,29,191)	RS1/16S0R0J
R	8204	(B,29,189)	RS1/16S0R0J
R	8205	(B,29,187)	RS1/16S0R0J
R	8206	(B,29,185)	RS1/16S0R0J
R	8207	(B,29,183)	RS1/16S0R0J
R	8208	(B,29,181)	RS1/16S0R0J
R	8209	(B,29,180)	RS1/16S0R0J
R	8210	(B,29,178)	RS1/16S0R0J
R	8214	(A,130,20)	RS1/16S0R0J
R	8215	(A,175,16)	RS1/16S0R0J
R	8216	(B,256,69)	RS1/16S0R0J
R	8217	(A,148,12)	RS1/16S0R0J
R	8218	(A,205,13)	RS1/16S0R0J
R	8219	(A,239,13)	RS1/16S0R0J
R	8220	(A,256,56)	RS1/16S0R0J
R	8221	(A,106,39)	RS1/16S0R0J
R	8222	(A,108,39)	RS1/16S0R0J
R	8223	(A,109,39)	RS1/16S0R0J
R	8224	(A,111,39)	RS1/16S0R0J
R	8252	(A,130,29)	RS1/16S0R0J
R	8253	(A,105,200)	RS1/16S103J
R	8254	(A,105,202)	RS1/16S472J
R	8255	(A,260,128)	RS1/16S101J
R	8256	(A,264,134)	RS1/16S103J
R	8257	(A,256,128)	RS1/16S272J
R	8258	(A,241,138)	RS1/16S0R0J
R	8259	(A,243,141)	RS1/16S0R0J
R	8901	(B,66,184)	RS1/16S183J

CAPACITORS

C	8001	(A,61,192)	CKSRYB105K10
C	8002	(A,73,207)	CKSRYB104K16
C	8003	(A,97,184)	CKSRYB103K50
C	8004	(A,66,190)	CKSRYB104K16
C	8006	(B,81,196)	CKSRYB472K50
C	8008	(A,97,192)	CKSRYB104K16
C	8009	(B,59,184)	CKSRYB103K50
C	8010	(B,61,184)	CKSRYB103K50
C	8014	(A,108,199)	CKSRYB104K16
C	8016	(B,77,204)	CKSRYB103K50
C	8017	(B,82,206)	CKSRYB103K50

Mark	No.	Description	Part No.
C	8018 (B,86,206)		CKSRYB103K50
C	8019 (A,82,217)		CKSRYB103K50
C	8020 (B,86,220)		CKSRYB103K50
C	8022 (A,250,128)	ELECT. CAPACITOR	CEAT102M16
C	8024 (A,121,136)		CKSRYB104K16
C	8025 (A,125,143)		CKSRYB104K16
C	8026 (A,122,145)		CKSRYB104K16
C	8042 (A,112,183)	ELECT. CAPACITOR	CEAT682M6R3
C	8043 (A,59,200)		CKSRYB104K16
C	8044 (A,59,185)		CKSRYB104K16
C	8045 (A,85,165)		CKSRYB104K16
C	8048 (A,102,156)		CKSRYB104K16
C	8049 (A,50,190)		CKSRYB104K16
C	8053 (A,89,118)		CKSRYB104K16
C	8071 (A,57,165)		CKSRYB104K16
C	8081 (A,79,170)		CKSRYB104K16
C	8082 (A,69,156)		CKSRYB104K16
C	8092 (A,75,118)		CKSRYB104K16
C	8093 (A,101,119)		CKSRYB104K16
C	8121 (A,60,117)		CKSRYB104K16
C	8202 (A,32,210)		CKSRYB104K16
C	8203 (B,70,32)		CKSRYB104K16
C	8205 (B,45,35)		CKSRYB104K16
C	8207 (B,131,27)		CKSRYB104K16
C	8208 (B,264,15)		CKSRYB104K16
C	8209 (B,264,22)		CKSRYB104K16
C	8215 (A,250,116)	ELECT. CAPACITOR	CEAT102M16
C	8216 (A,240,129)		CKSRYB104K16
C	8217 (A,238,138)		CKSRYB104K16
C	8218 (A,237,129)		CKSRYB104K16
C	8219 (A,239,142)		CKSRYB104K16
C	8220 (A,246,148)		CKSRYB104K16
C	8221 (A,239,145)		CKSRYB104K16
C	8222 (B,70,36)		CKSRYB104K16

W ICE INTERFACE ASSY

MISCELLANEOUS

IC	8303 (A,292,31)	PORT EXPANDER IC	BU4094BCFV
IC	8304 (A,280,31)	IC	TC74VHCT08AFTS1
IC	8305 (A,292,45)	PORT EXPANDER IC	BU4094BCFV
IC	8306 (A,300,57)	IC	TC74VHCT08AFTS1
IC	8307 (A,280,57)	IC	TC74VHCT08AFTS1
IC	8308 (A,277,73)	IC	TC74VHCT08AFTS1
IC	8309 (A,280,45)	IC	TC74VHCT08AFTS1
KN	8301 (A,317,20)	WRAPPING TERMINAL	VNF1084
CN	8301 (A,257,39)	24P CONNECTOR	RKN1065
CN	8302 (A,260,68)	L-PLUG(7P)	KM200NA7L
CN	8304 (A,277,9)	19P CONNECTOR	19R-1.25FJ
	8304 (A,257,76)	PCB BINDER	VEF1040

RESISTORS

R	8305 (B,296,29)		RS1/16S104J
R	8306 (B,290,29)		RS1/16S104J
R	8307 (B,287,29)		RS1/16S104J
R	8308 (A,297,31)		RS1/16S224J
R	8309 (A,263,34)		RS1/16S0R0J
R	8310 (A,266,35)		RS1/16S0R0J
R	8311 (A,263,36)		RS1/16S0R0J
R	8312 (A,266,37)		RS1/16S0R0J
R	8313 (A,263,38)		RS1/16S0R0J
R	8314 (A,263,42)		RS1/16S0R0J
R	8315 (A,266,43)		RS1/16S0R0J
R	8316 (A,263,44)		RS1/16S0R0J
R	8317 (A,266,45)		RS1/16S0R0J
R	8318 (A,263,46)		RS1/16S0R0J
R	8319 (A,264,53)		RS1/16S0R0J
R	8320 (A,263,50)		RS1/16S0R0J
R	8321 (A,263,49)		RS1/16S0R0J
R	8322 (A,266,41)		RS1/16S0R0J
R	8328 (A,266,31)		RS1/16S101J
R	8333 (A,263,32)		RS1/16S101J
R	8334 (A,263,30)		RS1/16S101J
R	8335 (A,263,40)		RS1/16S101J
R	8336 (A,266,33)		RS1/16S101J
R	8337 (A,266,29)		RS1/16S101J
R	8338 (A,264,27)		RS1/16S0R0J
R	8340 (B,304,18)		RS1/16S0R0J
R	8341 (B,283,29)		RS1/16S104J
R	8342 (B,283,27)		RS1/16S104J
R	8343 (A,290,22)		RS1/16S104J
R	8344 (A,288,22)		RS1/16S104J
R	8345 (A,285,37)		RS1/16S104J
R	8347 (A,285,39)		RS1/16S104J
R	8348 (A,285,54)		RS1/16S104J
R	8349 (B,291,50)		RS1/16S104J
R	8350 (B,286,50)		RS1/16S104J
R	8351 (A,288,53)		RS1/16S104J
R	8352 (B,292,50)		RS1/16S104J
R	8353 (A,312,68)		RS1/16S0R0J
R	8354 (A,310,68)		RS1/16S0R0J
R	8355 (A,309,68)		RS1/16S0R0J
R	8358 (A,306,76)		RS1/16S0R0J
R	8359 (A,313,85)		RS1/16S0R0J
R	8360 (A,312,85)		RS1/16S0R0J
R	8361 (A,309,86)		RS1/16S0R0J
R	8364 (A,305,86)		RS1/16S0R0J
R	8370 (A,273,66)		RS1/16S0R0J
R	8371 (B,279,34)		RS1/16S0R0J
R	8372 (B,267,62)		RS1/16S0R0J
R	8378 (A,281,74)		RS1/16S104J
R	8380 (A,266,62)		RS1/16S0R0J
R	8381 (A,314,55)		RS1/16S0R0J
R	8382 (A,312,56)		RS1/16S0R0J
R	8383 (A,311,56)		RS1/16S0R0J
R	8386 (A,307,60)		RS1/16S0R0J
R	8393 (A,304,36)		RS1/16S0R0J
R	8394 (A,310,39)		RS1/16S0R0J
R	8395 (A,308,40)		RS1/16S0R0J
R	8397 (A,308,42)		RS1/16S0R0J
R	8398 (A,305,44)		RS1/16S0R0J
R	8402 (A,265,47)		RS1/16S0R0J
R	8405 (A,281,77)		RS1/16S0R0J
R	8406 (A,298,50)		RS1/16S0R0J
R	8407 (A,300,50)		RS1/16S0R0J
R	8408 (A,304,54)		RS1/16S0R0J
R	8409 (A,304,58)		RS1/16S0R0J
R	8410 (B,278,50)		RS1/16S0R0J

Mark	No.	Description	Part No.
R	8411 (A,284,54)		RS1/16S0R0J
R	8412 (A,285,57)		RS1/16S0R0J
R	8413 (A,284,57)		RS1/16S0R0J
R	8414 (A,287,28)		RS1/16S0R0J
R	8415 (B,292,29)		RS1/16S0R0J
R	8416 (B,294,29)		RS1/16S0R0J
R	8417 (A,297,33)		RS1/16S0R0J
R	8418 (B,293,44)		RS1/16S0R0J
R	8419 (A,294,39)		RS1/16S0R0J
R	8420 (B,294,40)		RS1/16S0R0J
R	8421 (A,296,45)		RS1/16S0R0J
R	8422 (A,286,41)		RS1/16S0R0J
R	8423 (A,284,41)		RS1/16S0R0J
R	8424 (A,285,49)		RS1/16S0R0J
R	8425 (A,285,48)		RS1/16S0R0J
R	8426 (A,285,24)		RS1/16S0R0J
R	8427 (A,285,22)		RS1/16S0R0J
R	8428 (A,284,32)		RS1/16S0R0J
R	8429 (A,284,28)		RS1/16S0R0J
R	8430 (A,309,53)		RS1/16S0R0J
R	8431 (A,308,72)		RS1/16S0R0J
R	8432 (A,309,84)		RS1/16S0R0J
R	8498		RS1/16S0R0J
R	8499		RS1/16S0R0J

CAPACITORS

C	8303 (A,273,74)		CKSRYB104K16
C	8304 (A,276,32)		CKSRYB104K16
C	8305 (A,276,58)		CKSRYB104K16
C	8306 (A,296,58)		CKSRYB104K16
C	8307 (A,288,31)		CKSRYB104K16
C	8308 (A,288,45)		CKSRYB104K16
C	8309 (A,276,46)		CKSRYB104K16
C	8325 (A,306,34)		CEAL100M16

X COMPOSITE ASSY

MISCELLANEOUS

IC	2001 (A,254,121)	MULTIPLEXER(8CH*1)	TC74LVX4051FT
IC	2002 (A,274,124)	MULTIPLEXER(8CH*1)	TC74LVX4051FT
IC	2003 (A,235,124)	MULTIPLEXER(8CH*1)	TC74LVX4051FT
IC	2005 (A,254,138)	MULTIPLEXER(4CH*2)	TC74LVX4052FT
IC	2006 (A,293,138)	MULTIPLEXER(4CH*2)	TC74LVX4052FT
IC	2007 (A,274,140)	MULTIPLEXER(4CH*2)	TC74LVX4052FT
IC	2008 (A,291,162)	MULTIPLEXER(4CH*2)	TC74LVX4052FT
IC	2009 (A,237,140)	MULTIPLEXER(4CH*2)	TC74LVX4052FT
IC	2010 (A,213,148)	LOGIC IC	TC74HC4052AFT
IC	2011 (A,219,131)	VIDEO SW IC	NJM2279M
IC	2012 (A,256,193)	LOGIC IC	TC4094BFN
IC	2013 (A,274,192)	LOGIC IC	TC4094BFN
IC	2014 (A,239,193)	LOGIC IC	TC4094BFN
IC	2015 (A,292,193)	LOGIC IC	TC4094BFN
IC	2016 (B,296,232)	CHARACTER GENERATOR	PDC162A
IC	2017 (B,257,232)	CHARACTER GENERATOR	PDC162A
IC	2018 (A,232,226)	LOGIC IC	TC74VHCT32AFT
IC	2019 (A,232,217)	LOGIC IC	TC74VHCT32AFT
Q	2025 (A,207,160)	TRANSISTOR	2SA1576A
Q	2026 (A,207,163)	TRANSISTOR	2SA1576A
Q	2030 (A,259,161)	TRANSISTOR	2SA1576A
Q	2031 (A,262,161)	TRANSISTOR	2SA1576A
Q	2035 (A,280,164)	TRANSISTOR	2SC4081
Q	2040 (A,252,163)	TRANSISTOR	2SC4081
Q	2045 (A,271,163)	TRANSISTOR	2SC4081
Q	2050 (A,229,163)	TRANSISTOR	2SC4081
Q	2055 (A,243,165)	TRANSISTOR	2SC4081
Q	2060 (A,295,115)	TRANSISTOR	2SC4081
Q	2101 (B,285,221)	TRANSISTOR	2SC4081
Q	2102 (B,247,219)	TRANSISTOR	2SC4081
Q	2151 (A,312,112)	TRANSISTOR	2SC4081
Q	2152 (A,313,117)	TRANSISTOR	2SA1576A
L	2101 (A,292,216)	AXIAL INDUCTOR	LAU330J
L	2102 (A,253,216)	AXIAL INDUCTOR	LAU330J
L	2103 (A,315,220)	CHIP SOLID INDUCTOR	QTL1013
L	2104 (A,313,220)	CHIP SOLID INDUCTOR	QTL1013
L	2105 (A,277,222)	CHIP SOLID INDUCTOR	QTL1013
L	2106 (A,275,222)	CHIP SOLID INDUCTOR	QTL1013
JA	2001 (A,202,92)	JACK	VKB1156
JA	2002 (A,223,92)	2P RCA PINJACK	AKB7187
JA	2003 (A,251,92)	2P RCA PINJACK	AKB7187
JA	2004 (A,279,92)	2P RCA PINJACK	AKB7187
JA	2005 (A,307,92)	2P RCA PINJACK	AKB7187
X	2101 (A,305,221)	CRYSTAL RESONATOR	ASS7080
X	2102 (A,266,221)	CRYSTAL RESONATOR	ASS7080
CN	2001 (A,207,211)	24P CONNECTOR	RKN1065
CN	2002 (A,315,128)	23P SOCKET	XKP3083
CN	2003 (A,315,166)	23P SOCKET	XKP3083
CN	2004 (A,237,236)	CONNECTOR	CKS3370
CN	2005 (A,224,235)	PLUG(4P)	KM200NA4
	2001 (A,205,239)	PCB BINDER	VEF1040

RESISTORS

R	2001 (B,215,101)	CHIP RESISTOR	RS1/16S75R0F
R	2002 (B,243,101)	CHIP RESISTOR	RS1/16S75R0F
R	2003 (B,257,101)	CHIP RESISTOR	RS1/16S75R0F
R	2004 (B,271,101)	CHIP RESISTOR	RS1/16S75R0F
R	2005 (B,285,101)	CHIP RESISTOR	RS1/16S75R0F
R	2006 (B,299,101)	CHIP RESISTOR	RS1/16S75R0F
R	2007 (B,313,101)	CHIP RESISTOR	RS1/16S75R0F
R	2008 (A,282,127)		RS1/16S0R0J
R	2009 (A,244,141)		RS1/16S0R0J
R	2020 (B,217,168)		RS1/16S473J
R	2025 (A,206,156)		RS1/16S184J
R	2026 (A,207,154)		RS1/16S114J
R	2028 (A,209,166)		RS1/16S471J
R	2030 (B,259,165)		RS1/16S184J
R	2031 (B,262,156)		RS1/16S114J
R	2033 (A,265,163)		RS1/16S471J
R	2035 (B,282,160)		RS1/16S0R0J
R	2036 (B,281,156)		RS1/16S472J
R	2037 (B,282,165)		RS1/16S0R0J
R	2038 (A,281,161)		RS1/16S472J
R	2039 (B,279,160)		RS1/16S472J
R	2040 (B,252,161)		RS1/16S0R0J
R	2041 (B,252,157)		RS1/16S103J
R	2042 (B,252,167)		RS1/16S0R0J
R	2043 (A,252,160)		RS1/16S472J
R	2045 (B,271,159)		RS1/16S0R0J
R	2046 (B,271,155)		RS1/16S103J

Mark	No.	Description	Part No.
R	2047 (B,273,171)		RS1/16S0R0J
R	2048 (A,271,161)		RS1/16S472J
R	2050 (B,239,170)		RS1/16S0R0J
R	2051 (B,241,170)		RS1/16S103J
R	2052 (A,229,169)		RS1/16S0R0J
R	2053 (A,229,160)		RS1/16S472J
R	2055 (B,240,159)		RS1/16S0R0J
R	2056 (B,240,155)		RS1/16S103J
R	2057 (B,242,165)		RS1/16S0R0J
R	2058 (A,243,160)		RS1/16S472J
R	2060 (A,296,111)		RS1/16S0R0J
R	2061 (A,294,111)		RS1/16S103J
R	2062 (A,298,115)		RS1/16S0R0J
R	2063 (A,300,112)		RS1/16S472J
R	2065 (A,303,122)		RS1/16S0R0J
R	2070 (A,197,123)	CHIP RESISTOR	RS1/16S75R0F
R	2071 (B,223,116)	CHIP RESISTOR	RS1/16S75R0F
R	2073 (A,258,164)		RS1/16S102J
R	2074 (A,261,164)		RS1/16S100J
R	2075 (B,261,167)		RS1/16S330J
R	2076 (A,208,158)		RS1/16S102J
R	2077 (A,210,160)		RS1/16S100J
R	2078 (A,210,163)		RS1/16S330J
R	2092 (A,212,195)		RS1/16S0R0J
R	2101 (A,306,229)		RS1/16S0R0J
R	2102 (A,305,236)		RS1/16S0R0J
R	2105 (A,302,238)		RS1/16S102J
R	2106 (B,284,235)		RS1/16S562J
R	2107 (B,281,235)		RS1/16S392J
R	2108 (B,283,216)		RS1/16S102J
R	2110 (A,282,235)		RS1/16S101J
R	2111 (A,283,235)		RS1/16S101J
R	2112 (A,285,235)		RS1/16S101J
R	2115 (A,237,220)		RS1/16S101J
R	2116 (A,225,220)		RS1/16S101J
R	2117 (B,225,217)		RS1/16S101J
R	2121 (A,267,229)		RS1/16S0R0J
R	2122 (A,266,236)		RS1/16S0R0J
R	2124 (A,263,238)		RS1/16S102J
R	2125 (B,246,232)		RS1/16S562J
R	2126 (B,244,232)		RS1/16S392J
R	2127 (B,248,213)		RS1/16S102J
R	2129 (A,247,229)		RS1/16S101J
R	2130 (A,247,231)		RS1/16S101J
R	2131 (A,247,233)		RS1/16S101J
R	2135 (A,239,225)		RS1/16S101J
R	2136 (A,238,227)		RS1/16S101J
R	2137 (A,225,226)		RS1/16S101J
R	2138 (B,232,232)		RS1/16S101J
R	2140 (A,248,194)		RS1/16S473J
R	2141 (A,248,193)		RS1/16S473J
R	2142 (A,248,191)		RS1/16S473J
R	2143 (A,248,190)		RS1/16S473J
R	2144 (A,264,196)		RS1/16S473J
R	2145 (B,255,191)		RS1/16S473J
R	2146 (B,257,191)		RS1/16S473J
R	2147 (A,265,194)		RS1/16S473J
R	2148 (A,265,193)		RS1/16S473J
R	2149 (A,265,191)		RS1/16S473J

Mark	No.	Description	Part No.
R	2150 (A,265,190)		RS1/16S473J
R	2151 (A,283,199)		RS1/16S473J
R	2152 (A,283,197)		RS1/16S473J
R	2153 (A,283,196)		RS1/16S473J
R	2154 (A,230,192)		RS1/16S473J
R	2155 (A,230,191)		RS1/16S473J
R	2156 (A,230,189)		RS1/16S473J
R	2157 (A,230,188)		RS1/16S473J
R	2158 (A,246,196)		RS1/16S473J
R	2159 (B,240,187)		RS1/16S473J
R	2160 (B,238,187)		RS1/16S473J
R	2161 (A,283,194)		RS1/16S473J
R	2162 (A,283,192)		RS1/16S473J
R	2163 (A,283,191)		RS1/16S473J
R	2165 (A,299,193)		RS1/16S473J
R	2166 (A,301,193)		RS1/16S473J
R	2167 (A,280,192)		RS1/16S473J
R	2170 (B,306,152)		RS1/16S0R0J
R	2171 (B,309,158)		RS1/16S0R0J
R	2177 (A,316,114)		RS1/16S153J
R	2178 (A,315,111)		RS1/16S333J
R	2179 (A,315,117)		RS1/16S153J
R	2180 (A,315,121)		RS1/16S333J
R	2181 (A,316,113)		RS1/16S0R0J
R	2182 (A,313,121)		RS1/16S0R0J
R	2183 (A,214,213)		RS1/16S101J
R	2184 (A,227,200)		RS1/16S101J
R	2185 (A,224,202)		RS1/16S101J
R	2186 (A,213,214)		RS1/16S101J
R	2187 (A,250,213)		RS1/16S0R0J
R	2188 (A,242,232)		RS1/10S0R0J
R	2189 (B,252,184)		RS1/16S0R0J
R	2190 (B,260,183)		RS1/16S0R0J
R	2191 (B,270,183)		RS1/16S0R0J
R	2192 (B,278,183)		RS1/16S0R0J
R	2193 (B,293,181)		RS1/16S0R0J
R	2194 (B,297,181)		RS1/16S0R0J

CAPACITORS

C	2001 (A,254,117)		CKSRYB104K16
C	2002 (A,257,125)		CKSRYB104K16
C	2003 (A,274,119)		CKSRYB104K16
C	2004 (A,278,127)		CKSRYB104K16
C	2005 (A,235,120)		CKSRYB104K16
C	2006 (A,239,128)		CKSRYB104K16
C	2009 (A,254,134)		CKSRYB104K16
C	2010 (A,257,143)		CKSRYB104K16
C	2011 (A,273,136)		CKSRYB104K16
C	2012 (A,278,144)		CKSRYB104K16
C	2013 (A,237,136)		CKSRYB104K16
C	2014 (A,241,144)		CKSRYB104K16
C	2015 (A,293,134)		CKSRYB104K16
C	2016 (A,293,143)		CKSRYB104K16
C	2017 (A,290,158)		CKSRYB104K16
C	2018 (A,296,165)		CKSRYB104K16
C	2020 (A,212,144)		CKSRYB104K16
C	2021 (A,215,152)		CKSRYB104K16
C	2022 (A,232,222)		CKSRYB103K50
C	2023 (A,231,214)		CKSRYB103K50

Mark	No.	Description	Part No.
C	2025 (A,207,151)		CKSRYB103K50
C	2026 (A,212,152)		CKSRYB103K50
C	2027 (A,216,157)		CEAT221M10
C	2030 (A,265,160)		CKSRYB103K50
C	2031 (A,263,159)		CKSRYB103K50
C	2032 (A,259,157)		CEAT221M10
C	2035 (A,282,164)		CKSRYB103K50
C	2036 (A,281,159)		CKSRYB103K50
C	2037 (A,277,157)		CEAT221M10
C	2040 (A,255,164)		CKSRYB103K50
C	2041 (A,253,157)		CKSRYB103K50
C	2042 (A,248,159)		CEAT331M10
C	2045 (A,273,163)		CKSRYB103K50
C	2046 (A,272,159)		CKSRYB103K50
C	2047 (A,268,157)		CEAT331M10
C	2050 (A,232,167)		CKSRYB103K50
C	2051 (A,229,159)		CKSRYB103K50
C	2052 (A,237,166)		CEAT221M10
C	2055 (A,246,165)		CKSRYB103K50
C	2056 (A,243,159)		CKSRYB103K50
C	2057 (A,237,159)		CEAT221M10
C	2060 (A,292,113)		CKSRYB103K50
C	2061 (A,300,110)		CKSRYB103K50
C	2062 (A,303,115)		CEAT221M10
C	2070 (A,218,137)		CKSRYB103K50
C	2071 (A,217,124)		CKSRYB103K50
C	2072 (A,201,127)		CEAT101M10
C	2073 (A,208,127)		CEAT101M10
C	2074 (A,222,138)		CEAT101M10
C	2075 (A,211,114)	ELECT. CAPACITOR	CEAT102M6R3
C	2076 (A,220,114)	ELECT. CAPACITOR	CEAT102M6R3
C	2077 (A,199,123)		CCSRCH101J50
C	2078 (B,225,116)		CCSRCH101J50
C	2090 (A,206,192)	ELECTROLYTIC CAPACIT	ACH7298
C	2091 (A,216,191)	ELECTROLYTIC CAPACIT	ACH7298
C	2092 (B,211,189)		CKSRYB104K16
C	2093 (B,217,188)		CKSRYB104K16
C	2095 (A,217,206)		CEAT331M10
C	2096 (A,218,199)		CEAT331M10
C	2101 (A,312,226)	ELECTROLYTIC CAPACIT	ACH7278
C	2102 (A,311,234)	ELECTROLYTIC CAPACIT	ACH7278
C	2103 (B,306,231)		CKSRYB473K25
C	2104 (A,311,215)		CCSRCH471J50
C	2105 (B,303,217)		CCSRCH5R0C50
C	2106 (B,299,217)		CCSRCH5R0C50
C	2107 (A,298,226)		CCSRCH240J50
C	2108 (A,296,226)		CCSRCH240J50
C	2109 (A,293,227)		CCSRCH331J50
C	2110 (A,291,227)		CCSRCH331J50
C	2111 (A,290,227)		CCSRCH331J50
C	2112 (A,302,236)		CCSRCH101J50
C	2113 (A,297,236)		CKSRYB122K50
C	2114 (A,293,236)		CKSRYB122K50
C	2116 (B,283,227)		CKSRYB103K50
C	2117 (B,285,227)		CKSRYB473K25
C	2118 (A,281,220)		CEAT101M10
C	2120 (A,273,226)	ELECTROLYTIC CAPACIT	ACH7278
C	2121 (A,272,233)	ELECTROLYTIC CAPACIT	ACH7278
C	2122 (B,267,231)		CKSRYB473K25
C	2123 (A,273,216)		CCSRCH471J50
C	2124 (B,264,217)		CCSRCH5R0C50
C	2125 (B,259,217)		CCSRCH5R0C50
C	2126 (A,258,226)		CCSRCH240J50
C	2127 (A,257,226)		CCSRCH240J50
C	2128 (A,251,225)		CCSRCH331J50
C	2129 (A,250,225)		CCSRCH331J50
C	2130 (A,248,225)		CCSRCH331J50
C	2131 (A,263,237)		CCSRCH101J50
C	2132 (A,258,237)		CKSRYB122K50
C	2133 (A,253,237)		CKSRYB122K50
C	2135 (B,244,227)		CKSRYB103K50
C	2136 (B,248,230)		CKSRYB473K25
C	2137 (A,243,220)		CEAT101M10
C	2138 (A,313,215)		CKSRYB103K50
C	2139 (A,273,214)		CKSRYB103K50
C	2140 (A,256,199)		CKSRYB103K50
C	2141 (A,274,199)		CKSRYB103K50
C	2142 (A,240,199)		CKSRYB103K50
C	2143 (A,292,200)		CKSRYB103K50
C	2144 (B,308,227)		CKSRYB102K50
C	2145 (B,269,227)		CKSRYB102K50
C	2173 (A,316,111)		CKSRYB224K16
C	2174 (A,315,120)		CKSRYB224K16

Y S-VIDEO ASSY

MISCELLANEOUS

IC	2201 (A,94,61)	LOGIC IC	TC74HC4052AF
IC	2202 (A,111,61)	LOGIC IC	TC74HC4052AF
IC	2203 (A,76,61)	LOGIC IC	TC74HC4052AF
IC	2204 (A,129,61)	LOGIC IC	TC74HC4053AF
IC	2208 (A,129,48)	OP AMP	EL5260IYZ
IC	2209 (B,69,40)	VIDEO SW IC	NJM2279M
IC	2210 (B,86,40)	VIDEO SW IC	NJM2279M
IC	2211 (A,155,43)	OP AMP	EL5260IYZ
IC	2212 (B,144,106)	LOGIC IC	TC4094BFN
IC	2213 (B,144,89)	LOGIC IC	TC4094BFN
IC	2301 (A,103,84)	IC	NJM12904V
Q	2201 (A,89,76)	TRANSISTOR	2SC4081
Q	2202 (A,98,73)	TRANSISTOR	2SC4081
Q	2203 (A,105,76)	TRANSISTOR	2SC4081
Q	2204 (A,115,75)	TRANSISTOR	2SC4081
Q	2330 (A,113,85)	TRANSISTOR	2SC4081
Q	2331 (A,98,99)	TRANSISTOR	UMH1N
Q	2332 (A,105,99)	TRANSISTOR	UMH1N
D	2301 (B,111,89)	DIODE	1SS352
D	2302 (B,96,87)	DIODE	1SS352
JA	2201 (A,73,13)	SOCKET	AKP7049
JA	2202 (A,115,13)	SOCKET	AKP7049
JA	2203 (A,150,13)	2P RCA PINJACK	AKB7187
CN	2201 (A,64,103)	26P CONNECTOR	RKN1067
CN	2202 (A,172,85)	23P SOCKET	XKP3083
CN	2203 (A,110,115)	9P SOCKET	XKP3075
	2204 (A,65,87)	PCB BINDER	VEF1040

RESISTORS

R	2201 (B,114,28)	CHIP RESISTOR	RS1/16S75R0F
R	2202 (B,116,28)	CHIP RESISTOR	RS1/16S75R0F

Mark	No.	Description	Part No.
R	2203 (B,72,28)	CHIP RESISTOR	RS1/16S75R0F
R	2204 (B,74,28)	CHIP RESISTOR	RS1/16S75R0F
R	2205 (B,100,28)	CHIP RESISTOR	RS1/16S75R0F
R	2206 (B,102,28)	CHIP RESISTOR	RS1/16S75R0F
R	2226 (B,137,49)		RS1/16S682J
R	2227 (B,120,50)		RS1/16S682J
R	2228 (B,135,49)	CHIP RESISTOR	RS1/16S7500F
R	2229 (B,122,50)	CHIP RESISTOR	RS1/16S7500F
R	2230 (A,134,48)		RS1/16S8200F
R	2231 (A,124,49)		RS1/16S8200F
R	2232 (A,137,49)	CHIP RESISTOR	RS1/16S75R0F
R	2233 (A,118,47)	CHIP RESISTOR	RS1/16S75R0F
R	2237 (A,109,74)		RS1/16S472J
R	2238 (A,86,74)		RS1/16S103J
R	2240 (A,86,79)		RS1/16S472J
R	2242 (A,96,71)		RS1/16S103J
R	2244 (A,96,75)		RS1/16S472J
R	2246 (A,108,76)		RS1/16S472J
R	2248 (A,106,79)		RS1/16S472J
R	2250 (A,118,74)		RS1/16S472J
R	2252 (A,114,78)		RS1/16S472J
R	2255 (A,117,71)		RS1/16S472J
R	2264 (B,59,37)	CHIP RESISTOR	RS1/16S75R0F
R	2265 (B,79,48)	CHIP RESISTOR	RS1/16S75R0F
R	2266 (A,142,92)		RS1/16S473J
R	2267 (A,144,92)		RS1/16S473J
R	2268 (A,145,92)		RS1/16S473J
R	2269 (A,147,92)		RS1/16S473J
R	2270 (A,142,85)		RS1/16S473J
R	2272 (B,93,28)	CHIP RESISTOR	RS1/16S75R0F
R	2273 (B,84,30)	CHIP RESISTOR	RS1/16S75R0F
R	2274 (B,133,91)		RS1/16S101J
R	2275 (B,127,91)		RS1/16S101J
R	2276 (A,137,85)		RS1/16S101J
R	2277 (B,133,93)		RS1/16S101J
R	2284 (B,167,77)		RS1/16S0R0J
R	2285 (B,167,73)		RS1/16S0R0J
R	2286 (A,117,108)		RS1/16S104J
R	2287 (A,114,108)		RS1/16S104J
R	2288 (A,142,109)		RS1/16S473J
R	2289 (A,144,109)		RS1/16S473J
R	2290 (A,145,109)		RS1/16S473J
R	2291 (A,147,109)		RS1/16S473J
R	2292 (A,141,102)		RS1/16S473J
R	2293 (A,143,102)		RS1/16S473J
R	2294 (A,144,102)		RS1/16S473J
R	2295 (A,146,102)		RS1/16S473J
R	2301 (A,109,84)		RS1/16S103J
R	2302 (A,96,84)		RS1/16S103J
R	2303 (A,108,86)		RS1/16S470J
R	2304 (A,97,86)		RS1/16S470J
R	2305 (B,103,91)		RS1/16S274J
R	2306 (B,94,91)		RS1/16S274J
R	2307 (B,109,83)		RS1/16S105J
R	2308 (B,100,83)		RS1/16S105J
R	2330 (B,118,87)		RS1/16S153J
R	2331 (B,118,91)		RS1/16S333J
R	2333 (A,101,96)		RS1/16S473J
R	2334 (A,96,96)		RS1/16S473J
R	2335 (A,109,95)		RS1/16S473J
R	2336 (A,104,96)		RS1/16S473J
R	2352 (B,150,42)		RS1/16S682J
R	2353 (B,160,42)		RS1/16S682J
R	2354 (B,148,42)	CHIP RESISTOR	RS1/16S7500F
R	2355 (B,162,42)	CHIP RESISTOR	RS1/16S7500F
R	2356 (A,150,42)		RS1/16S8200F
R	2357 (A,160,42)		RS1/16S8200F
R	2358 (A,147,39)	CHIP RESISTOR	RS1/16S75R0F
R	2359 (A,162,38)	CHIP RESISTOR	RS1/16S75R0F
R	9299		RS1/16S0R0J

CAPACITORS

C	2201 (B,112,30)		CKSRYB104K16
C	2202 (B,70,29)		CKSRYB104K16
C	2203 (B,98,29)		CKSRYB104K16
C	2210 (A,157,71)	ELECTROLYTIC CAPACIT	ACH7298
C	2211 (A,157,64)	ELECTROLYTIC CAPACIT	ACH7298
C	2212 (A,80,108)		CEAT331M10
C	2213 (B,78,104)		CKSRYB104K16
C	2216 (A,91,53)		CKSRYB104K16
C	2217 (A,96,53)		CKSRYB104K16
C	2218 (A,130,54)		CKSRYB104K16
C	2219 (A,127,54)		CKSRYB104K16
C	2220 (A,134,41)		CEAT101M10
C	2221 (A,126,41)		CEAT101M10
C	2222 (A,130,45)		CKSRYB103K50
C	2223 (A,127,45)		CKSRYB103K50
C	2224 (A,137,58)		CEAT331M10
C	2225 (B,124,57)		CKSRYB104K16
C	2231 (A,120,49)		CKSRYB104K16
C	2232 (B,132,29)		CCSRCH101J50
C	2233 (B,126,29)		CCSRCH101J50
C	2234 (A,109,53)		CKSRYB104K16
C	2235 (A,114,53)		CKSRYB104K16
C	2236 (A,74,53)		CKSRYB104K16
C	2237 (A,79,53)		CKSRYB104K16
C	2238 (A,87,70)	ELECT. CAPACITOR	ACH7290
C	2239 (B,88,76)		CKSRYB103K50
C	2240 (B,88,80)		CKSRYB103K50
C	2242 (A,100,69)	CERAMIC CAPACITOR	CKSQYB104K16
C	2243 (B,97,72)		CKSRYB103K50
C	2244 (B,97,76)		CKSRYB103K50
C	2246 (A,108,70)	ELECT. CAPACITOR	ACH7290
C	2247 (B,106,75)		CKSRYB103K50
C	2248 (B,106,79)		CKSRYB103K50
C	2250 (A,117,69)	CERAMIC CAPACITOR	CKSQYB104K16
C	2251 (B,115,72)		CKSRYB103K50
C	2252 (B,115,76)		CKSRYB103K50
C	2260 (A,64,57)		CEAT331M10
C	2261 (B,84,48)		CKSRYB104K16
C	2262 (A,59,46)	ELECT. CAPACITOR	CEAT102M6R3
C	2263 (B,58,29)		CCSRCH101J50
C	2264 (B,60,29)		CCSRCH101J50
C	2265 (B,63,47)		CKSRYB103K50
C	2266 (B,75,40)		CKSRYB103K50
C	2267 (B,87,48)		CKSRYB104K16
C	2268 (A,89,31)	ELECT. CAPACITOR	CEAT102M6R3
C	2269 (B,86,32)		CKSRYB104K16

Mark	No.	Description	Part No.
C	2270 (B,89,28)		CCSRCH101J50
C	2271 (B,86,28)		CCSRCH101J50
C	2272 (B,93,40)		CKSRYB103K50
C	2273 (B,79,40)		CKSRYB103K50
C	2286 (B,151,106)		CKSRYB103K50
C	2287 (B,151,89)		CKSRYB103K50
C	2301 (A,108,84)		CKSRYB104K16
C	2302 (A,98,84)		CKSRYB104K16
C	2303 (A,108,91)		CEAT100M50
C	2304 (A,97,91)		CEAT100M50
C	2305 (A,104,87)		CKSRYB103K50
C	2331 (B,116,91)		CKSRYB224K16
C	2332 (A,114,91)		CKSRYB103K50
C	2350 (A,149,35)		CEAT101M10
C	2351 (A,157,35)		CEAT101M10
C	2352 (A,153,40)		CKSRYB103K50
C	2353 (A,156,40)		CKSRYB103K50
C	2354 (A,150,53)		CEAT221M10
C	2355 (A,157,53)		CEAT221M10
C	2362 (B,141,30)		CCSRCH101J50
C	2363 (B,157,27)		CCSRCH101J50

Z COMPONENT ASSY

MISCELLANEOUS

IC	2401 (A,244,47)	MULTIPLEXER(8CH*1)	TC74LVX4051FT
IC	2402 (A,217,49)	MULTIPLEXER(8CH*1)	TC74LVX4051FT
IC	2403 (A,231,49)	MULTIPLEXER(8CH*1)	TC74LVX4051FT
IC	2404 (A,280,83)	MULTIPLEXER(2CH*3)	TC74LVX4053FT
IC	2405 (A,267,57)	VIDEO OP AMP IC	ADA4861-3YRZ
IC	2407 (A,249,89)	IC	NJM12904V
IC	2408 (A,244,60)	MULTIPLEXER(8CH*1)	TC74LVX4051FT
IC	2409 (A,217,62)	MULTIPLEXER(8CH*1)	TC74LVX4051FT
IC	2410 (A,231,62)	MULTIPLEXER(8CH*1)	TC74LVX4051FT
IC	2411 (A,289,83)	MULTIPLEXER(2CH*3)	TC74LVX4053FT
IC	2412 (A,279,57)	VIDEO OP AMP IC	ADA4861-3YRZ
IC	2414 (A,300,45)	OP AMP	EL5260IYZ
IC	2415 (A,282,109)	LOGIC IC	TC4094BFN
IC	2416 (A,298,109)	LOGIC IC	TC4094BFN
Q	2402 (A,229,101)	TRANSISTOR	2SA1226S1
Q	2403 (A,221,101)	TRANSISTOR	2SA1226S1
Q	2404 (A,229,97)	TRANSISTOR	2SA1226S1
Q	2405 (A,221,97)	TRANSISTOR	2SA1226S1
Q	2406 (A,229,92)	TRANSISTOR	2SA1226S1
Q	2407 (A,221,92)	TRANSISTOR	2SA1226S1
Q	2409 (A,229,88)	TRANSISTOR	2SA1226S1
Q	2410 (A,221,88)	TRANSISTOR	2SA1226S1
Q	2411 (A,229,83)	TRANSISTOR	2SA1226S1
Q	2412 (A,221,83)	TRANSISTOR	2SA1226S1
Q	2413 (A,229,79)	TRANSISTOR	2SA1226S1
Q	2414 (A,221,79)	TRANSISTOR	2SA1226S1
Q	2420 (A,264,64)	DIGITAL TR(SC-70)	RT1P241M
Q	2430 (A,273,63)	DIGITAL TR(SC-70)	RT1P241M
Q	2520 (A,257,51)	TRANSISTOR	2SC4081
Q	2521 (A,257,65)	TRANSISTOR	2SA1576A
D	2401 (A,254,96)	DIODE	1SS352
D	2402 (A,254,84)	DIODE	1SS352
JA	2401 (A,203,13)	PIN JACK(6P)	AKB7183
JA	2402 (A,238,13)	PIN JACK(9P)	AKB7184
JA	2403 (A,273,13)	PIN JACK(6P)	AKB7183
JA	2404 (A,294,13)	JACK	VKB1156
CN	2401 (A,201,70)	30P CONNECTOR	RKN1039
CN	2402 (A,309,85)	19P SOCKET	XKP3080
CN	2403 (A,248,115)	9P SOCKET	XKP3075
CN	2405 (A,237,114)	5P CONNECTOR	52044-0545
	2401 (A,195,46)	PCB BINDER	VEF1040

RESISTORS

R	2401 (B,195,34)	CHIP RESISTOR	RS1/16S75R0F
R	2402 (B,203,28)	CHIP RESISTOR	RS1/16S75R0F
R	2403 (B,194,29)	CHIP RESISTOR	RS1/16S75R0F
R	2404 (B,208,30)	CHIP RESISTOR	RS1/16S75R0F
R	2405 (B,213,30)	CHIP RESISTOR	RS1/16S75R0F
R	2406 (B,208,22)	CHIP RESISTOR	RS1/16S75R0F
R	2407 (B,218,30)	CHIP RESISTOR	RS1/16S75R0F
R	2408 (B,227,30)	CHIP RESISTOR	RS1/16S75R0F
R	2409 (B,222,22)	CHIP RESISTOR	RS1/16S75R0F
R	2410 (B,236,30)	CHIP RESISTOR	RS1/16S75R0F
R	2411 (B,243,30)	CHIP RESISTOR	RS1/16S75R0F
R	2412 (B,236,22)	CHIP RESISTOR	RS1/16S75R0F
R	2413 (B,250,30)	CHIP RESISTOR	RS1/16S75R0F
R	2414 (B,256,30)	CHIP RESISTOR	RS1/16S75R0F
R	2415 (B,250,22)	CHIP RESISTOR	RS1/16S75R0F
R	2420 (B,269,69)		RS1/16S0R0J
R	2421 (B,271,69)		RS1/16S0R0J
R	2422 (B,273,69)		RS1/16S0R0J
R	2423 (B,264,56)		RS1/16S123J
R	2424 (B,269,62)		RS1/16S123J
R	2425 (B,268,56)		RS1/16S123J
R	2426 (B,262,45)	CHIP RESISTOR	RS1/16S75R0F
R	2427 (B,270,33)	CHIP RESISTOR	RS1/16S75R0F
R	2428 (B,264,45)	CHIP RESISTOR	RS1/16S75R0F
R	2429 (A,261,66)		RS1/16S104J
R	2430 (B,276,69)		RS1/16S0R0J
R	2431 (B,282,66)		RS1/16S0R0J
R	2432 (B,280,68)		RS1/16S0R0J
R	2433 (B,278,56)		RS1/16S123J
R	2434 (B,284,64)		RS1/16S123J
R	2435 (B,283,56)		RS1/16S123J
R	2436 (B,281,52)	CHIP RESISTOR	RS1/16S75R0F
R	2437 (B,285,45)	CHIP RESISTOR	RS1/16S75R0F
R	2438 (B,283,47)	CHIP RESISTOR	RS1/16S75R0F
R	2439 (A,278,63)		RS1/16S104J
R	2443 (A,216,102)		RS1/16S471J
R	2444 (A,216,97)		RS1/16S471J
R	2445 (A,215,93)		RS1/16S471J
R	2446 (A,233,103)		RS1/16S184J
R	2447 (A,233,98)		RS1/16S184J
R	2448 (A,233,94)		RS1/16S184J
R	2449 (A,236,100)		RS1/16S101J
R	2450 (A,236,96)		RS1/16S101J
R	2451 (A,236,91)		RS1/16S101J
R	2452 (A,234,101)		RS1/16S114J
R	2453 (A,234,96)		RS1/16S114J
R	2454 (A,234,92)		RS1/16S114J
R	2455 (B,229,89)		RS1/16S472J
R	2456 (B,229,85)		RS1/16S472J
R	2457 (B,229,80)		RS1/16S472J

Mark	No.	Description	Part No.
R	2458	(A,215,88)	RS1/16S471J
R	2459	(A,215,84)	RS1/16S471J
R	2460	(A,215,79)	RS1/16S471J
R	2461	(A,233,89)	RS1/16S184J
R	2462	(A,233,85)	RS1/16S184J
R	2463	(A,233,80)	RS1/16S184J
R	2464	(A,236,87)	RS1/16S101J
R	2465	(A,236,82)	RS1/16S101J
R	2466	(A,236,78)	RS1/16S101J
R	2467	(A,234,87)	RS1/16S114J
R	2468	(A,234,83)	RS1/16S114J
R	2469	(A,233,78)	RS1/16S114J
R	2470	(A,245,93)	RS1/16S103J
R	2471	(A,246,89)	RS1/16S103J
R	2472	(A,252,95)	RS1/16S470J
R	2473	(A,252,84)	RS1/16S470J
R	2474	(A,253,91)	RS1/16S274J
R	2475	(A,253,89)	RS1/16S274J
R	2476	(B,250,91)	RS1/16S105J
R	2477	(B,246,87)	RS1/16S105J
R	2485	(B,281,107)	RS1/16S473J
R	2486	(B,283,107)	RS1/16S473J
R	2487	(B,286,107)	RS1/16S473J
R	2488	(B,288,107)	RS1/16S473J
R	2489	(B,279,116)	RS1/16S473J
R	2490	(B,281,116)	RS1/16S473J
R	2491	(B,284,115)	RS1/16S473J
R	2492	(B,288,115)	RS1/16S473J
R	2493	(B,297,107)	RS1/16S473J
R	2494	(B,300,107)	RS1/16S473J
R	2495	(B,232,105)	RS1/16S104J
R	2496	(B,234,105)	RS1/16S104J
R	2497	(B,236,105)	RS1/16S104J
R	2498	(B,238,105)	RS1/16S104J
R	2500	(A,295,47)	RS1/16S682J
R	2501	(A,306,47)	RS1/16S682J
R	2502	(A,295,45) CHIP RESISTOR	RS1/16S7500F
R	2503	(A,296,43)	RS1/16S8200F
R	2504	(A,306,45) CHIP RESISTOR	RS1/16S7500F
R	2505	(A,305,43)	RS1/16S8200F
R	2506	(A,292,40) CHIP RESISTOR	RS1/16S75R0F
R	2507	(A,309,41) CHIP RESISTOR	RS1/16S75R0F
R	2510	(B,210,114)	RS1/16S104J
R	2511	(B,208,114)	RS1/16S104J
R	2512	(B,206,114)	RS1/16S104J
R	2513	(A,201,107)	RS1/16S104J
R	2514	(A,201,109)	RS1/16S104J
R	2515	(A,201,111)	RS1/16S104J
R	2520	(A,256,47)	RS1/16S153J
R	2521	(A,260,47)	RS1/16S333J
R	2522	(A,257,61)	RS1/16S153J
R	2523	(A,260,61)	RS1/16S333J
R	2535	(A,238,88)	RS1/16S472J
R	2536	(A,238,84)	RS1/16S472J
R	2537	(A,238,80)	RS1/16S472J
R	2540	(B,264,54)	RS1/16S3000F
R	2541	(B,263,51) CHIP RESISTOR	RS1/16S3300F
R	2542	(B,271,62)	RS1/16S3000F
R	2543	(A,273,59) CHIP RESISTOR	RS1/16S3300F
R	2544	(B,268,54)	RS1/16S3000F
R	2545	(B,271,53) CHIP RESISTOR	RS1/16S3300F
R	2546	(B,278,53)	RS1/16S3000F
R	2547	(B,276,51) CHIP RESISTOR	RS1/16S3300F
R	2548	(B,286,65)	RS1/16S3000F
R	2549	(A,284,60) CHIP RESISTOR	RS1/16S3300F
R	2550	(B,283,52)	RS1/16S3000F
R	2551	(A,285,53) CHIP RESISTOR	RS1/16S3300F
R	2553	(A,227,102)	RS1/16S102J
R	2554	(A,227,97)	RS1/16S102J
R	2555	(A,227,93)	RS1/16S102J
R	2556	(A,225,102)	RS1/16S390J
R	2557	(A,225,97)	RS1/16S390J
R	2558	(A,225,93)	RS1/16S390J
R	2559	(A,218,102)	RS1/16S330J
R	2560	(A,218,97)	RS1/16S330J
R	2561	(A,218,93)	RS1/16S330J
R	2562	(A,227,88)	RS1/16S102J
R	2563	(A,227,84)	RS1/16S102J
R	2564	(A,227,79)	RS1/16S102J
R	2565	(A,225,88)	RS1/16S390J
R	2566	(A,225,84)	RS1/16S390J
R	2567	(A,225,79)	RS1/16S390J
R	2568	(A,218,88)	RS1/16S330J
R	2569	(A,218,84)	RS1/16S330J
R	2570	(A,218,79)	RS1/16S330J
R	2571	(B,276,112)	RS1/16S101J
R	2572	(B,270,115)	RS1/16S101J
R	2573	(B,264,116)	RS1/16S101J
R	2574	(B,270,113)	RS1/16S101J
R	9588		RS1/16S0R0J
R	9589		RS1/16S0R0J

CAPACITORS

C	2416	(A,268,46)	CEAT101M10
C	2417	(A,276,46)	CEAT101M10
C	2418	(A,266,51)	CKSRYB104K16
C	2419	(A,269,51)	CKSRYB104K16
C	2420	(A,272,81)	CEAT331M10
C	2421	(A,271,73) ELECT. CAPACITOR	ACH7290
C	2422	(A,277,73) ELECT. CAPACITOR	ACH7290
C	2430	(A,284,73)	CEAT331M10
C	2431	(A,296,84) ELECT. CAPACITOR	ACH7290
C	2432	(A,291,73)	CEAT221M10
C	2437	(B,278,30)	CCSRCH120J50
C	2438	(B,282,23)	CCSRCH120J50
C	2439	(B,274,29)	CCSRCH120J50
C	2440	(B,232,101) CHIP CERAMIC C.	DCH1165
C	2441	(B,232,96) CHIP CERAMIC C.	DCH1165
C	2442	(B,232,92) CHIP CERAMIC C.	DCH1165
C	2443	(A,236,103)	CKSRYB103K50
C	2444	(A,236,98)	CKSRYB103K50
C	2445	(A,236,94)	CKSRYB103K50
C	2449	(A,223,100)	CKSRYB103K50
C	2450	(A,223,96)	CKSRYB103K50
C	2451	(A,223,91)	CKSRYB103K50
C	2455	(B,232,87) CHIP CERAMIC C.	DCH1165
C	2456	(B,232,82) CHIP CERAMIC C.	DCH1165
C	2457	(B,231,78) CHIP CERAMIC C.	DCH1165

Mark	No.	Description	Part No.
C	2458 (A,236,89)		CKSRYB103K50
C	2459 (A,236,85)		CKSRYB103K50
C	2460 (A,236,80)		CKSRYB103K50
C	2464 (A,223,87)		CKSRYB103K50
C	2465 (A,223,82)		CKSRYB103K50
C	2466 (A,223,78)		CKSRYB103K50
C	2467 (A,278,51)		CKSRYB104K16
C	2468 (A,281,51)		CKSRYB104K16
C	2470 (A,245,96)		CKSRYB104K16
C	2471 (A,246,86)		CKSRYB104K16
C	2472 (A,253,92)	CHIP CERAMIC C.	DCH1165
C	2473 (A,253,87)	CHIP CERAMIC C.	DCH1165
C	2478 (A,276,113)		CKSRYB103K50
C	2479 (A,292,110)		CKSRYB103K50
C	2484 (A,243,42)		CKSRYB104K16
C	2485 (A,248,51)		CKSRYB104K16
C	2486 (A,216,45)		CKSRYB104K16
C	2487 (A,220,53)		CKSRYB104K16
C	2488 (A,230,45)		CKSRYB104K16
C	2489 (A,233,53)		CKSRYB104K16
C	2490 (A,276,84)		CKSRYB104K16
C	2491 (A,284,81)		CKSRYB104K16
C	2492 (A,244,56)		CKSRYB104K16
C	2493 (A,247,64)		CKSRYB104K16
C	2494 (A,216,58)		CKSRYB104K16
C	2495 (A,220,66)		CKSRYB104K16
C	2496 (A,230,58)		CKSRYB104K16
C	2497 (A,232,66)		CKSRYB104K16
C	2498 (A,284,84)		CKSRYB104K16
C	2499 (A,293,81)		CKSRYB104K16
C	2500 (A,295,38)		CEAT101M10
C	2501 (A,303,38)		CEAT101M10
C	2502 (A,299,42)		CKSRYB103K50
C	2503 (A,302,42)		CKSRYB103K50
C	2504 (A,299,52)		CEAT221M10
C	2505 (A,306,53)		CEAT221M10
C	2510 (B,292,32)		CCSRCH101J50
C	2511 (B,300,32)		CCSRCH101J50
C	2516 (A,301,79)	ELECTROLYTIC CAPACIT	ACH7298
C	2517 (A,303,69)	ELECTROLYTIC CAPACIT	ACH7298
C	2518 (B,298,77)		CKSRYB103K50
C	2519 (B,300,64)		CKSRYB103K50
C	2522 (A,260,49)		CKSRYB224K16
C	2523 (A,260,62)		CKSRYB224K16
C	2590 (A,292,95)		CEAT221M10
C	2591 (A,284,95)		CEAT221M10
C	2592 (A,264,102)		CEAT331M10
C	2593 (A,207,106)		CEAT221M10
C	2594 (A,261,110)	ELECT. CAPACITOR	ACH7290
C	2595 (A,269,109)		CEAT331M10

AA VIDEO BRIDGE ASSY

MISCELLANEOUS

CN	2501 (A,150,202)	9P PLUG	XKP3064
CN	2502 (A,174,202)	9P PLUG	XKP3064

Mark	No.	Description	Part No.

AC IR 232C ASSY

MISCELLANEOUS

IC	6001 (A,38,113)	RS232 IC	HIN202EIBNZ
IC	6051 (A,58,93)	IC	TC74VHC125FTS1
IC	6052 (A,57,106)	IC	TC74VHCT125AFTS1
IC	6053 (A,112,56)	IC	TC74VHCT125AFTS1
IC	6201 (A,132,73)	MICROCOMPUTER IC	PDC158A8
IC	6301 (A,93,89)	CPU	PEG292A8
IC	6391 (A,93,112)	FLASH ROM	AYW7229
IC	6392 (A,110,120)	IC	TC7SH08FUS1
IC	6411 (A,78,47)	REGULATOR IC	NJM2880U1-33
Q	6001 (A,42,102)	TRANSISTOR	2SC4154
Q	6101 (A,43,92)	CHIP TRANSISTOR	RN4903
Q	6102 (A,45,81)	CHIP TRANSISTOR	RN4903
Q	6103 (A,49,70)	CHIP TRANSISTOR	RN4903
Q	6104 (A,49,58)	CHIP TRANSISTOR	RN4903
Q	6151 (A,57,52)	TRANSISTOR(SC-70)	2SA1602A
Q	6152 (A,47,48)	TRANSISTOR	RT1N241M
Q	6201 (A,122,94)	DIGITAL TR(SC-70)	RT1P431M
Q	6301 (B,110,81)	TRANSISTOR	RT1N241M
D	6001 (A,45,102)	DIODE	1SS352
D	6002 (A,38,106)	DIODE	1SS352
D	6101 (B,35,94)	CHIP DIODE	RB501V-40
D	6102 (B,33,88)	CHIP DIODE	RB501V-40
D	6103 (B,33,78)	CHIP DIODE	RB501V-40
D	6104 (B,33,70)	CHIP DIODE	RB501V-40
D	6121 (A,38,86)	DIODE	MC2848-11
D	6122 (A,44,64)	DIODE	MC2848-11
D	6151 (A,58,46)	DIODE	1SS352
D	6152 (A,49,45)	DIODE	MC2848-11
D	6153 (A,47,51)	DIODE	1SS352
D	6201 (A,118,61)	DIODE	MC2848-11
D	6391 (A,113,111)	CHIP DIODE	RB501V-40
D	6401 (A,119,37)	DIODE	MC2848-11
D	6402 (A,123,37)	DIODE	MC2848-11
D	6411 (A,75,54)	DIODE	MC2848-11
L	6001 (B,53,116)	CHIP SOLID INDUCTOR	QTL1013
L	6101 (B,30,93)	CHIP SOLID INDUCTOR	QTL1013
L	6102 (B,30,88)	CHIP SOLID INDUCTOR	QTL1013
L	6103 (B,30,75)	CHIP SOLID INDUCTOR	QTL1013
L	6104 (B,30,70)	CHIP SOLID INDUCTOR	QTL1013
L	6105 (B,28,58)	CHIP SOLID INDUCTOR	QTL1013
L	6106 (B,30,51)	CHIP SOLID INDUCTOR	QTL1013
L	6107 (B,30,37)	CHIP SOLID INDUCTOR	QTL1013
L	6108 (B,30,30)	CHIP SOLID INDUCTOR	QTL1013
L	6201 (B,124,50)	CHIP SOLID INDUCTOR	QTL1013
L	6301 (B,74,75)	CHIP SOLID INDUCTOR	QTL1013
JA	6101 (A,16,93)	JACK	RKN1004
JA	6102 (A,16,83)	JACK	RKN1004
JA	6103 (A,16,73)	JACK	RKN1004
JA	6104 (A,16,63)	JACK	RKN1004
JA	6105 (A,16,53)	JACK	RKN1004
JA	6106 (A,16,43)	JACK	RKN1004
JA	6107 (A,16,33)	JACK	RKN1004
JA	6108 (A,16,23)	JACK	RKN1004
X	6201 (A,132,91)	CRYSTAL OSCILLATOR CRYSTAL OSC	CSS1653
X	6301 (A,93,74)	CERAMIC RESONATOR	ASS7087
CN	6001 (A,12,115)	9P D-SUB SOCKET	AKP1213

Mark	No.	Description	Part No.
	CN 6281 (A,126,118)	9P CONNECTOR	VKN1413
	CN 6381 (A,65,118)	10P CONNECTOR	VKN1414
	CN 6401 (A,154,18)	13P SOCKET	XKP3077
	CN 6402 (A,102,15)	PLUG	CKS1764
	CN 6403 (A,67,15)	PLUG	CKS1764
	CN 6404 (A,34,15)	PLUG	CKS1764
	CN 6405 (A,155,89)	14P CONNECTOR	VKN1418
	CN 6406 (A,155,109)	12P CONNECTOR	VKN1416
	CN 6407 (A,155,47)	PLUG(7P)	KM200NA7
	CN 6408 (A,154,39)	CONNECTOR	CKS3374
	CN 6409 (A,145,120)	8P CONNECTOR	VKN1412
	6001 (A,134,120)	PCB BINDER	VEF1040

RESISTORS

	R	6001 (A,27,116)	RS1/16S0R0J
	R	6002 (A,30,110)	RS1/16S101J
	R	6003 (A,30,108)	RS1/16S101J
	R	6004 (A,44,106)	RS1/16S101J
	R	6005 (A,45,111)	RS1/16S101J
	R	6006 (B,36,117)	RS1/16S101J
	R	6007 (A,34,106)	RS1/16S224J
	R	6008 (A,34,104)	RS1/16S474J
	R	6009 (A,39,104)	RS1/16S103J
	R	6010 (A,36,102)	RS1/16S224J
	R	6051 (B,56,101)	RS1/16S182J
	R	6052 (B,59,101)	RS1/16S101J
	R	6053 (B,60,91)	RS1/16S104J
	R	6054 (B,57,108)	RS1/16S101J
	R	6101 (A,29,64)	RS1/16S0R0J
	R	6102 (A,29,53)	RS1/16S0R0J
	R	6103 (A,30,44)	RS1/16S0R0J
	R	6104 (A,30,40)	RS1/16S0R0J
	R	6109 (A,37,91)	RS1/16S104J
	R	6110 (A,39,80)	RS1/16S104J
	R	6111 (A,43,69)	RS1/16S104J
	R	6112 (A,43,58)	RS1/16S104J
	R	6113 (A,39,92)	RS1/16S223J
	R	6114 (A,41,81)	RS1/16S223J
	R	6115 (A,46,70)	RS1/16S223J
	R	6116 (A,46,58)	RS1/16S223J
	R	6121 (A,39,91)	RS1/16S622J
	R	6122 (A,41,79)	RS1/16S622J
	R	6123 (A,46,68)	RS1/16S622J
	R	6124 (A,46,57)	RS1/16S622J
	R	6152 (A,59,51)	RS1/16S104J
	R	6153 (A,59,54)	RS1/16S104J
	R	6154 (A,54,49)	RS1/16S103J
	R	6155 (A,53,47)	RS1/16S102J
	R	6156 (A,49,55)	RS1/16S472J
	R	6191	RS1/16S0R0J
	R	6192	RS1/16S0R0J
	R	6193	RS1/16S0R0J
	R	6194	RS1/16S0R0J
	R	6195	RS1/16S0R0J
	R	6196	RS1/16S0R0J
	R	6201 (A,143,95)	RS1/16S101J
	R	6202 (B,137,72)	RS1/16S104J
	R	6203 (A,134,87)	RS1/16S105J
	R	6204 (B,134,88)	RS1/16S0R0J

Mark	No.	Description	Part No.
R	6205 (A,126,98)		RAB4C101J
R	6206 (B,129,81)		RS1/16S104J
R	6207 (A,118,83)		RS1/16S104J
R	6208 (A,119,92)		RS1/16S473J
R	6209 (A,122,91)		RS1/16S473J
R	6210 (A,119,86)		RS1/16S101J
R	6211 (A,118,86)		RS1/16S101J
R	6212 (A,121,83)		RS1/16S474J
R	6214 (A,117,78)		RAB4C473J
R	6215 (A,124,59)		RS1/16S104J
R	6216 (B,139,67)		RS1/16S473J
R	6217 (A,133,60)		RS1/16S101J
R	6218 (A,135,54)		RS1/16S473J
R	6219 (A,138,55)		RS1/16S101J
R	6220 (A,140,55)		RS1/16S101J
R	6221 (A,147,59)		RS1/16S101J
R	6222 (A,152,68)		RS1/16S473J
R	6223 (B,148,76)		RS1/16S101J
R	6224 (B,150,77)		RS1/16S101J
R	6225 (B,152,77)		RS1/16S101J
R	6226 (A,150,76)		RS1/16S331J
R	6227 (A,150,77)		RS1/16S331J
R	6228 (A,149,78)		RS1/16S331J
R	6229 (A,156,78)		RS1/16S221J
R	6231 (A,122,100)		RS1/16S104J
R	6251 (A,147,84)		RAB4C101J
R	6252 (B,146,80)		RS1/16S472J
R	6253 (B,146,82)		RS1/16S472J
R	6254 (B,146,84)		RS1/16S472J
R	6301 (A,83,72)		RAB4C331J
R	6302 (A,87,72)		RAB4C101J
R	6303 (A,101,74)		RAB4C221J
R	6304 (A,111,82)		RAB4C101J
R	6306 (A,109,88)		RAB4C101J
R	6307 (A,75,92)		RAB4C331J
R	6308 (A,75,87)		RAB4C331J
R	6309 (A,109,85)		RS1/16S101J
R	6310 (B,106,92)		RS1/16S221J
R	6311 (B,104,92)		RS1/16S221J
R	6312 (B,108,97)		RS1/16S101J
R	6313 (B,100,99)		RS1/16S101J
R	6314 (A,81,81)		RS1/16S331J
R	6315 (A,81,80)		RS1/16S331J
R	6316 (A,81,78)		RS1/16S331J
R	6317 (B,57,91)		RS1/16S224J
R	6318 (B,97,87)		RS1/16S104J
R	6320 (B,101,92)		RS1/16S473J
R	6321 (B,83,79)		RS1/16S473J
R	6322 (B,85,79)		RS1/16S472J
R	6323 (B,87,79)		RS1/16S473J
R	6324 (B,88,72)		RS1/16S473J
R	6325 (B,99,85)		RS1/16S473J
R	6326 (B,102,79)		RS1/16S473J
R	6327 (B,106,79)		RS1/16S473J
R	6329 (B,110,87)		RS1/16S104J
R	6331 (A,111,95)		RS1/16S473J
R	6332 (A,108,102)		RS1/16S473J
R	6333 (B,79,88)		RS1/16S473J
R	6334 (B,76,87)		RS1/16S473J
R	6335 (A,111,97)		RS1/16S473J

Mark	No.	Description	Part No.
R	6337 (B,100,97)		RS1/16S101J
R	6338 (B,108,99)		RS1/16S101J
R	6340 (B,83,91)		RS1/16S101J
R	6341 (B,81,91)		RS1/16S101J
R	6342 (B,87,92)		RS1/16S101J
R	6343 (B,85,92)		RS1/16S101J
R	6392 (B,91,108)		RS1/16S473J
R	6401 (A,152,78)		RS1/16S104J
R	6402 (A,139,84)		RS1/16S104J
R	6403 (A,154,71)		RS1/16S104J
R	6404 (B,79,74)		RS1/16S104J
R	6405 (A,111,93)		RS1/16S104J
R	6406 (B,100,77)		RS1/16S104J
R	6407 (A,78,81)		RS1/16S104J
R	6408 (B,104,74)		RS1/16S104J
R	6409 (B,98,77)		RS1/16S104J
R	6410 (B,98,70)		RS1/16S104J
R	6411 (A,113,92)		RS1/16S104J
R	6499 (B,60,22)		RS1/16S0R0J

CAPACITORS

C	6001 (A,50,118)		CEJQ101M16
C	6002 (A,43,117)		CKSRYB103K50
C	6003 (B,40,113)		CKSRYB104K16
C	6004 (A,38,120)		CKSRYB104K16
C	6005 (A,31,117)		CKSRYB104K16
C	6006 (A,31,113)		CKSRYB104K16
C	6007 (A,29,106)		CKSRYB103K50
C	6008 (A,38,102)		CCSRCH331J50
C	6009 (A,44,117)		CKSRYB105K16
C	6051 (A,54,95)		CKSRYB104K16
C	6052 (A,53,107)		CKSRYB104K16
C	6053 (A,107,59)		CKSRYB104K16
C	6101 (A,42,95)		CKSRYB103K50
C	6102 (A,45,83)		CKSRYB103K50
C	6103 (A,49,72)		CKSRYB103K50
C	6104 (A,49,61)		CKSRYB103K50
C	6105 (A,43,90)		CKSRYB153K50
C	6106 (A,45,79)		CKSRYB153K50
C	6107 (A,49,67)		CKSRYB153K50
C	6108 (A,49,56)		CKSRYB153K50
C	6151 (A,54,52)		CKSRYB103K50
C	6201 (A,128,50)		CEAT221M16
C	6202 (A,133,84)		CKSRYB104K16
C	6203 (B,124,58)		CKSRYB104K16
C	6204 (B,150,68)		CKSRYB104K16
C	6205 (B,113,67)		CKSRYB104K16
C	6206 (B,147,65)		CKSRYB104K16
C	6207 (B,141,58)		CKSRYB104K16
C	6208 (A,138,84)		CKSRYB104K16
C	6209 (B,136,95)		CCSRCH120J50
C	6210 (B,132,95)		CCSRCH120J50
C	6211 (A,119,83)		CKSRYB103K50
C	6222 (B,133,84)		CKSRYB102K50
C	6223 (A,126,62)		CKSRYB102K50
C	6224 (A,147,71)		CKSRYB102K50
C	6225 (A,117,73)		CKSRYB102K50
C	6226 (A,146,67)		CKSRYB102K50
C	6227 (A,143,62)		CKSRYB102K50
C	6228 (B,138,84)		CKSRYB104K16

Mark	No.	Description	Part No.
C	6301 (A,73,79)		CEAT101M16
C	6302 (A,97,69)		CKSRYB104K16
C	6303 (B,92,101)		CKSRYB104K16
C	6304 (B,78,80)		CKSRYB104K16
C	6312 (A,97,75)		CKSRYB102K50
C	6313 (A,94,101)		CKSRYB102K50
C	6314 (A,81,84)		CKSRYB102K50
C	6391 (B,80,109)		CKSRYB104K16
C	6393 (A,111,118)		CKSRYB104K16
C	6394 (A,79,112)		CKSRYB102K50
C	6401 (B,59,29)		CKSRYB105K16
C	6402 (B,150,29)		CKSRYB105K16
C	6403 (A,125,37)		CKSRYB105K16
C	6411 (A,73,44)		CKSRYB104K16
C	6412 (A,79,42)		CKSRYB104K16
C	6413 (A,79,53)		CKSQYB225K10

AD MOTHER 2 ASSY

MISCELLANEOUS

⚠ IC	4751 (A,153,43)	PROTECTOR(7A)	AEK7021
⚠ IC	4752 (A,139,77)	IC	NJM78M05FA
IC	8501 (A,113,99)	PORT EXPANDER IC	BU4094BCFV
IC	8502 (A,89,96)	PORT EXPANDER IC	BU4094BCFV
⚠ IC	8503 (A,61,42)	REGULATOR IC	NJM78M56FA
IC	8504 (A,144,105)	IC	TC74VHCT08AFTS1
IC	8506 (A,108,50)	IC	TC74VHCT541AFTS1
IC	8507 (A,47,69)	OP-AMP IC	BA4560RF
Q	8501 (A,77,31)	TRANSISTOR	RT1N141M-11
Q	8502 (A,70,31)	DIGITAL TR(SC-70)	RT1P241M
Q	8504 (A,26,100)	TRANSISTOR	2SB1189
Q	8505 (A,31,100)	TRANSISTOR(SC-70)	2SA1602A
Q	8506 (A,29,83)	TRANSISTOR	2SB1189
Q	8507 (A,30,77)	TRANSISTOR(SC-70)	2SA1602A
Q	8508 (A,35,100)	TRANSISTOR	RT1N241M
Q	8509 (A,31,72)	TRANSISTOR	2SB1189
Q	8510 (A,30,67)	TRANSISTOR(SC-70)	2SA1602A
Q	8511 (A,30,54)	TRANSISTOR	2SB1189
Q	8512 (A,30,49)	TRANSISTOR(SC-70)	2SA1602A
Q	8513 (A,38,78)	TRANSISTOR	RT1N241M
Q	8514 (A,33,59)	TRANSISTOR	RT1N241M
Q	8515 (A,42,48)	TRANSISTOR	RT1N241M
D	4751 (A,160,58)	DIODE	D5SBA20(B)
D	4752 (A,167,89)	DIODE	MTZJ6R2(B)
D	8501 (B,56,26)	CHIP DIODE	RB501V-40
D	8503 (A,41,79)	DIODE	UDZS5R1(B)
D	8505 (B,24,94)	DIODE	1SS352
D	8506 (B,32,78)	DIODE	1SS352
D	8507 (B,32,68)	DIODE	1SS352
D	8508 (B,32,58)	DIODE	1SS352
D	8509 (A,29,31)	DIODE	1SS352
D	8510 (A,37,34)	DIODE	1SS352
D	8512 (A,115,51)	DIODE	1SS352
L	8502 (A,37,38)	CHIP SOLID INDUCTOR	QTL1013
L	8503 (A,29,35)	CHIP SOLID INDUCTOR	QTL1013
L	8504 (A,27,32)	CHIP SOLID INDUCTOR	QTL1013
L	8505 (A,25,25)	CHIP SOLID INDUCTOR	QTL1013
L	8506 (B,33,27)	CHIP SOLID INDUCTOR	QTL1013
L	8507 (A,22,14)	CHIP SOLID INDUCTOR	QTL1013

Mark	No.	Description	Part No.
L	8508 (B,31,24)	CHIP SOLID INDUCTOR	QTL1013
J	8512 (A,79,40)	2P HOUSING ASSY	ADX7580
JA	8501 (A,11,88)	JACK	RKN1004
JA	8502 (A,11,78)	JACK	RKN1004
JA	8503 (A,11,68)	JACK	RKN1004
JA	8504 (A,11,58)	JACK	RKN1004
JA	8505 (A,10,36)	MINI JACK(4P) /W SW	XKN3015
JA	8506 (A,10,24)	MINI JACK(4P) /W SW	XKN3015
KN	8501 (A,9,47)	SCREW PLATE	VNE1948
CN	4751 (A,233,44)	2P TOP POST	B2B-EH
CN	4752 (A,167,80)	PLUG(3P)	KM200NA3R
CN	8501 (A,165,139)	19P CONNECTOR	19R-1.25FJ
CN	8502 (A,134,139)	13P CONNECTOR	13R-1.25FJ
CN	8503 (A,105,139)	21P CONNECTOR	21R-1.25FJ
CN	8504 (A,110,108)	23P PLUG	XKP3071
CN	8505 (A,73,108)	23P PLUG	XKP3071
CN	8506 (A,81,84)	23P PLUG	XKP3071
CN	8507 (A,80,60)	19P PLUG	XKP3069
CN	8508 (A,151,13)	13P PLUG	XKP3066
CN	8509 (A,99,12)	CONNECTOR	CKS1730
CN	8510 (A,88,14)	CONNECTOR	CKS1730
CN	8511 (A,30,12)	CONNECTOR	CKS1730
CN	8513 (A,240,15)	CONNECTOR(05P)	TUC-P05P-B1
CN	8514 (A,77,50)	PLUG(11P)	KM200NA11
	8506	SCREW	BBZ30P080FNI
	8501 (A,169,15)	PCB BINDER	VEF1040
	8502 (A,197,46)	PCB BINDER	VEF1040
	8504 (A,157,38)	PCB BINDER	VEF1040
	8507	HEAT SINK	ANH-575
	8509	SCREW	BBZ30P080FNI
	8503 (A,202,17)	PCB BINDER	VEF1040

RESISTORS

Mark	No.	Description	Part No.
⚠ R	4751 (A,143,50)	CARBON FILM RESISTOR	RD1/4MUF4R7J
R	8501 (A,107,90)		RS1/16S104J
R	8502 (A,107,89)		RS1/16S104J
R	8503 (A,73,31)		RS1/16S104J
R	8504 (A,41,58)	CARBON FILM RESISTOR	RD1/4MUF1R8J
R	8507 (A,29,104)		RS1/16S101J
R	8508 (A,28,108)		RS1/16S103J
R	8509 (A,33,100)		RS1/16S272J
R	8510 (A,34,81)		RS1/16S101J
R	8511 (A,36,84)		RS1/16S103J
R	8512 (A,37,81)		RS1/16S272J
R	8513 (A,35,69)		RS1/16S101J
R	8514 (A,37,68)		RS1/16S103J
R	8515 (A,29,60)		RS1/16S272J
R	8516 (A,37,53)		RS1/16S101J
R	8517 (A,39,52)		RS1/16S103J
R	8518 (A,39,48)		RS1/16S272J
R	8526 (A,140,109)		RS1/16S224J
R	8527 (A,137,106)		RS1/16S104J
R	8528 (A,151,104)		RS1/16S104J
R	8529 (A,148,109)		RS1/16S104J
R	8530 (A,125,102)		RS1/16S473J
R	8531 (A,123,102)		RS1/16S473J
R	8532 (A,120,103)		RS1/16S473J
R	8533 (A,118,103)		RS1/16S473J
R	8534 (A,107,95)		RS1/16S473J
R	8571 (A,48,61)		RS1/16S822J
R	8572 (A,51,59)		RS1/16S822J
R	8573 (A,51,61)		RS1/16S104J
R	8574 (A,45,61)		RS1/16S104J
R	8575 (A,43,75)		RS1/16S1102F
R	8576 (A,43,79)		RS1/16S1502F
R	8577 (A,51,69)		RS1/16S103J
R	8578 (A,44,75)		RS1/16S103J
R	8579 (A,46,75)		RS1/16S472J
R	8581 (A,111,60)		RS1/16S331J
R	8582 (A,110,57)		RS1/16S331J
R	8583 (A,109,60)		RS1/16S331J
R	8584 (A,108,57)		RS1/16S331J
R	8585 (A,107,60)		RS1/16S331J
R	8586 (A,106,57)		RS1/16S331J
R	8587 (A,105,60)		RS1/16S331J
R	8588 (A,104,57)		RS1/16S331J
R	8589 (A,106,30)	RESISTOR ARRAY	RAB4C104J
R	8590 (A,102,30)	RESISTOR ARRAY	RAB4C104J

CAPACITORS

Mark	No.	Description	Part No.
C	4751 (A,153,50)	FILM CAPACITOR	CQMBA104J50
C	4753 (A,155,66)	ELECT. CAPACITOR	CEAT472M16
C	4754 (B,138,74)		CKSRYB103K50
C	4755 (A,151,85)		CEAT101M16
C	4756 (B,146,82)		CKSRYB103K50
C	8501 (A,112,94)		CKSRYB104K16
C	8502 (A,88,92)		CKSRYB104K16
C	8503 (B,65,41)		CKSRYB103K50
C	8504 (A,53,40)		CEAT101M16
C	8505 (B,57,38)		CKSRYB103K50
C	8507 (B,22,94)		CKSRYB103K50
C	8508 (B,29,78)		CKSRYB103K50
C	8509 (B,29,68)		CKSRYB103K50
C	8510 (B,29,59)		CKSRYB103K50
C	8511 (B,31,30)		CKSRYB103K50
C	8512 (B,29,30)		CKSRYB471K50
C	8513 (B,28,34)		CKSRYB103K50
C	8514 (B,28,36)		CKSRYB471K50
C	8516 (A,27,42)		CCSRCH221J50
C	8517 (A,27,37)		CCSRCH221J50
C	8518 (A,70,42)		CEAT100M50
C	8524 (A,145,101)		CKSRYB104K16
C	8530 (A,113,51)		CKSRYB104K16
C	8573 (A,43,70)		CKSRYB103K50

AE HDMI ASSY

SEMICONDUCTORS

Mark	No.	Description	Part No.
⚠ IC	11		NJM2885DL1-25
⚠ IC	12		NJM2846DL3-18
⚠ IC	13,53,54		TPS54350PWP
⚠ IC	14,15		NJM2872BF05
⚠ IC	16		S-1112B15MC-L6A
⚠ IC	17		NJM2885DL1-05
⚠ IC	18,252		S-1112B33MC-L6S
⚠ IC	51		S-1170B26UC-OTL
⚠ IC	52		S-1200B25-M5
⚠ IC	55		PQ070XH01Z

Mark	No.	Description	Part No.
⚠	IC	56	NJM2846DL3-33
⚠	IC	57	NJM2845DL1-33
	IC	101,103,106,151	BR24L02FV-W
	IC	102,105,107,152	TC7MB3257FK
	IC	104,154	SII9185ACTU
	IC	153,156	BR24L02FV-W
	IC	155,157	TC7MB3257FK
	IC	201	SII9135CTU
	IC	202	ICS571MLF
	IC	203	TC7WH74FU
	IC	204,205,208	TC7WH157FU
	IC	209,605,606	TC74LCX541FTS1
	IC	301	K4H561638H-UCB3
⚠	IC	302,501	LP2995M
	IC	303	ADV7802BSTZ-150
	IC	304,711,713	MM1117XF
	IC	305	TC7PAU04FU
	IC	307-311,601-604	TC74VCX541FT
	IC	401,1207	TC74LCX157FTS1
	IC	421,461	SII9134CTU
	IC	502	88DE2710
	IC	503,504	K4H561638H-UCCC
	IC	607	ADV7340BSTZ
	IC	609-611,614-617	TC74VCX541FT
	IC	612	ADR512ARTZ
	IC	613	SM5309AV
	IC	701-703,1201,1202	TC74LCX541FTS1
	IC	704	AYW7189
	IC	705	MB90092E1
	IC	706	LC822973
	IC	707	TC74VHCU04FT
	IC	708	TC7WHU04FU
	IC	709,802,1214	TC7WH125FU
	IC	710	AYW7188
	IC	712	MM1108XFS1
	IC	714	MM1504XN
	IC	716,902	ADV7180BSTZ
	IC	717	PDC166A
	IC	803,1007	TC74VHC125FTS1
	IC	804	PEG279B8
	IC	805	TC74VHCT541AFTS1
	IC	806	TC74HC4053AFT
	IC	807,808	BU4094BCFV
	IC	901	ADV7172KSTZ
	IC	1001	TC7SH08FUS1
	IC	1002	TSB43CA42ZGW
	IC	1003	K4S641632K-UC75
	IC	1004	AYW7113
	IC	1005	NJU7093AF
	IC	1006	PD5787A
	IC	1008	PD8112A
	IC	1009	PST9245
	IC	1010	TC7WH126FU
	IC	1204	TC74VHC04FTS1
	IC	1205	TC74VHC32FTS1
	IC	1206	SM5819AF
	IC	1208-1213	TC74LCX541FTS1
⚠	Q	11,51,52	RTQ045N03
	Q	12,53,706	DTC124EUA
	Q	13,201,1001,1002	DTA124EUA
	Q	14,55,57,58	2SC4081
	Q	54,101-106	DTC114YUA
	Q	56,803	RN4903
	Q	107	HN1K02FU
	Q	151-156,422,462	DTC114YUA
	Q	251	2SK2034
	Q	421,461	UMB1N
	Q	601-603,701,702	2SA1576A
	Q	703,704	2SC4081
	Q	705,901-904	2SA1576A
	Q	801	2SB1689
	Q	802	DTC114YUA
	Q	1202	DTC143EUA
⚠	D	11	1SR154-400
⚠	D	12	UDZS3R6(B)
⚠	D	54,55	UDZS2R4(B)
	D	56	RB551V-30
	D	101-103,151-153	DAN202U
	D	251	RB751V-40
	D	421,461	UDZS5R1(B)
	D	701	1SS352
	D	702,703,1001	RB501V-40
	TH	201,501	CCX1055

MISCELLANEOUS

	L	11,15 POWER INDUCTOR	ATH7050
	L	12-14,101-103 CHIP BEADS	ATL7010
	L	51-54 POWER INDUCTOR	ATH7050
	L	151-153,201-203 CHIP BEADS	ATL7010
	L	204,205 CHIP SOLID INDUCTOR	QTL1013
	L	206,301-303,313 CHIP BEADS	ATL7010
	L	207-210 CHIP SOLID INDUCTOR	QTL1013
	L	213,214 CHIP SOLID INDUCTOR	QTL1013
	L	304-306 CHIP SOLID INDUCTOR	QTL1013
	L	315,401 CHIP SOLID INDUCTOR	QTL1013
	L	316,421-425 CHIP BEADS	ATL7010
	L	426-429,466-469 COIL	ATH7022
	L	461-465,502-506 CHIP BEADS	ATL7010
	L	501 CHIP SOLID INDUCTOR	QTL1013
	L	507-509 CHIP SOLID INDUCTOR	QTL1013
	L	601,603 CHIP SOLID INDUCTOR	QTL1013
	L	602,604,701,703 CHIP BEADS	ATL7010
	L	608-610,708 INDUCTOR	ATL7015
	L	611,702 CHIP SOLID INDUCTOR	QTL1013
	L	704 INDUCTOR	LCTC6R8K1608
	L	705,711-714,716 CHIP BEADS	ATL7010
	L	706,707 CHIP SOLID INDUCTOR	QTL1013
	L	709,710 CHIP SOLID INDUCTOR	QTL1013
	L	715,802 CHIP SOLID INDUCTOR	QTL1013
	L	801,901-904,909 CHIP BEADS	ATL7010
	L	905-908 INDUCTOR	ATL7015
	L	910,1001,1008,1009 CHIP BEADS	ATL7010
	L	1002-1005 COIL	ATH7015
	L	1006,1007 CHIP SOLID INDUCTOR	QTL1013
	L	1010,1011 CHIP SOLID INDUCTOR	QTL1013
	L	1203 CHIP SOLID INDUCTOR	QTL1013
	L	1204 CHIP BEADS	ATL7010
	JA	101-103 HDMI CONNECTOR	AKP1318
	JA	151-153 HDMI CONNECTOR	AKP1318

Mark	No.	Description	Part No.
JA	421,461	HDMI CONNECTOR	AKP7220
JA	1001,1002	1394-TERMINAL	VKN1800
KN	11	EARTH METAL FITTING	VNF1109
X	201	CRYSTAL	ASS1192
X	301	CRYSTAL OSCILLATOR	ASS7073
X	501	CRYSTAL RESONATOR	VSS1223
X	701	CRYSTAL RESONATOR	ASS7066
X	702	CERAMIC RESONATOR (12 MHz)	VSS1216
X	703	RESONATOR	CSS1737
X	704	RESONATOR	CSS1750
X	801	CERAMIC RESONATOR	XSS3004
X	1001	CERAMIC RESONATOR	VSS1179
X	1002	CRYSTAL OSCILLATOR	ASS7071
X	1003	CRYSTAL OSCILLATOR	ASS7072
CN	11	CONNECTOR	B5P-VH
CN	251	8P CONNECTOR	VKN1412
CN	601	24P CONNECTOR	VKN1428
CN	602	26P CONNECTOR	VKN1430
CN	603	30P CONNECTOR	VKN1434
CN	701	6P CONNECTOR	VKN1410
CN	801	CONNECTOR	AKM1274
CN	804	18P CONNECTOR	VKN1422
CN	805	CONNECTOR	AKM1288
CN	1001	07P CONNECTOR	RKN1048
CN	1201	CONNECTOR	CKS3570
CN	1202	CONNECTOR	CKS3567
NSP	0	ID LABEL ASSY	AXW7018

RESISTORS

Mark	No.	Part No.
R	11,51,52	RS1/8S0R0J
R	12,53,54	RS1/8S4R7J
R	13,55,56	RS1/16S1002F
R	14,57,58,265	RS1/16S101J
R	15	RS1/16S3601F
R	20	RS1/16S121J
R	21,63,64	RS1/16S152J
R	22,69	RS1/16S114J
R	23	RS1/16S332J
R	24,73	RS1/16S102J
R	25,70,71	RS1/16S202J
R	26,28,30	RS1/16S0R0J
R	31	RS1/16S222J
R	32-35,40,41	RS1/16S0R0J
R	59	RS1/16S8201F
R	60	RS1/16S2402F
R	61	RS1/16S1501F
R	62	RS1/16S4701F
R	65,66	RS1/16S3301F
R	67	RS1/16S1001F
R	72,80,82	RS1/16S0R0J
R	84-86,237,264	RS1/16S0R0J
R	141,142,191,192	RS1/16SS1501F
R	202,216	RAB4CQ100J
R	207,301-304,336	RAB4CQ473J
R	208,608-614	RAB4CQ680J
R	221,223,229-235	RAB4CQ220J
R	236,595	RS1/16SS4701F
R	271,570,574,577	RAB4CQ470J
R	308,309,311-313	RAB4CQ330J
R	319-321,337,339	RAB4CQ220J
R	330,331,517-519	RAB4CQ330J
R	340,343,347,421	RAB4CQ473J
R	341,342,344	RAB4CQ220J
R	348-350,404-412	RAB4CQ220J
R	424,425,427-431	RAB4CQ473J
R	436,440,638-644	RAB4CQ473J
R	439,469	RS1/16SS6800F
R	525-527,531,540	RAB4CQ330J
R	544,546-548,551	RAB4CQ330J
R	552,561,562	RAB4CQ330J
R	582,583,922,925	RAB4CQ470J
R	599-603,685-689	RAB4CQ220J
R	648,649	RS1/16SS3901F
R	652,653,937,941	RS1/16SS2200F
R	655,656,671	RS1/16SS3000F
R	657-661	RAB4CQ680J
R	672-674	RS1/16SS3900F
R	675,789-792,810	RS1/16S0R0J
R	676	RS1/16SS1801F
R	677-679	RS1/16SS1501F
R	702-705,6011-6015	RAB4CQ473J
R	716,720	RS1/16SS75R0F
R	747	RS1/16SS1003F
R	748,753	RAB4CQ560J
R	767,842,868,870	RAB4CQ101J
R	771-775	RAB4CQ820J
R	802-804,1247-1249	RAB4CQ0R0J
R	809,898	RS1/10S911J
R	871,874,879,893	RAB4CQ101J
R	915-918	RS1/16SS1201F
R	926,928,932,933	RS1/16SS4700F
R	929,931,936,938	RS1/10S0R0J
R	949,950	RS1/16SS2200F
R	1001-1004,1037,1041	RAB4CQ101J
R	1009,1010,1013,1014	RS1/16SS56R0D
R	1011,1015	RS1/16SS5101F
R	1017,1020-1022	RS1/16SS56R0D
R	1018,1023,1024,1026	RAB4CQ472J
R	1029-1031,1033,1040	RAB4CQ472J
R	1042,1043,1048,1049	RS1/16S0R0J
R	1050	RS1/16SS6341D
R	1053,1071,1074,1077	RAB4CQ472J
R	1060,1082,1083,1085	RAB4CQ101J
R	1062,1063,1068,1069	RS1/16S0R0J
R	1081	RAB4CQ472J
R	1086,1089,1099,1108	RAB4CQ470J
R	1087,1097,1207-1210	RAB4CQ101J
R	1109	RAB4CQ103J
R	1126,1127,1135-1137	RAB4CQ470J
R	1221	RAB4CQ470J
R	1224-1227,1242-1245	RAB4CQ910J
R	6003	RAB4CQ101J
R	6008-6010	RS1/10S0R0J
Other Resistors		RS1/16SS###J

CAPACITORS

Mark	No.	Part No.
C	11,12,42,59	CKSQYB475K6R3
C	13,51,52	CCG1230

Mark	No.	Description	Part No.
C	14,54,55		CKSQYB332K50
C	15,21,56,57		CKSRYB153K50
C	16,17,19,22		CKSRYB105K10
C	18,24-26,38		CKSRYB104K16
C	20,37,47,48		CKSRYB102K50
C	23,28,29,43		CKSRYB105K10
C	27,78,79		CCG1233
C	30,32		CCG1236
C	31,33,46,64		CEVW101M16
C	34,53,80,117		CKSQYB106K6R3
C	39,44,60,62		CKSRYB104K16
C	40,89,90,574		CKSQYB102K50
C	41,91,92,101		CKSSYB104K10
C	49,50,58,61		CKSRYB105K10
C	63,65,73,76		CKSRYB105K10
C	66,74,75,84		CKSRYB104K16
C	67,68,83,85		CKSRYB102K50
C	69,70		CKSRYB153K50
C	71,72		CKSQYB225K10
C	77,81,82,252		CKSRYB105K10
C	86-88		CKSRYB104K16
C	102,116,152,166		BCG1059
C	103-115,119-123		CKSSYB104K10
C	118,168,228,241		CKSSYB103K16
C	151,153-165		CKSSYB104K10
C	167,201,203,374		CKSQYB106K6R3
C	169-173,204-210		CKSSYB104K10
C	202,211,213,225		CKSSYB105K6R3
C	212,232,421,431		BCG1059
C	215,216,219,220		CKSSYB104K10
C	218,250,257		CKSSYB102K50
C	221,239,761		CCSSCH120J50
C	222,223,227,229		CKSSYB104K10
C	224,743,744,747		CCSSCH100D50
C	226,230,231,313		CKSSYB105K6R3
C	233-238,243-245		CKSSYB104K10
C	240		CEVW4R7M35
C	242,359,363,371		CKSSYB103K16
C	248,249,259		CKSSYB104K10
C	253		CKSRYB105K10
C	256,321,502,764		CEVW470M6R3
C	262-273,301,350		CKSSYB102K50
C	302-307,311,312		CKSSYB104K10
C	308,503,516,543		ACH7276
C	309,310,357,402		CEVW101M16
C	314-318,320,322		CKSSYB104K10
C	319,324,325,333		CKSSYB105K6R3
C	323,326,327		CKSSYB104K10
C	329-332,354-356		CKSSYB104K10
C	336,341,346		CCSSCH470J50
C	349,358,401		CKSSYB105K6R3
C	351-353,636,742		CCSSCH101J50
C	368,370,375-381		CKSSYB104K10
C	369,784,931		CKSSYB823K10
C	372		CKSRYB824K10
C	373		CKSSYB393K10
C	382,449-457		CKSSYB102K50
C	383,384,430,470		CKSSYB103K16
C	385-392,396-399		CKSSYB104K10
C	393,394,433-435		CKSQYB106K6R3
C	395,400,601,618		CEVW100M16
C	403,425-427,432		CKSSYB104K10
C	422-424,428,429		CKSSYB105K6R3
C	436,438,462-464		CKSSYB105K6R3
C	437,439,440		CKSSYB104K10
C	441-448,481-488		VCG1066
C	461,471		BCG1059
C	465-467,472,477		CKSSYB104K10
C	468,469,476,478		CKSSYB105K6R3
C	473-475,627-629		CKSQYB106K6R3
C	479,480,504-515		CKSSYB104K10
C	489-497,749,786		CKSSYB102K50
C	501,712,729,750		CKSSYB105K6R3
C	517-542,544,547		CKSSYB104K10
C	545,1003,1076,1216		ACH7276
C	546,666,667,704		CKSSYB103K16
C	548,550-573,575		CKSSYB104K10
C	549,617,625,633		CEVW101M16
C	576,578		CKSQYB102K50
C	577,579,580		CKSSYB104K10
C	581,582		CCSSCH9R0D50
C	602-610,613-616		CKSSYB104K10
C	611,620		CKSRYB154K10
C	612,619		CKSSYB123K16
C	622-624,626,634		CKSSYB104K10
C	635,637,638		CKSSYB104K10
C	639-644		CCSSCH150J50
C	645-647,650-655		CKSSYB104K10
C	648,649,1046		CKSQYB106K6R3
C	657,701-703,706		CKSSYB104K10
C	669-671		CCSSCH680J50
C	705,718,737,752		CEVW101M16
C	710,711,713,714		CKSSYB104K10
C	716,719,723		CKSSYB104K10
C	717,721		CCSSCH180J50
C	720,724,753,783		CKSSYB103K16
C	725-728,731,732		CKSSYB104K10
C	734,740,741,748		CKSSYB104K10
C	738,739		CEVW100M16
C	745,958-963		CCSSCH101J50
C	746		CCSSCH6R0D50
C	751,755,756,760		CKSSYB104K10
C	754		CKSQYB335K6R3
C	757-759,765,766		CKSSYB105K6R3
C	762,763,767-769		CKSSYB104K10
C	770		CCSRCH561J50
C	771		CKSSYB392K50
C	772		CKSSYB561K50
C	773,787,795,938		CKSSYB105K6R3
C	774,777-781,788		CKSSYB104K10
C	775,776,782,790		CEVW101M16
C	785,794,806,905		CKSSYB103K16
C	789,791-793,799		CKSSYB104K10
C	796		CCSSCH7R0D50
C	797,798,801,802		CKSSYB102K50
C	804,805,807		CKSSYB104K10
C	808,901,909,910		CEVW101M16
C	809-811,814-817		CKSSYB104K10

Mark	No.	Description	Part No.
C	902-904,906-908		CKSSYB104K10
C	911-916,921,922		CKSSYB104K10
C	917,940,1038,1067		CEVW101M16
C	920,923,929,930		CCSSCH390J50
C	924,927,934,935		CCSSCH820J50
C	928,933,952,953		CKSSYB103K16
C	932,937,939,941		CKSSYB104K10
C	936,1004,1018,1019		CKSSYB102K50
C	942,949-951,1001		CKSSYB104K10
C	943-948,1012,1013		CKSSYB105K6R3
C	1002,1005-1009		CKSSYB104K10
C	1010,1011		CCSSCH221J50
C	1014-1017,1020,1021		CKSSYB104K10
C	1022,1027,1061,1064		CKSSYB102K50
C	1023-1026,1028-1032		CKSSYB104K10
C	1033,1048		CEVW470M6R3
C	1034-1037,1040-1042		CKSSYB104K10
C	1039,1055,1062,1070		CKSSYB103K16
C	1043,1049,1060,1065		CKSSYB105K6R3
C	1044		CKSRYB474K10
C	1045,1050-1054		CKSSYB104K10
C	1047		CKSSYB472K25
C	1056-1059,1063,1068		CKSSYB104K10
C	1066,1075		CKSSYB102K50
C	1069,1071-1074,1077		CKSSYB104K10
C	1205-1207,1215		CKSSYB104K10
C	1214		CKSSYB103K16
C	1217-1226,1228-1232		CKSSYB104K10
C	1227		ACH7276

AF DISPLAY ASSY

MISCELLANEOUS

Mark	No.	Description	Part No.
IC	5001 (A,136,168)	PORT EXPANDER	BU4094BCF
IC	5002 (A,136,156)	PORT EXPANDER	BU4094BCF
IC	5003 (A,116,156)	PORT EXPANDER	BU4094BCF
IC	5004 (A,31,216)	REMOTE RECEIVER UNIT	RPM7540-H4
Q	5001 (B,43,195)	TRANSISTOR	RT1N241M
Q	5002 (B,45,172)	TRANSISTOR	RT1N241M
Q	5003 (B,176,182)	TRANSISTOR	RT1N241M
Q	5005 (B,174,159)	TRANSISTOR	RT1N241M
Q	5006 (B,38,187)	TRANSISTOR(SC-70)	2SA1602A
Q	5007 (B,40,170)	TRANSISTOR(SC-70)	2SA1602A
Q	5008 (B,183,165)	TRANSISTOR(SC-70)	2SA1602A
Q	5009 (B,185,187)	TRANSISTOR(SC-70)	2SA1602A
Q	5011 (B,34,197)	TRANSISTOR	2SC4154
Q	5012 (B,34,176)	TRANSISTOR	2SC4154
Q	5013 (B,180,165)	TRANSISTOR	2SC4154
Q	5014 (B,176,193)	TRANSISTOR	2SC4154
Q	5021 (B,59,211)	TRANSISTOR	RT1N241M
Q	5022 (B,59,203)	TRANSISTOR	RT1N241M
Q	5023 (B,59,197)	TRANSISTOR	RT1N241M
Q	5024 (B,56,209)	TRANSISTOR	2SC4154
Q	5025 (A,58,204)	TRANSISTOR	RT1N241M
Q	5026 (A,58,198)	TRANSISTOR	RT1N241M
Q	5027 (A,58,194)	TRANSISTOR	RT1N241M
Q	5028 (A,58,211)	TRANSISTOR	2SC4154
Q	5029 (A,48,215)	TRANSISTOR(SC-70)	2SA1602A
Q	5030 (A,49,227)	TRANSISTOR	RT1N241M

Mark	No.	Description	Part No.
D	5001 (A,31,194)	LED(RED)	SLR-343VC(NP)
D	5002 (A,31,172)	LED(RED)	SLR-343VC(NP)
D	5003 (A,181,172)	LED(RED)	SLR-343VC(NP)
D	5004 (A,181,194)	LED(BLUE)	SLR343BC4T(JKLM)
D	5011 (B,49,214)	DIODE	1SS352
D	5012 (B,39,212)	DIODE	MC2848-11
D	5013 (B,48,203)	DIODE	1SS352
D	5014 (B,48,197)	DIODE	1SS352
D	5021 (B,62,220)	DIODE	MC2848-11
D	5022 (A,55,216)	DIODE	1SS352
D	5023 (A,52,216)	DIODE	1SS352
D	5024 (B,56,214)	DIODE	1SS352
J	5005	JUMPER WIRE	D20PYY0820E
CN	5001 (A,185,232)	28P CONNECTOR	RKN1069
CN	5002 (A,14,194)	26P CONNECTOR	RKN1067
CN	5003 (A,14,164)	26P CONNECTOR	RKN1067
CN	5004 (A,195,160)	7P CONNECTOR	52044-0745
CN	5006 (A,195,177)	CONNECTOR	52044-0345
CN	5007 (A,26,229)	CONNECTOR	52044-0345
CN	5008 (A,100,154)	CONNECTOR	CKS3369
	5005 (A,15,229)	8P CABLE HOLDER	51048-0800
	5021 (A,198,224)	PCB BINDER	VEF1040

RESISTORS

R	5000 (B,140,155)		RS1/16S101J
R	5001 (B,39,199)		RS1/16S821J
R	5002 (B,37,199)		RS1/16S821J
R	5003 (B,38,177)		RS1/16S821J
R	5004 (B,40,177)		RS1/16S821J
R	5005 (B,175,164)		RS1/16S821J
R	5006 (B,177,164)		RS1/16S821J
R	5007 (B,179,187)		RS1/16S821J
R	5011 (B,62,215)		RS1/16S392J
R	5012 (B,62,210)		RS1/16S471J
R	5013 (B,62,203)		RS1/16S151J
R	5014 (B,62,197)		RS1/16S392J
R	5015 (B,60,215)		RS1/16S682J
R	5016 (B,55,203)		RS1/16S102J
R	5017 (A,39,213)		RS1/16S0R0J
R	5018 (B,26,220)		RS1/16S0R0J
R	5019 (B,30,202)		RS1/16S101J
R	5020 (A,39,182)		RAB4C101J
R	5021 (A,30,182)		RAB4C101J
R	5022 (A,39,187)		RAB4C101J
R	5023 (A,39,193)		RAB4C101J
R	5024 (A,29,202)		RAB4C101J
R	5025 (B,192,215)		RS1/16S101J
R	5026 (B,190,215)		RS1/16S101J
R	5027 (A,174,208)		RAB4C101J
R	5028 (A,172,213)		RAB4C101J
R	5029 (A,179,225)		RAB4C101J
R	5030 (A,176,222)		RS1/16S101J
R	5031 (A,39,176)		RAB4C101J
R	5032 (A,39,171)		RAB4C101J
R	5033 (A,39,167)		RAB4C101J
R	5034 (A,146,170)		RAB4C473J
R	5035 (A,145,164)		RAB4C473J
R	5036 (A,147,159)		RAB4C473J
R	5037 (A,151,153)		RAB4C473J

Mark	No.	Description	Part No.
R	5038 (A,127,158)		RAB4C473J
R	5039 (A,127,154)		RAB4C473J
R	5040 (B,169,220)		RS1/16S0R0J
R	5048 (A,191,220)		RS1/16S0R0J
R	5049 (A,188,221)		RS1/16S0R0J
R	5051 (B,41,188)		RS1/16S333J
R	5052 (B,43,170)		RS1/16S333J
R	5053 (A,181,161)		RS1/16S333J
R	5054 (A,181,183)		RS1/16S333J
R	5056 (B,43,188)		RS1/16S272J
R	5057 (B,45,166)		RS1/16S272J
R	5058 (A,179,161)		RS1/16S272J
R	5059 (A,179,183)		RS1/16S272J
R	5061 (B,55,190)		RS1/16S331J
R	5062 (B,60,168)		RS1/16S331J
R	5063 (B,164,164)		RS1/16S331J
R	5064 (B,166,187)		RS1/16S331J
R	5066 (A,55,211)		RS1/16S222J
R	5067 (A,54,205)		RS1/16S152J
R	5068 (A,54,201)		RS1/16S152J
R	5069 (A,54,198)		RS1/16S682J
R	5070 (A,56,208)		RS1/16S102J
R	5088 (A,46,215)		RS1/16S103J
R	5089 (A,50,224)		RS1/16S331J
R	5090 (A,187,205)		RS1/16S0R0J
R	5091 (A,185,205)		RS1/16S0R0J
R	5092 (A,188,205)		RS1/16S0R0J
R	5093 (A,189,196)		RS1/16S0R0J
R	5094 (A,189,192)		RS1/16S0R0J
R	5095 (A,189,188)		RS1/16S0R0J
R	5096 (A,196,220)		RS1/16S0R0J

CAPACITORS

C	5001 (B,35,193)		CCSRCH471J50
C	5002 (B,35,171)		CCSRCH471J50
C	5003 (B,185,171)		CCSRCH471J50
C	5004 (B,185,193)		CCSRCH471J50
C	5006 (B,33,202)		CKSRYB103K25
C	5007 (A,39,206)		CEJQ101M6R3
C	5008 (A,31,224)		CEJQ101M6R3
C	5009 (A,65,226)		CEAL101M16
C	5012 (A,130,170)		CKSRYB103K25
C	5013 (A,130,159)		CKSRYB103K25
C	5014 (A,109,157)		CKSRYB103K25
C	5021 (B,166,222)		CKSRYB105K16

AG ICEBLUE ASSY

MISCELLANEOUS

Q	5072 (B,94,226)	TRANSISTOR	RT1N241M
Q	5073 (B,112,226)	TRANSISTOR	RT1N241M
Q	5074 (B,124,225)	TRANSISTOR	RT1N241M
Q	5077 (B,96,224)	TRANSISTOR(SC-70)	2SA1602A
Q	5078 (B,115,226)	TRANSISTOR(SC-70)	2SA1602A
Q	5079 (B,127,226)	TRANSISTOR(SC-70)	2SA1602A
Q	5082 (B,100,231)	TRANSISTOR(SC-70)	2SA1602A
Q	5083 (B,122,231)	TRANSISTOR(SC-70)	2SA1602A
Q	5084 (B,132,231)	TRANSISTOR(SC-70)	2SA1602A
D	5072 (A,103,230)	LED	SMLE12BC7T(NP)
D	5073 (A,113,230)	LED(WHITE)	SMLE12WBC7W(Z)
D	5074 (A,123,230)	LED	SMLE12BC7T(NP)
CN	5071 (A,103,222)	CONNECTOR	52044-0445

RESISTORS

R	5072 (B,99,226)		RS1/4SA331J
R	5073 (B,121,227)		RS1/4SA271J
R	5074 (B,131,227)		RS1/4SA331J
R	5077 (B,97,230)		RS1/16S333J
R	5078 (B,118,230)		RS1/16S333J
R	5079 (B,128,230)		RS1/16S333J
R	5082 (B,95,230)		RS1/16S272J
R	5083 (B,116,230)		RS1/16S272J
R	5084 (B,126,230)		RS1/16S272J

CAPACITORS

C	5072 (A,107,230)		CCSRCH471J50
C	5073 (A,115,230)		CCSRCH471J50
C	5074 (A,125,230)		CCSRCH471J50

AH PERCH FFC ASSY

MISCELLANEOUS

CN	5091 (A,225,80)	26P CONNECTOR	VKN1430
CN	5092 (A,226,66)	12P CONNECTOR	VKN1416
CN	5093 (A,239,66)	14P CONNECTOR	VKN1418
	5094 (A,192,88)	PCB BINDER	VEF1040
	5095 (A,191,56)	PCB BINDER	VEF1040

AI PERCH DISP ASSY

MISCELLANEOUS

CN	5082 (A,97,208)	CONNECTOR(08P)	TUC-P08X-B1
	5081 (A,107,206)	8P CABLE HOLDER	51048-0800

AJ PERCH PS ASSY

MISCELLANEOUS

F	6501 (A,132,207)	COMMON MODE COIL	ATF7043
CN	6501 (A,125,201)	PLUG(7P)	KM200NA7
CN	6502 (A,143,203)	CONNECTOR(08P)	TUC-P08P-B1

CAPACITORS

C	6501 (A,140,211)		CEAT101M16

AK 5.1 TFT MODULE

5.1 TFT MODULE has no service part.

AL TACT ASSY

MISCELLANEOUS

Q	5101 (B,86,171)	TRANSISTOR	RT1N241M
Q	5102 (B,101,171)	TRANSISTOR	RT1N241M
Q	5103 (B,115,171)	TRANSISTOR	RT1N241M
Q	5104 (B,129,171)	TRANSISTOR	RT1N241M

Mark	No.	Description	Part No.
Q	5105 (B,144,171)	TRANSISTOR	RT1N241M
Q	5106 (B,158,169)	TRANSISTOR	RT1N241M
Q	5107 (B,173,171)	TRANSISTOR	RT1N241M
Q	5108 (B,189,171)	TRANSISTOR	RT1N241M
Q	5109 (B,202,171)	TRANSISTOR	RT1N241M
Q	5110 (B,214,171)	TRANSISTOR	RT1N241M
Q	5111 (B,86,176)	TRANSISTOR(SC-70)	2SA1602A
Q	5112 (B,98,171)	TRANSISTOR(SC-70)	2SA1602A
Q	5113 (B,115,176)	TRANSISTOR(SC-70)	2SA1602A
Q	5114 (B,126,171)	TRANSISTOR(SC-70)	2SA1602A
Q	5115 (B,144,176)	TRANSISTOR(SC-70)	2SA1602A
Q	5116 (B,158,175)	TRANSISTOR(SC-70)	2SA1602A
Q	5117 (B,173,176)	TRANSISTOR(SC-70)	2SA1602A
Q	5118 (B,186,171)	TRANSISTOR(SC-70)	2SA1602A
Q	5119 (B,202,176)	TRANSISTOR(SC-70)	2SA1602A
Q	5120 (B,214,176)	TRANSISTOR(SC-70)	2SA1602A
Q	5121 (B,82,176)	TRANSISTOR(SC-70)	2SA1602A
Q	5122 (B,95,176)	TRANSISTOR(SC-70)	2SA1602A
Q	5123 (B,111,176)	TRANSISTOR(SC-70)	2SA1602A
Q	5124 (B,123,176)	TRANSISTOR(SC-70)	2SA1602A
Q	5125 (B,140,176)	TRANSISTOR(SC-70)	2SA1602A
Q	5126 (B,154,176)	TRANSISTOR(SC-70)	2SA1602A
Q	5127 (B,169,176)	TRANSISTOR(SC-70)	2SA1602A
Q	5128 (B,183,176)	TRANSISTOR(SC-70)	2SA1602A
Q	5129 (B,198,176)	TRANSISTOR(SC-70)	2SA1602A
Q	5130 (B,210,176)	TRANSISTOR(SC-70)	2SA1602A
D	5101 (A,84,175)	LED	SMLE12BC7T(NP)
D	5102 (A,98,175)	LED	SMLE12BC7T(NP)
D	5103 (A,113,175)	LED	SMLE12BC7T(NP)
D	5104 (A,127,175)	LED	SMLE12BC7T(NP)
D	5105 (A,142,175)	LED	SMLE12BC7T(NP)
D	5106 (A,156,175)	LED	SMLE12BC7T(NP)
D	5107 (A,171,175)	LED	SMLE12BC7T(NP)
D	5108 (A,185,175)	LED	SMLE12BC7T(NP)
D	5109 (A,200,175)	LED	SMLE12BC7T(NP)
D	5110 (A,214,175)	LED	SMLE12BC7T(NP)
S	5121 (A,51,152)	SWITCH	VSG1024
S	5122 (A,38,152)	SWITCH	VSG1024
S	5123 (A,38,133)	SWITCH	VSG1024
S	5124 (A,51,133)	SWITCH	VSG1024
S	5125 (A,132,157)	SWITCH	VSG1024
S	5126 (A,161,157)	SWITCH	VSG1024
S	5127 (A,132,127)	SWITCH	VSG1024
S	5128 (A,161,127)	SWITCH	VSG1024
S	5131 (A,64,152)	SWITCH	VSG1024
S	5132 (A,147,155)	SWITCH	VSG1024
S	5133 (A,133,142)	SWITCH	VSG1024
S	5134 (A,147,128)	SWITCH	VSG1024
S	5135 (A,160,142)	SWITCH	VSG1024
S	5136 (A,186,152)	SWITCH	VSG1024
S	5137 (A,199,152)	SWITCH	VSG1024
S	5138 (A,212,152)	SWITCH	VSG1024
S	5142 (A,147,142)	SWITCH	VSG1024
S	5143 (A,90,152)	SWITCH	VSG1024
S	5144 (A,103,152)	SWITCH	VSG1024
CN	5101 (A,32,151)	26P CONNECTOR	RKN1067
CN	5102 (A,29,178)	CONNECTOR	52044-0445

Mark	No.	Description	Part No.
RESISTORS			
R	5101 (B,81,172)		RS1/4SA331J
R	5102 (B,95,172)		RS1/4SA331J
R	5103 (B,110,172)		RS1/4SA331J
R	5104 (B,123,172)		RS1/4SA331J
R	5105 (B,139,172)		RS1/4SA331J
R	5106 (B,154,172)		RS1/4SA331J
R	5107 (B,169,172)		RS1/4SA331J
R	5108 (B,183,172)		RS1/4SA331J
R	5109 (B,197,172)		RS1/4SA331J
R	5110 (B,209,172)		RS1/4SA331J
R	5121 (B,40,152)		RS1/16S681J
R	5122 (B,40,134)		RS1/16S821J
R	5123 (B,53,134)		RS1/16S122J
R	5124 (B,134,157)		RS1/16S162J
R	5125 (B,164,156)		RS1/16S272J
R	5126 (B,134,132)		RS1/16S512J
R	5127 (B,164,128)		RS1/16S123J
R	5131 (B,149,155)		RS1/16S681J
R	5132 (B,136,143)		RS1/16S821J
R	5133 (B,149,129)		RS1/16S122J
R	5134 (B,162,142)		RS1/16S162J
R	5135 (B,188,153)		RS1/16S272J
R	5136 (B,201,153)		RS1/16S512J
R	5137 (B,214,153)		RS1/16S123J
R	5141 (B,149,143)		RS1/16S681J
R	5142 (B,86,153)		RS1/16S821J
R	5143 (B,105,154)		RS1/16S122J
R	5144 (B,66,134)		RS1/16S162J
R	5145 (B,73,134)		RS1/16S272J
R	5146 (B,79,134)		RS1/16S512J
R	5161 (B,89,176)		RS1/16S333J
R	5162 (B,104,175)		RS1/16S333J
R	5163 (B,118,176)		RS1/16S333J
R	5164 (B,132,175)		RS1/16S333J
R	5165 (B,147,176)		RS1/16S333J
R	5166 (B,163,174)		RS1/16S333J
R	5167 (B,176,176)		RS1/16S333J
R	5168 (B,192,175)		RS1/16S333J
R	5169 (B,205,176)		RS1/16S333J
R	5170 (B,216,176)		RS1/16S333J
R	5171 (B,89,171)		RS1/16S272J
R	5172 (B,104,171)		RS1/16S272J
R	5173 (B,118,171)		RS1/16S272J
R	5174 (B,132,171)		RS1/16S272J
R	5175 (B,147,171)		RS1/16S272J
R	5176 (B,161,174)		RS1/16S272J
R	5177 (B,176,171)		RS1/16S272J
R	5178 (B,192,171)		RS1/16S272J
R	5179 (B,205,171)		RS1/16S272J
R	5180 (B,216,172)		RS1/16S272J
CAPACITORS			
C	5101 (A,85,175)		CCSRCH471J50
C	5102 (A,100,175)		CCSRCH471J50
C	5103 (A,114,175)		CCSRCH471J50
C	5104 (A,129,175)		CCSRCH471J50
C	5105 (A,143,175)		CCSRCH471J50
C	5106 (A,158,175)		CCSRCH471J50

Mark	No.	Description	Part No.
C	5107 (A,172,175)		CCSRCH471J50
C	5108 (A,187,175)		CCSRCH471J50
C	5109 (A,201,175)		CCSRCH471J50
C	5110 (A,216,175)		CCSRCH471J50
C	5121 (B,53,152)		CKSRYB102K50
C	5131 (B,66,153)		CKSRYB102K50
C	5141 (B,79,152)		CKSRYB102K50
C	5151 (A,82,175)		CKSRYB104K16
C	5152 (A,97,175)		CKSRYB104K16
C	5153 (A,111,175)		CKSRYB104K16
C	5154 (A,126,175)		CKSRYB104K16
C	5155 (A,140,175)		CKSRYB104K16
C	5156 (A,155,175)		CKSRYB104K16
C	5157 (A,169,175)		CKSRYB104K16
C	5158 (A,184,175)		CKSRYB104K16
C	5159 (A,198,175)		CKSRYB104K16
C	5160 (A,213,175)		CKSRYB104K16
C	5161 (B,79,167)		CKSRYB104K16
C	5162 (B,108,167)		CKSRYB104K16
C	5163 (B,137,167)		CKSRYB104K16
C	5164 (B,171,165)		CKSRYB104K16
C	5165 (B,195,167)		CKSRYB104K16
C	5166 (B,58,164)		CKSRYB104K16
C	5167 (B,219,164)		CKSRYB104K16
C	5168 (B,32,163)		CKSRYB104K16

AM POWER SW ASSY

MISCELLANEOUS

Q	5191 (B,294,78)	DIGITAL TR(SC-70)	RT1N431M
D	5191 (A,288,77)	LED(BLUE)	SLR343BC4T(JKLM)
S	5191 (A,286,68)	SWITCH	VSG1024
CN	5191 (A,310,94)	CONNECTOR	52044-0445

RESISTORS

R	5191 (B,297,75)		RS1/16S151J

CAPACITORS

C	5191 (B,283,76)		CCSRCH471J50
C	5192 (B,281,76)		CKSRYB104K16
C	5193 (B,305,87)		CKSRYB104K16

AN VOL ENCODER ASSY

MISCELLANEOUS

S	5081	ROTARY ENCODER	ASX7049
CN	5081	CONNECTOR	52044-0345

CAPACITORS

C	5081,5082		CKSRYB103K50

AO FUNC ENCODER ASSY

MISCELLANEOUS

S	5085	ROTARY ENCODER	ASX7050
CN	5085	CONNECTOR	52044-0345

Mark	No.	Description	Part No.

CAPACITORS

C	5085,5086		CKSRYB103K50

AP ICE REG ASSY

SEMICONDUCTORS

⚠ D	4801		S1WB(A)60SD
D	4803,4804,4853,4863		RB501V-40
⚠ D	4805,4806		MTZJ6R2(B)
⚠ D	4851,4852,4861,4862		1SR154-400

MISCELLANEOUS

H	4801-4804	FUSE CLIP	AKR7001
CN	4801	3PIN CONNECTOR	S3B-EH
CN	4802	3PIN CONNECTOR	AKM1363
CN	4851	4PIN CONNECTOR	AKM1364
	4801,4851	5P CABLE HOLDER	51048-0500
	4811,4812	PCB BINDER	VEF1040
JP	4801,4851	5P JUMPER WIRE	D20PYY0505E

RESISTORS

R	4851		RS1/16S0R0J
⚠ R	4801		RD1/4MUF4R7J

CAPACITORS

C	4801		CFTNA105J50
C	4802,4803,4851,4861		CEAT332M16
C	4809,4812		CKSRYB103K50
C	4852,4862		CEAT472M35
C	4866,4867		CEAT221M25

AQ ICE 5 ASSY

SEMICONDUCTORS

⚠ IC	4803		NJM7805FA
⚠ IC	4804		NJM7905FA

MISCELLANEOUS

	4802	5P CABLE HOLDER	51048-0500

CAPACITORS

C	4804,4805		CKSRYB103K50
C	4806,4807		CEAT101M16

AR ICE 12 ASSY

SEMICONDUCTORS

⚠ IC	4851		NJM78M12FA
⚠ IC	4861		NJM79M12FA

MISCELLANEOUS

	4852	5P CABLE HOLDER	51048-0500

Mark	No.	Description	Part No.
CAPACITORS			
	C	4853,4863	CKSQYB474K25
	C	4854,4864	CEAT101M16
	C	4855,4865	CKSRYB104K25

AS DD DSP ASSY

MISCELLANEOUS

⚠	IC	4301 (A,171,46)	REGULATOR IC	LTC1735EGN
⚠	IC	4303 (A,178,56)	POWER MOS FET	RSS065N03
⚠	IC	4304 (A,187,49)	POWER MOS FET	RSS065N03
⚠	IC	4305 (A,156,75)	PROTECTOR(5A)	AEK7046
⚠	IC	4321 (A,243,23)	REGULATOR IC	BD9718G
⚠	IC	4351 (A,234,61)	REGULATOR IC	LT3430EFE
⚠	Q	4321 (A,238,16)	TRANSISTOR	2SD1664
	D	4303 (A,194,49)	CHIP DIODE	RB050L-40
	D	4304 (A,179,47)	DIODE	RB160M-40
	D	4306 (A,170,29)	CHIP ZENER DIODE	RLZ6.2B
	D	4307 (A,214,16)	CHIP ZENER DIODE	RLZ6.2B
	D	4321 (A,234,21)	DIODE	RB551V-30
	D	4352 (A,244,60)	CHIP DIODE	RB050L-40
	D	4353 (A,232,46)	CHIP DIODE	RB050L-40
	L	4301 (A,204,53)	INDUCTOR	ATH7033
	L	4303 (A,160,29)	COMMON MODE COIL	ATF7042
	L	4304 (A,160,23)	COMMON MODE COIL	ATF7042
	L	4321 (A,243,16)	POWER INDUCTOR(10U)	DTL1124
	L	4322 (A,230,17)	POWER INDUCTOR(10U)	DTL1124
	L	4351 (A,236,38)	INDUCTOR	ATH1220
	H	4301 (A,148,60)	FUSE CLIP	AKR7001
	H	4302 (A,148,82)	FUSE CLIP	AKR7001
	H	4351 (A,137,73)	FUSE CLIP	AKR7001
	H	4352 (A,137,94)	FUSE CLIP	AKR7001
	J	4303 (A,215,31)	2P HOUSING ASSY	ADX7592
	KN	4301 (A,143,110)	SCREW PLATE	VNE1948
	KN	4302 (A,183,15)	SCREW PLATE	VNE1948
	KN	4351 (A,245,110)	SCREW PLATE	VNE1948
	CN	4302 (A,144,22)	CONNECTOR	B3P-VH
		4301 (A,139,37)	PCB BINDER	VEF1040

RESISTORS

⚠	R	4301 (A,159,80)	CARBON FILM RESISTOR	RD1/4MUF4R7J
	R	4302 (A,164,47)		RS1/16S222J
	R	4303 (A,165,40)		RS1/16S100J
	R	4304 (A,166,40)		RS1/16S100J
⚠	R	4305 (A,210,43)		CCN1148
	R	4306 (A,162,44)		RN1/16SE1103D
	R	4307 (A,158,44)		RN1/16SE2002D
	R	4308 (A,177,51)		RS1/16S4R7J
	R	4309 (A,183,47)		RS1/16S4R7J
	R	4310 (A,164,50)		RS1/16S514J
	R	4321 (A,239,25)		RS1/16S153J
	R	4322 (A,240,20)		RS1/16S101J
⚠	R	4351 (A,207,95)	CARBON FILM RESISTOR	RD1/4MUF4R7J
	R	4352 (A,226,62)		RS1/16S332J
	R	4353 (A,223,62)		RS1/16S0R0J
	R	4354 (A,222,58)		RN1/16SE1602D
	R	4355 (A,221,62)		RN1/16SE5101D
	R	4356 (A,221,38)		RS1/8SQ0R0J
	R	4357 (A,221,36)		RS1/8SQ0R0J
	R	4358 (A,221,27)		RS1/8SQ0R0J
	R	4359 (A,221,25)		RS1/8SQ0R0J

CAPACITORS

	C	4301 (A,154,90)	FILM CAPACITOR	CQMBA104J50
	C	4302 (A,172,79)	ELECTR.CAPACITOR	ACH7295
	C	4303 (A,170,53)		CCG1236
	C	4304 (A,176,44)		CKSYB475K16
	C	4305 (A,164,52)		CCSRCH220J50
	C	4306 (A,164,49)		CKSRYB103K50
	C	4307 (A,164,46)		CCSRCH221J50
	C	4308 (A,160,47)		CCSRCH681J50
	C	4310 (A,166,42)		CCSRCH102J50
	C	4311 (A,181,52)		CKSRYB224K16
	C	4312 (A,159,42)		CCSRCH471J50
	C	4313 (A,202,43)	CHIP CAPACITOR	CKSYB106K10
	C	4314 (A,204,36)	OS CAPACITOR	ACH7203
	C	4317 (A,174,62)		CCG1236
	C	4321 (A,247,22)	CHIP CAPACITOR	CKSYB106K10
	C	4322 (A,238,21)		CKSRYB222K50
	C	4323 (A,242,20)		CKSRYB103K50
	C	4324 (A,234,16)		CKSRYB105K16
	C	4325 (A,224,18)	ELECT. CAPACITOR	CEHAZL100M50
	C	4351 (A,223,100)	FILM CAPACITOR	CQMBA104J50
	C	4352 (A,205,80)	ELECTR.CAPACITOR	ACH7294
	C	4353 (A,245,64)		CCG1236
	C	4354 (A,227,64)		CCSRCH221J50
	C	4355 (A,226,64)		CKSRYB223K50
	C	4356 (A,239,46)		CKSYB684K25
	C	4357 (A,226,47)		CKSYB475K16
	C	4358 (A,221,48)	ELECT. CAPACITOR	CEHAZL221M10

AT DSP DIODE ASSY

MISCELLANEOUS

	D	4301 (A,160,133)	DIODE	D5SBA20(B)
	J	4301	8P HOUSING ASSY	ADX7609

CAPACITORS

	C	4345 (A,180,130)		CKSRYB103K50
	C	4346 (B,166,131)		CKSRYB103K50
	C	4347 (B,180,131)		CKSRYB103K50
	C	4348 (A,168,130)		CKSRYB103K50

AU HN DIODE ASSY

MISCELLANEOUS

	D	4351 (A,202,133)	DIODE	D3SBA20(B)
	J	4351	4P HOUSING ASSY	ADX7608

CAPACITORS

	C	4363 (A,220,129)		CKSRYB103K50
	C	4364 (B,208,131)		CKSRYB103K50
	C	4365 (B,219,130)		CKSRYB103K50
	C	4366 (A,208,130)		CKSRYB103K50

Mark	No.	Description	Part No.

AV FAN-12V ASSY

MISCELLANEOUS

⚠ IC	4713 (A,121,133)	REGULATOR IC	NJM79M12FA
D	4715 (A,125,118)	CHIP DIODE	RB501V-40
J	4710	JUMPER WIRE	D20PYY0305E
	4710	3P CABLE HOLDER	51048-0300

RESISTORS

R	4708 (A,118,120)		RS1/16S0R0J
R	4709 (A,118,124)		RS1/16S0R0J

CAPACITORS

C	4713 (B,123,119)		CKSRYB103K50
C	4714 (A,127,127)		CEAT100M50

AW DD DISP ASSY

MISCELLANEOUS

⚠ IC	4501 (A,26,68)	REGULATOR IC	LT1766EFE
⚠ IC	4701 (A,90,67)	REGULATOR IC	LT3430EFE
⚠ IC	4702 (A,123,59)	PROTECTOR(7A)	AEK7021
⚠ IC	4703 (A,123,69)	PROTECTOR(7A)	AEK7047
D	4501 (A,24,44)	DIODE	D3SBA20(B)
D	4503 (A,23,74)	CHIP DIODE	RB050L-40
D	4504 (A,17,68)	DIODE	RR264M-400
D	4505 (A,17,76)	DIODE	PTZ3R6(B)
D	4506 (A,31,87)	CHIP ZENER DIODE	RLZ10B
D	4701 (A,116,38)	DIODE	D3SBA20(B)
D	4703 (A,78,76)	CHIP DIODE	RB050L-40
D	4704 (A,87,73)	CHIP DIODE	RB050L-40
D	4705 (A,90,76)	DIODE	PTZ6R8(B)
D	4706 (A,100,87)	CHIP ZENER DIODE	RLZ15B
L	4501 (A,21,88)	INDUCTOR	CTH1255
L	4701 (A,88,85)	INDUCTOR	ATH7036
H	4501 (A,60,13)	FUSE CLIP	AKR7001
H	4502 (A,39,13)	FUSE CLIP	AKR7001
J	4502 (A,35,92)	15P HOUSING ASSY	ADX7598
J	4702 (A,78,99)	3P HOUSING ASSY	ADX7627
KN	4501 (A,120,110)	SCREW PLATE	VNE1948
KN	4701 (A,63,110)	SCREW PLATE	VNE1948
CN	4702 (A,122,50)	3PIN CONNECTOR	S3B-EH
	4331 (A,124,20)	PCB BINDER	VEF1040
	4305	3P CABLE HOLDER	51048-0300

RESISTORS

⚠ R	4501 (A,37,36)	CARBON FILM RESISTOR	RD1/4MUF4R7J
R	4502 (A,34,68)		RS1/16S682J
R	4503 (A,37,71)		RS1/16S0R0J
R	4504 (A,36,74)		RS1/16S152J
R	4505 (A,33,72)		RN1/16SE2702D
R	4506 (A,35,71)		RN1/16SE5101D
⚠ R	4701 (A,116,71)	CARBON FILM RESISTOR	RD1/4MUF4R7J
R	4702 (A,96,65)		RS1/16S332J
R	4703 (A,100,65)		RS1/16S0R0J
R	4704 (A,102,70)		RS1/16S222J
R	4705 (A,100,68)		RN1/16SE4302D
R	4706 (A,101,65)		RN1/16SE5101D
R	4707 (A,71,87)		RS1/16S0R0J

CAPACITORS

C	4501 (A,32,27)	FILM CAPACITOR	CQMBA104J50
C	4502 (A,28,54)	ELECT. CAPACITOR	CEAT472M25
C	4503 (A,20,62)		CCG1236
C	4504 (A,33,66)		CCSRCH221J50
C	4505 (A,35,66)		CKSQYB563K25
C	4506 (A,19,68)		CKSQYB334K16
C	4507 (A,26,79)		CKSYB475K16
C	4508 (A,34,83)	ELECT. CAPACITOR	CEHAZL471M10
C	4510 (A,29,32)		CKSRYB103K50
C	4511 (A,31,41)		CKSRYB103K50
C	4512 (A,29,35)		CKSRYB103K50
C	4513 (A,29,41)		CKSRYB103K50
C	4701 (A,116,59)	FILM CAPACITOR	CFTLA104J2A
C	4702 (A,98,26)	ELECT. CAPACITOR	CEAT332M35
C	4703 (A,82,68)		CCG1236
C	4704 (A,97,65)		CCSRCH221J50
C	4705 (A,96,63)		CKSRYB223K50
C	4706 (A,81,75)		CKSYB684K25
C	4707 (A,96,77)		CKSYB475K16
C	4708 (A,103,81)		CEHAZL471M16
C	4712 (A,98,43)	ELECT. CAPACITOR	CEAT222M35
C	4715 (A,116,53)	CAPACITOR(CERAMIC)	ACG7062
C	4716 (B,111,40)	CAPACITOR(CERAMIC)	ACG7062
C	4717 (B,107,53)	CAPACITOR(CERAMIC)	ACG7062
C	4718 (A,114,53)	CAPACITOR(CERAMIC)	ACG7062

AX DD HDMI ASSY

MISCELLANEOUS

⚠ IC	4602 (A,80,205)	PROTECTOR(7A)	AEK7047
D	4606 (A,66,233)	CHIP ZENER DIODE	RLZ6.8B
D	4607 (A,66,221)	CHIP ZENER DIODE	RLZ7.5B
L	4613 (A,73,232)	COMMON MODE COIL	ATF7042
L	4614 (A,79,234)	LINE FILTER	ATF7041
L	4633 (A,73,223)	COMMON MODE COIL	ATF7042
H	4601 (A,123,174)	FUSE CLIP	AKR7001
H	4602 (A,123,152)	FUSE CLIP	AKR7001
J	4602 (A,112,224)	5P HOUSHING ASSY	ADX7546
KN	4601 (A,114,136)	SCREW PLATE	VNE1948
KN	4602 (A,28,136)	SCREW PLATE	VNE1948
CN	4601 (A,124,187)	2P CONNECTOR	B2P-VH
CN	4604 (A,61,182)	9P SOCKET	KP250NA9
CN	4605 (A,56,234)	12P SOCKET	KP250NA12

RESISTORS

⚠ R	4601 (A,104,159)	CARBON FILM RESISTOR	RD1/4MUF4R7J
R	4645 (B,70,217)		RS1/16S0R0J

CAPACITORS

C	4601 (A,116,159)	FILM CAPACITOR	CQMBA104J50
C	4602 (A,109,202)	ELECTR.CAPACITOR	ACH7296
C	4642 (B,75,218)		CKSRYB104K50

Mark	No.	Description	Part No.

AY HDMI DIODE ASSY

MISCELLANEOUS

	D	4601 (A,81,118) BRIDGE DIODE	D15XB20
	J	4601 12P HOUSING ASSY	ADX7610

CAPACITORS

	C	4658 (B,85,128)	CKSRYB103K50
	C	4659 (A,66,123)	CKSRYB103K50
	C	4660 (B,66,128)	CKSRYB103K50
	C	4661 (A,74,126)	CKSRYB103K50

AZ 2CH DD ASSY

MISCELLANEOUS

⚠	IC	4601 (A,44,46) REGULATOR IC	LTC3728LEGN
⚠	IC	4611 (A,75,60) POWER MOS FET	RSS065N03
⚠	IC	4612 (A,81,52) POWER MOS FET	RSS065N03
⚠	IC	4631 (A,75,32) POWER MOS FET	RSS065N03
⚠	IC	4632 (A,81,40) POWER MOS FET	RSS065N03
	D	4611 (A,54,52) DIODE	RB160M-40
	D	4612 (A,86,52) CHIP DIODE	RB050L-40
	D	4631 (A,56,52) DIODE	RB160M-40
	D	4632 (A,86,40) CHIP DIODE	RB050L-40
	L	4611 (A,95,59) INDUCTOR	ATH7055
	L	4631 (A,95,33) INDUCTOR	ATH7055
	CN	4606 (A,65,64) CONNECTOR	B9B-XH-A
	CN	4607 (A,117,60) CONNECTOR	B12B-XH-A

RESISTORS

	R	4602 (A,60,49)	RS1/4S100J
	R	4603 (A,52,57)	RS1/16S103J
	R	4604 (A,37,52)	RS1/16S103J
	R	4605 (A,33,52)	RS1/16S103J
	R	4606 (A,33,50)	RS1/16S0R0J
	R	4608 (A,37,45)	RS1/16S0R0J
⚠	R	4611 (A,104,63)	CCN1148
	R	4612 (A,40,55)	RS1/16S100J
	R	4613 (A,42,55)	RS1/16S100J
	R	4614 (A,37,54)	RN1/16SE1103D
	R	4615 (A,33,54)	RN1/16SE2002D
	R	4616 (A,44,53)	RS1/16S105J
	R	4617 (A,35,48)	RS1/16S153J
	R	4618 (A,77,64)	RS1/16S0R0J
	R	4619 (A,82,47)	RS1/16S0R0J
⚠	R	4631 (A,104,29)	CCN1148
	R	4632 (A,38,37)	RS1/16S100J
	R	4633 (A,40,37)	RS1/16S100J
	R	4634 (A,39,30)	RN1/16SE1303D
	R	4635 (A,36,30)	RN1/16SE2002D
	R	4636 (A,44,39)	RS1/16S105J
	R	4637 (A,35,42)	RS1/16S333J
	R	4638 (A,39,33) CHIP RESISTOR	ACN7159
	R	4639 (A,36,33) CHIP RESISTOR	ACN7159
	R	4640 (A,41,35) CHIP RESISTOR	ACN7159
	R	4641 (A,36,35) CHIP RESISTOR	ACN7159
	R	4642 (A,77,37)	RS1/16S0R0J
	R	4643 (A,78,45)	RS1/16S0R0J

Mark	No.	Description	Part No.

CAPACITORS

	C	4603 (A,72,43)	CCG1236
	C	4604 (A,72,46)	CCG1236
	C	4605 (A,72,50)	CCG1236
	C	4606 (A,55,43)	CKSYB475K16
	C	4607 (A,33,44)	CKSRYB103K50
	C	4608 (A,59,53)	CKSRYB104K50
	C	4609 (A,52,43)	CKSYB475K16
	C	4611 (A,106,67) CAPACITOR(CERAMIC)	ACG7061
	C	4612 (A,111,64) OS CAPACITOR	ACH7282
	C	4613 (A,52,53)	CKSYB104K25
	C	4615 (A,41,52)	CCSRCH102J50
	C	4616 (A,44,56)	CKSRYB223K50
	C	4617 (A,33,46)	CCSRCH102J50
	C	4618 (A,33,49)	CCSRCH330J50
	C	4631 (A,106,25) CAPACITOR(CERAMIC)	ACG7061
	C	4632 (A,111,29) OS CAPACITOR	ACH7282
	C	4633 (A,52,38)	CKSYB104K25
	C	4635 (A,39,40)	CCSRCH102J50
	C	4636 (A,44,37)	CKSRYB223K50
	C	4637 (A,33,40)	CKSRYB472K50
	C	4638 (A,33,43)	CCSRCH330J50

BA A-REG ASSY

SEMICONDUCTORS

⚠	IC	4101	AEK7046
⚠	IC	4111,4151	NJM7805FA
⚠	IC	4121	LM2940CT-5.0
⚠	IC	4131	NJM78M15FA
⚠	IC	4132	NJM79M15FA
⚠	IC	4133	NJM78M12FA
⚠	IC	4152	NJM7905FA
	Q	4131,4151	2SC4154
	Q	4132	2SA1602A
⚠	Q	4133,4152	2SJ539
⚠	Q	4134	2SK2927
⚠	D	4111,4131,4151	D3SBA20(B)
⚠	D	4112,4122,4154	MTZJ6R2(B)
	D	4133,4134,4152	UDZS4R7(B)
	D	4135,4136	UDZS18(B)
	D	4137,4138,4157,4159	RB501V-40

MISCELLANEOUS

	H	4103-4112 FUSE CLIP	AKR7001
	CN	4101,4121 CONNECTOR	B4B-EH
	CN	4102 PLUG(2P)	KM200NA2
	CN	4103 PLUG(5P)	KM200NA5
	CN	4104 2P TOP POST	B2B-EH
	CN	4105 CONNECTOR	B6B-EH
		4111,4113,4115-4119 PCB BINDER	VEF1040
	JP	4102 CONNECTOR ASSY	PF04PG0S20

RESISTORS

⚠	R	4131,4151	RD1/4MUF4R7J
		Other Resistors	RS1/16S###J

Mark	No.	Description	Part No.
CAPACITORS			
C	4112,4122,4154		CEAT472M16
C	4113,4115-4118,4123		CKSRYB103K50
C	4114,4124,4155-4157		CEAT101M16
C	4131		CQMBA104J2A
C	4132,4141,4142,4159		CKSRYB103K50
C	4133,4134		CEAT472M35
C	4135,4137-4139		CEAT470M25
C	4136		CEAL470M25
C	4143,4144,4160		CEAL2R2M50
C	4151		CQMBA104J50
C	4153		CEAT682M16
C	4161-4164,4808		CKSRYB103K50
C	4171-4174		ACG7062

BB DA DIODE ASSY

Mark	No.	Description	Part No.
SEMICONDUCTORS			
⚠ D	4121		D15XB20
MISCELLANEOUS			
JP	4121	4P HOUSING ASSY	ADX7611
CAPACITORS			
C	4127,4128		CKSRYB103K50

BC PRIMARY ASSY

Mark	No.	Description	Part No.
SEMICONDUCTORS			
⚠ IC	4002		PQ20RX11
Q	4001,4032		RT1N241M
Q	4011,4012,4021,4023		2SC4154
Q	4013,4043		2SA1602A
Q	4014		2SD1858X
Q	4022		2SD1664
Q	4024,4033,4039-4042		2SC4154
Q	4031		RT1P241M
Q	4034		2SB1237X
Q	4035,4036		RT1N140M
Q	4037		RT1N431M
Q	4038		2SB1132
⚠ D	4001		S1WB(A)60SD
D	4002,4003,4006		1SS352
D	4005		UDZS3R3(B)
D	4007,4008,4011		UDZS5R6(B)
D	4031-4036		1SS352
D	4038		UDZS5R1(B)
D	4039		1SR154-400
MISCELLANEOUS			
⚠ L	31	LINE FILTER	XTF3004
H	31,32,41,42	FUSE CLIP	AKR7001
KN	4001	WRAPPING TERMINAL	VNF1084
KN	4002	SCREW TERMINAL	VNE1949
⚠ RY	21	RELAY	XSR3010
⚠ T	21	STANDBY TRANSFORMER	ATT7100
⚠ CN	22	CONNECTOR	B2P3-VH
⚠ CN	23	CONNECTOR	B2P4-VH
⚠ CN	24	CONNECTOR	B2P3S-VH
CN	4001	CONNECTOR(05P)	TUC-P05X-B1
CN	4002	KR CONNECTOR	B3B-PH-K-Y
CN	4004	L-PLUG(9P)	KM200NA9L
CN	4005	PLUG(2P)	KM200NA2LR
CN	4007	PLUG(2P)	KM200NA2
CN	4012	9P CONNECTOR	52044-0945
RESISTORS			
⚠ R	4001		RD1/4MUF151J
⚠ R	4045,4046		RS1/2LMF330J
Other Resistors			RS1/16S###J
CAPACITORS			
⚠ C	21		ACG7039
⚠ C	31,32,41,42		ACE7013
C	4001		CQMBA103J50
C	4002,4003,4007,4008		CKSRYB102K50
C	4004		CEAT332M25
C	4005		CEAT221M25
C	4006		CKSRYB103K50
C	4010		CKSQYB224K25
C	4011		CKSRYB104K25
C	4012		CKSRYB105K16
C	4031,4032		CEAT220M50
C	4035		CEAT221M16

BD ICE INPUT 4CH ASSY

Mark	No.	Description	Part No.
MISCELLANEOUS			
IC	5611 (A,271,105)	IC	OPA2134UA
IC	5621 (A,270,69)	IC	OPA2134UA
IC	5631 (A,272,44)	IC	OPA2134UA
IC	5641 (A,267,26)	IC	OPA2134UA
CN	5602 (A,258,45)	12PIN CONNECTOR	AKM1372
CN	5603 (A,282,110)	L-PLUG(6P)	KM200NA6L
CN	5604 (A,275,76)	L-PLUG(6P)	KM200NA6L
CN	5605 (A,282,51)	L-PLUG(6P)	KM200NA6L
CN	5606 (A,282,21)	L-PLUG(6P)	KM200NA6L
RESISTORS			
R	5601 (A,267,104)		RS1/16S471J
R	5602 (A,267,103)		RS1/16S471J
R	5603 (A,265,70)		RS1/16S471J
R	5604 (A,265,68)		RS1/16S471J
R	5605 (A,267,41)		RS1/16S471J
R	5606 (A,267,39)		RS1/16S471J
R	5607 (A,264,25)		RS1/16S471J
R	5608 (A,264,22)		RS1/16S471J
R	5611 (A,280,105)	CHIP RESISTOR	RS1/16S1000F
R	5612 (B,274,91)		RS1/16S151J
R	5613 (B,265,106)		RS1/16S151J
R	5614 (A,280,103)	CHIP RESISTOR	RS1/16S1000F
R	5615 (A,273,110)		RS1/16S0R0J
R	5616 (A,271,100)		RS1/16S0R0J
R	5619 (A,264,103)		RS1/16S104J

Mark	No.	Description	Part No.
R	5621 (A,275,72)	CHIP RESISTOR	RS1/16S1000F
R	5622 (A,282,65)		RS1/16S151J
R	5623 (B,268,82)		RS1/16S151J
R	5624 (A,276,72)	CHIP RESISTOR	RS1/16S1000F
R	5625 (A,271,74)		RS1/16S0R0J
R	5626 (A,269,64)		RS1/16S0R0J
R	5629 (A,266,56)		RS1/16S104J
R	5631 (A,281,47)	CHIP RESISTOR	RS1/16S1000F
R	5632 (B,285,45)		RS1/16S151J
R	5633 (B,275,50)		RS1/16S151J
R	5634 (A,283,47)	CHIP RESISTOR	RS1/16S1000F
R	5635 (A,273,49)		RS1/16S0R0J
R	5636 (A,271,39)		RS1/16S0R0J
R	5639 (A,263,36)		RS1/16S104J
R	5641 (A,272,28)	CHIP RESISTOR	RS1/16S1000F
R	5642 (B,274,26)		RS1/16S151J
R	5643 (B,276,31)		RS1/16S151J
R	5644 (A,272,26)	CHIP RESISTOR	RS1/16S1000F
R	5645 (A,269,31)		RS1/16S0R0J
R	5646 (A,268,21)		RS1/16S0R0J
R	5649 (A,262,22)		RS1/16S104J

CAPACITORS

C	5611 (A,274,100)		CKSRYB103K50
C	5612 (A,267,107)		CKSRYB103K50
C	5613 (A,274,94)	ELECT. CAPACITOR	ACH7287
C	5614 (A,264,113)	ELECT. CAPACITOR	ACH7287
C	5621 (A,274,68)		CKSRYB103K50
C	5622 (A,265,73)		CKSRYB103K50
C	5623 (A,274,63)	ELECT. CAPACITOR	ACH7287
C	5624 (A,265,78)	ELECT. CAPACITOR	ACH7287
C	5631 (A,276,41)		CKSRYB103K50
C	5632 (A,268,45)		CKSRYB103K50
C	5633 (A,282,40)	ELECT. CAPACITOR	ACH7287
C	5634 (A,273,54)	ELECT. CAPACITOR	ACH7287
C	5641 (A,270,20)		CKSRYB103K50
C	5642 (A,263,28)		CKSRYB103K50
C	5643 (A,274,18)	ELECT. CAPACITOR	ACH7287
C	5644 (A,274,35)	ELECT. CAPACITOR	ACH7287

BE ICE INPUT 6CH ASSY

MISCELLANEOUS

IC	5511 (A,294,175)	IC	OPA2134UA
IC	5521 (A,267,174)	IC	OPA2134UA
IC	5531 (A,241,177)	IC	OPA2134UA
IC	5541 (A,209,179)	IC	OPA2134UA
IC	5551 (A,179,179)	IC	OPA2134UA
IC	5561 (A,152,174)	IC	OPA2134UA
L	5501 (A,309,173)	CHIP COIL	ATL7016
L	5502 (A,312,183)	CHIP COIL	ATL7016
CN	5501 (A,308,168)	7PIN CONNECTOR	AKM7084
CN	5503 (A,156,163)	15PIN CONNECTOR	AKM1375
CN	5504 (A,145,163)	3PIN CONNECTOR	AKM1363
CN	5505 (A,305,186)	L-PLUG(6P)	KM200NA6L
CN	5506 (A,271,186)	L-PLUG(6P)	KM200NA6L
CN	5507 (A,247,186)	L-PLUG(6P)	KM200NA6L
CN	5508 (A,213,186)	L-PLUG(6P)	KM200NA6L
CN	5509 (A,188,186)	L-PLUG(6P)	KM200NA6L
CN	5510 (A,156,186)	L-PLUG(6P)	KM200NA6L

RESISTORS

R	5511 (A,293,180)	CHIP RESISTOR	RS1/16S1000F
R	5512 (A,299,180)		RS1/16S151J
R	5513 (A,287,173)		RS1/16S151J
R	5514 (A,295,180)	CHIP RESISTOR	RS1/16S1000F
R	5515 (A,289,177)		RS1/16S0R0J
R	5516 (A,299,175)		RS1/16S0R0J
R	5519 (A,294,167)		RS1/16S104J
R	5521 (A,268,180)	CHIP RESISTOR	RS1/16S1000F
R	5522 (A,271,178)		RS1/16S151J
R	5523 (A,260,171)		RS1/16S151J
R	5524 (A,267,180)	CHIP RESISTOR	RS1/16S1000F
R	5525 (A,272,174)		RS1/16S0R0J
R	5526 (A,262,175)		RS1/16S0R0J
R	5529 (A,266,167)		RS1/16S104J
R	5531 (A,240,181)	CHIP RESISTOR	RS1/16S1000F
R	5532 (A,246,181)		RS1/16S151J
R	5533 (A,234,174)		RS1/16S151J
R	5534 (A,242,181)	CHIP RESISTOR	RS1/16S1000F
R	5535 (A,236,178)		RS1/16S0R0J
R	5536 (A,246,176)		RS1/16S0R0J
R	5539 (A,241,170)		RS1/16S104J
R	5541 (A,209,184)	CHIP RESISTOR	RS1/16S1000F
R	5542 (A,217,184)		RS1/16S151J
R	5543 (A,202,178)		RS1/16S151J
R	5544 (A,208,184)	CHIP RESISTOR	RS1/16S1000F
R	5545 (A,214,179)		RS1/16S0R0J
R	5546 (A,204,181)		RS1/16S0R0J
R	5549 (A,210,171)		RS1/16S104J
R	5551 (A,179,183)	CHIP RESISTOR	RS1/16S1000F
R	5552 (A,188,183)		RS1/16S151J
R	5553 (A,172,177)		RS1/16S151J
R	5554 (A,180,183)	CHIP RESISTOR	RS1/16S1000F
R	5555 (A,174,180)		RS1/16S0R0J
R	5556 (A,184,179)		RS1/16S0R0J
R	5559 (A,180,171)		RS1/16S104J
R	5561 (A,154,182)	CHIP RESISTOR	RS1/16S1000F
R	5562 (A,157,179)		RS1/16S151J
R	5563 (A,144,173)		RS1/16S151J
R	5564 (A,152,182)	CHIP RESISTOR	RS1/16S1000F
R	5565 (A,157,174)		RS1/16S0R0J
R	5566 (A,147,176)		RS1/16S0R0J
R	5569 (A,152,168)		RS1/16S104J
R	5571 (A,293,170)		RS1/16S471J
R	5572 (A,294,170)		RS1/16S471J
R	5573 (A,267,169)		RS1/16S471J
R	5574 (A,265,169)		RS1/16S471J
R	5575 (A,240,172)		RS1/16S471J
R	5576 (A,242,172)		RS1/16S471J
R	5577 (A,211,175)		RS1/16S471J
R	5578 (A,209,175)		RS1/16S471J
R	5579 (A,179,173)		RS1/16S471J
R	5580 (A,180,173)		RS1/16S471J
R	5581 (A,153,170)		RS1/16S471J
R	5582 (A,152,170)		RS1/16S471J

Mark	No.		Description	Part No.
CAPACITORS				
C	5501	(A,318,186)	ELECT. CAPACITOR	ACH7287
C	5502	(A,312,193)	ELECT. CAPACITOR	ACH7287
C	5511	(A,300,178)		CKSRYB103K50
C	5512	(A,289,172)		CKSRYB103K50
C	5513	(A,305,182)	ELECT. CAPACITOR	ACH7287
C	5514	(A,284,170)	ELECT. CAPACITOR	ACH7287
C	5521	(A,272,178)		CKSRYB103K50
C	5522	(A,262,170)		CKSRYB103K50
C	5523	(A,277,177)	ELECT. CAPACITOR	ACH7287
C	5524	(A,255,171)	ELECT. CAPACITOR	ACH7287
C	5531	(A,247,179)		CKSRYB103K50
C	5532	(A,236,174)		CKSRYB103K50
C	5533	(A,253,181)	ELECT. CAPACITOR	ACH7287
C	5534	(A,229,175)	ELECT. CAPACITOR	ACH7287
C	5541	(A,216,182)		CKSRYB103K50
C	5542	(A,204,177)		CKSRYB103K50
C	5543	(A,222,184)	ELECT. CAPACITOR	ACH7287
C	5544	(A,197,178)	ELECT. CAPACITOR	ACH7287
C	5551	(A,186,181)		CKSRYB103K50
C	5552	(A,174,176)		CKSRYB103K50
C	5553	(A,195,188)	ELECT. CAPACITOR	ACH7287
C	5554	(A,170,187)	ELECT. CAPACITOR	ACH7287
C	5561	(A,158,176)		CKSRYB103K50
C	5562	(A,147,172)		CKSRYB103K50
C	5563	(A,163,181)	ELECT. CAPACITOR	ACH7287
C	5564	(A,141,181)	ELECT. CAPACITOR	ACH7287

BF PFC ASSY

MISCELLANEOUS

Mark	No.		Description	Part No.
D	11	(B,221,239)	DIODE	1SS352
D	12	(B,229,239)	DIODE	1SS352
D	13	(B,162,239)	DIODE	1SS352
D	14	(B,171,239)	DIODE	1SS352
D	15	(B,199,202)	DIODE	1SS352
D	16	(B,208,202)	DIODE	1SS352
⚠ L	11	(A,84,215)	PFC REACTOR	ATH7062
H	13	(A,287,226)	FUSE HOLDER	AKR7004
H	14	(A,252,226)	FUSE HOLDER	AKR7004
J	13	9P HOUSHING ASSY		ADX7545
KN	11	(A,47,233)	WRAPPING TERMINAL	VNF1084
⚠ RY	11	(A,212,227)	RELAY	ASR7031
⚠ RY	12	(A,215,214)	RELAY	ASR7031
⚠ RY	13	(A,154,227)	RELAY	ASR7031
⚠ CN	14	(A,47,204)	2P CONNECTOR	AKM7079
CN	15	(A,232,191)	PLUG(2P)	AKM7083
CN	16	(A,185,188)	PLUG(2P)	AKM7083
⚠ VA	11	(A,118,217)	VARISTOR	TND10V-911KB00AAA0
⚠ VA	12	(A,53,210)	VARISTOR	TND10V-511KB00AAA0
Y	15	AWG16 BOARD IN		ADX7616

RESISTORS

Mark	No.		Description	Part No.
⚠ R	18	(A,144,231)	RESISTOR (1OHM,20W)	ACN7158

CAPACITORS

Mark	No.		Description	Part No.
⚠ C	11	(A,220,220)	CERAMIC CAPACITOR	ACG1069
⚠ C	12	(A,199,221)	CERAMIC CAPACITOR	ACG1069
C	14	(B,189,197)		CKSRYB103K50
C	15	(B,227,190)		CKSRYB103K50
⚠ C	16	(A,133,225)	CERAMIC CAPACITOR	ACG1067
⚠ C	17	(A,133,212)	CERAMIC CAPACITOR	ACG1067
⚠ C	18	(A,47,229)	CAP (2200P/AC250V)	ACG7047

BG INLET ASSY

MISCELLANEOUS

Mark	No.		Description	Part No.
H	11	(A,291,145)	FUSE CLIP	AKR7001
H	12	(A,270,145)	FUSE CLIP	AKR7001
⚠ J	11	(A,266,175)	2P HOUSING ASSY	ADX7560
⚠ Y	13	AWG16 BOARD IN		ADX7516
⚠ Y	14	AWG16 BOARD IN		ADX7517